

SPECIFICATION SHEET
JFW MODEL 50KFA-005
FIXED ATTENUATOR KIT

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Description Kit of RF components supplied together in a case

Frequency Range DC-2200 MHz

Impedance 50 Ohms nominal

RF Connectors BNC

Parts Included (1 each) Fixed Attenuators: 1, 2, 3, 6, 10, & 20dB
(1 piece) Feedthru Termination 50 Ohm
(1 piece) Feedthru Termination 75 Ohm
(1 piece) Impedance Matching Pad 50/75 Ohm
(1 piece) Impedance Matching Pad 75/50 Ohm
(1 piece) Adapter N male to BNC female
(1 piece) Adapter N female to BNC male

Model Numbers for Each Individual Part

50F-001	BNC	(1dB Fixed Attenuator, BNC male/female)
50F-002	BNC	(2dB Fixed Attenuator, BNC male/female)
50F-003	BNC	(3dB Fixed Attenuator, BNC male/female)
50F-006	BNC	(6dB Fixed Attenuator, BNC male/female)
50F-010	BNC	(10dB Fixed Attenuator, BNC male/female)
50F-020	BNC	(20dB Fixed Attenuator, BNC male/female)
50L-001	BNC	(Feedthru Termination, BNC male/female)
75L-001	BNC	(Feedthru Termination, BNC male/female)
57Z	BNC M/F	(Impedance Matching Pad, 50/75 Ohm)
75Z	BNC M/F	(Impedance Matching Pad, 75/50 Ohm)
015-056		(50 Ohm Adapter, BNC female/N male)
015-057		(50 Ohm Adapter, N female/BNC male)

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
	09/24/2014		TRS 09/24/2014				