

June 2002

EXAR'S XR68C92/192 COMPARED WITH PHILIP'S SCC68692

Author: PY

1.0 INTRODUCTION

This application note describes the major difference between Exar's XR68C92/192 with Philips's SCC68692. These devices are very similar, with a few hardware, firmware-related and bus timing differences.

1.1 HARDWARE DIFFERENCES

- The Philips SCC68692 and Exar XR68C92/192 are both available in two footprints: 44-pin PLCC and 40-pin PDIP. Additionally, the SCC68692 is available in a 40-pin CDIP and the XR68C92/192 is available in a 44-pin TQFP. In the PLCC and PDIP packages, the Exar and Philips DUARTs are pin-to-pin compatible.

1.2 FIRMWARE DIFFERENCES

All the internal registers in the SCC68692 and XR68C92/192 are identical with only a few exceptions:

- The XR68C92/192 has an additional mode register, Mode Register 0 (Watch dog timer, RX and TX trigger levels and extended baud rate tables), for channels A and B while the SCC68692 does not.
- Since the XR68C92/192 has a larger FIFO than the SCC68692, the selectable transmit and receive trigger levels are different.
- At the address offset of 0x2 and 0xA, the SCC68692 has a read-only BRG Test Register and 1X/16X Test Register, respectively, while these offsets are reserved for the XR68C92/192.
- The XR68C92/192 has a Miscellaneous Command in the CRA and CRB register bits 7-4 that has a different function than the SCC68692. When 0xB is written to the upper nibble of CRA or CRB, the XR68C92/192 sets the MR pointer to MR0, but this has no effect on the SCC68692.

1.3 BUS TIMING DIFFERENCES

- The XR68C92/192 is much faster than the SCC68692. For example, the data access time (from -CS low to data valid) during a read is a maximum of 32 ns for the XR68C92/192, whereas it is a maximum of 175 ns for the SCC68692.

1.4 SUMMARY OF DIFFERENCES

In the table below, some differences between the XR68C92/192 and SCC68692 are summarized.

TABLE 1: DIFFERENCES BETWEEN EXAR'S XR68C92/192 WITH PHILIPS'S SCC68692

DIFFERENCES	XR68C92/192	SCC68692
Data Bus Standard	Motorola	Motorola
Power Supply Operation	3.3 and 5 V	5 V only
Max Operating Current	3 mA @ 3.3 V 6 mA @ 5 V	10 mA @ 5 V
Max Frequency on XTAL1	24 MHz	4 MHz
Max Data Rate	1 Mbps	125 Kbps
Operating Temperature Range	Commercial and Industrial	Commercial and Industrial
Package	44-TQFP, 44-PLCC, 40-PDIP	44-PLCC, 40-PDIP, 40-CDIP
TX FIFO Size	8 (XR68C92) 16 (XR68C192)	1
RX FIFO Size	8 (XR68C92) 16 (XR68C192)	3
TX FIFO Trigger Levels	8, 4, 6, 1 (XR68C92) 16, 8, 12, 1 (XR68C192)	1
RX FIFO Trigger Levels	1, 3, 6, 8 (XR68C92) 1, 6, 12, 16 (XR68C192)	1, 3

1.5 REPLACING THE SCC68692 WITH THE XR68C92/192

You can directly replace the Philips SCC68692 with Exar's XR68C92/192 without any hardware changes if using either the 44-PLCC or 40-PDIP packages. Hardware changes will be necessary to upgrade to the smaller 44-TQFP package.

Since the XR68C92/192 has a larger Transmit and Receive FIFO, the software will need to be updated to fully utilize the features of the XR68C92/192. The XR68C92/192 allows the hardware designer to choose either a 5 or 3.3 V power supply instead of being limited to a 5 V power supply only. Also, the XR68C92/192 has a lower power consumption than the SCC68692.

The XR68C92/192 can accept up to a 24 MHz frequency on XTAL1 whereas the SCC68692 can only accept up to a 4 MHz frequency. The maximum data transfer rate for the XR68C92/192 is 1 Mbps compared to only 125 Kbps for the SCC68692.

NOTICE

EXAR Corporation reserves the right to make changes to the products contained in this publication in order to improve design, performance or reliability. EXAR Corporation assumes no responsibility for the use of any circuits described herein, conveys no license under any patent or other right, and makes no representation that the circuits are free of patent infringement. Charts and schedules contained here in are only for illustration purposes and may vary depending upon a user's specific application. While the information in this publication has been carefully checked; no responsibility, however, is assumed for inaccuracies.

EXAR Corporation does not recommend the use of any of its products in life support applications where the failure or malfunction of the product can reasonably be expected to cause failure of the life support system or to significantly affect its safety or effectiveness. Products are not authorized for use in such applications unless EXAR Corporation receives, in writing, assurances to its satisfaction that: (a) the risk of injury or damage has been minimized; (b) the user assumes all such risks; (c) potential liability of EXAR Corporation is adequately protected under the circumstances.

Copyright 2002 EXAR Corporation

June 2002

Send your UART technical inquiry with technical details to hotline: uarttechsupport@exar.com

Reproduction, in part or whole, without the prior written consent of EXAR Corporation is prohibited.