



LEOPARD IMAGING INC

Rev 1.1


LI-JETSON-KIT-IMX264M12-X

Data Sheet

Key Features

- Compatible with Nvidia Jetson TX1/TX2 Developer Kit
- MIPI CSI-2 interface
- Support up to six cameras
- Two adapter board options
 - LI-JTX1-MIPI-ADPT
Includes three 4-lane interface
 - LI-JTX1-MIPI-ADPT-6CAM
Includes six 2-lane interface
- Sony Diagonal 11.1 mm (Type 2/3) CMOS Image Sensor IMX264
- Active pixels: 2464H x 2056V
- Pixel size: 3.45 um x 3.45 um
- Color camera
- Global Shutter
- Length of the I-PEX cable: 300mm
- Support multiple length cables
- Connector Part#: 20525-030E-02C
- Support M12 x P0.5 lens
- Provide customization services
- Part#:

(1 cam) **LI-JETSON-KIT-IMX264M12**
(2 cam) **LI-JETSON-KIT-IMX264M12-D**
(3 cam) **LI-JETSON-KIT-IMX264M12-T**
(6 cam) **LI-JETSON-KIT-IMX264M12-H**



Lens Spec

- Model: FIFO-F1225FM
- Focal length: 12 mm
- Aperture, F/#: 2.5
- Built in 650nm IR cut filter
- FOV (H): 37 °
- TV Distortion: < -1.2 %

BOM

Nvidia TX1/TX2 Developer Kit not included

#	Items	QTY
1	LI-JTX1-MIPI-ADPT or LI-JTX1-MIPI-ADPT-6CAM	1
2	LI-IMX264-MIPI-M12	1,2,3 or 6
3	FAW-1233-03 cable	1,2,3 or 6



Leopard Imaging Inc.

48820 Kato Road, Suite 100B, Fremont, CA 94538, USA
Phone: +1-408-263-0988
Fax: +1-408-217-1960
Email: sales@leopardimaging.com
Website: www.leopardimaging.com

LI-JETSON-KIT-IMX264M12

BOM

#	Items	QTY
1	LI-JTX1-MIPI-ADPT	1
2	LI-IMX264-MIPI-M12	1
3	FAW-1233-03 cable	1



LI-JETSON-KIT-IMX264M12-D

BOM

#	Items	QTY
1	LI-JTX1-MIPI-ADPT	1
2	LI-IMX264-MIPI-M12	2
3	FAW-1233-03 cable	2



LI-JETSON-KIT-IMX264M12-T

BOM


#	Items	QTY
1	LI-JTX1-MIPI-ADPT	1
2	LI-IMX264-MIPI-M12	3
3	FAW-1233-03 cable	3



LI-JETSON-KIT-IMX264M12-H

BOM

#	Items	QTY
1	LI-JTX1-MIPI-ADPT-6CAM	1
2	LI-IMX264-MIPI-M12	6
3	FAW-1233-03 cable	6



Leopard Imaging Inc.

48820 Kato Road, Suite 100B, Fremont, CA 94538, USA

Phone: +1-408-263-0988


Fax: +1-408-217-1960

Email: sales@leopardimaging.com


Website: www.leopardimaging.com

Dimensions


LI-IMX264-MIPI-M12




LI-JTX1-MIPI-ADPT



LI-JTX1-MIPI-ADPT-6CAM




FAW-1233-03



Leopard Imaging Inc.

48820 Kato Road, Suite 100B, Fremont, CA 94538, USA
 Phone: +1-408-263-0988
 Fax: +1-408-217-1960
 Email: sales@leopardimaging.com
 Website: www.leopardimaging.com


LI-JTX1-MIPI-ADPT



Interfaces


Interface J1

- Part#: 20525-030E-02C
- Number of Positions: 30
- Pitch: 0.4mm
- Mating I-PEX cable: FAW-1233-03 (300mm)




Interface J2

- Part#: 20525-030E-02C
- Number of Positions: 30
- Pitch: 0.4mm
- Mating I-PEX cable: FAW-1233-03 (300mm)



Interface J3

- Part#: 20525-030E-02C
- Number of Positions: 30
- Pitch: 0.4mm
- Mating I-PEX cable: FAW-1233-03 (300mm)




Leopard Imaging Inc.

48820 Kato Road, Suite 100B, Fremont, CA 94538, USA
 Phone: +1-408-263-0988
 Fax: +1-408-217-1960
 Email: sales@leopardimaging.com
 Website: www.leopardimaging.com

Interface J10

- Part#: QTH-060-01-L-D-A
- Number of Positions: 120
- Number of Rows: 2
- Pitch: 0.5 mm



Vertical Mating connector of Jetson TX1 J22 QTH-060-01-D-A



Leopard Imaging Inc.

48820 Kato Road, Suite 100B, Fremont, CA 94538, USA
 Phone: +1-408-263-0988
 Fax: +1-408-217-1960
 Email: sales@leopardimaging.com
 Website: www.leopardimaging.com


LI-JTX1-MIPI-ADPT-6CAM



Interfaces


Interface J1

- Part#: 20525-030E-02C
- Number of Positions: 30
- Pitch: 0.4mm
- Mating I-PEX cable: FAW-1233-03 (300mm)



Interface J2

- Part#: 20525-030E-02C
- Number of Positions: 30
- Pitch: 0.4mm
- Mating I-PEX cable: FAW-1233-03 (300mm)




Leopard Imaging Inc.

48820 Kato Road, Suite 100B, Fremont, CA 94538, USA
 Phone: +1-408-263-0988
 Fax: +1-408-217-1960
 Email: sales@leopardimaging.com
 Website: www.leopardimaging.com


Interface J3

- Part#: 20525-030E-02C
- Number of Positions: 30
- Pitch: 0.4mm
- Mating I-PEX cable: FAW-1233-03 (300mm)




Interface J4

- Part#: 20525-030E-02C
- Number of Positions: 30
- Pitch: 0.4mm
- Mating I-PEX cable: FAW-1233-03 (300mm)



Interface J5

- Part#: 20525-030E-02C
- Number of Positions: 30
- Pitch: 0.4mm
- Mating I-PEX cable: FAW-1233-03 (300mm)




Leopard Imaging Inc.

48820 Kato Road, Suite 100B, Fremont, CA 94538, USA
Phone: +1-408-263-0988
Fax: +1-408-217-1960
Email: sales@leopardimaging.com
Website: www.leopardimaging.com

Interface J9


- Part#: 20525-030E-02C
 - Number of Positions: 30
 - Pitch: 0.4mm
- Mating I-PEX cable: FAW-1233-03 (300mm)



Interface J10

- Part#: QTH-060-01-L-D-A
- Number of Positions: 120
- Number of Rows: 2
- Pitch: 0.5 mm

Vertical Mating connector of Jetson TX1 J22



Leopard Imaging Inc.

48820 Kato Road, Suite 100B, Fremont, CA 94538, USA
 Phone: +1-408-263-0988
 Fax: +1-408-217-1960
 Email: sales@leopardimaging.com
 Website: www.leopardimaging.com

LI-IMX264-MIPI-M12



Camera Spec	
Image Sensor	Sony Diagonal 11.1 mm (Type 2/3) CMOS Image Sensor IMX264
Optical format	2/3"
Number of active pixels	2464 (H) x 2056(V)
Pixel size	3.45um (H) x 3.45um (V)
Color or Mono	Color
Interface	MIPI interface
Lens mount	M12
Weight	14 g
Interfaces	
Interface J4: - Part#: 20525-030E-02C - Number of Positions: 30 - Pitch: 0.4mm - Mating I-PEX cable: FAW-1233-03 (300mm)	
Interface J8: - Part#: 1734829-2 - Number of Positions: 2 - Pitch: 1.25mm	
Interface J2: - Part#: 20021321-00010C4LF - Number of Positions: 10 - Pitch: 1.27mm	
Interface J3: - Part#: 20021321-00006C4LF - Number of Positions: 6 - Pitch: 1.27mm	



Leopard Imaging Inc.

48820 Kato Road, Suite 100B, Fremont, CA 94538, USA
 Phone: +1-408-263-0988
 Fax: +1-408-217-1960
 Email: sales@leopardimaging.com
 Website: www.leopardimaging.com


Absolute Maximum Ratings

Item	Symbol	Rating			Unit	Remarks
Supply voltage (Analog 3.3 V)	AV _{DD}	-0.3	to	+4.0	V	
Supply voltage (Interface 1.8 V)	OV _{DD}	-0.3	to	+3.3	V	
Supply voltage (Digital 1.2 V)	DV _{DD}	-0.3	to	+2.0	V	
Input voltage	VI	-0.3	to	OV _{DD} +0.3	V	Not exceed 3.3 V
Output voltage	VO	-0.3	to	OV _{DD} +0.3	V	Not exceed 3.3 V
Operating temperature	Topr	-30	to	+75	°C	
Storage temperature	Tstg	-40	to	+85	°C	
Performance guarantee temperature	Tspec	-10	to	+60	°C	

Recommended Operating Conditions


Item	Symbol	Min.	Typ.	Max.	Unit
Supply voltage (Analog 3.3 V)	AV _{DD}	3.15	3.30	3.45	V
Supply voltage (Interface 1.8 V)	OV _{DD}	1.70	1.80	1.90	V
Supply voltage (Digital 1.2 V)	DV _{DD}	1.10	1.20	1.30	V

Spectral Sensitivity Characteristics



DC Characteristics

Item		Pins	Symbol	Conditions	Min.	Typ.	Max.	Unit
Supply voltage	Analog	V _{DDHx}	AV _{DD}	—	3.15	3.30	3.45	V
	Interface	V _{DDMx}	OV _{DD}	—	1.70	1.80	1.90	V
	Digital	V _{DDLx}	DV _{DD}	—	1.10	1.20	1.30	V
Digital input voltage		XHS XVS XCLR INCK XMASTER SLAMODE	VIH	XVS / XHS in Slave mode	0.8 × OV _{DD}	—	—	V
		SCK SDI XCE XTRIG	VIL		—	—	0.2 × OV _{DD}	V
Digital output voltage		DLOPx1 DLOMx1 DCKP1 DCKM1 x: C to F	VCM	Low voltage LVDS (termination resistance: 100 Ω)	—	OV _{DD} /2	—	V
			VOD		100	150	210	mV
		XHS XVS SDO	VOH	XVS / XHS in Master mode	OV _{DD} -0.4	—	—	V
		TOUT1 TOUT2	VOL		—	—	0.4	V



Power Consumption

Item	Pins	Symbol	Typ.	Max.	Unit
Operating current Serial LVDS 4 ch 12 bit 35.7 frame/s	V _{DDH}	IAV _{DD}	120	175	mA
	V _{DDM}	IOV _{DD}	11	20	mA
	V _{DDL}	IDV _{DD}	120	180	mA
Standby current	V _{DDH}	IAV _{DD_STB}	—	0.5	mA
	V _{DDM}	IOV _{DD_STB}	—	0.5	mA
	V _{DDL}	IDV _{DD_STB}	—	20	mA

Operating current:

(Typical value condition):

Supply voltage: 3.30 V / 1.80 V / 1.20 V, T_j = 25 °C

(Maximum value condition):

Supply voltage: 3.45 V / 1.90 V / 1.30 V, T_j = 60 °C

Worst state of internal circuit operating current consumption.

Standby current:

(Maximum value condition):


Supply voltage: 3.45 V / 1.90 V / 1.30 V, T_j = 60 °C, INCK = 0 V,
The device in the light-obstructed state.



Leopard Imaging Inc.

48820 Kato Road, Suite 100B, Fremont, CA 94538, USA
Phone: +1-408-263-0988
Fax: +1-408-217-1960
Email: sales@leopardimaging.com
Website: www.leopardimaging.com


AC Characteristics



Item	Symbol	Min.	Typ.	Max.	Unit	Remarks
INCK clock frequency	f_{INCK}	$f_{INCK} \times 0.96$	f_{INCK}	$f_{INCK} \times 1.02$	MHz	$f_{INCK} =$ 37.125 MHz, 74.25 MHz, 54 MHz
INCK Low level pulse width	t_{WLINCK}	4	—	—	ns	
INCK High level pulse width	t_{WHINCK}	4	—	—	ns	
INCK clock duty	—	45.0	50.0	55.0	%	Define with $0.5 \times OV_{DD}$

* The INCK fluctuation affects the frame rate.

XVS / XHS Input Characteristics in Slave Mode (XMASTER = High)



Item	Symbol	Min.	Typ.	Max.	Unit
XHS Low level pulse width	t_{WLXHS}	$4/f_{INCK}$	—	—	ns
XHS High level pulse width	t_{WHXHS}	$4/f_{INCK}$	—	—	ns
XVS - XHS fall width	t_{HFDLY}	$1/f_{INCK}$	—	—	ns
XHS - XVS rise width	t_{VRDLY}	$1/f_{INCK}$	—	—	ns


Synchronization cannot be performed from XVS and XHS signal in mater mode. Detect the sync code.



Leopard Imaging Inc.

48820 Kato Road, Suite 100B, Fremont, CA 94538, USA
 Phone: +1-408-263-0988
 Fax: +1-408-217-1960
 Email: sales@leopardimaging.com
 Website: www.leopardimaging.com

I²C Communication



I²C Specification

Item	Symbol	Min.	Typ.	Max.	Unit	Remarks
Low level input voltage	V_{IL}	-0.3	—	$0.3 \times OV_{DD}$	V	
High level input voltage	V_{IH}	$0.7 \times OV_{DD}$	—	1.9	V	
Low level output voltage	V_{OL}	0	—	$0.2 \times OV_{DD}$	V	$OV_{DD} < 2$ V, Sink 3 mA
High level output voltage	V_{OH}	$0.8 \times OV_{DD}$	—	—	V	
Output fall time	t_{of}	—	—	250	ns	Load 10 pF – 400 pF, $0.7 \times OV_{DD} - 0.3 \times OV_{DD}$
Input current	I_i	-10	—	10	μA	$0.1 \times OV_{DD} - 0.9 \times OV_{DD}$
Capacitance for SCK (/SCL) , SDI (/SDA)	C_i	—	—	10	pF	

I²C AC Characteristics

Item	Symbol	Min.	Typ.	Max.	Unit
SCL clock frequency	f_{SCL}	0	—	400	kHz
Hold time (Start Condition)	t_{HDSTA}	0.6	—	—	μs
Low period of the SCL clock	t_{LOW}	1.3	—	—	μs
High period of the SCL clock	t_{HIGH}	0.6	—	—	μs
Set-up time (Repeated Start Condition)	t_{SUSTA}	0.6	—	—	μs
Data hold time	t_{HDDAT}	0	—	0.9	μs
Data set-up time	t_{SUDAT}	100	—	—	ns
Rise time of both SDA and SCL signals	t_R	—	—	300	ns
Fall time of both SDA and SCL signals	t_F	—	—	300	ns
Set-up time (Stop Condition)	t_{SUSTO}	0.6	—	—	μs
Bus free time between a Stop and Start Condition	t_{BUF}	1.3	—	—	μs




Leopard Imaging Inc.

48820 Kato Road, Suite 100B, Fremont, CA 94538, USA
 Phone: +1-408-263-0988
 Fax: +1-408-217-1960
 Email: sales@leopardimaging.com
 Website: www.leopardimaging.com

Power-on Sequence

Follow the sequence below to turn On the power supplies.

1. Turn On the power supplies so that the power supplies rise in order of 1.2 V power supply (DV_{DD}) → 1.8 V power supply (OV_{DD}) → 3.3 V power supply (AV_{DD}). In addition, all power supplies should finish rising within 200 ms.
2. The register values are undefined immediately after power-on, so the system must be cleared. Hold XCLR at Low level for 500 ns or more after all the power supplies have finished rising. (The register values after a system clear are the default values.)
In addition, hold XCE to High level during this period. Rise XCE after 1.8 V power supply (OV_{DD}), so hold XCE at High level until INCK is input.
3. Start the input of INCK after turning the level of XCLR into the high.
4. Make the sensor setting by register communication after the system clear. A period of 0 μ s or more should be provided after setting XCLR High before inputting the communication enable signal XCE.




Leopard Imaging Inc.

48820 Kato Road, Suite 100B, Fremont, CA 94538, USA
 Phone: +1-408-263-0988
 Fax: +1-408-217-1960
 Email: sales@leopardimaging.com
 Website: www.leopardimaging.com

Power-off Sequence

Turn Off the power supplies so that the power supplies fall in order of 3.3 V power supply (AV_{DD}) → 1.8 V power supply (OV_{DD}) → 1.2 V power supply (DV_{DD}). In addition, all power supplies should finish falling within 200 ms. Set each digital input pin (INCK, XCE, SCK, SDI, XCLR, XMASTER, XTRIG, SLAMODE, XVS, XHS) to 0 V or high impedance before the 1.8 V power supply (OV_{DD}) falls.



Leopard Imaging Inc.

48820 Kato Road, Suite 100B, Fremont, CA 94538, USA
Phone: +1-408-263-0988
Fax: +1-408-217-1960
Email: sales@leopardimaging.com
Website: www.leopardimaging.com