

<http://onsemi.com>

Low power consumption and high efficiency Step-down Switching Regulator Controller

LV5069JA is Step-down switching regulator controller. The recommended operating range is 4.5V-23V. The operating current is about 68μA, and low power consumption is achieved.

- Typical value of light load mode current is 68μA
- 4.5V to 23V Operating input voltage range
- The oscillatory frequency can be set by the external pin. The oscillatory frequency is 300kHz - 1MHz.
- Output voltage adjustable to 1.26V
- Built-in OCP circuit with P-by-P method
- When P-by-P is generated continuously, It shifts to the HICCUP operation
- If connect C-HICCUP to GND pin, Then latch-off when over current
- External capacitor Soft-Start
- Under voltage lock-out, Thermal shutdown and power good indication

- DVD/Blu-ray™ Drivers and HDD
- LCD Monitors and TVs
- Point of Load DC/DC Converters
- Office Supplies

EN

PG

FB

REF

COMP

SS

C-HICCUP

RT

GND

V_{IN}

PDR

I_{LIM}

RSNS

HDRV

Q1

L1

D1

V_{OUT}

V_{FB}

R1

R2

R3

C1

C2

C3

C4

L1

D1

R4

R5

R6

R7

R8

R9

R10

R11

R12

R13

R14

R15

R16

R17

R18

R19

R20

R21

R22

R23

R24

R25

R26

R27

R28

R29

R30

R31

R32

R33

R34

R35

R36

R37

R38

R39

R40

R41

R42

R43

R44

R45

R46

R47

R48

R49

R50

R51

R52

R53

R54

R55

R56

R57

R58

R59

R60

R61

R62

R63

R64

R65

R66

R67

R68

R69

R70

R71

R72

R73

R74

R75

R76

R77

R78

R79

R80

R81

R82

R83

R84

R85

R86

R87

R88

R89

R90

R91

R92

R93

R94

R95

R96

R97

R98

R99

R100

R101

R102

R103

R104

R105

R106

R107

R108

R109

R110

R111

R112

R113

R114

R115

R116

R117

R118

R119

R120

R121

R122

R123

R124

R125

R126

R127

R128

R129

R130

R131

R132

R133

R134

R135

R136

R137

R138

R139

R140

R141

R142

R143

R144

R145

R146

R147

R148

R149

R150

R151

R152

R153

R154

R155

R156

R157

R158

R159

R160

R161

R162

R163

R164

R165

R166

R167

R168

R169

R170

R171

R172

R173

R174

R175

R176

R177

R178

R179

R180

R181

R182

R183

R184

R185

R186

R187

R188

R189

R190

R191

R192

R193

R194

R195

R196

R197

R198

R199

R200

R201

R202

R203

R204

R205

R206

R207

R208

R209

R210

R211

R212

R213

R214

R215

R216

R217

R218

R219

R220

R221

R222

R223

R224

R225

R226

R227

R228

R229

R230

R231

R232

R233

R234

R235

R236

R237

R238

R239

R240

R241

R242

R243

R244

R245

R246

R247

R248

R249

R250

R251

R252

R253

R254

R255

R256

R257

R258

R259

R260

R261

R262

R263

R264

R265

R266

R267

R268

R269

R270

R271

R272

R273

R274

R275

R276

R277

R278

R279

R280

R281

R282

R283

R284

R285

R286

R287

R288

R289

R290

R291

R292

R293

R294

R295

R296

R297

R298

R299

R300

R301

R302

R303

R304

R305

R306

R307

R308

R309

R310

R311

R312

R313

R314

R315

R316

R317

R318

R319

R320

R321

R322

R323

R324

R325

R326

R327

R328

R329

R330

R331

R332

R333

R334

R335

R336

R337

R338

R339

R340

R341

R342

R343

R344

R345

R346

R347

R348

R349

R350

R351

R352

R353

R354

R355

R356

R357

R358

R359

R360

R361

R362

R363

R364

R365

R366

R367

R368

R369

R370

R371

R372

R373

R374

R375

R376

R377

R378

R379

R380

R381

R382

R383

R384

R385

R386

R387

R388

R389

R390

R391

R392

R393

R394

R395

R396

R397

R398

R399

R400

R401

R402

R403

R404

R405

R406

R407

R408

R409

R410

R411

R412

R413

R414

R415

R416

R417

R418

R419

R420

R421

R422

R423

R424


R425

R426

R427

R428

R429



Specifications

Absolute Maximum Ratings at Ta = 25°C

Parameter	Symbol	Conditions	Ratings	Unit
Input voltage	V _{IN} max		25	V
Allowable pin voltage	PDR		V _{IN}	V
	V _{IN} -PDR		6	V
	HDRV		V _{IN}	V
	RSNS		V _{IN}	V
	I _{LIM}		V _{IN}	V
	EN		V _{IN}	V
	PG		V _{IN}	V
	REF		6	V
	RT		REF	V
	SS		REF	V
	FB		REF	V
	COMP		REF	V
	C-HICCUP		REF	V
Allowable power dissipation	Pd max	Specified substrate *1	0.74	W
Operating temperature	T _{opr}		-40 to +85	°C
Storage temperature	T _{stg}		-55 to +150	°C

*1 Specified substrate : 114.3mm × 76.1mm × 1.6mm, fiberglass epoxy printed circuit board

Caution 1) Absolute maximum ratings represent the values which cannot be exceeded for any length of time.

Caution 2) Even when the device is used within the range of absolute maximum ratings, as a result of continuous usage under high temperature, high current, high voltage, or drastic temperature change, the reliability of the IC may be degraded. Please contact us for the further details.

Stresses exceeding Maximum Ratings may damage the device. Maximum Ratings are stress ratings only. Functional operation above the Recommended Operating Conditions is not implied. Extended exposure to stresses above the Recommended Operating Conditions may affect device reliability.

Recommendation Operating Conditions at Ta = 25°C

Parameter	Symbol	Conditions	Ratings	Unit
Input voltage range	V _{IN}		4.5 to 23	V

Electrical Characteristics at Ta = 25°C, V_{IN} = 15V

Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max	
[Reference voltage]						
Internal reference voltage	V _{REF}		1.247	1.260	1.273	V
Pch drive voltage	V _{PDR}	I _{OUT} = 0 to -5mA	V _{IN} -5.5	V _{IN} -5.0	V _{IN} -4.5	V
[Saw wave oscillator]						
Oscillatory frequency	F _{OSC}	RT = 470kΩ	280	330	380	kHz
[ON/OFF circuit]						
IC startup voltage (EN PIN)	V _{CNT_ON}		2.0		V _{IN}	V
Disable voltage (EN PIN)	V _{CNT_OFF}				0.3	V
[Soft start circuit]						
Soft start source current	I _{SS_SC}	EN > 2V	1.3	2.0	2.7	μA
Soft start sink current	I _{SS_SK}	EN < 0.3V, SS = 0.4V	2	3	4	mA
[UVLO circuit]						
UVLO release voltage	V _{UVLON}	FB = COMP	3.3	3.7	4.1	V
UVLO lock voltage	V _{UVLOF}	FB = COMP	3.02	3.42	3.82	V
[Error amplifier]						
Input bias current	I _{EA_IN}		-100	-50	100	nA
Error amplifier gain	G _{EA}		100	250	400	μA/V
Output sink current	I _{EA_OSK}	FB = 1.75V	-40	-20	-10	μA
Output source current	I _{EA_OSC}	FB = 0.75V	10	20	40	μA

Continued on next page.

LV5069JA

Continued from preceding page.



Parameter	Symbol	Conditions	Ratings			Unit
			min	typ	max	
[Over current limit circuit]						
Reference current	I _{LIM}		48.4	55	61.6	μA
Over current detection comparator offset voltage	V _{LIM_OFS}		-5		5	mV
RSNS pin input range	V _{RSNS}		V _{IN} -0.23		V _{IN}	V
HICCUP timer start-up cycle	N _{CYC}			15		cycle
HICCUP comparator threshold voltage	V _{tHIC}		1.23	1.29	1.35	V
HICCUP timer charge current	I _{HIC}		1	2	3	μA
[PWM Comparator]						
Maximum on-duty	D _{MAX}	RT = 470kΩ	94			%
[Logic output]						
Power good “L” sink current	I _{PWRGD_L}	PG = 5V	4	5	6	mA
Power good “H” leakage current	I _{PWRGD_H}	PG = 5V			1	μA
Power good threshold voltage	V _{TPG}		1.0	1.1	1.2	V
Power good hysteresis	V _{PG_H}		40	50	60	mV
[Output]						
High side output on resistance	R _{ONH}			5		Ω
Low side output on resistance	R _{ONL}			9		Ω
High side output on current	I _{ONH}		300			mA
Low side output on current	I _{ONL}		150			mA
[The entire device]						
Standby current	I _{CCS}	EN < 0.3V			1	μA
Light load mode consumption current	I _{SLEEP}	EN > 2V No switching	48	68	88	μA
Thermal shutdown	TSD	*Design guarantee		170		°C

*Design guarantee: Signifies target value in design. These parameters are not tested in an independent IC.


Package Dimensions

unit : mm (typ)

3178B



Mounting pad sketch




(Unit: mm)


Reference symbol	SSOP16(225mil)
eE	5.80
e	0.65
b3	0.32
l1	1.00

Caution: The mounting pad sketch is a reference value, which is not a guaranteed value.


Evaluation Board Pattern diagram




Top



Bottom




2nd Layer



3rd Layer

LV5069JA


Pin Assignment



Pin Function Description

Pin No	Pin Name	Description
1	PG	Power good pin. Connect to open drain of MOS-FET in ICs inside. Setting output voltage to "L", when FB voltage is 1.05V or less.
2	EN	ON/OFF Pin.
3	I _{LIM}	For current detection. Sink current is about 55μA. The current limiter comparator works when an external resistor is connected between this pin and V _{IN} , and if the voltage of this resistor is less than the voltage of RSNS then Pch MOS is turned off. This operation is reset each PWM pulse.
4	V _{IN}	Supply voltage pin. It is observed by the UVLO function. When its voltage becomes 3.7V or more, ICs startup in soft start.
5	RSNS	Current detection resistor connection pin. Resistor is connected between V _{IN} and this pin, and the current flow to MOSFET is measured.
6	HDRV	The external high-side MOSFET gate drive pin.
7	PDR	Pch MOSFET gate drive voltage. The bypass capacitor is necessarily connected between this pin and V _{IN} .
8	GND	Ground Pin. Ground pin voltage is reference voltage
9	NC	NC Pin. The NC Pin becomes open in an IC.
10	RT	Oscillation frequency setting pin. Resistor is connected between this pin and GND.
11	C-HICCUP	It is capacitor connection pin for setting re-startup cycle in HICCUP mode. If connect it to GND pin, then latch-off when over current.
12	SS	Capacitor connection pin for soft start. About 2.0μA current charges the soft start capacitor.
13	NC	NC Pin. The NC Pin becomes open in an IC.
14	COMP	Error amplifier output pin. The phase compensation network is connected between GND pin and COMP pin. Thanks to current-mode control, comp pin voltage would tell you the output current amplitude. Comp pin is connected internally to an Init.comparator which compares with 0.9V reference. If comp pin voltage is larger than 0.9V, IC operates in "continuous mode". If comp pin voltage is smaller than 0.9V, IC operates in "discontinuous mode (low consumption mode)".
15	FB	Error amplifier reverse input pin. ICs make its voltage keep 1.26V. Output voltage is divided by external resistances and it across FB.
16	REF	Reference voltage.

Block Diagram



Pin Equivalent Circuit

Pin No.	Pin name	Equivalent circuit
1	PG	
2	EN	
3	I _{LIM}	
4	V _{IN}	
5	RSNS	
6	HDRV	

Continued on next page.

LV5069JA

Continued from preceding page.

Pin No.	Pin name	Equivalent circuit
7	PDR	
8	GND	
9	NC	
10	RT	
11	C-HICCUP	
12	SS	
13	NC	

Continued on next page.

LV5069JA

Continued from preceding page.


Pin No.	Pin name	Equivalent circuit
14	COMP	
15	FB	
16	REF	

Detailed Description

Power-save Feature

This IC has Power-saving feature to enhance efficiency when the load is light.

By shutting down unnecessary circuits, operating current of the IC is minimized and high efficiency is realized.



Output Voltage Setting


Output voltage (V_{OUT}) is configurable by the resistance $R4$ between V_{OUT} and FB and the $R5$ between FB and GND. V_{OUT} is given by the following equation (1).

$$V_{OUT} = (1 + \frac{R4}{R5}) \times V_{REF} = (1 + \frac{R4}{R5}) \times 1.26 \text{ [V]} \quad (1)$$

Switching Frequency Setting

The switching frequency (F_{OSC}) is set by resistance $R7$ between RT and GND.

The relation of resistance $R7$ to switching frequency is shown in a right graph.



Soft Start

Soft start time (T_{SS}) is configurable by the capacitor $C7$ between SS and GND.

The setting value of T_{SS} is given by the equation (2).

$$T_{SS} = C7 \times \frac{V_{REF}}{I_{SS}} = C7 \times \frac{1.26}{2.0 \times 10^{-6}} \text{ [ms]} \quad (2)$$

Power Good

FB constantly monitors V_{OUT} . When FB voltage is lower than 1.05V, PG is pulled down to Low. PG comparator has hysteresis of 50mV. Because PG is open-drain output, you can connect other ICs with PG to realize wired-or with other ICs.

Hiccup Over-Current Protection

Over current limit (I_{CL}) is set by current sensing resistor $R1$ and resistance ($R2$) between V_{IN} and I_{LIM} .
The setting value of I_{CL} is given by the equations (3) and (4).

$$V_{LIM} = R2 \times I_{LIM} = R2 \times 55 \times 10^{-6} \text{ [V]} \quad (3)$$

$$I_{CL} = \frac{V_{LIM}}{R1} = \frac{R2 \times 55 \times 10^{-6}}{R1} \text{ [A]} \quad (4)$$


When the voltage between V_{IN} and $RSNS$ (V_{RSNS}) is higher than the voltage between V_{IN} and I_{LIM} for 15 consecutive times, the protection deems it as over current and stops the IC.

Stop period (T_{HIC}) is defined by the external capacitor ($C8$) of the C-HICCUP.

The setting value of T_{HIC} is given by the equations (5).

$$T_{HIC} = \frac{C8 \times V_{tHIC}}{I_{HIC}} = \frac{C8 \times 1.29}{2.0 \times 10^{-6}} \text{ [s]} \quad (5)$$

When C-HICCUP is about 1.29V, the IC starts up. Regardless of a status; whether it starts up or SS charge, once over current is detected, the IC stops again and when the protection does not detect over current status, the IC starts up again.



Design Procedure

Inductor Selection

When conditions for input voltage, output voltage and ripple current are defined, the following equations (6) give inductance value.

$$\left\{ \begin{array}{l} L = \frac{V_{IN} - V_{OUT}}{\Delta I_R} \times T_{ON} \\ T_{ON} = \frac{1}{\{((V_{IN} - V_{OUT}) \div (V_{OUT} + V_F)) + 1\} \times F_{OSC}} \\ \begin{array}{ll} F_{OSC} & : \text{Oscillatory Frequency} \\ V_F & : \text{Forward voltage of Schottky Barrier diode} \\ V_{IN} & : \text{Input voltage} \\ V_{OUT} & : \text{Output voltage} \end{array} \end{array} \right\} \quad (6)$$

- Inductor current: Peak value (I_{RP})

Current peak value (I_{RP}) of the inductor is given by the equation (7).

$$I_{RP} = I_{OUT} + \frac{V_{IN} - V_{OUT}}{2L} \times T_{ON} \quad (7)$$

Make sure that rating current value of the inductor is higher than a peak value of ripple current.

- Inductor current: ripple current (ΔI_R)

Ripple current (ΔI_R) is given by the equation (8).

$$\Delta I_R = \frac{V_{IN} - V_{OUT}}{L} \times T_{ON} \quad (8)$$

When load current (I_{OUT}) is less than 1/2 of the ripple current, inductor current flows discontinuously.

Output Capacitor Selection

Make sure to use a capacitor with low impedance for switching power supply because of large ripple current flows through output capacitor.

This IC is a switching regulator which adopts current mode control method. Therefore, you can use capacitor such as ceramic capacitor and OS capacitor in which equivalent series resistance (ESR) is exceedingly small.

Effective value is given by the equation (9) because the ripple current (AC) that flows through output capacitor is saw tooth wave.

$$I_{C_OUT} = \frac{1}{2\sqrt{3}} \times \frac{V_{OUT} \times (V_{IN} - V_{OUT})}{L \times F_{OSC} \times V_{IN}} \quad [\text{Arms}] \quad (9)$$

Input Capacitor Selection

Ripple current flows through input capacitor which is higher than that of the output capacitors.

Therefore, caution is also required for allowable ripple current value.

The effective value of the ripple current flows through input capacitor is given by the equation (10).

$$I_{C_IN} = \sqrt{D(1-D)} \times I_{OUT} \quad [\text{Arms}] \quad (10)$$

$$D = \frac{T_{ON}}{T} = \frac{V_{OUT}}{V_{IN}}$$

In (10), D signifies the ratio between ON/OFF period. When the value is 0.5, the ripple current is at a maximum. Make sure that the input capacitor does not exceed the allowable ripple current value given by equation (10).

In the board wiring from input capacitor, V_{IN} to GND, make sure that wiring is wide enough to keep impedance low because of the current fluctuation. Make sure to connect input capacitor near output capacitor to lower voltage bound due to regeneration current. When change of load current is excessive (I_{OUT}: high ⇒ low), the power of output electric capacitor is regenerated to input capacitor. If input capacitor is small, input voltage increases. Therefore, you need to implement a large input capacitor. Regeneration power changes according to the change of output voltage, inductance of a coil and load current.


Selection of external phase compensation component

This IC adopts current mode control which allows use of ceramic capacitor with low ESR and solid polymer capacitor such as OS capacitor for output capacitor with simple phase compensation. Therefore, you can design long-life and high quality step-down power supply circuit easily.

Frequency Characteristics

The frequency characteristic of this IC is constituted with the following transfer functions.

- | | |
|--|-------------|
| (1) Output resistance breeder | : H_R |
| (2) Voltage gain of error amplifier | : G_{VEA} |
| Current gain | : G_{MEA} |
| (3) Impedance of phase compensation external element | : Z_C |
| (4) Current sense loop gain | : G_{CS} |
| (5) Output smoothing impedance | : Z_O |



Closed loop gain is obtained with the following formula (11).

$$G = H_R \cdot G_{MER} \cdot Z_C \cdot G_{CS} \cdot Z_O$$

$$= \frac{V_{REF}}{V_{OUT}} \cdot G_{MER} \cdot \left(R_C + \frac{1}{sC_C} \right) \cdot G_{CS} \cdot \frac{R_L}{1 + sC_O \cdot R_L} \quad (11)$$

Frequency characteristics of the closed loop gain is given by pole fp1 consists of output capacitor C_O and output load resistance R_L , zero point fz consists of external capacitor C_C of the phase compensation and resistance R_C , and pole fp2 consists of output impedance Z_{ER} of error amplifier and external capacitor of phase compensation C_C as shown in equation (9). fp1, fz, fp2 are obtained with the following equations (12) to (14).

$$fp1 = \frac{1}{2\pi \cdot C_O \cdot R_L} \quad (12)$$

$$fz = \frac{1}{2\pi \cdot C_C \cdot R_C} \quad (13)$$

$$fp2 = \frac{1}{2\pi \cdot Z_{ER} \cdot C_C} \quad (14)$$

Calculation of external phase compensation constant

Generally, to stabilize switching regulator, the frequency where closed loop gain is 1 (zero-cross frequency f_{ZC}) should be $\frac{1}{10}$ of the switching frequency (or $\frac{1}{5}$). Since the switching frequency of this IC is 330kHz, the zero-cross frequency should be 33kHz. Based on the above condition, we obtain the following formula (15).

$$\frac{V_{REF}}{V_{OUT}} \cdot G_{MER} \cdot \left(R_C + \frac{1}{SCC} \right) \cdot G_{CS} \cdot \frac{R_L}{1 + SC_O \cdot R_L} = 1 \quad (15)$$

As for zero-cross frequency, since the impedance element of phase compensation is $R_C \gg \frac{1}{SCC}$, the following equation (16) is obtained.

$$\frac{V_{REF}}{V_{OUT}} \cdot G_{MER} \cdot R_C \cdot G_{CS} \cdot \frac{R_L}{1 + 2\pi \cdot f_{ZC} \cdot C_O \cdot R_L} = 1 \quad (16)$$

Phase compensation external resistance can be obtained with the following equation (16), the variation of the equation (17). Since $2\pi \cdot f_{ZC} \cdot C_O \cdot R_L \gg 1$ in the equation (17), we know that the external resistance is independent of load resistance.

$$R_C = \frac{V_{OUT}}{V_{REF}} \cdot \frac{1}{G_{MER}} \cdot \frac{1}{G_{CS}} \cdot \frac{1 + 2\pi \cdot f_{ZC} \cdot C_O \cdot R_L}{R_L} \quad (17)$$

When output is 5V and load resistance is 5Ω (1A load), R_{SNS} is 30mΩ, the resistances of phase compensation are as follows.

$$\begin{aligned} G_{CS} &= \frac{0.125}{R_{SNS}} = 4.167A/V, G_{MER} = 250\mu A/V, f_{ZC} = 33kHz \\ R_C &= \frac{5}{1.26} \times \frac{1}{250 \times 10^{-6}} \times \frac{1}{4.167} \times \frac{1 + 2 \times 3.14 \times (33 \times 10^3) \times (30 \times 10^{-6}) \times 5}{5} = 24.45... \times 10^3 \\ &= 24.45 [k\Omega] \end{aligned}$$

If frequency of zero point f_z and pole f_{p1} are in the same position, they cancel out each other. Therefore, only the pole frequency remains for frequency characteristics of the closed loop gain.


In other words, gain decreases at -20dB/dec and phase only rotates by 90° and this allows characteristics where oscillation never occurs.

$$\begin{aligned} f_{p1} &= f_z \\ \frac{1}{2\pi \cdot C_O \cdot R_L} \cdot \frac{1}{2\pi \cdot C_O \cdot R_C} \\ C_C &= \frac{R_L \cdot C_O}{R_C} \cdot \frac{5 \times (30 \times 10^{-6})}{24.45 \times 10^3} = 6.13... \times 10^{-9} \\ &= 6.13 [nF] \end{aligned}$$

The above shows external compensation constant obtained through ideal equations. In reality, we need to define phase constant through testing to verify constant IC operation at all temperature range, load range and input voltage range. In the evaluation board for delivery, phase compensation constants are defined based on the above constants. The zero-cross frequency required in the actual system board, in other word, transient response is adjusted by external compensation resistance. Also, if the influence of noise is significant, use of external phase compensation capacitor with higher value is recommended.

Caution in pattern design

Pattern design of the board affects the characteristics of DC-DC converter. This IC switches high current at a high speed. Therefore, if inductance element in a pattern wiring is high, it could be the cause of noise. Make sure that the pattern of the main circuit is wide and short.



(1) Pattern design of the input capacitor

Connect a capacitor near the IC for noise reduction between V_{IN} and the GND. The change of current is at the largest in the pattern between an input capacitor and V_{IN} as well as between GND and an input capacitor among all the main circuits. Hence make sure that the pattern is as thick and short as possible.

(2) Pattern design of an inductor and the output capacitor

High electric current flows into the choke coil and the output capacitor. Therefore this pattern should also be as thick and short as possible.

(3) Pattern design with current channel into consideration

Make sure that when High side MOSFET is ON (red arrow) and OFF (orange arrow), the two current channels runs through the same channel and an area is minimized.

(4) Pattern design of the capacitor between V_{IN} -PDR

Make sure that the pattern of the capacitor between V_{IN} and PDR is as short as possible.

(5) Pattern design of the RSNS

RSNS pattern should also be as think and short as possible for noise reduction.

(6) Pattern design of the small signal GND

The GND of the small signal should be separated from the power GND.

(7) Pattern design of the FB-OUT line

Wire the line shown in red between FB and OUT to the output capacitor as near as possible. When the influence of noise is significant, use of feedback resistors R2 and R3 with lower value is recommended.










Fig: FB-OUT Line

Typical Performance Characteristics
Application curves at $T_a = 25^\circ\text{C}$




Operation Waveforms (Circuit from Typical Application, $T_a = 25^\circ\text{C}$, $V_{IN} = 15\text{V}$, $V_{OUT} = 5\text{V}$)




Discontinuous current mode

$I_{OUT} = 200\text{mA}$




Output Voltage

$I_{OUT} = 200\text{mA}$




Continuous current mode

$I_{OUT} = 2\text{A}$




Output Voltage

$I_{OUT} = 2\text{A}$




Load Transient response

$I_{OUT} = 0.5 \leftrightarrow 2.5\text{A}$, Slew Rate = $100\mu\text{s}$




Soft start and shutdown

$I_{OUT} = 2\text{A}$











Over current protection



OUT - GND short



LV5069JA

Characterization curves at $T_a = 25^\circ\text{C}$, $V_{IN} = 15\text{V}$





ON Semiconductor and the ON logo are registered trademarks of Semiconductor Components Industries, LLC (SCILLC). SCILLC owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of SCILLC's product/patent coverage may be accessed at www.onsemi.com/site/pdf/Patent-Marking.pdf. SCILLC reserves the right to make changes without further notice to any products herein. SCILLC makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does SCILLC assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in SCILLC data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. SCILLC does not convey any license under its patent rights nor the rights of others. SCILLC products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the SCILLC product could create a situation where personal injury or death may occur. Should Buyer purchase or use SCILLC products for any such unintended or unauthorized application, Buyer shall indemnify and hold SCILLC and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that SCILLC was negligent regarding the design or manufacture of the part. SCILLC is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.