M37272M6H/M8H/MAH/MFH–XXXSP/FP
M37272E8SP/FP, M37272EFSP/FP

SINGLE-CHIP 8-BIT CMOS MICROCOMPUTER with CLOSED CAPTION DECODER and ON-SCREEN DISPLAY CONTROLLER

1. DESCRIPTION

The M37272M6H/M8H/MAH/MFH-XXXSP/FP are single-chip microcomputers designed with CMOS silicon gate technology. They have a OSD, data slicer, and I^2C-BUS interface, so it is useful for a channel selection system for TV with a closed caption decoder.

The features of the M37272E8SP/FP and M37272EFSP/FP are similar to those of the M37272M6H-XXXSP/FP except that the chip has a built-in PROM which can be written electrically. The difference between M37272M6H/M8H/MAH/MFH-XXXSP/FP are the ROM size and RAM size. Accordingly, the following descriptions will be for the M37272M6H-XXXSP/FP.

2. FEATURES

- Number of basic instructions 71
- Memory size
  - ROM ..... 24K bytes (M37272M6H-XXXSP/FP)
    32K bytes (M37272M8H-XXXSP/FP, M37272E8SP/FP)
    40K bytes (M37272MAH-XXXSP/FP)
    60K bytes (M37272MFH-XXXSP/FP, M37272EFSP/FP)
  - RAM ..... 1024 bytes (M37272M6H-XXXSP/FP)
    1152 bytes (M37272M8H-XXXSP/FP, M37272E8SP/FP)
    1472 bytes (M37272MAH-XXXSP/FP, M37272MFH-XXXSP/FP, M37272EFSP/FP)
  - (*ROM correction memory included)
- Minimum instruction execution time ..... 0.5 µs (at 8 MHz oscillation frequency)
- Power source voltage ..... 5 V ± 10 %
- Subroutine nesting ..... 128 levels (Max.)
- Interrupts ..... 17 types, 16 vectors
- 8-bit timers 6
- Programmable I/O ports (Ports P0, P1, P2, $P3_0$, $P3_1$) 26
- Input ports (Ports $P5_0$, $P5_1$) 2
- Output ports (Ports $P5_2$–$P5_5$) 4
- 12 V withstand ports 6
- LED drive ports 4
- Serial I/O ..... 8-bit × 1 channel
- Multi-master I^2C-BUS interface ..... 1 (2 systems)
- A-D comparator (6-bit resolution) ..... 6 channels
- PWM output circuit ..... 8-bit × 6
- Power dissipation
  - In high-speed mode ..... 165 mW (at V_{CC} = 5.5V, 8 MHz oscillation frequency, OSD on, and Data slicer on)
  - In low-speed mode ..... 0.33 mW (at V_{CC} = 5.5V, 32 kHz oscillation frequency)
- ROM correction function ..... 2 vectors
- Closed caption data slicer
- OSD function
  - Display characters ..... 32 characters × 2 lines (It is possible to display 3 lines or more by software)
  - Kinds of characters ..... 254 kinds
  - Character display area ..... CC mode: 16 × 26 dots
    OSD mode: 16 × 20 dots
  - Kinds of character sizes ..... CC mode: 1 kind
    OSD mode: 8 kinds
  - Kinds of character colors ..... 8 colors (R, G, B)
  - Coloring unit ..... character, character background, raster
  - Display position
    - Horizontal: 128 levels Vertical: 512 levels
  - Attribute .....
    - CC mode: smooth italic, underline, flash, automatic solid space
    - OSD mode: border
  - Smoth roll-up
  - Window function

3. APPLICATION

TV with a closed caption decoder


M37272M6H/M8H/MAH/MFH–XXXSP/FP
M37272E8SP/FP, M37272EFSP/FP

SINGLE-CHIP 8-BIT CMOS MICROCOMPUTER with CLOSED CAPTION DECODER
and ON-SCREEN DISPLAY CONTROLLER

TABLE OF CONTENTS

1. DESCRIPTION 1
2. FEATURES 1
3. APPLICATION 1
4. PIN CONFIGURATION 3
5. FUNCTIONAL BLOCK DIAGRAM 4
6. PERFORMANCE OVERVIEW 5
7. PIN DESCRIPTION 7
8. FUNCTIONAL DESCRIPTION 11
    8.1 CENTRAL PROCESSING UNIT (CPU) 11
    8.2 MEMORY 12
    8.3 INTERRUPTS 18
    8.4 TIMERS 23
    8.5 SERIAL I/O 26
    8.6 MULTI-MASTER I2C-BUS INTERFACE 29
    8.7 PWM OUTPUT FUNCTION 42
    8.8 A-D COMPARATOR 46
    8.9 ROM CORRECTION FUNCTION 48
    8.10 DATA SLICER 49
    8.11 OSD FUNCTIONS 60
        8.11.1 Display Position 65
        8.11.2 Dot Size 69
        8.11.3 Clock for OSD 70
        8.11.4 Field Determination Display 71
        8.11.5 Memory for OSD 73
        8.11.6 Character color 77
        8.11.7 Character background color 77
        8.11.8 OUT1, OUT2 signals 78
        8.11.9 Attribute 79
        8.11.10 Multiline Display 84
        8.11.11 Automatic Solid Space Function 85
        8.11.12 Window Function 86
        8.11.13 OSD Output Pin Control 88
        8.11.14 Raster Coloring Function 89
    8.12 SOFTWARE RUNAWAY DETECT FUNCTION 91
    8.13. RESET CIRCUIT 92
    8.14 CLOCK GENERATING CIRCUIT 93
    8.15 DISPLAY OSCILLATION CIRCUIT 96
    8.16 AUTO-CLEAR CIRCUIT 96
    8.17 ADDRESSING MODE 96
    8.18 MACHINE INSTRUCTIONS 96
9. PROGRAMMING NOTES 96
10. ABSOLUTE MAXIMUM RATINGS 97
11. RECOMMENDED OPERATING CONDITIONS 97
12. ELECTRIC CHARACTERISTICS 98
13. A-D CONVERTER CHARACTERISTICS 100
14. MULTI-MASTER I2C-BUS BUS LINE CHARACTERISTICS 100
15. PROM PROGRAMMING METHOD 101
16. DATA REQUIRED FOR MASK ORDERS 102
17. ONE TIME PROM VERSION M37272E8SP/FP, M37272EFSP/FP MARKING 103
18. APPENDIX 104
19. PACKAGE OUTLINE 129


4. PIN CONFIGURATION



Outline 42P4B

Note: Only 14th pin is NC pin of M37272M6H/M8H/MAH/MFH-XXXSP. This pin is AVcc pin of M37272E8/EFSP. But NC pin of M37272M6H/M8H/MAH/MFH-XXX SP is not connect in the IC. You can apply to Vcc.

Fig. 4.1 Pin Configuration (1) (Top View)



Outline 42P2R-A/E

Note: Only 14th pin is NC pin of M37272M6H/M8H/MAH/MFH-XXXFP. This pin is AVcc pin of M37272E8/EFSP. But NC pin of M37272M6H/M8H/MAH/MFH-XXX SP is not connect in the IC. You can apply to Vcc.

Fig. 4.2 Pin Configuration (2) (Top View)

5. FUNCTIONAL BLOCK DIAGRAM




Fig. 5.1 Functional Block Diagram of M37272

6. PERFORMANCE OVERVIEW

Table 6.1 Performance Overview

Parameter				Functions
Number of basic instructions				71
Instruction execution time				0.5 μs (the minimum instruction execution time, at 8 MHz oscillation frequency)
Clock frequency				8 MHz (maximum)
Memory size	ROM	M37272M6H-XXXSP/FP		24K bytes
		M37272M8H-XXXSP/FP,M37272E8SP/FP		32K bytes
		M37272MAH-XXXSP/FP		40K bytes
		M37272MFH-XXXSP/FP, M37272EFSP/FP		60K bytes
	RAM	M37272M6H-XXXSP/FP		1024 bytes (ROM correction memory included)
		M37272M8H-XXXSP/FP,M37272E8SP/FP		1152 bytes (ROM correction memory included)
		M37272MAH-XXXSP/FP, M37272MFH-XXXSP/FP, M37272EFSP/FP		1472 bytes (ROM correction memory included)
	OSD ROM			10K bytes
	OSD RAM			128 bytes
Input/Output ports	P0		I/O	8-bit × 1 (N-channel open-drain output structure, can be used as PWM output pins, INT input pins, A-D input pin)
	$P1_0$–$P1_7$		I/O	8-bit × 1 (CMOS input/output structure, however, N-channel open-drain output structure, when $P1_1$–$P1_4$ are used as multi-master I^2C-BUS interface, can be used as OSD output pin, A-D input pins, INT input pin, multi-master I^2C-BUS interface)
	$P2_0$–$P2_7$		I/O	8-bit × 1 (P2 is CMOS input/output structure, however, N-channel open-drain output structure when $P2_0$ and 2_1 are used as serial output, can be used as serial input/output pins, timer external clock input pins, OSD clock input/output pin, sub-clock input/output pins)
	$P3_0$, $P3_1$		I/O	2-bit × 1 (CMOS input/output or N-channel open-drain output structure, can be used as A-D input pins)
	$P5_0$, $P5_1$		Input	2-bit × 1 (can be used as OSD input pins)
	$P5_2$–$P5_5$		Output	4-bit × 1 (CMOS output structure, can be used as OSD output pins)
Serial I/O				8-bit × 1
Multi-master I^2C-BUS interface				1 (2 systems)
A-D comparator				6 channels (6-bit resolution)
PWM output circuit				8-bit × 6
Timers				8-bit timer × 6
ROM correction function				2 vectors
Subroutine nesting				128 levels (maximum)
Interrupt				<17 types> INT external interrupt × 3, Internal timer interrupt × 6, Serial I/O interrupt × 1, OSD interrupt × 1, Multi-master I^2C-BUS interface interrupt × 1, Data slicer interrupt × 1, f(X_{IN})/4096 interrupt × 1, V_{SYNC} interrupt × 1, BRK instruction interrupt × 1, reset × 1
Clock generating circuit				2 built-in circuits (externally connected to a ceramic resonator or a quartz-crystal oscillator)
Data slicer				Built-in

Table 6.2 Performance Overview (Continued)

Parameter				Functions
OSD function		Number of display characters		32 characters × 2 lines
		Dot structure		CC mode: 16 × 26 dots (character display area : 16 × 20 dots) OSD mode: 16 × 20 dots
		Kinds of characters		254 kinds
		Kinds of character sizes 1 screen : 8		CC mode: 1 kinds OSD mode: 8 kinds
		Character font coloring		1 screen: 8 kinds (per character unit)
		Display position		Horizontal: 128 levels, Vertical: 512 levels
Power source voltage				5V ± 10%
Power dissipation	In high-speed mode	OSD ON	Data slicer ON	165 mW typ. (at oscillation frequency f(XIN) = 8 MHz, fOSC = 27 MHz)
		OSD OFF	Data slicer OFF	82.5 mW typ. (at oscillation frequency f(XIN) = 8 MHz)
	In low-speed mode	OSD OFF	Data slicer OFF	0.33 mW typ. (at oscillation frequency f(XCIN) = 32 kHz, f(XIN) = stopped)
	In stop mode			0.055 mW (maximum)
Operating temperature range				–10 °C to 70 °C
Device structure				CMOS silicon gate process
Package				42-pin plastic molded DIP
				42-pin plastic molded SSOP

7. PIN DESCRIPTION

Table 7.1 Pin Description

Pin	Name	Input/ Output	Functions
V_{CC}, (AV_{CC},) V_{SS}	Power source		Apply voltage of 5 V ± 10 % to (typical) V_{CC} , and 0 V to V_{SS}. When use M37272E8SP/FP, M37272EFSP/FP, apply voltage of 5 V ± 10 % to (typical) AV_{CC}.
CNV_{SS}	CNV_{SS}		This is connected to V_{SS}.
$\overline{RESET}$	Reset input	Input	To enter the reset state, the reset input pin must be kept at a LOW for 2 μs or more (under normal V_{CC} conditions). If more time is needed for the quartz-crystal oscillator to stabilize, this LOW condition should be maintained for the required time.
X_{IN}	Clock input	Input	This chip has an internal clock generating circuit. To control generating frequency, an external ceramic resonator or a quartz-crystal oscillator is connected between pins X_{IN} and X_{OUT}. If an external clock is used, the clock source should be connected to the X_{IN} pin and the X_{OUT} pin should be left open.
X_{OUT}	Clock output	Output	
$P0_0$/PWM0–$P0_5$/PWM5, $P0_6$/INT2/AD4, $P0_7$/INT1	I/O port P0	I/O	Port P0 is an 8-bit I/O port with direction register allowing each I/O bit to be individually programmed as input or output. At reset, this port is set to input mode. The output structure is N-channel open-drain output. (See note 1)
	PWM output	Output	Pins $P0_0$–$P0_5$ are also used as PWM output pins PWM0–PWM5 respectively. The output structure is N-channel open-drain output.
	External interrupt input	Input	Pins $P0_6$ and $P0_7$ are also used as INT external interrupt input pins INT2 and INT1 respectively.
	Analog input	Input	$P0_6$ pin is also used as analog input pin AD4.
$P1_0$/OUT2, $P1_1$/SCL1, $P1_2$/SCL2, $P1_3$/SDA1, $P1_4$/SDA2, $P1_5$/AD1/INT3, $P1_6$/AD2, $P1_7$/AD3	I/O port P1	I/O	Port P1 is an 8-bit I/O port and has basically the same functions as port P0. The output structure is CMOS output. (See note 1)
	OSD output	Output	Pins $P1_0$ is also used as OSD output pin OUT2. The output structure is CMOS output.
	Multi-master I^2C-BUS interface	I/O	Pins $P1_1$–$P1_4$ are used as SCL1, SCL2, SDA1 and SDA2 respectively, when multi-master I^2C-BUS interface is used. The output structure is N-channel open-drain output.
	Analog input	Input	Pins $P1_0$, $P1_5$–$P1_7$ are also used as analog input pin AD8, AD1–AD3 respectively.
	External interrupt input	Input	$P1_5$ pin is also used as INT external interrupt input pin INT3.
$P2_0$/S_{CLK}, $P2_1$/S_{OUT}, $P2_2$/S_{IN}, $P2_3$/TIM3, $P2_4$/TIM2, $P2_5$, $P2_6$/OSC1/ X_{CIN}, $P2_7$/OSC2/ X_{COUT}	I/O port P2	I/O	Port P2 is an 8-bit I/O port and has basically the same functions as port P0. The output structure is CMOS output. (See note 1)
	Serial I/O synchronous clock input/output port	I/O	$P2_0$ pin is also used as serial I/O synchronous clock input/output pin S_{CLK}. The output structure is N-channel open-drain output.
	Serial I/O data output	I/O	$P2_1$ pin is also used as serial I/O data output pin S_{OUT}. The output structure is open-drain output.
	Serial I/O data input	Input	$P2_2$ pin is also used as serial I/O data input pin S_{IN}.
	External clock input for timer	Input	Pins $P2_3$ and $P2_4$ are also used as timer external clock input pins TIM3 and TIM2 respectively.
	Clock input for OSD	Input	$P2_6$ pin is also used as OSD clock input pin OSC1. (See note 2)
	Clock output for OSD	Output	$P2_7$ pin is also used as OSD clock input pin OSC2. The output structure is CMOS output. (See note 2)
	Sub-clock input	Input	$P2_6$ pin is also used as sub-clock input pin X_{CIN}.
	Sub-clock output	Output	$P2_7$ pin is also used as sub-clock output pin X_{COUT}.


Table 7.2 Pin Description (continued)

Pin	Name	Input/ Output	Functions
$P3_0$/AD5, $P3_1$/AD6	I/O port P3	I/O	Ports $P3_0$ and $P3_1$ are a 2-bit I/O port and has basically the same functions as port 0. The output structure can be selected either CMOS output or N-channel open-drain output structure. (See notes 1, 3)
	Analog input	Input	Pins $P3_0$ and $P3_1$ are also used as analog input pins AD5 and AD6 respectively.
$P5_0$/H_{SYNC}, $P5_1$/V_{SYNC}	Input port P5	Input	Pin $P5_0$ and $P5_1$ are 2-bit input ports.
	H_{SYNC} input	Input	Pin $P5_0$ is also used as H_{SYNC} input. This is a horizontal synchronous signal input for OSD.
	V_{SYNC} input	Input	Pin $P5_1$ is also used as V_{SYNC} input. This is a vertical synchronous signal input for OSD.
$P5_2$/R, $P5_3$/G, $P5_4$/B, $P5_5$/OUT1	Output port P5	Output	Ports $P5_2$–$P5_5$ are a 4-bit output port. The output structure is CMOS output.
	OSD output	Output	Pins $P5_2$–$P5_5$ are also used as OSD output pins R, G, B, OUT1 respectively. The output structure is CMOS output.
CV_{IN}	I/O for data slicer	Input	Input composite video signal through a capacitor.
V_{HOLD}		Input	Connect a capacitor between V_{HOLD} and Vss.
HLF		I/O	Connect a filter using of a capacitor and a resistor between HLF and Vss.

Notes 1: Port Pi (i = 0 to 3) has the port Pi direction register which can be used to program each bit as an input (“0”) or an output (“1”). The pins programmed as “1” in the direction register are output pins. When pins are programmed as “0,” they are input pins. When pins are programmed as output pins, the output data are written into the port latch and then output. When data is read from the output pins, the output pin level is not read but the data of the port latch is read. This allows a previously-output value to be read correctly even if the output LOW voltage has risen, for example, because a light emitting diode was directly driven. The input pins are in the floating state, so the values of the pins can be read. When data is written into the input pin, it is written only into the port latch, while the pin remains in the floating state.

2: To switch output functions, set the raster color register and OSD control register. When pins $P2_6$ and $P2_7$ are used as the OSD clock input/output pins, set the corresponding bits of the port P2 direction register to “0” (input mode).

3: To switch output structures, set bits 2 and 3 of the port P3 direction register, When “0,” CMOS output ; when “1,” N-channel open-drain output.



Notes 1: Each port is also used as follows :

P10 : OUT2	P20 : SCLK
P11 : SCL1	P21 : SOUT
P12 : SCL2	P22 : SIN
P13 : SDA15	P23 : TIM3
P14 : SDA2	P24 : TIM2
P15 : AD1/INT3	P30 : AD5
P16 : AD2	P31 : AD6
P17 : AD3	

2: The output structure of ports P30 and P31 can be selected either CMOS output or N-channel open-drain output structure (when selecting N-channel open-drain, it is the same with P06 and P07).

3: The output structure of ports P11–P14 is N-channel open-drain output when using as multi-master I^2C-BUS interface (it is the same with P06 and P07).

4: The output structure of ports P20 and P21 is N-channel open-drain output when using as serial output (it is the same as P06 and P07).

Fig. 7.1 I/O Pin Block Diagram (1)




Fig. 7.2 I/O Pin Block Diagram (2)

8. FUNCTIONAL DESCRIPTION
8.1 CENTRAL PROCESSING UNIT (CPU)

This microcomputer uses the standard 740 Family instruction set. Refer to the table of 740 Family addressing modes and machine instructions or the SERIES 740 <Software> User's Manual for details on the instruction set.

Machine-resident 740 Family instructions are as follows:

The FST, SLW instruction cannot be used.

The MUL, DIV, WIT and STP instructions can be used.

8.1.1 CPU Mode Register

The CPU mode register contains the stack page selection bit and internal system clock selection bit. The CPU mode register is allocated at address 00FB16.

CPU Mode Register

b7 b6 b5 b4 b3 b2 b1 b0

			1	1		0	0

CPU mode register (CM) [Address 00FB16]

B	Name	Functions	After reset	R	W
0, 1	Processor mode bits (CM0, CM1)	b1 b0 0 0: Single-chip mode 0 1: 1 0: 1 1: } Not available	0	R	W
2	Stack page selection bit (CM2) (See note)	0: 0 page 1: 1 page	1	R	W
3, 4	Fix these bits to 1.		1	R	W
5	XCOUT drivability selection bit (CM5)	0: LOW drive 1: HIGH drive	1	R	W
6	Main Clock (XIN—XOUT) stop bit (CM6)	0: Oscillating 1: Stopped	0	R	W
7	Internal system clock selection bit (CM7)	0: XIN—XOUT selected (high-speed mode) 1: XCIN—XCOUT selected (high-speed mode)	0	R	W

Note: This bit is set to 1 after the reset release.

Fig. 8.1.1 CPU Mode Register

8.2 MEMORY

8.2.1 Special Function Register (SFR) Area

The special function register (SFR) area in the zero page contains control registers such as I/O ports and timers.

8.2.2 RAM

RAM is used for data storage and for stack area of subroutine calls and interrupts.

8.2.3 ROM

ROM is used for storing user programs as well as the interrupt vector area.

8.2.4 OSD RAM

RAM for display is used for specifying the character codes and colors to display.

8.2.5 OSD ROM

ROM for display is used for storing character data.

8.2.6 Interrupt Vector Area

The interrupt vector area contains reset and interrupt vectors.

8.2.7 Zero Page

The 256 bytes from addresses 0000_{16} to $00FF_{16}$ are called the zero page area. The internal RAM and the special function registers (SFR) are allocated to this area.

The zero page addressing mode can be used to specify memory and register addresses in the zero page area. Access to this area with only 2 bytes is possible in the zero page addressing mode.

8.2.8 Special Page

The 256 bytes from addresses $FF00_{16}$ to $FFFF_{16}$ are called the special page area. The special page addressing mode can be used to specify memory addresses in the special page area. Access to this area with only 2 bytes is possible in the special page addressing mode.

8.2.9 ROM Correction Memory (RAM)

This is used as the program area for ROM correction.





Fig. 8.2.1 Memory Map (M37272M6H/M8H-XXXSP/FP, M37272E8SP/FP)

■ M37272MAH/MFH-XXXSP/FP, M37272EFSP/FP



Note: Refer to Table 8.11.3 OSD RAM.

Fig. 8.2.2 Memory Map (M37272MAH/MFH-XXXSP/FP, M37272EFSP/FP)

<Bit allocation>

: } Function bit
Name :

: No function bit

0 : Fix this bit to "0" (do not write "1")

1 : Fix this bit to "1" (do not write "0")

<State immediately after reset>

0 : "0" immediately after reset

1 : "1" immediately after reset

? : Indeterminate immediately after reset

Address	Register	Bit allocation b7	b6	b5	b4	b3	b2	b1	b0	State immediately after reset b7	b6	b5	b4	b3	b2	b1	b0
$C0_{16}$	Port P0 (P0)									?							
$C1_{16}$	Port P0 direction register (D0)									00_{16}							
$C2_{16}$	Port P1 (P1)									?							
$C3_{16}$	Port P1 direction register (D1)									00_{16}							
$C4_{16}$	Port P2 (P2)									?							
$C5_{16}$	Port P2 direction register (D2)									00_{16}							
$C6_{16}$	Port P3 (P3)							P31	P30	0	0	0	0	0	0	?	?
$C7_{16}$	Port P3 direction register (D3)		T3SC			P31C	P30C	P31D	P30D	00_{16}							
$C8_{16}$										?							
$C9_{16}$										?							
CA_{16}	Port P5 (P5)									?							
CB_{16}	OSD port control register (PF)	PF7		PF5	PF4	PF3	PF2	0	0	00_{16}							
CC_{16}		00_{16}								00_{16}							
CD_{16}										?							
CE_{16}	Caption data register 3 (CD3)	CDL27	CDL26	CDL25	CDL24	CDL23	CDL22	CDL21	CDL20	?							
CF_{16}	Caption data register 4 (CD4)	CDH27	CDH26	CDH25	CDH24	CDH23	CDH22	CDH21	CDH20	?							
$D0_{16}$	OSD control register (OC)	0	OC6	OC5	OC4	OC3	OC2	OC1	OC0	00_{16}							
$D1_{16}$	Horizontal position register (HP)		HP6	HP5	HP4	HP3	HP2	HP1	HP0	00_{16}							
$D2_{16}$	Block control register 1 (BC1)	BC17	BC16	BC15	BC14	BC13	BC12	BC11	BC10	?							
$D3_{16}$	Block control register 2 (BC2)	BC27	BC26	BC25	BC24	BC23	BC22	BC21	BC20	?							
$D4_{16}$	Vertical position register 1 (VP1)	VP17	VP16	VP15	VP14	VP13	VP12	VP11	VP10	?							
$D5_{16}$	Vertical position register 2 (VP2)	VP27	VP26	VP25	VP24	VP23	VP22	VP21	VP20	?							
$D6_{16}$	Window register 1 (WN1)	WN17	WN16	WN15	WN14	WN13	WN12	WN11	WN10	?							
$D7_{16}$	Window register 2 (WN2)	WN27	WN26	WN25	WN24	WN23	WN22	WN21	WN20	?							
$D8_{16}$	I/O polarity control register (PC)	0	PC6	PC5	PC4	PC3	PC2	PC1	PC0	40_{16}							
$D9_{16}$	Raster color register (RC)	RC7	0	0	RC4	RC3	RC2	RC1	RC0	00_{16}							
DA_{16}										?							
DB_{16}										?							
DC_{16}	Interrupt input polarity control register (RE)						INT3	INT2	INT1	00_{16}							
DD_{16}		00_{16}								00_{16}							
DE_{16}		00_{16}								00_{16}							
DF_{16}		00_{16} (See note 1)								00_{16} (See note 2)							

Notes 1: This is only M37272MAH/MFH-XXXSP/FP, M37272EFSP/FP.
2: As for M37272M6H/M8H-XXXSP/FP and M37272E8SP/FP, the reset value is ? (indeterminate).

Fig. 8.2.3 Memory Map of Special Function Register 1 (SFR1) (1)

■ SFR1 Area (addresses $E0_{16}$ to FF_{16})

<Bit allocation>

: } Function bit

Name : } Function bit

: No function bit

0 : Fix this bit to "0" (do not write "1")

1 : Fix this bit to "1" (do not write "0")

<State immediately after reset>

0 : "0" immediately after reset

1 : "1" immediately after reset

? : Indeterminate immediately after reset

Address	Register	Bit allocation b7							b0	State immediately after reset b7							b0
$E0_{16}$	Data slicer control register 1 (DSC1)	0	1	1	0	0	DSC12	DSC11	DSC10	00_{16}							
$E1_{16}$	Data slicer control register 2 (DSC2)		0	DSC25	DSC24	DSC23		1	DSC20	?	0	?	0	?	?	0	?
$E2_{16}$	Caption data register 1 (CD1)	CDL17	CDL16	CDL15	CDL14	CDL13	CDL12	CDL11	CDL10	00_{16}							
$E3_{16}$	Caption data register 2 (CD2)	CDH17	CDH16	CDH15	CDH14	CDH13	CDH12	CDH11	CDH10	00_{16}							
$E4_{16}$	Clock run-in detect register (CRD)	CRD7	CRD6	CRD5	CRD4	CRD3				00_{16}							
$E5_{16}$	Data clock position register (DPS)	DPS7	DPS6	DPS5	DPS4	DPS3	0	1	0	09_{16}							
$E6_{16}$	Caption position register (CPS)	CPS7	CPS6	CPS5	CPS4	CPS3	CPS2	CPS1	CPS0	0	0	?	0	0	0	0	0
$E7_{16}$	Data slicer test register 2									00_{16}							
$E8_{16}$	Data slicer test register 1									00_{16}							
$E9_{16}$	Synchronous signal counter register			HC5	HC4	HC3	HC2	HC1	HC0	00_{16}							
EA_{16}	Serial I/O register (SIO)									?							
EB_{16}	Serial I/O mode register (SM)	0	SM6	SM5	0	SM3	SM2	SM1	SM0	00_{16}							
EC_{16}	A-D control register 1 (AD1)				ADC14		ADC12	ADC11	ADC10	0	0	0	?	0	0	0	0
ED_{16}	A-D control register 2 (AD2)			ADC25	ADC24	ADC23	ADC22	ADC21	ADC20	00_{16}							
EE_{16}	Timer 5 (T5)									07_{16}							
EF_{16}	Timer 6 (T6)									FF_{16}							
$F0_{16}$	Timer 1 (T1)									FF_{16}							
$F1_{16}$	Timer 2 (T2)									07_{16}							
$F2_{16}$	Timer 3 (T3)									FF_{16}							
$F3_{16}$	Timer 4 (T4)									07_{16}							
$F4_{16}$	Timer mode register 1 (TM1)	TM17	TM16	TM15	TM14	TM13	TM12	TM11	TM10	00_{16}							
$F5_{16}$	Timer mode register 2 (TM2)	TM27	TM26	TM25	TM24	TM23	TM22	TM21	TM20	00_{16}							
$F6_{16}$	I^2C data shift register (S0)	D7	D6	D5	D4	D3	D2	D1	D0	?							
$F7_{16}$	I^2C address register (S0D)	SAD6	SAD5	SAD4	SAD3	SAD2	SAD1	SAD0	RBW	00_{16}							
$F8_{16}$	I^2C status register (S1)	MST	TRX	BB	PIN	AL	AAS	AD0	LRB	0	0	0	1	0	0	0	?
$F9_{16}$	I^2C control register (S1D)	BSEL1	BSEL0	10BIT SAD	ALS	ESO	BC2	BC1	BC0	00_{16}							
FA_{16}	I^2C clock control register (S2)	ACK	ACK BIT	FAST MODE	CCR4	CCR3	CCR2	CCR1	CCR0	00_{16}							
FB_{16}	CPU mode register (CPUM)	CM7	CM6	CM5	1	1	CM2	0	0	$3C_{16}$							
FC_{16}	Interrupt request register 1 (IREQ1)		IN3R	VSCR	OSDR	TM4R	TM3R	TM2R	TM1R	00_{16}							
FD_{16}	Interrupt request register 2 (IREQ2)	0	TM56R	IICR	IN2R	CKR	S1R	DSR	IN1R	00_{16}							
FE_{16}	Interrupt control register 1 (ICON1)		IN3E	VSCE	OSDE	TM4E	TM3E	TM2E	TM1E	00_{16}							
FF_{16}	Interrupt control register 2 (ICON2)	TM56C	TM56E	IICE	IN2E	CKE	S1E	DSE	IN1E	00_{16}							

Fig. 8.2.4 Memory Map of Special Function Register 1 (SFR1) (2)

■ SFR2 Area (addresses 200_{16} to $20F_{16}$)

<Bit allocation>

: Function bit (Name)

: No function bit

0 : Fix this bit to "0" (do not write "1")

1 : Fix this bit to "1" (do not write "0")

<State immediately after reset>

0 : "0" immediately after reset

1 : "1" immediately after reset

? : Indeterminate immediately after reset

Address	Register	Bit allocation b7 b0	State immediately after reset b7 b0
200_{16}	PWM0 register (PWM0)		?
201_{16}	PWM1 register (PWM1)		?
202_{16}	PWM2 register (PWM2)		?
203_{16}	PWM3 register (PWM3)		?
204_{16}	PWM4 register (PWM4)		?
205_{16}	PWM5 register (PWM5)		?
206_{16}		00_{16}	?
207_{16}		00_{16}	?
208_{16}	PWM mode register 1 (PM1)	PM13 PM10	? ? ? ? 0 ? ? 0
209_{16}	PWM mode register 2 (PM2)	0 0 PM25 PM24 PM23 PM22 PM21 PM20	00_{16}
$20A_{16}$	ROM correction address 1 (high-order)		00_{16}
$20B_{16}$	ROM correction address 1 (low-order)		00_{16}
$20C_{16}$	ROM correction address 2 (high-order)		00_{16}
$20D_{16}$	ROM correction address 2 (low-order)		00_{16}
$20E_{16}$	ROM correction enable register (RCR)	RC1 RC0	00_{16}
$20F_{16}$			?

Fig. 8.2.5 Memory Map of Special Function Register 2 (SFR2)




Fig. 8.2.6 Internal State of Processor Status Register and Program Counter at Reset

8.3 INTERRUPTS

Interrupts can be caused by 17 different sources consisting of 4 external, 11 internal, 1 software, and reset. Interrupts are vectored interrupts with priorities as shown in Table 8.3.1. Reset is also included in the table because its operation is similar to an interrupt.

When an interrupt is accepted,

① The contents of the program counter and processor status register are automatically stored into the stack.

② The interrupt disable flag I is set to "1" and the corresponding interrupt request bit is set to "0."

③ The jump destination address stored in the vector address enters the program counter.

Other interrupts are disabled when the interrupt disable flag is set to "1."

All interrupts except the BRK instruction interrupt have an interrupt request bit and an interrupt enable bit. The interrupt request bits are in interrupt request registers 1 and 2 and the interrupt enable bits are in interrupt control registers 1 and 2. Figures 8.3.2 to 8.3.6 show the interrupt-related registers.

Interrupts other than the BRK instruction interrupt and reset are accepted when the interrupt enable bit is "1," interrupt request bit is "1," and the interrupt disable flag is "0." The interrupt request bit can be set to "0" by a program, but not set to "1." The interrupt enable bit can be set to "0" and "1" by a program.

Reset is treated as a non-maskable interrupt with the highest priority. Figure 8.3.1 shows interrupt control.

8.3.1 Interrupt Causes

(1) VSYNC, OSD interrupts

The VSYNC interrupt is an interrupt request synchronized with the vertical sync signal.

The OSD interrupt occurs after character block display to the CRT is completed.

(2) INT1 to INT3 external interrupts

The INT1 to INT3 interrupts are external interrupt inputs, the system detects that the level of a pin changes from LOW to HIGH or from HIGH to LOW, and generates an interrupt request. The input active edge can be selected by bits 3 to 5 of the interrupt input polarity register (address $00DC_{16}$) : when this bit is "0," a change from LOW to HIGH is detected; when it is "1," a change from HIGH to LOW is detected. Note that both bits are cleared to "0" at reset.

(3) Timers 1 to 4 interrupts

An interrupt is generated by an overflow of timers 1 to 4.

Table 8.3.1 Interrupt Vector Addresses and Priority

Priority	Interrupt Source	Vector Addresses	Remarks
1	Reset	$FFFF_{16}$, $FFFE_{16}$	Non-maskable
2	OSD interrupt	$FFFD_{16}$, $FFFC_{16}$	
3	INT1 external interrupt	$FFFB_{16}$, $FFFA_{16}$	Active edge selectable
4	Data slicer interrupt	$FFF9_{16}$, $FFF8_{16}$	
5	Serial I/O interrupt	$FFF7_{16}$, $FFF6_{16}$	
6	Timer 4 interrupt	$FFF5_{16}$, $FFF4_{16}$	
7	f(XIN)/4096 interrupt	$FFF3_{16}$, $FFF2_{16}$	
8	VSYNC interrupt	$FFF1_{16}$, $FFF0_{16}$	
9	Timer 3 interrupt	$FFEF_{16}$, $FFEE_{16}$	
10	Timer 2 interrupt	$FFED_{16}$, $FFEC_{16}$	
11	Timer 1 interrupt	$FFEB_{16}$, $FFEA_{16}$	
12	INT3 external interrupt	$FFE9_{16}$, $FFE8_{16}$	Active edge selectable
13	INT2 external interrupt	$FFE7_{16}$, $FFE6_{16}$	Active edge selectable
14	Multi-master I^2C-BUS interface interrupt	$FFE5_{16}$, $FFE4_{16}$	
15	Timer 5 • 6 interrupt	$FFE3_{16}$, $FFE2_{16}$	Source switch by software (see note)
16	BRK instruction interrupt	$FFDF_{16}$, $FFDE_{16}$	Non-maskable

Note: Switching a source during a program causes an unnecessary interrupt. Therefore, set a source at initializing of program.

(4) Serial I/O interrupt

This is an interrupt request from the clock synchronous serial I/O function.

(5) f(XIN)/4096 interrupt

The f (XIN)/4096 interrupt occurs regularly with a f(XIN)/4096 period. Set bit 0 of the PWM mode register 1 to “0.”

(6) Data slicer interrupt

An interrupt occurs when slicing data is completed.

(7) Multi-master I²C-BUS interface interrupt

This is an interrupt request related to the multi-master I²C-BUS interface.

(8) Timer 5 • 6 interrupt

An interrupt is generated by an overflow of timer 5 or 6. Their priorities are same, and can be switched by software.

(9) BRK instruction interrupt

This software interrupt has the least significant priority. It does not have a corresponding interrupt enable bit, and it is not affected by the interrupt disable flag I (non-maskable).





Fig. 8.3.1 Interrupt Control

Interrupt Request Register 1




Interrupt request register 1 (IREQ1) [Address $00FC_{16}$]

B	Name	Functions	After reset	R	W
0	Timer 1 interrupt request bit (TM1R)	0 : No interrupt request issued 1 : Interrupt request issued	0	R	✻
1	Timer 2 interrupt request bit (TM2R)	0 : No interrupt request issued 1 : Interrupt request issued	0	R	✻
2	Timer 3 interrupt request bit (TM3R)	0 : No interrupt request issued 1 : Interrupt request issued	0	R	✻
3	Timer 4 interrupt request bit (TM4R)	0 : No interrupt request issued 1 : Interrupt request issued	0	R	✻
4	OSD interrupt request bit (OSDR)	0 : No interrupt request issued 1 : Interrupt request issued	0	R	✻
5	V_{SYNC} interrupt request bit (VSCR)	0 : No interrupt request issued 1 : Interrupt request issued	0	R	✻
6	INT3 external interrupt request bit (VSCR)	0 : No interrupt request issued 1 : Interrupt request issued	0	R	✻
7	Nothing is assigned. This bit is a write disable bit. When this bit is read out, the value is “0.”		0	R	—

✻: “0” can be set by software, but “1” cannot be set.

Fig. 8.3.2 Interrupt Request Register 1

Interrupt Request Register 2




Interrupt request register 2 (IREQ2) [Address $00FD_{16}$]

B	Name	Functions	After reset	R	W
0	INT1 external interrupt request bit (INIR)	0 : No interrupt request issued 1 : Interrupt request issued	0	R	✻
1	Data slicer interrupt request bit (DSR)	0 : No interrupt request issued 1 : Interrupt request issued	0	R	✻
2	Serial I/O interrupt request bit (S1R)	0 : No interrupt request issued 1 : Interrupt request issued	0	R	✻
3	f(X_{IN})/4096 interrupt request bit (CKR)	0 : No interrupt request issued 1 : Interrupt request issued	0	R	✻
4	INT2 external interrupt request bit (IN2R)	0 : No interrupt request issued 1 : Interrupt request issued	0	R	✻
5	Multi-master I^2C-BUS interrupt request bit (IICR)	0 : No interrupt request issued 1 : Interrupt request issued	0	R	✻
6	Timer 5 • 6 interrupt request bit (TM56R)	0 : No interrupt request issued 1 : Interrupt request issued	0	R	✻
7	Fix this bit to “0.”		0	R	W

✻: “0” can be set by software, but “1” cannot be set.

Fig. 8.3.3 Interrupt Request Register 2

Interrupt Control Register 1




Interrupt control register 1 (ICON1) [Address $00FE_{16}$]

B	Name	Functions	After reset	R	W
0	Timer 1 interrupt enable bit (TM1E)	0 : Interrupt disabled 1 : Interrupt enabled	0	R	W
1	Timer 2 interrupt enable bit (TM2E)	0 : Interrupt disabled 1 : Interrupt enabled	0	R	W
2	Timer 3 interrupt enable bit (TM3E)	0 : Interrupt disabled 1 : Interrupt enabled	0	R	W
3	Timer 4 interrupt enable bit (TM4E)	0 : Interrupt disabled 1 : Interrupt enabled	0	R	W
4	OSD interrupt enable bit (OSDE)	0 : Interrupt disabled 1 : Interrupt enabled	0	R	W
5	V_{SYNC} interrupt enable bit (VSCE)	0 : Interrupt disabled 1 : Interrupt enabled	0	R	W
6	INT3 external interrupt enable bit (IN3E)	0 : Interrupt disabled 1 : Interrupt enabled	0	R	W
7	Nothing is assigned. This bit is a write disable bit. When this bit is read out, the value is “0.”		0	R	—

Fig. 8.3.4 Interrupt Control Register 1

Interrupt Control Register 2




Interrupt control register 2 (ICON2) [Address $00FF_{16}$]

B	Name	Functions	After reset	R	W
0	INT1 external interrupt enable bit (IN1E)	0 : Interrupt disabled 1 : Interrupt enabled	0	R	W
1	Data slicer interrupt enable bit (DSE)	0 : Interrupt disabled 1 : Interrupt enabled	0	R	W
2	Serial I/O interrupt enable bit (S1E)	0 : Interrupt disabled 1 : Interrupt enabled	0	R	W
3	$f(X_{IN})/4096$ interrupt enable bit (CKE)	0 : Interrupt disabled 1 : Interrupt enabled	0	R	W
4	INT2 external interrupt enable bit (IN2E)	0 : Interrupt disabled 1 : Interrupt enabled	0	R	W
5	Multi-master I^2C-BUS interface interrupt enable bit (IICE)	0 : Interrupt disabled 1 : Interrupt enabled	0	R	W
6	Timer 5 • 6 interrupt enable bit (TM56E)	0 : Interrupt disabled 1 : Interrupt enabled	0	R	W
7	Timer 5 • 6 interrupt switch bit (TM56C)	0 : Timer 5 1 : Timer 6	0	R	W

Fig. 8.3.5 Interrupt Control Register 2

Interrupt Input Polarity Register



Interrupt input polarity register (RE) [Address 00DC 16]

B	Name	Functions	After reset	R	W
0	INT1 polarity switch bit (INT1)	0 : Positive polarity 1 : Negative polarity	0	R	W
4	INT2 polarity switch bit (INT2)	0 : Positive polarity 1 : Negative polarity	0	R	W
5	INT3 polarity switch bit (INT3)	0 : Positive polarity 1 : Negative polarity	0	R	W
4 to 7	Nothing is assigned. These bits are write disable bits. When these bits are read out, the values are “0.”		0	R	—

Fig. 8.3.6 Interrupt Input Polarity Register

8.4 TIMERS

This microcomputer has 6 timers: timer 1, timer 2, timer 3, timer 4, timer 5, and timer 6. All timers are 8-bit timers with the 8-bit timer latch. The timer block diagram is shown in Figure 8.4.3.

All of the timers count down and their divide ratio is 1/(n+1), where n is the value of timer latch. By writing a count value to the corresponding timer latch (addresses $00F0_{16}$ to $00F3_{16}$: timers 1 to 4, addresses $00EE_{16}$ and $00EF_{16}$: timers 5 and 6), the value is also set to a timer, simultaneously.

The count value is decremented by 1. The timer interrupt request bit is set to "1" by a timer overflow at the next count pulse, after the count value reaches "00_{16}".

8.4.1 Timer 1

Timer 1 can select one of the following count sources:

- f(XIN)/16 or f(XCIN)/16
- f(XIN)/4096 or f(XCIN)/4096
- External clock from the TIM2 pin

The count source of timer 1 is selected by setting bits 5 and 0 of timer mode register 1 (address $00F4_{16}$). Either f(XIN) or f(XCIN) is selected by bit 7 of the CPU mode register.

Timer 1 interrupt request occurs at timer 1 overflow.

8.4.2 Timer 2

Timer 2 can select one of the following count sources:

- f(XIN)/16 or f(XCIN)/16
- Timer 1 overflow signal
- External clock from the TIM2 pin

The count source of timer 2 is selected by setting bits 4 and 1 of timer mode register 1 (address $00F4_{16}$). Either f(XIN) or f(XCIN) is selected by bit 7 of the CPU mode register. When timer 1 overflow signal is a count source for the timer 2, the timer 1 functions as an 8-bit prescaler.

Timer 2 interrupt request occurs at timer 2 overflow.

8.4.3 Timer 3

Timer 3 can select one of the following count sources:

- f(XIN)/16 or f(XCIN)/16
- f(XCIN)
- External clock from the TIM3 pin

The count source of timer 3 is selected by setting bit 0 of timer mode register 2 (address $00F5_{16}$) and bit 6 at address $00C7_{16}$. Either f(XIN) or f(XCIN) is selected by bit 7 of the CPU mode register.

Timer 3 interrupt request occurs at timer 3 overflow.

8.4.4 Timer 4

Timer 4 can select one of the following count sources:

- f(XIN)/16 or f(XCIN)/16
- f(XIN)/2 or f(XCIN)/2
- f(XCIN)

The count source of timer 3 is selected by setting bits 1 and 4 of the timer mode register 2 (address $00F5_{16}$). Either f(XIN) or f(XCIN) is selected by bit 7 of the CPU mode register. When timer 3 overflow signal is a count source for the timer 4, the timer 3 functions as an 8-bit prescaler.

Timer 4 interrupt request occurs at timer 4 overflow.

8.4.5 Timer 5

Timer 5 can select one of the following count sources:

- f(XIN)/16 or f(XCIN)/16
- Timer 2 overflow signal
- Timer 4 overflow signal

The count source of timer 3 is selected by setting bit 6 of timer mode register 1 (address $00F4_{16}$) and bit 7 of the timer mode register 2 (address $00F5_{16}$). When overflow of timer 2 or 4 is a count source for timer 5, either timer 2 or 4 functions as an 8-bit prescaler. Either f(XIN) or f(XCIN) is selected by bit 7 of the CPU mode register.

Timer 5 interrupt request occurs at timer 5 overflow.

8.4.6 Timer 6

Timer 6 can select one of the following count sources:

- f(XIN)/16 or f(XCIN)/16
- Timer 5 overflow signal

The count source of timer 6 is selected by setting bit 7 of the timer mode register 1 (address $00F4_{16}$). Either f(XIN) or f(XCIN) is selected by bit 7 of the CPU mode register. When timer 5 overflow signal is a count source for timer 6, the timer 5 functions as an 8-bit prescaler.

Timer 6 interrupt request occurs at timer 6 overflow.

At reset, timers 3 and 4 are connected by hardware and "FF_{16}" is automatically set in timer 3; "07_{16}" in timer 4. The f(XIN) * /16 is selected as the timer 3 count source. The internal reset is released by timer 4 overflow in this state and the internal clock is connected.


At execution of the STP instruction, timers 3 and 4 are connected by hardware and "FF_{16}" is automatically set in timer 3; "07_{16}" in timer 4. However, the f(XIN) * /16 is not selected as the timer 3 count source. So set both bit 0 of timer mode register 2 (address $00F5_{16}$) and bit 6 at address $00C7_{16}$ to "0" before the execution of the STP instruction (f(XIN) * /16 is selected as timer 3 count source). The internal STP state is released by timer 4 overflow in this state and the internal clock is connected.

As a result of the above procedure, the program can start under a stable clock.

*: When bit 7 of the CPU mode register (CM_7) is "1," f(XIN) becomes f(XCIN).

The timer-related registers is shown in Figures 8.4.1 and 8.4.2.

Timer Mode Register 1




Timer mode register 1 (TM1) [Address 00F4 16]

B	Name	Functions	After reset	R	W
0	Timer 1 count source selection bit 1 (TM10)	0: f(XIN)/16 or f(XCIN)/16 (See note) 1: Count source selected by bit 5 of TM1	0	R	W
1	Timer 2 count source selection bit 1 (TM11)	0: Count source selected by bit 4 of TM1 1: External clock from TIM2 pin	0	R	W
2	Timer 1 count stop bit (TM12)	0: Count start 1: Count stop	0	R	W
3	Timer 2 count stop bit (TM13)	0: Count start 1: Count stop	0	R	W
4	Timer 2 count source selection bit 2 (TM14)	0: f(XIN)/16 or f(XCIN)/16 (See note) 1: Timer 1 overflow	0	R	W
5	Timer 1 count source selection bit 2 (TM15)	0: f(XIN)/4096 or f(XCIN)/4096 (See note) 1: External clock from TIM2 pin	0	R	W
6	Timer 5 count source selection bit 2 (TM16)	0: Timer 2 overflow 1: Timer 4 overflow	0	R	W
7	Timer 6 internal count source selection bit (TM17)	0: f(XIN)/16 or f(XCIN)/16 (See note) 1: Timer 5 overflow	0	R	W

Note: Either f(XIN) or f(XCIN) is selected by bit 7 of the CPU mode register.

Fig. 8.4.1 Timer Mode Register 1

Timer Mode Register 2




Timer mode register 2 (TM2) [Address 00F5 16]

B	Name	Functions	After reset	R	W
0	Timer 3 count source selection bit (TM20)	(b6 at address 00C7 16) ↓ b0 0 0 : f(XIN)/16 or f(XCIN)/16 (See note) 0 1 : f(XCIN) 1 0 : 1 1 : } External clock from TIM3 pin	0	R	W
1, 4	Timer 4 count source selection bits (TM21, TM24)	b4 b1 0 0 : Timer 3 overflow signal 0 1 : f(XIN)/16 or f(XCIN)/16 (See note) 1 0 : f(XIN)/2 or f(XCIN)/2 (See note) 1 1 : f(XCIN)	0	R	W
2	Timer 3 count stop bit (TM22)	0: Count start 1: Count stop	0	R	W
3	Timer 4 count stop bit (TM23)	0: Count start 1: Count stop	0	R	W
5	Timer 5 count stop bit (TM25)	0: Count start 1: Count stop	0	R	W
6	Timer 6 count stop bit (TM26)	0: Count start 1: Count stop	0	R	W
7	Timer 5 count source selection bit 1 (TM27)	0: f(XIN)/16 or f(XCIN)/16 (See note) 1: Count source selected by bit 6 of TM1	0	R	W

Note: Either f(XIN) or f(XCIN) is selected by bit 7 of the CPU mode register.

Fig. 8.4.2 Timer Mode Register 2



Notes 1: HIGH pulse width of external clock inputs TIM2 and TIM3 needs 4 machine cycles or more.
2: When the external clock source is selected, timers 1, 2, and 3 are counted at a rising edge of input signal.
3: In the stop mode or the wait mode, external clock inputs TIM2 and TIM3 cannot be used.

Fig. 8.4.3 Timer Block Diagram


8.5 SERIAL I/O

This microcomputer has a built-in serial I/O which can either transmit or receive 8-bit data serially in the clock synchronous mode.

The serial I/O block diagram is shown in Figure 8.5.1. The synchronous clock I/O pin (SCLK), and data output pin (SOUT) also function as port P4, data input pin (SIN) also functions as port P20–P22.

Bit 3 of the serial I/O mode register (address 00EB16) selects whether the synchronous clock is supplied internally or externally (from the SCLK pin). When an internal clock is selected, bits 1 and 0 select whether f(XIN) or f(XCIN) is divided by 8, 16, 32, or 64. To use the SIN pin for serial I/O, set the corresponding bit of the port P2 direction register (address 00C516) to "0."

The operation of the serial I/O is described below. The operation of the serial I/O differs depending on the clock source; external clock or internal clock.




Note : When the data is set in the serial I/O register (address 00EA16), the register functions as the serial I/O shift register.

Fig. 8.5.1 Serial I/O Block Diagram

Internal clock : The serial I/O counter is set to “7” during the write cycle into the serial I/O register (address 00EA16), and the transfer clock goes HIGH forcibly. At each falling edge of the transfer clock after the write cycle, serial data is output from the SOUT pin. Transfer direction can be selected by bit 5 of the serial I/O mode register. At each rising edge of the transfer clock, data is input from the SIN pin and data in the serial I/O register is shifted 1 bit.
After the transfer clock has counted 8 times, the serial I/O counter becomes “0” and the transfer clock stops at HIGH. At this time the interrupt request bit is set to “1.”

External clock : The an external clock is selected as the clock source, the interrupt request is set to “1” after the transfer clock has been counted 8 counts. However, transfer operation does not stop, so the clock should be controlled externally. Use the external clock of 1 MHz or less with a duty cycle of 50%.
The serial I/O timing is shown in Figure 8.5.2. When using an external clock for transfer, the external clock must be held at HIGH for initializing the serial I/O counter. When switching between an internal clock and an external clock, do not switch during transfer. Also, be sure to initialize the serial I/O counter after switching.


Notes 1: On programming, note that the serial I/O counter is set by writing to the serial I/O register with the bit managing instructions, such as SEB and CLB.
2: When an external clock is used as the synchronous clock, write transmit data to the serial I/O register when the transfer clock input level is HIGH.



Note : When an internal clock is selected, the SOUT pin is at high-impedance after transfer is completed.

Fig. 8.5.2 Serial I/O Timing (for LSB first)

Serial I/O Mode Register



Serial I/O mode register (SM) [Address 00EB16]

B	Name	Functions	After reset	R	W
0, 1	Internal synchronous clock selection bits (SM0, SM1)	b1 b0 0 0: f(XIN)/4 or f(XCIN)/4 0 1: f(XIN)/16 or f(XCIN)/16 1 0: f(XIN)/32 or f(XCIN)/32 1 1: f(XIN)/64 or f(XCIN)/64	0	R	W
2	Synchronous clock selection bit (SM2)	0: External clock 1: Internal clock	0	R	W
3	Port function selection bit (SM3)	0: P20, P21 1: SCLK, SOUT	0	R	W
4	Fix this bit to “0.”		0	R	W
5	Transfer direction selection bit (SM5)	0: LSB first 1: MSB first	0	R	W
6	Transfer clock input pin selection bit (SM6)	0: Input signal from SIN pin 1: Input signal from SOUT pin	0	R	W
7	Fix this bit to “0.”		0	R	W

Fig. 8.5.3 Serial I/O Mode Register

8.6 MULTI-MASTER I²C-BUS INTERFACE

The multi-master I²C-BUS interface is a serial communications circuit, conforming to the Philips I²C-BUS data transfer format. This interface, offering both arbitration lost detection and a synchronous functions, is useful for the multi-master serial communications.

Figure 8.6.1 shows a block diagram of the multi-master I²C-BUS interface and Table 8.6.1 shows multi-master I²C-BUS interface functions.

This multi-master I²C-BUS interface consists of the I²C address register, the I²C data shift register, the I²C clock control register, the I²C control register, the I²C status register and other control circuits.

Table 8.6.1 Multi-master I²C-BUS Interface Functions

Item	Function
Format	In conformity with Philips I²C-BUS standard: 10-bit addressing format 7-bit addressing format High-speed clock mode Standard clock mode
Communication mode	In conformity with Philips I²C-BUS standard: Master transmission Master reception Slave transmission Slave reception
SCL clock frequency	16.1 kHz to 400 kHz (at ϕ = 4 MHz)

ϕ : System clock = f(X_{IN})/2

Note : We are not responsible for any third party's infringement of patent rights or other rights attributable to the use of the control function (bits 6 and 7 of the I²C control register at address 00F9$_{16}$) for connections between the I²C-BUS interface and ports (SCL1, SCL2, SDA1, SDA2).




Fig. 8.6.1 Block Diagram of Multi-master I²C-BUS Interface

8.6.1 I²C Data Shift Register

The I²C data shift register (S0 : address 00F6₁₆) is an 8-bit shift register to store receive data and write transmit data.
When transmit data is written into this register, it is transferred to the outside from bit 7 in synchronization with the SCL clock, and each time one-bit data is output, the data of this register are shifted one bit to the left. When data is received, it is input to this register from bit 0 in synchronization with the SCL clock, and each time one-bit data is input, the data of this register are shifted one bit to the left.
The I²C data shift register is in a write enable status only when the ESO bit of the I²C control register (address 00F9₁₆) is "1." The bit counter is reset by a write instruction to the I²C data shift register. When both the ESO bit and the MST bit of the I²C status register (address 00F8₁₆) are "1," the SCL is output by a write instruction to the I²C data shift register. Reading data from the I²C data shift register is always enabled regardless of the ESO bit value.

Note: To write data into the I²C data shift register after setting the MST bit to "0" (slave mode), keep an interval of 8 machine cycles or more.

I²C Data Shift Register

b7 b6 b5 b4 b3 b2 b1 b0

I²C data shift register1(S0) [Address 00F6₁₆]

B	Name	Functions	After reset	R	W
0 to 7	D0 to D7	This is an 8-bit shift register to store receive data and write transmit data.	Indeterminate	R	W

Note: To write data into the I²C data shift register after setting the MST bit to "0" (slave mode), keep an interval of 8 machine cycles or more.

Fig. 8.6.2 Data Shift Register

8.6.2 I²C Address Register


The I²C address register (address 00F7₁₆) consists of a 7-bit slave address and a $\overline{\text{read}}$/write bit. In the addressing mode, the slave address written in this register is compared with the address data to be received immediately after the START condition are detected.

(1) Bit 0: $\overline{\text{read}}$/write bit (RBW)

Not used when comparing addresses, in the 7-bit addressing mode. In the 10-bit addressing mode, the first address data to be received is compared with the contents (SAD6 to SAD0 + RBW) of the I²C address register.
The RBW bit is cleared to "0" automatically when the stop condition is detected.

(2) Bits 1 to 7: slave address (SAD0–SAD6)

These bits store slave addresses. Regardless of the 7-bit addressing mode and the 10-bit addressing mode, the address data transmitted from the master is compared with the contents of these bits.



B	Name	Functions	After reset	R	W
0	$\overline{\text{Read}}$/write bit (RBW)	<Only in 10-bit addressing (in slave) mode> The last significant bit of address data is compared. 0: Wait the first byte of slave address after START condition (read state) 1: Wait the first byte of slave address after RESTART condition (write state)	0	R	—
1 to 7	Slave address (SAD0 to SAD6)	<In both modes> The address data is compared.	0	R	W

Fig. 8.6.3 I²C Address Register

8.6.3 I²C Clock Control Register

The I²C clock control register (address 00FA16) is used to set ACK control, SCL mode and SCL frequency.

(1) Bits 0 to 4: SCL frequency control bits (CCR0–CCR4)

These bits control the SCL frequency.

(2) Bit 5: SCL mode specification bit (FAST MODE)

This bits specifies the SCL mode. When this bit is set to "0," the standard clock mode is set. When the bit is set to "1," the high-speed clock mode is set.

(3) Bit 6: ACK bit (ACK BIT)

This bits sets the SDA status when an ACK clock* is generated. When this bit is set to "0," the ACK return mode is set and SDA goes to LOW at the occurrence of an ACK clock. When the bit is set to "1," the ACK non-return mode is set. The SDA is held in the HIGH status at the occurrence of an ACK clock.
However, when the slave address matches the address data in the reception of address data at ACK BIT = "0," the SDA is automatically made LOW (ACK is returned). If there is a mismatch between the slave address and the address data, the SDA is automatically made HIGH (ACK is not returned).

✻ACK clock: Clock for acknowledgement

(4) Bit 7: ACK clock bit (ACK)

This bit specifies a mode of acknowledgment which is an acknowledgment response of data transmission. When this bit is set to "0," the no ACK clock mode is set. In this case, no ACK clock occurs after data transmission. When the bit is set to "1," the ACK clock mode is set and the master generates an ACK clock upon completion of each 1-byte data transmission.The device for transmitting address data and control data releases the SDA at the occurrence of an ACK clock (make SDA HIGH) and receives the ACK bit generated by the data receiving device.

Note: Do not write data into the I²C clock control register during transmission. If data is written during transmission, the I²C clock generator is reset, so that data cannot be transmitted normally.

I²C Clock Control Register

b7 b6 b5 b4 b3 b2 b1 b0

I²C clock control register (S2 : address 00FA16)

B	Name	Functions			After reset	R	W
0 to 4	SCL frequency control bits (CCR0 to CCR4)	Setup value of CCR4–CCR0	Standard clock mode	High speed clock mode	0	R	W
		00 to 02	Setup disabled	Setup disabled			
		03	Setup disabled	333			
		04	Setup disabled	250			
		05	100	400 (See note)			
		06	83.3	166			
		⋮	500/CCR value	1000/CCR value			
		1D	17.2	34.5			
		1E	16.6	33.3			
		1F	16.1	32.3			
		(at ϕ = 4 MHz, unit : kHz)					
5	SCL mode specification bit (FAST MODE)	0: Standard clock mode 1: High-speed clock mode			0	R	W
6	ACK bit (ACK BIT)	0: ACK is returned. 1: ACK is not returned.			0	R	W
7	ACK clock bit (ACK)	0: No ACK clock 1: ACK clock			0	R	W

Note: At 4000kHz in the high-speed clock mode, the duty is as below .
"0" period : "1" period = 3 : 2
In the other cases, the duty is as below.
"0" period : "1" period = 1 : 1

Fig. 8.6.4 I²C Address Register

8.6.4 I²C Control Register

The I²C control register (address 00F9₁₆) controls the data communication format.

(1) Bits 0 to 2: bit counter (BC0–BC2)

These bits decide the number of bits for the next 1-byte data to be transmitted. An interrupt request signal occurs immediately after the number of bits specified with these bits are transmitted.
When a START condition is received, these bits become "000₂" and the address data is always transmitted and received in 8 bits.

(2) Bit 3: I²C interface use enable bit (ESO)

This bit enables usage of the multimaster I²C BUS interface. When this bit is set to "0," the use disable status is provided, so the SDA and the SCL become high-impedance. When the bit is set to "1," use of the interface is enabled.
When ESO = "0," the following is performed.

- PIN = "1," BB = "0" and AL = "0" are set (they are bits of the I²C status register at address 00F8₁₆).
- Writing data to the I²C data shift register (address 00F6₁₆) is disabled.

(3) Bit 4: data format selection bit (ALS)


This bit decides whether or not to recognize slave addresses. When this bit is set to "0," the addressing format is selected, so that address data is recognized. When a match is found between a slave address and address data as a result of comparison or when a general call (refer to "8.6.5 I²C Status Register," bit 1) is received, transmission processing can be performed. When this bit is set to "1," the free data format is selected, so that slave addresses are not recognized.

(4) Bit 5: addressing format selection bit (10BIT SAD)

This bit selects a slave address specification format. When this bit is set to "0," the 7-bit addressing format is selected. In this case, only the high-order 7 bits (slave address) of the I²C address register (address 00F7₁₆) are compared with address data. When this bit is set to "1," the 10-bit addressing format is selected, all the bits of the I²C address register are compared with address data.

(5) Bits 6 and 7: connection control bits between I²C-BUS interface and ports (BSEL0, BSEL1)


These bits controls the connection between SCL and ports or SDA and ports (refer to Figure 8.6.5).



Note: Set the corresponding direction register to "1" to use the port as multi-master I²C-BUS interface.

Fig. 8.6.5 Connection Port Control by BSEL0 and BSEL1

I^2C Control Register



I^2C control register (S1D address $00F9_{16}$)

B	Name	Functions	After reset	R	W
0 to 2	Bit counter (Number of transmit/recieve bits) (BC0 to BC2)	b2 b1 b0 0 0 0 : 8 0 0 1 : 7 0 1 0 : 6 0 1 1 : 5 1 0 0 : 4 1 0 1 : 3 1 1 0 : 2 1 1 1 : 1	0	R	W
3	I^2C-BUS interface use enable bit (ESO)	0 : Disabled 1 : Enabled	0	R	W
4	Data format selection bit(ALS)	0 : Addressing mode 1 : Free data format	0	R	W
5	Addressing format selection bit (10BIT SAD)	0 : 7-bit addressing format 1 : 10-bit addressing format	0	R	W
6, 7	Connection control bits between I^2C-BUS interface and ports	b7 b6 Connection port (See note) 0 0 : None 0 1 : SCL1, SDA1 1 0 : SCL2, SDA2 1 1 : SCL1, SDA1 SCL2, SDA2	0	R	W

Note: When using ports $P1_1$-$P1_4$ as I^2C-BUS interface, the output structure changes automatically from CMOS output to N-channel open-drain output.

Fig. 8.6.6 I^2C Control Register

8.6.5 I²C Status Register

The I²C status register (address 00F8₁₆) controls the I²C-BUS interface status. The low-order 4 bits are read-only bits and the high-order 4 bits can be read out and written to.

(1) Bit 0: last receive bit (LRB)

This bit stores the last bit value of received data and can also be used for ACK receive confirmation. If ACK is returned when an ACK clock occurs, the LRB bit is set to "0." If ACK is not returned, this bit is set to "1." Except in the ACK mode, the last bit value of received data is input. The state of this bit is changed from "1" to "0" by executing a write instruction to the I²C data shift register (address 00F6₁₆).

(2) Bit 1: general call detecting flag (AD0)

This bit is set to "1" when a general call* whose address data is all "0" is received in the slave mode. By a general call of the master device, every slave device receives control data after the general call. The AD0 bit is set to "0" by detecting the STOP condition or START condition.

*General call: The master transmits the general call address "00₁₆" to all slaves.

(3) Bit 2: slave address comparison flag (AAS)

This flag indicates a comparison result of address data.

■ In the slave receive mode, when the 7-bit addressing format is selected, this bit is set to "1" in one of the following conditions.
- The address data immediately after occurrence of a START condition matches the slave address stored in the high-order 7 bits of the I²C address register (address 00F7₁₆).
- A general call is received.

■ In the slave reception mode, when the 10-bit addressing format is selected, this bit is set to "1" with the following condition.
- When the address data is compared with the I²C address register (8 bits consists of slave address and RBW), the first bytes match.

■ The state of this bit is changed from "1" to "0" by executing a write instruction to the I²C data shift register (address 00F6₁₆).

(4) Bit 3: arbitration lost* detecting flag (AL)

n the master transmission mode, when a device other than the microcomputer sets the SDA to "L,", arbitration is judged to have been lost, so that this bit is set to "1." At the same time, the TRX bit is set to "0," so that immediately after transmission of the byte whose arbitration was lost is completed, the MST bit is set to "0." When arbitration is lost during slave address transmission, the TRX bit is set to "0" and the reception mode is set. Consequently, it becomes possible to receive and recognize its own slave address transmitted by another master device.

*Arbitration lost: The status in which communication as a master is disabled.

(5) Bit 4: I²C-BUS interface interrupt request bit (PIN)

This bit generates an interrupt request signal. Each time 1-byte data is transmitted, the state of the PIN bit changes from "1" to "0." At the same time, an interrupt request signal is sent to the CPU. The PIN bit is set to "0" in synchronization with a falling edge of the last clock (including the ACK clock) of an internal clock and an interrupt request signal occurs in synchronization with a falling edge of the PIN bit. When detecting the STOP condition in slave, the multi-master I²C-BUS interface interrupt request bit (IR) is set to "1" (interrupt request) regardless of falling of PIN bit. When the PIN bit is "0," the SCL is kept in the "0" state and clock generation is disabled. Figure 8.6.8 shows an interrupt request signal generating timing chart.

The PIN bit is set to "1" in any one of the following conditions.
- Writing "1" to the PIN bit
- Executing a write instruction to the I²C data shift register (address 00F6₁₆). (See note)
- When the ESO bit is "0"
- At reset

Note: It takes 8 BCLK cycles or more until PIN bit becomes "1" after write instructions are executed to these registers.

The conditions in which the PIN bit is set to "0" are shown below:
- Immediately after completion of 1-byte data transmission (including when arbitration lost is detected)
- Immediately after completion of 1-byte data reception
- In the slave reception mode, with ALS = "0" and immediately after completion of slave address or general call address reception
- In the slave reception mode, with ALS = "1" and immediately after completion of address data reception

(6) Bit 5: bus busy flag (BB)

This bit indicates the status of use of the bus system. When this bit is set to "0," this bus system is not busy and a START condition can be generated. When this bit is set to "1," this bus system is busy and the occurrence of a START condition is disabled by the START condition duplication prevention function (See note).

This flag can be written by software only in the master transmission mode. In the other modes, this bit is set to "1" by detecting a START condition and set to "0" by detecting a STOP condition. When the ESO bit of the I²C control register (address 00F9₁₆) is "0" and at reset, the BB flag is kept in the "0" state.

(7) Bit 6: communication mode specification bit (transfer direction specification bit: TRX)

This bit decides the direction of transfer for data communication. When this bit is "0," the reception mode is selected and the data of a transmitting device is received. When the bit is "1," the transmission mode is selected and address data and control data are output into the SDA in synchronization with the clock generated on the SCL.

When the ALS bit of the I²C control register (address 00F9₁₆) is "0" in the slave reception mode is selected, the TRX bit is set to "1" (transmit) if the least significant bit (R/$\overline{W}$ bit) of the address data transmitted by the master is "1." When the ALS bit is "0" and the R/$\overline{W}$ bit is "0," the TRX bit is cleared to "0" (receive).

The TRX bit is cleared to "0" in one of the following conditions.
- When arbitration lost is detected.
- When a STOP condition is detected.
- When occurence of a START condition is disabled by the START condition duplication prevention function (Note).
- With MST = "0" and when a START condition is detected.
- With MST = "0" and when ACK non-return is detected.
- At reset

(8) Bit 7: Communication mode specification bit (master/slave specification bit: MST)

This bit is used for master/slave specification for data communication. When this bit is "0," the slave is specified, so that a START condition and a STOP condition generated by the master are received, and data communication is performed in synchronization with the clock generated by the master. When this bit is "1," the master is specified and a START condition and a STOP condition are generated, and also the clocks required for data communication are generated on the SCL.

The MST bit is cleared to "0" in one of the following conditions.

- Immediately after completion of 1-byte data transmission when arbitration lost is detected
- When a STOP condition is detected.
- When occurence of a START condition is disabled by the START condition duplication preventing function (Note).
- At reset

Note: The START condition duplication prevention function disables the START condition generation, reset of bit counter reset, and SCL output, when the following condition is satisfied:
a START condition is set by another master device.

I^2C Status Register

b7 b6 b5 b4 b3 b2 b1 b0

I^2C status register (S1) [Address $00F8_{16}$]

B	Name	Functions	After reset	R	W
0	Last receive bit (LRB) (See note)	0 : Last bit = "0 " 1 : Last bit = "1 " (See note)	Indeterminate	R	—
1	General call detecting flag (AD0) (See note)	0 : No general call detected 1 : General call detected (See note)	0	R	—
2	Slave address comparison flag (AAS) (See note)	0 : Address mismatch 1 : Address match (See note)	0	R	—
3	Arbitration lost detecting flag (AL) (See note)	0 : Not detected 1 : Detected (See note)	0	R	—
4	I^2C-BUS interface interrupt request bit (PIN)	0 : Interrupt request issued 1 : No interrupt request issued	1	R	W
5	Bus busy flag (BB)	0 : Bus free 1 : Bus busy	0	R	W
6, 7	Communication mode specification bits (TRX, MST)	b7 b6 0 0 : Slave recieve mode 0 1 : Slave transmit mode 1 0 : Master recieve mode 1 1 : Master transmit mode	0	R	W

Note : These bits and flags can be read out, but cannnot be written.

Fig. 8.6.7 I^2C Status Register




Fig. 8.6.8 Interrupt Request Signal Generation Timing

8.6.6 START Condition Generation Method

When the ESO bit of the I²C control register (address 00F9₁₆) is "1," execute a write instruction to the I²C status register (address 00F8₁₆) to set the MST, TRX and BB bits to "1." A START condition will then be generated. After that, the bit counter becomes "000₂" and an SCL for 1 byte is output. The START condition generation timing and BB bit set timing are different in the standard clock mode and the high-speed clock mode. Refer to Figure 8.6.9 for the START condition generation timing diagram, and Table 8.6.2 for the START condition/STOP condition generation timing table.




Fig. 8.6.9 START Condition Generation Timing Diagram

8.6.7 STOP Condition Generation Method

When the ESO bit of the I²C control register (address 00F9₁₆) is "1," execute a write instruction to the I²C status register (address 00F8₁₆) for setting the MST bit and the TRX bit to "1" and the BB bit to "0". A STOP condition will then be generated. The STOP condition generation timing and the BB flag reset timing are different in the standard clock mode and the high-speed clock mode. Refer to Figure 8.6.10 for the STOP condition generation timing diagram, and Table 8.6.2 for the START condition/STOP condition generation timing table.




Fig. 8.6.10 STOP Condition Generation Timing Diagram

Table 8.6.2 START Condition/STOP Condition Generation Timing Table

Item	Standard Clock Mode	High-speed Clock Mode
Setup time (START condition)	5.0 μs (20 cycles)	2.5 μs (10 cycles)
Setup time (STOP condition)	4.25 μs (17 cycles)	1.75 μs (7 cycles)
Hold time	5.0 μs (20 cycles)	2.5 μs (10 cycles)
Set/reset time for BB flag	3.0 μs (12 cycles)	1.5 μs (6 cycles)

Note: Absolute time at ϕ = 4 MHz. The value in parentheses denotes the number of ϕ cycles.

8.6.8 START/STOP Condition Detect Conditions

The START/STOP condition detect conditions are shown in Figure 8.6.11 and Table 8.6.3. Only when the 3 conditions of Table 8.6.3 are satisfied, a START/STOP condition can be detected.

Note: When a STOP condition is detected in the slave mode (MST = 0), an interrupt request signal "IICIRQ" is generated to the CPU.




Fig. 8.6.11 START Condition/STOP Condition Detect Timing Diagram

Table 8.6.3 START Condition/STOP Condition Detect Conditions

Standard Clock Mode	High-speed Clock Mode
6.5 μs (26 cycles) < SCL release time	1.0 μs (4 cycles) < SCL release time
3.25 μs (13 cycles) < Setup time	0.5 μs (2 cycles) < Setup time
3.25 μs (13 cycles) < Hold time	0.5 μs (2 cycles) < Hold time

Note: Absolute time at ϕ = 4 MHz. The value in parentheses denotes the number of ϕ cycles.

8.6.9 Address Data Communication

There are two address data communication formats, namely, 7-bit addressing format and 10-bit addressing format. The respective address communication formats is described below.

(1) 7-bit addressing format

To meet the 7-bit addressing format, set the 10BIT SAD bit of the I^2C control register (address $00F9_{16}$) to "0." The first 7-bit address data transmitted from the master is compared with the high-order 7-bit slave address stored in the I^2C address register (address $00F7_{16}$). At the time of this comparison, address comparison of the RBW bit of the I^2C address register (address $00F7_{16}$) is not made. For the data transmission format when the 7-bit addressing format is selected, refer to Figure 8.6.12, (1) and (2).

(2) 10-bit addressing format

To meet the 10-bit addressing format, set the 10BIT SAD bit of the I^2C control register (address $00F9_{16}$) to "1." An address comparison is made between the first-byte address data transmitted from the master and the 7-bit slave address stored in the I^2C address register (address $00F7_{16}$). At the time of this comparison, an address comparison between the RBW bit of the I^2C address register (address $00F7_{16}$) and the R/$\overline{W}$ bit which is the last bit of the address data transmitted from the master is made. In the 10-bit addressing mode, the R/$\overline{W}$ bit which is the last bit of the address data not only specifies the direction of communication for control data but also is processed as an address data bit.

When the first-byte address data matches the slave address, the AAS bit of the I^2C status register (address $00F8_{16}$) is set to "1." After the second-byte address data is stored into the I^2C data shift register (address $00F6_{16}$), make an address comparison between the second-byte data and the slave address by software. When the address data of the 2nd bytes matches the slave address, set the RBW bit of the I^2C address register (address $00F7_{16}$) to "1" by software. This processing can match the 7-bit slave address and R/$\overline{W}$ data, which are received after a RESTART condition is detected, with the value of the I^2C address register (address $00F7_{16}$). For the data transmission format when the 10-bit addressing format is selected, refer to Figure 8.6.12, (3) and (4).

8.6.10 Example of Master Transmission

An example of master transmission in the standard clock mode, at the SCL frequency of 100 kHz and in the ACK return mode is shown below.

① Set a slave address in the high-order 7 bits of the I^2C address register (address $00F7_{16}$) and "0" in the RBW bit.
② Set the ACK return mode and SCL = 100 kHz by setting "85_{16}" in the I^2C clock control register (address $00FA_{16}$).
③ Set "10_{16}" in the I^2C status register (address $00F8_{16}$) and hold the SCL at the HIGH.
④ Set a communication enable status by setting "48_{16}" in the I^2C control register (address $00F9_{16}$).
⑤ Set the address data of the destination of transmission in the high-order 7 bits of the I^2C data shift register (address $00F6_{16}$) and set "0" in the least significant bit.
⑥ Set "$F0_{16}$" in the I^2C status register (address $00F8_{16}$) to generate a START condition. At this time, an SCL for 1 byte and an ACK clock automatically occurs.
⑦ Set transmit data in the I^2C data shift register (address $00F6_{16}$). At this time, an SCL and an ACK clock automatically occurs.
⑧ When transmitting control data of more than 1 byte, repeat step ⑦.
⑨ Set "$D0_{16}$" in the I^2C status register (address $00F8_{16}$). After this, if ACK is not returned or transmission ends, a STOP condition will be generated.

8.6.11 Example of Slave Reception

An example of slave reception in the high-speed clock mode, at the SCL frequency of 400 kHz, in the ACK non-return mode, using the addressing format, is shown below.

① Set a slave address in the high-order 7 bits of the I^2C address register (address $00F7_{16}$) and "0" in the RBW bit.
② Set the no ACK clock mode and SCL = 400 kHz by setting "25_{16}" in the I^2C clock control register (address $00FA_{16}$).
③ Set "10_{16}" in the I^2C status register (address $00F8_{16}$) and hold the SCL at the HIGH.
④ Set a communication enable status by setting "48_{16}" in the I^2C control register (address $00F9_{16}$).
⑤ When a START condition is received, an address comparison is made.
⑥ •When all transmitted address are"0" (general call):
AD0 of the I^2C status register (address $00F8_{16}$) is set to "1"and an interrupt request signal occurs.
•When the transmitted addresses match the address set in ①:
ASS of the I^2C status register (address $00F8_{16}$) is set to "1" and an interrupt request signal occurs.
•In the cases other than the above:
AD0 and AAS of the I^2C status register (address $00F8_{16}$) are set to "0" and no interrupt request signal occurs.
⑦ Set dummy data in the I^2C data shift register (address $00F6_{16}$).
⑧ When receiving control data of more than 1 byte, repeat step ⑦.
⑨ When a STOP condition is detected, the communication ends.




Fig. 8.6.12 Address Data Communication Format

8.6.12 Precautions when using multi-master I²C-BUS interface

(1) Read-modify-write instruction

The precautions when the raead-modify-write instruction such as SEB, CLB etc. is executed for each register of the multi-master I²C-BUS interface are described below.

•I²C data shift register (S0)
When executing the read-modify-write instruction for this register during transfer, data may become a value not intended.

•I²C address register (S0D)
When the read-modify-write instruction is executed for this register at detecting the STOP condition, data may become a value not intended. It is because hardware changes the read/write bit (RBW) at the above timing.

•I²C status register (S1)
Do not execute the read-modify-write instruction for this register because all bits of this register are changed by hardware.

•I²C control register (S1D)
When the read-modify-write instruction is executed for this register at detecting the START condition or at completing the byte transfer, data may become a value not intended. Because hardware changes the bit counter (BC0–BC2) at the above timing.

•I²C clock control register (S2)
The read-modify-write instruction can be executed for this register.

(2) START condition generating procedure using multi-master

①Procedure example (The necessary conditions of the generating procedure are described as the following ② to ⑤).

```
                •
                •
        LDA     —               (Taking out of slave address value)
        SEI                     (Interrupt disabled)
        BBS  5,S1,BUSBUSY       (BB flag confirming and branch process)
BUSFREE:
        STA  S0                 (Writing of slave address value)
        LDM #$F0, S1            (Trigger of START condition generating)
        CLI                     (Interrupt enabled)
                •
                •
BUSBUSY:
        CLI                     (Interrupt enabled)
                •
                •
```

②Use "STA," "STX" or "STY" of the zero page addressing instruction for writing the slave address value to the I²C data shift register.

③Use "LDM" instruction for setting trigger of START condition generating.

④Write the slave address value of above ② and set trigger of START condition generating of above ③ continuously shown the above procedure example.

⑤Disable interrupts during the following three process steps:
• BB flag confirming
• Writing of slave address value
• Trigger of START condition generating
When the condition of the BB flag is bus busy, enable interrupts immediately.

(3) RESTART condition generating procedure

①Procedure example (The necessary conditions of the generating procedure are described as the following ② to ⑥.)

Execute the following procedure when the PIN bit is “0.”

```
        •
        •
LDM   #$00, S1    (Select slave receive mode)
LDA   —           (Taking out of slave address value)
SEI               (Interrupt disabled)
STA   S0          (Writing of slave address value)
LDM   #$F0, S1    (Trigger of RESTART condition generating)
CLI               (Interrupt enabled)
        •
        •
```

②Select the slave receive mode when the PIN bit is “0.” Do not write “1” to the PIN bit. Neither “0” nor “1” is specified for the writing to the BB bit.

The TRX bit becomes “0” and the SDA pin is released.

③The SCL pin is released by writing the slave address value to the I^2C data shift register. Use “STA,” “STX” or “STY” of the zero page addressing instruction for writing.

④Use “LDM” instruction for setting trigger of RESTART condition generating.

⑤Write the slave address value of above ③ and set trigger of RESTART condition generating of above ④ continuously shown the above procedure example.

⑥Disable interrupts during the following two process steps:

- Writing of slave address value
- Trigger of RESTART condition generating

(4) STOP condition generating procedure

①Procedure example (The necessary conditions of the generating procedure are described as the following ② to ④.)

```
        •
        •
SEI               (Interrupt disabled)
LDM   #$C0, S1    (Select master transmit mode)
NOP               (Set NOP)
LDM   #$D0, S1    (Trigger of STOP condition generating)
CLI               (Interrupt enabled)
        •
        •
```

②Write “0” to the PIN bit when master transmit mode is select.

③Execute “NOP” instruction after setting of master transmit mode. Also, set trigger of STOP condition generating within 10 cycles after selecting of master trasmit mode.

④Disable interrupts during the following two process steps:

- Select of master transmit mode
- Trigger of STOP condition generating

(5) Writing to I^2C status register

Do not execute an instruction to set the PIN bit to “1” from “0” and an instruction to set the MST and TRX bits to “0” from “1” simultaneously. It is because it may enter the state that the SCL pin is released and the SDA pin is released after about one machine cycle. Do not execute an instruction to set the MST and TRX bits to “0” from “1” simultaneously when the PIN bit is “1.” It is because it may become the same as above.

(6) Process of after STOP condition generating

Do not write data in the I^2C data shift register S0 and the I^2C status register S1 until the bus busy flag BB becomes “0” after generating the STOP condition in the master mode. It is because the STOP condition waveform might not be normally generated. Reading to the above registers do not have the problem.

8.7 PWM OUTPUT FUNCTION

This microcomputer is equipped with six 8-bit PWMs (PWM0–PWM5). PWM0–PWM5 have the same circuit structure and an 8-bit resolution with minimum resolution bit width of 4 μs (for f(XIN) = 8 MHz) and repeat period of 1024 μs (for f(XIN) = 8 MHz).
Figure 8.7.1 shows the PWM block diagram. The PWM timing generating circuit applies individual control signals to PWM0–PWM5 using f(XIN) divided by 2 as a reference signal.

8.7.1 Data Setting

When outputting PWM0–PWM5, set 8-bit output data to the PWMi register (i means 0 to 5; addresses 0200_{16} to 0205_{16}).

8.7.2 Transmitting Data from Register to PWM circuit

Data transfer from the 8-bit PWM register to the 8-bit PWM circuit is executed at writing data to the register.
The signal output from the 8-bit PWM output pin corresponds to the contents of this register.

8.7.3 Operating of 8-bit PWM

The following explains PWM operation.
First, set the bit 0 of PWM mode register 1 (address 0208_{16}) to “0” (at reset, bit 0 is already set to “0” automatically), so that the PWM count source is supplied.
PWM0–PWM5 are also used as pins $P0_0$–$P0_5$. Set the corresponding bits of the port P0 direction register to “1” (output mode). And select each output polarity by bit 3 of PWM mode register 1 (address 0208_{16}). Then, set bits 5 to 0 of PWM mode register 2 (address 0209_{16}) to “1” (PWM output).
The PWM waveform is output from the PWM output pins by setting these registers.
Figure 17 shows the 8-bit PWM timing. One cycle (T) is composed of 256 (2^8) segments. The 8 kinds of pulses relative to the weight of each bit (bits 0 to 7), are output inside the circuit during 1 cycle. Refer to Figure 17 (a). The 8-bit PWM outputs waveform which is the logical sum (OR) of pulses corresponding to the contents of bits 0 to 7 of the 8-bit PWM register. Several examples are shown in Figure 17 (b). 256 kinds of output (HIGH area: 0/256 to 255/256) are selected by changing the contents of the PWM register. A length of entirely HIGH cannot be output, i.e. 256/256.

8.7.4 Output after Reset

At reset, the output of ports $P0_0$–$P0_5$ is in the high-impedance state, and the contents of the PWM register and the PWM circuit are undefined. Note that after reset, the PWM output is undefined until setting the PWM register.




Fig. 8.7.1 PWM Block Diagram





Fig. 8.7.2 PWM Timing

PWM Mode Register 1




PWM mode register 1 (PM1) [Address 0208_{16}]

B	Name	Functions	After reset	R	W
0	PWM counts source selection bit (PM10)	0 : Count source supply 1 : Count source stop	0	R	W
1, 2	Nothing is assigned. These bits are write disable bits. When these bits are read out, the values are 0.		Indeterminate	R	
3	PWM output polarity selection bit (PM13)	0 : Positive polarity 1 : Negative polarity	0	R	W
4 to 7	Nothing is assigned. These bits are write disable bits. When these bits are read out, the values are 0.		Indeterminate	R	

Fig. 8.7.3 PWM Mode Register 1

PWM Mode Register 2



PWM mode register 2 (PM2) [Address 0209_{16}]

B	Name	Functions	After reset	R	W
0	$P0_0$/PWM0 output selection bit (PM20)	0 : $P0_0$ output 1 : PWM0 output	0	R	W
1	$P0_1$/PWM1 output selection bit (PM21)	0 : $P0_1$ output 1 : PWM1 output	0	R	W
2	$P0_2$/PWM2 output selection bit (PM22)	0 : $P0_2$ output 1 : PWM2 output	0	R	W
3	$P0_3$/PWM3 output selection bit (PM23)	0 : $P0_3$ output 1 : PWM3 output	0	R	W
4	$P0_4$/PWM4 output selection bit (PM24)	0 : $P0_4$ output 1 : PWM4 output	0	R	W
5	$P0_5$/PWM5 output selection bit (PW25)	0: $P0_5$ output 1: PWM5 output	0	R	W
6, 7	Fix these bits to 0.		0	R	W

Fig. 8.7.4 PWM Mode Register 2

8.8 A-D COMPARATOR

A-D comparator consists of 6-bit D-A converter and comparator. A-D comparator block diagram is shown in Figure 8.8.1.

The reference voltage "V_{ref}" for D-A conversion is set by bits 0 to 5 of A-D control register 2 (address $00ED_{16}$).

The comparison result of the analog input voltage and the reference voltage "V_{ref}" is stored in bit 4 of A-D control register 1 (address $00EC_{16}$).

For A-D comparison, set "0" to corresponding bits of the direction register to use ports as analog input pins. Write the data for select of analog input pins to bits 0 to 2 of A-D control register 1 and write the digital value corresponding to V_{ref} to be compared to the bits 0 to 5 of A-D control register 2. The voltage comparison starts by writing to A-D control register 2, and it is completed after 16 machine cycles (NOP instruction × 8).




Fig. 8.8.1 A-D Comparator Block Diagram

A-D Control Register 1

b7 b6 b5 b4 b3 b2 b1 b0

A-D control register 1 (AD1) [Address 00EC16]

B	Name	Functions	After reset	R	W
0 to 2	Analog input pin selection bits (ADC10 to ADC12)	b2 b1 b0 0 0 0 : AD1 0 0 1 : AD2 0 1 0 : AD3 0 1 1 : AD4 1 0 0 : AD5 1 0 1 : AD6 1 1 0 : } Do not set. 1 1 1 : }	0	R	W
3	This bit is a write disable bit. When this bit is read out, the value is "0."		0	R	—
4	Storage bit of comparison result (ADC14)	0: Input voltage < reference voltage 1: Input voltage > reference voltage	Indeterminate	R	W
5 to 7	Nothing is assigned. This bits are write disable bits. When these bits are read out, the values are "0."		0	R	—

Fig. 8.8.2 A-D Control Register 1

A-D Control Register 2

b7 b6 b5 b4 b3 b2 b1 b0

A-D control register 2 (AD2) [Address 00ED16]

B	Name	Functions	After reset	R	W
0 to 5	D-A converter set bits (ADC20 to ADC25)	b5 b4 b3 b2 b1 b0 0 0 0 0 0 0 : 1/128Vcc 0 0 0 0 0 1 : 3/128Vcc 0 0 0 0 1 0 : 5/128Vcc ⋮ 1 1 1 1 0 1 : 123/128Vcc 1 1 1 1 1 0 : 125/128Vcc 1 1 1 1 1 1 : 127/128Vcc	0	R	W
6, 7	Nothing is assigned. These bits are write disable bits. When these bits are reed out, the values are 0.		0	R	

Fig. 8.8.3 A-D Control Register 2

8.9 ROM CORRECTION FUNCTION

This can correct program data in ROM. Up to 2 addresses can be corrected, a program for correction is stored in the ROM correction vector in RAM as the top address. The ROM correction vectors are 2 vectors.

Vector 1 : address 0300_{16}
Vector 2 : address 0320_{16}

Set the address of the ROM data to be corrected into the ROM correction address register. When the value of the counter matches the ROM data address in the ROM correction vector as the top address, the main program branches to the correction program stored in the ROM memory for correction. To return from the correction program to the main program, the op code and operand of the JMP instruction (total of 3 bytes) are necessary at the end of the correction program. The ROM correction function is controlled by the ROM correction enable register.

Notes 1: Specify the first address (op code address) of each instruction as the ROM correction address.
2: Use the JMP instruction (total of 3 bytes) to return from the correction program to the main program.
3: Do not set the same ROM correction address to vectors 1 and 2.




Fig. 8.9.1 ROM Correction Address Registers

ROM Correction Enable Register

b7 b6 b5 b4 b3 b2 b1 b0

ROM correction enable register (RCR) [Address 020E 16]

B	Name	Functions	After reset	R	W
0	Vector 1 enable bit (RC0)	0: Disabled 1: Enabled	0	R	W
1	Vector 2 enable bit (RC1)	0: Disabled 1: Enabled	0	R	W
2 to 7	Nothing is assigned. These bits are write disable bits. When these bits are read out, the values are “0.”		0	R	—

Fig. 8.9.2 ROM Correction Enable Register

8.10 DATA SLICER

This microcomputer includes the data slicer function for the closed caption decoder (referred to as the CCD). This function takes out the caption data superimposed in the vertical blanking interval of a composite video signal. A composite video signal which makes the sync chip's polarity negative is input to the CV_{IN} pin.

When the data slicer function is not used, the data slicer circuit and the timing signal generating circuit can be cut off by setting bit 0 of the data slicer control register 1 (address $00E0_{16}$) to "0." These settings can realize the low-power dissipation.




Fig. 8.10.1 Data Slicer Block Diagram

8.10.1 Notes When not Using Data Slicer

When bit 0 of data slicer control register 1 (address $00E0_{16}$) is "0," terminate the pins as shown in Figure 8.10.2.

<When data slicer circuit and timing signal generating circuit is in OFF state>

*(Apply the same voltage as V_{CC} to AV_{CC} pin.)

Leave HLF pin open.

Leave V_{HOLD} pin open.

Pull-down CV_{IN} pin to V_{SS} through a resistor of 5 kΩ or more.

*( ) ... M37272E8/EF




Fig. 8.10.2 Termination of Data Slicer Input/Output Pins when Data Slicer Circuit and Timing Generating Circuit Is in OFF State

When both bits 0 and 2 of data slicer control register 1 (address $00E0_{16}$) are "1," terminate the pins as shown in Figure 8.10.3.

<When using a reference clock generated in timing signal generating circuit as OSD clock>

*(Apply the same voltage as V_{CC} to AV_{CC} pin.)

Connect the same external circuit as when using data slicer to HLF pin.

Leave V_{HOLD} pin open.

Pull-up CV_{IN} to V_{CC} through a resistor of 5 kΩ or more.

*( ) ... M37272E8/EF




Fig. 8.10.3 Termination of Data Slicer Input/Output Pins when Timing Signal Generating Circuit Is in ON State

Figures 8.10.4 and 8.10.5 the data slicer control registers.

Data Slicer Control Register 1

b7 b6 b5 b4 b3 b2 b1 b0
0 1 1 0 0 | | | |

Data slicer control register 1(DSC1) [Address $00E0_{16}$]

B	Name	Functions	After reset	R	W
0	Data slicer and timing signal generating circuit control bit (DSC10)	0: Stopped 1: Operating	0	R	W
1	Selection bit of data slice reference voltage generating field (DSC11)	0: F2 1: F1	0	R	W
2	Reference clock source selection bit (DSC12)	0: Video signal 1: HSYNC signal	0	R	W
3, 4	Fix these bits to "0."		0	R	W
5, 6	Fix these bits to "1."		0	R	W
7	Fix this bit to "0."		0	R	W

Definition of fields 1 (F1) and 2 (F2)




Fig. 8.10.4 Data Slicer Control Register 1

Data Slicer Control Register 2

b7 b6 b5 b4 b3 b2 b1 b0
| 0 | | | | | | 1 | |

Data slicer control register 2 (DSC2) [Address $00E1_{16}$]

B	Name	Functions	After reset	R	W
0	Caption data latch completion flag 1 (DSC20)	0: Data is not latched yet and a clock-run-in is not determined. 1: Data is latched and a clock-run-in is determined.	Indeterminate	R	—
1	Fix this bit to "1."		0	R	W
2	Test bit	Read-only	Indeterminate	R	—
3	Field determination flag(DSC23)	0: F2 1: F1	Indeterminate	R	—
4	Vertical synchronous signal (V_{sep}) generating method selection bit (DSC24)	0: Method (1) 1: Method (2)	0	R	W
5	V-pulse shape determination flag (DSC25)	0: Match 1: Mismatch	Indeterminate	R	—
6	Fix this bit to "o."		0	R	W
7	Test bit	Read-only	Indeterminate	R	—

Definition of fields 1 (F1) and 2 (F2)




Fig. 8.10.5 Data Slicer Control Register 2

8.10.2 Clamping Circuit and Low-pass Filter

The clamp circuit clamps the sync chip part of the composite video signal input from the CV_{IN} pin. The low-pass filter attenuates the noise of clamped composite video signal. The CV_{IN} pin to which composite video signal is input requires a capacitor (0.1 μF) coupling outside. Pull down the CV_{IN} pin with a resistor of hundreds of kiloohms to 1 MΩ. In addition, we recommend to install externally a simple low-pass filter using a resistor and a capacitor at the CV_{IN} pin (refer to Figure 8.10.1).

8.10.3 Sync Slice Circuit

This circuit takes out a composite sync signal from the output signal of the low-pass filter.

8.10.4 Synchronous Signal Separation Circuit

This circuit separates a horizontal synchronous signal and a vertical synchronous signal from the composite sync signal taken out in the sync slice circuit.

(1)Horizontal Synchronous Signal (H_{sep})

A one-shot horizontal synchronizing signal Hsep is generated at the falling edge of the composite sync signal.

(2)Vertical Synchronous Signal (V_{sep})

As a V_{sep} signal generating method, it is possible to select one of the following 2 methods by using bit 4 of the data slicer control register 2 (address $00E1_{16}$).

- •Method 1 The LOW level width of the composite sync signal is measured. If this width exceeds a certain time, a V_{sep} signal is generated in synchronization with the rising of the timing signal immediately after this LOW level.
- •Method 2 The LOW level width of the composite sync signal is measured. If this width exceeds a certain time, it is detected whether a falling of the composite sync signal exits or not in the LOW level period of the timing signal immediately after this LOW level. If a falling exists, a V_{sep} signal is generated in synchronization with the rising of the timing signal (refer to Figure 8.10.6).

Figure 8.10.6 shows a V_{sep} generating timing. The timing signal shown in the figure is generated from the reference clock which the timing generating circuit outputs.

Reading bit 5 of data slicer control register 2 permits determinating the shape of the V-pulse portion of the composite sync signal. As shown in Figure 8.10.7, when the A level matches the B level, this bit is “0.” In the case of a mismatch, the bit is “1.”




Fig. 8.10.6 Vsep Generating Timing (method 2)

8.10.5 Timing Signal Generating Circuit

This circuit generates a reference clock which is 832 times as large as the horizontal synchronous signal frequency. It also generates various timing signals on the basis of the reference clock, horizontal synchronous signal and vertical synchronizing signal. The circuit operates by setting bit 0 of data slicer control register 1 (address $00E0_{16}$) to "1."

The reference clock can be used as a display clock for OSD function in addition to the data slicer. The HSYNC signal can be used as a count source instead of the composite sync signal. However, when the HSYNC signal is selected, the data slicer cannot be used. A count source of the reference clock can be selected by bit 2 of data slicer control register 1 (address $00E0_{16}$).

For the pins HLF, connect a resistor and a capacitor as shown in Figure 8.10.1. Make the length of wiring which is connected to these pins as short as possible so that a leakage current may not be generated.

Note: It takes a few tens of milliseconds until the reference clock becomes stable after the data slicer and the timing signal generating circuit are started. In this period, various timing signals, H_{sep} signals and V_{sep} signals become unstable. For this reason, take stabilization time into consideration when programming.




Fig. 8.10.7 Determination of V-pulse Waveform

8.10.6 Data Slice Line Specification Circuit

(1) Specification of data slice line

This circuit decides a line on which caption data is superimposed. The line 21 (fixed), 1 appropriate line for a period of 1 field (total 2 line for a period of 1 field), and both fields (F1 and F2) are sliced their data. The caption position register (address $00E6_{16}$) is used for each setting (refer to Table 8.10.1).

The counter is reset at the falling edge of V_{sep} and is incremented by 1 every H_{sep} pulse. When the counter value matched the value specified by bits 4 to 0 of the caption position register, this H_{sep} is sliced.

The values of "00_{16}" to "$1F_{16}$" can be set in the caption position register (at setting only 1 appropriate line). Figure 8.10.8 shows the signals in the vertical blanking interval. Figure 8.10.9 shows the structure of the caption position register.

(2) Specification of line to set slice voltage

The reference voltage for slicing (slice voltage) is generated for the clock run-in pulse in the particular line (refer to Table 8.10.1). The field to generate slice voltage is specified by bit 1 of data slicer control register 1. The line to generate slice voltage 1 field is specified by bits 6, 7 of the caption position register (refer to Table 8.10.1).

(3) Field determination

The field determination flag can be read out by bit 3 of data slicer control register 2. This flag charge at the falling edge of V_{sep}.





Fig. 8.10.8 Signals in Vertical Blanking Interval

Caption Position Register



Caption Position Register (CPS) [Address $00E6_{16}$]

B	Name	Functions	After reset	R	W
0 to 4	Caption position bits(CPS0 to CPS4)		0	R	W
5	Caption data latch completion flag 2 (CPS5)	0: Data is not latched yet and a clock-run-in is not determined. 1: Data is latched and a clock-run-in is determined.	Indeterminate	R	
6, 7	Slice line mode specification bits (in 1 field) (CPS6, CPS7)	Refer to the corresponding Table (Table 8.10.1).	0	R	W

Fig. 8.10.9 Caption Position Register

Table 8.10.1 Specification of Data Slice Line

CPS		Field and Line to Be Sliced Data	Field and Line to Generate Slice Voltage
b7	b6		
0	0	• Both fields of F1 and F2 • Line 21 and a line specified by bits 4 to 0 of CPS (total 2 lines) (See note 2)	• Field specified by bit 1 of DSC1 • Line 21 (total 1 line)
0	1	• Both fields of F1 and F2 • A line specified by bits 4 to 0 of CPS (total 1 line) (See note 3)	• Field specified by bit 1 of DSC1 • A line specified by bits 4 to 0 of CPS (total 1 line) (See note 3)
1	0	• Both fields of F1 and F2 • Line 21 (total 1 line)	• Field specified by bit 1 of DSC1 • Line 21 (total 1 line)
1	1	• Both fields of F1 and F2 • Line 21 and a line specified by bits 4 to 0 of CPS (total 2 lines) (See note 2)	• Field specified by bit 1 of DSC1 • Line 21 and a line specified by bits 4 to 0 of CPS (total 2 lines) (See note 2)

Notes 1: DSC1 is data slicer control register 1.
CPS is caption position register.
2: Set "00_{16}" to "10_{16}" to bits 4 to 0 of CPS.
3: Set "00_{16}" to "$1F_{16}$" to bits 4 to 0 of CPS.

8.10.7 Reference Voltage Generating Circuit and Comparator

The composite video signal clamped by the clamping circuit is input to the reference voltage generating circuit and the comparator.

(1) Reference voltage generating circuit

This circuit generates a reference voltage (slice voltage) by using the amplitude of the clock run-in pulse in line specified by the data slice line specification circuit. Connect a capacitor between the V_{HOLD} pin and the V_{SS} pin, and make the length of wiring as short as possible so that a leakage current may not be generated.

(2) Comparator

The comparator compares the voltage of the composite video signal with the voltage (reference voltage) generated in the reference voltage generating circuit, and converts the composite video signal into a digital value.

8.10.8 Start Bit Detecting Circuit

This circuit detects a start bit at line decided in the data slice line specification circuit.

The detection of a start bit is described below.

① A sampling clock is generated by dividing the reference clock output by the timing signal.
② A clock run-in pulse is detected by the sampling clock.
③ After detection of the pulse, a start bit pattern is detected from the comparator output.

8.10.9 Clock Run-in Determination Circuit

This circuit determinates clock run-in by counting the number of pulses in a window of the composite video signal.

The reference clock count value in one pulse cycle is stored in bits 3 to 7 of the clock run-in detect register (address $00E4_{16}$). Read out these bits after the occurrence of a data slicer interrupt (refer to "8.10.12 Interrupt Request Generating Circuit").

Figure 8.10.10 shows the structure of clock run-in detect register.

Clock Run-in Detect Register

b7 b6 b5 b4 b3 b2 b1 b0

Clock run-in detect register (CRD) [Address $00E4_{16}$]

B	Name	Functions	After reset	R	W
0 to 2	Test bits	Read-only	0	R	—
3 to 7	Clock run-in detection bit (CRD3 to CRD7)	Number of reference clocks to be counted in one clock run-in pulse period.	0	R	—

Fig. 8.10.10 Clock Run-in Detect Register

8.10.10 Data Clock Generating Circuit

This circuit generates a data clock synchronized with the start bit detected in the start bit detecting circuit. The data clock stores caption data to the 16-bit shift register. When the 16-bit data has been stored and the clock run-in determination circuit determines clock run-in, the caption data latch completion flag is set. This flag is reset at a falling of the vertical synchronous signal (V_{sep}).

Data Clock Position Register

b7	b6	b5	b4	b3	b2	b1	b0
					0	1	0

Data clock position register (DPS) [Address $00E5_{16}$]

B	Name	Functions	After reset	R	W
0	Fix this bit to “0.”		1	R	W
1	Fix this bit to “1.”		0	R	W
2	Fix this bit to “0.”		0	R	W
3	Data clock position set bits (DPS3 to DPS7)		1	R	W
4 to 7			0		

Fig. 8.10.11 Data Clock Position Register

8.10.11 16-bit Shift Register

The caption data converted into a digital value by the comparator is stored into the 16-bit shift register in synchronization with the data clock. The contents of the high-order 8 bits of the stored caption data can be obtained by reading out data register 2 (address $00E3_{16}$) and data register 4 (address $00CF_{16}$). The contents of the low-order 8 bits can be obtained by reading out data register 1 (address $00E2_{16}$) and data register 3 (address $00CE_{16}$), respectively. These registers are reset to "0" at a falling of V_{sep}. Read out data registers 1 and 2 after the occurrence of a data slicer interrupt (refer to "8.10.12 Interrupt Request Generating Circuit").

8.10.12 Interrupt Request Generating Circuit

The interrupt requests as shown in Table 8.10.3 are generated by combination of the following bits; bits 6 and 7 of the caption position register (address $00E6_{16}$). Read out the contents of data registers 1 to 4 and the contents of bits 3 to 7 of the clock run-in detect register after the occurrence of a data slicer interrupt request.

Table 8.10.2 Contents of Caption Data Latch Completion Flag and 16-bit Shift Register

Slice Line Specification Mode		Contents of Caption Data Latch Completion Flag		Contents of 16-bit Shift Register	
CPS		Completion Flag 1 (bit 0 of DSC2)	Completion Flag 2 (bit 5 of CPS)	Caption Data Registers 1, 2	Caption Data Registers 3, 4
bit 7	bit 6				
0	0	Line 21	A line specified by bits 4 to 0 of CPS	16-bit data of line 21	16-bit data of a line specified by bits 4 to 0 of CPS
0	1	A line specified by bits 4 to 0 of CPS	Invalid	16-bit data of a line specified by bits 4 to 0 of CPS	Invalid
1	0	Line 21	Invalid	16-bit data of line 21	Invalid
1	1	Line 21	A line specified by bits 4 to 0 of CPS	16-bit data of line 21	16-bit data of a line specified by bits 4 to 0 of CPS

CPS: Caption position register
DSC2: Data slicer control register 2

Table 8.10.3 Occurence Sources of Interrupt Request

Caption position register		Occurence Souces of Interrupt Request at End of Data Slice Line
b7	b6	
0	0	After slicing line 21
	1	After a line specified by bits 4 to 0 of CPS
1	0	After slicing line 21
	1	After slicing line 21

8.10.13 Synchronous Signal Counter

The synchronous signal counter counts the composite sync signal taken out from a video signal in the data slicer circuit or the vertical synchronous signal V_{sep} as a count source.

The count value in a certain time (T time) generated by $f(X_{IN})/2^{13}$ or $f(X_{IN})/2^{13}$ is stored into the 5-bit latch. Accordingly, the latch value changes in the cycle of T time. When the count value exceeds "$1F_{16}$," "$1F_{16}$" is stored into the latch.

The latch value can be obtained by reading out the sync pulse counter register (address $00E9_{16}$). A count source is selected by bit 5 of the sync pulse counter register.

The synchronous signal counter is used when bit 0 of PWM mode register 1 (address 0208_{16}).

Figure 8.10.12 shows the structure of the sync pulse counter and Figure 8.10.13 shows the synchronous signal counter block diagram.

Sync Pulse Counter Register

b7 b6 b5 b4 b3 b2 b1 b0

Sync pulse counter register (HC) [Address $00E9_{16}$]

B	Name	Functions	After reset	R	W
0 to 4	Count value (HC0 to HC4)		0	R	
5	Count source (HC5)	0: H_{SYNC} signal 1: Composite sync signal	0	R	W
6, 7	Nothing is assigned. These bits are write disable bits. When these bits are read out, the values are 0.		0	R	

Fig. 8.10.12 Sync Pulse Counter Register




Fig. 8.10.13 Synchronous Signal Counter Block Diagram

8.11 OSD FUNCTIONS

Table 8.11.1 outlines the OSD functions.

This microcomputer incorporates an OSD circuit of 32 characters × 2 lines. And also, there are 2 display modes and they are selected by a block unit. The display modes are selected by bits 0 and 1 of block control register i (i = 1 and 2).

The features of each mode are described below.

Table 8.11.1 Features of Each Display Mode

Parameter		Display mode	
		CC mode (Closed caption mode)	OSD mode (Border OFF) (On-screen display mode)
Number of display characters		32 characters × 2 lines	
Dot structure		16 × 26 dots (Character display area : 16 × 20 dots)	16 × 20 dots
Kinds of characters		254 kinds	
Kinds of character sizes		1 kinds	8 kinds
	Pre-divide ratio (See note)	× 2 (fixed)	× 2, × 3
	Dot size	1Tc × 1/2H	1Tc × 1/2H, 1Tc × 1H, 2Tc × 2H, 3Tc × 3H
Attribute		Smooth italic, under line, flash	Border (black)
Character font coloring		1 screen : 8 kinds (per character unit)	
Character background coloring		—	1 screen : 8 kinds (per character unit)
OSD output		R, G, B	
Raster coloring		Possible (per character unit)	
Function		Auto solid space function Window function	—
Display position		Horizontal: 128 levels, Vertical: 512 levels	
Display expansion (multiline display)		Possible	

Notes 1: The divide ratio of the frequency divider (the pre-divide circuit) is referred as “pre-divide ratio” hereafter.
2: The character size is specified with dot size and pre-divide ratio (refer to 8.11.2 Dot Size).

The OSD circuit has an extended display mode. This mode allows multiple lines (3 lines or more) to be displayed on the screen by interrupting the display each time one line is displayed and rewriting data in the block for which display is terminated by software.
Figure 8.11.1 shows the configuration of OSD character. Figure 8.11.2 shows the block diagram of the OSD circuit. Figure 8.11.3 shows the OSD control register. Figure 8.11.4 shows the block control register i.




Fig. 8.11.1 Configuration of OSD Character Display Area




Fig. 8.11.2 Block Diagram of OSD Circuit

OSD Control Register

b7 b6 b5 b4 b3 b2 b1 b0

0 | | | | | | | |


OSD control register (OC) [Address 00D0 16]

B	Name	Functions	After reset	R	W
0	OSD control bit (OC0) (See note)	0 : All-blocks display off 1 : All-blocks display on	0	R	W
1	Automatic solid space control bit (OC1)	0 : OFF 1 : ON	0	R	W
2	Window control bit (OC2)	0 : OFF 1 : ON	0	R	W
3	CC mode clock selection bit (OC3)	0 : Data slicer clock 1 : Clock from OSC1 pin	0	R	W
4	OSD mode clock selection bit (OC4)	0 : Data slicer clock 1 : Clock from OSC1 pin	0	R	W
5, 6	OSC1 clock selection bit (OC5, OC6)	b6 b5 0 0: 32 kHz oscillating 0 1: Do not set. 1 0: LC oscillating, Ceramic oscillating 1 1: Do not set.	0	R	W
7	Fix this bit to 0.		0	R	W

Note: Even this bit is switched during display, the display screen remains unchanged until a rising (falling) of the next V SYNC.

Fig. 8.11.3 OSD Control Register

Block Control register i



Block control register i (BCi) (i=1, 2) [Addresses 00D2 16 and 00D316]

B	Name	Functions	After reset	R	W
0, 1	Display mode selection bits (BCi0, BCi1) (See note 1)	b1 b0 0 0: Display OFF 0 1: CC mode 1 0: OSD mode (Border OFF) 1 1: OSD mode (Border ON)	Indeterminate	R	W
2, 3	Dot size selection bits (BCi2, BCi3)	b4 / b3 / b2 / Pre-divide Ratio / Dot Size 0 / 0 / 0 / ×2 / 1Tc × 1/2H 0 / 0 / 1 / ×2 / 1Tc × 1H 0 / 1 / 0 / ×2 / 2Tc × 2H 0 / 1 / 1 / ×2 / 3Tc × 3H	Indeterminate	R	W
4	Pre-divide ratio selection bit (BCi4)	1 / 0 / 0 / ×3 / 1Tc × 1/2H 1 / 0 / 1 / ×3 / 1Tc × 1H 1 / 1 / 0 / ×3 / 2Tc × 2H 1 / 1 / 1 / ×3 / 3Tc × 3H	Indeterminate	R	W
5	OUT1/OUT2 output control bit (BCi5) (See note 1)	0: OUT1 output control 1: OUT2 output control	Indeterminate	R	W
6	Vertical display start position control bit (BCi6)	BC16: Block 1 BC26: Block 1	Indeterminate	R	W
7	Window top/bottom boundary control bit (BCi7)	BC17: Window top boundary BC27: Window bottom boundary	Indeterminate	R	W

Notes 1: Bit RA3 of OSD RAM controls OUT1 output when bit 5 is “0.”
Bit RA3 of OSD RAM controls OUT2 output when bit 5 is “1.”
2: Tc is OSD clock cycle divided in pre-divide circuit.
3: H is HSYNC.

Fig. 8.11.4 Block Control Register i

8.11.1 Display Position

The display positions of characters are specified in units called a "block." There are 2 blocks, blocks 1 and 2. Up to 32 characters can be displayed in each block (refer to "8.11.5 Memory for OSD").


The display position of each block can be set in both horizontal and vertical directions by software.

The display start position in the horizontal direction can be selected for all blocks in common from 128-step display positions in units of 4TOSC (TOSC = OSD oscillation cycle).

The display start position in the vertical direction for each block can be selected from 512-step display positions in units of 1 TH (TH = HSYNC cycle).

Blocks are displayed in conformance with the following rules:

- When the display position of block 1 is overlapped with that of block 2 (Figure 8.11.5 (b)), the block 1 is displayed on the front.
- When another block display position appears while one block is displayed (Figure 8.11.5 (c)), the block with a larger set value as the vertical display start position is displayed.



(a) Example when each block is separated


(b) Example when block 2 overlaps with block 1

(c) Example when block 2 overlaps in process of block 1

Note: VP1 or VP2 indicates the vertical display start position of display block 1 or 2.

Fig. 8.11.5 Display Position

The vertical display start position is determined by counting the horizontal sync signal (HSYNC). At this time, when VSYNC and HSYNC are positive polarity (negative polarity), it starts to count the rising edge (falling edge) of HSYNC signal from after fixed cycle of rising edge (falling edge) of VSYNC signal. So interval from rising edge (falling edge) of VSYNC signal to rising edge (falling edge) of HSYNC signal needs enough time (2 machine cycles or more) for avoiding jitter. The polarity of HSYNC and VSYNC signals can select with the I/O polarity control register (address 00D8$_{16}$).




When bits 0 and 1 of the I/O polarity control register (address 00D8$_{16}$) are set to "1" (negative polarity)

Notes 1 : The vertical position is determined by counting falling edge of HSYNC signal after rising edge of VSYNC control signal in the microcomputer.
2 : Do not generate falling edge of HSYNC signal near rising edge of VSYNC control signal in microcomputer to avoid jitter.
3 : The pulse width of VSYNC and HSYNC needs 8 machine cycles or more.

Fig. 8.11.6 Supplement Explanation for Display Position

The vertical display start position for each block can be set in 512 steps (where each step is 1T_H (T_H: H_{SYNC} cycle)) as values "00$_{16}$" to "FF$_{16}$" in vertical position register i (i = 1 and 2) (addresses 00D4$_{16}$ and 00D5$_{16}$) and values "0" or "1" in bit 6 of block control register i (i = 1 and 2) (addresses 00D2$_{16}$ and 00D3$_{16}$). The vertical position registers is shown in Figure 8.11.7.

Vertical Position Register i



Vertical position register i (VPi) (i = 1 and 2) [Addresses 00D4$_{16}$, 00D5$_{16}$]

B	Name	Functions	After reset	R	W
0 to 7	Vertical display start position control bits (VPi0 to VPi7) (See note)	Vertical display start position = $T_H \times (BCi6 \times 16^2 + n)$ (n: setting value, T_H: H_{SYNC} cycle, BCi6: bit 6 of block control register i)	Inderterminate	R	W

Note: Set values except 00$_{16}$ to VPi when BCi6 is 0.

Fig. 8.11.7 Vertical Position Register i (i = 1 and 2)

The horizontal display start position is common to all blocks, and can be set in 128 steps (where 1 step is 4TOSC, TOSC being the OSD oscillation cycle) as values "00$_{16}$" to "FF$_{16}$" in bits 0 to 6 of the horizontal position register (address 00D1$_{16}$). The horizontal position register is shown in Figure 8.11.8.

Horizontal Position Register

b7 b6 b5 b4 b3 b2 b1 b0

Horizontal position register (HP) [Address 00D1 $_{16}$]

B	Name	Functions	After reset	R	W
0 to 6	Horizontal display start position control bits (HP0 to HP6)	Horizontal display start positions 128 steps (00$_{16}$ to 7F$_{16}$) (1 step is 4TOSC)	0	R	W
7	Nothing is assigned. This bit is a write disable bit. When this bit is read out, the value is "0."		0	R	—

Note: The setting value synchronizes with the V SYNC.

Fig. 8.11.8 Horizontal Position Register

Notes 1 : 1TC (TC : OSD clock cycle divided in pre-divide circuit) gap occurs between the horizontal display start position set by the horizontal position register and the most left dot of the 1st block. Accordingly, when 2 blocks have different pre-divide ratios, their horizontal display start position will not match.

2 : The horizontal start position is based on the OSD clock source cycle selected for each block. Accordingly, when 2 blocks have different OSD clock source cycles, their horizontal display start position will not match.

3 : When setting "00$_{16}$" to the horizontal position register, it needs approximately 62TOSC (= Tdef) interval from a rising edge (when negative polarity is selected) of HSYNC signal to the horizontal display start position.




Fig. 8.11.9 Notes on Horizontal Display Start Position

8.11.2 Dot Size

The dot size can be selected by a block unit. The dot size in vertical direction is determined by dividing HSYNC in the vertical dot size control circuit. The dot size in horizontal is determined by dividing the following clock in the horizontal dot size control circuit : the clock gained by dividing the OSD clock source (data slicer clock, OSC1) in the pre-divide circuit. The clock cycle divided in the pre-divide circuit is defined as 1TC.

The dot size of each block is specified by bits 2 to 4 of the block control register i.

Refer to Figure 8.11.4 (the structure of the block control register).

The block diagram of dot size control circuit is shown in Figure 8.11.10.




Fig. 8.11.10 Block Diagram of Dot Size Control Circuit




Fig. 8.11.11 Definition of Dot Sizes

8.11.3 Clock for OSD


As a clock for display to be used for OSD, it is possible to select one of the following 3 types.

- Data slicer clock output from the data slicer (approximately 26 MHz)
- OSC1 clock supplied from the pins OSC1 and OSC2
- Clock from the ceramic resonator or the LC oscillator from the pins OSC1 and OSC2

This OSD clock for each block can be selected by the following bits : bit 7 of the raster color register (address $00D9_{16}$), bits 3 to 6 of the clock source control register (addresses $00D0_{16}$). A variety of character sizes can be obtained by combining dot sizes with OSD clocks. When not using the pins OSC1 and OSC2 for the OSD clock I/O pins, the pins can be used as sub-clock I/O pins or port P2.

Table 8.11.2 Setting for $P2_6$/OSC1/X_{CIN}, $P2_7$/OSC2/X_{COUT}

Register \ Function		OSD clock I/O Pin	Sub-clock I/O Pin	I/O Port
b7 of raster color register		0	0	1
OSD control register	b6	1	0	1
	b5	0	0	0



Note : To use data slicer clock, set bit 0 of data slicer control register 1 to "1."

Fig. 8.11.12 Block Diagram of OSD Selection Circuit

8.11.4 Field Determination Display

To display the block with vertical dot size of 1/2H, whether an even field or an odd field is determined through differences in a synchronizing signal waveform of interlacing system. The dot line 0 or 1 (refer to Figure 8.11.14) corresponding to the field is displayed alternately.

In the following, the field determination standard for the case where both the horizontal sync signal and the vertical sync signal are negative-polarity inputs will be explained. A field determination is determined by detecting the time from a falling edge of the horizontal sync signal until a falling edge of the VSYNC control signal (refer to Figure 8.11.6) in the microcomputer and then comparing this time with the time of the previous field. When the time is longer than the comparing time, it is regarded as even field. When the time is shorter, it is regarded as odd field

The contents of this field can be read out by the field determination flag (bit 6 of the I/O polarity control register at address $00D8_{16}$). A dot line is specified by bit 5 of the I/O polarity control register (refer to Figure 8.11.14).

However, the field determination flag read out from the CPU is fixed to “0” at even field or “1” at odd field, regardless of bit 5.

I/O Polarity Control Register

b7 b6 b5 b4 b3 b2 b1 b0

0 | | | | | | | |

I/O polarity control register (PC) [Address $00D8_{16}$]

B	Name	Functions	After reset	R	W
0	HSYNC input polarity switch bit (PC0)	0 : Positive polarity input 1 : Negative polarity input	0	R	W
1	VSYNC input polarity switch bit (PC1)	0 : Positive polarity input 1 : Negative polarity input	0	R	W
2	R, G, B output polarity switch bit (PC2)	0 : Positive polarity output 1 : Negative polarity output	0	R	W
3	OUT1 output polarity switch bit (PC3)	0 : Positive polarity output 1 : Negative polarity output	0	R	W
4	OUT2 output polarity switch bit (PC4)	0 : Positive polarity output 1 : Negative polarity output	0	R	W
5	Display dot line selection bit (PC5) (See note)	0 : “□” at even field “▨” at odd field 1 : “▨” at even field “□” at odd field	0	R	W
6	Field determination flag (PC6)	0 : Even field 1 : Odd field	1	R	—
7	Fix this bit to “0.”		0	R	W


Note: Refer to the corresponding figure (8.11.14).

Fig. 8.11.13 I/O Polarity Control Register


Both HSYNC signal and VSYNC signal are negative-polarity input

HSYNC		Field	Field determination flag(Note)	Display dot line selection bit	Display dot line
VSYNC and VSYNC control signal in microcomputer Upper : VSYNC signal Lower : VSYNC control signal in microcomputer	(n –1) field (Odd-numbered) T1 0.25 to 0.50[μs] at f(XIN) = 8 MHz	Odd			
	(n) field (Even-numbered) T2	Even	0 (T2 > T1)	0	Dot line 1 □
				1	Dot line 0 ■
	(n + 1) field (Odd-numbered) T3	Odd	1 (T3 < T2)	0	Dot line 0 ■
				1	Dot line 1 □

When using the field determination flag, be sure to set bit 0 of the PWM mode register 1 (address 0208 16) to 0.



CC mode



OSD mode

When the display dot line selection bit is 0, the □ font is displayed at even field, the ■ font is displayed at odd field. Bit 6 of the I/O polarity control register can be read as the field determination flag : 1 is read at odd field, 0 is read at even field.

OSD ROM font configuration diagram

Note : The field determination flag changes at a rising edge of the V SYNC control signal (negative-polarity input) in the microcomputer.

Fig. 8.11.14 Relation between Field Determination Flag and Display Font

8.11.5 Memory for OSD

There are 2 types of memory for OSD : OSD ROM used to store character dot data and OSD RAM used to specify the characters and colors to be displayed.

<M37272M6H/M8H-XXXSP/FP, M37272E8SP/FP>
OSD ROM : addresses 1400_{16} to $3BFF_{16}$
OSD RAM : addresses 0800_{16} to $087F_{16}$

<M37272MAH/MFH-XXXSP/FP, M37272EFSP/FP>
OSD ROM : addresses 11400_{16} to $13BFF_{16}$
OSD RAM : addresses 0800_{16} to $087F_{16}$

(1) OSD ROM (addresses 1400_{16} to $3BFF_{16}$)


The dot pattern data for OSD characters is stored in OSD ROM. To specify the kinds of the character font, it is necessary to write the character code into the OSD RAM.
Data of the character font is specified shown in Figure 8.11.15.

OSD ROM address of character font data

OSD ROM address bit	AD16	AD15	AD14	AD13	AD12	AD11	AD10	AD9	AD8	AD7	AD6	AD5	AD4	AD3	AD2	AD1	AD0
Line number/character code/font bit	1 (Note)	0	0	Line number					Character code								Font bit

Line number = $0A_{16}$ to $1D_{16}$
Character code = 00_{16} to FF_{16} ($7F_{16}$ and 80_{16} cannot be used)
Font bit = 0 : Left area
1 : Right area

Note: Only M37272MAH/MFH-XXXSP/FP and M37272EFSP/FP have AD16.



Character font

Fig. 8.11.15 Character Font Data Storing Address

Notes 1 : The 80-byte addresses corresponding to the character code "7F16" and "8016" in OSD ROM are the test data storing area. Set data to the area as follows.

<Test data storing area>
■ M37272M6H/M8H-XXXSP/FP, M37272E8SP/FP
addresses 1000_{16} + (4 + 2n) × 100_{16} + FE_{16} to
1000_{16} + (5 + 2n) × 100_{16} + 01_{16}
(n = 0 to 19)
■ M37272MAH/MFH-XXXSP/FP, M37272EFSP/FP
addresses 11000_{16} + (4 + 2n) × 100_{16} + FE_{16} to
11000_{16} + (5 + 2n) × 100_{16} + 01_{16}
(n = 0 to 19)

(1)Mask version (M37272M6H/M8H/MAH/MFH-XXXSP/FP)
Set "FF16" to the area (We stores the test data to this area and the different data from "FF16" is stored for the actual products.) When using our font editor, the test data is written automatically.
(2)EPROM version (M37272E8SP/FP, M37272EFSP/FP)
Set the test data to the area. When using our font editor, the test data is written automatically.

■M37272E8SP/FP

<"FF16"> address (test data)	<"8016"> address (test data)
14FE16 (0916), 14FF16 (5116)	1500$_{16}$ (90$_{16}$), 1501$_{16}$ (A1$_{16}$)
16FE16 (0016), 16FF16 (5216)	1700$_{16}$ (00$_{16}$), 1701$_{16}$ (A2$_{16}$)
18FE16 (1216), 18FF16 (5316)	1900$_{16}$ (48$_{16}$), 1901$_{16}$ (A3$_{16}$)
1AFE16 (0016), 1AFF16 (5416)	1B00$_{16}$ (00$_{16}$), 1B01$_{16}$ (A4$_{16}$)
1CFE16 (2416), 1CFF16 (5516)	1D00$_{16}$ (24$_{16}$), 1D01$_{16}$ (A5$_{16}$)
1EFE16 (0016), 1EFF16 (5616)	1F00$_{16}$ (00$_{16}$), 1F01$_{16}$ (A6$_{16}$)
20FE16 (8816), 20FF16 (5716)	2100$_{16}$ (12$_{16}$), 2101$_{16}$ (A7$_{16}$)
22FE16 (0016), 22FF16 (5816)	2300$_{16}$ (00$_{16}$), 2301$_{16}$ (A8$_{16}$)
24FE16 (9016), 24FF16 (5916)	2500$_{16}$ (09$_{16}$), 2501$_{16}$ (A9$_{16}$)
26FE16 (4816), 26FF16 (5A16)	2700$_{16}$ (00$_{16}$), 2701$_{16}$ (AA$_{16}$)
28FE16 (2416), 28FF16 (5B16)	2900$_{16}$ (81$_{16}$), 2901$_{16}$ (AB$_{16}$)
2AFE16 (0016), 2AFF16 (5C16)	2B00$_{16}$ (18$_{16}$), 2B01$_{16}$ (AC$_{16}$)
2CFE16 (2416), 2CFF16 (5D16)	2D00$_{16}$ (00$_{16}$), 2D01$_{16}$ (AD$_{16}$)
2EFE16 (4816), 2EFF16 (5E16)	2F00$_{16}$ (42$_{16}$), 2F01$_{16}$ (AE$_{16}$)
30FE16 (0016), 30FF16 (5F16)	3100$_{16}$ (24$_{16}$), 3101$_{16}$ (AF$_{16}$)
32FE16 (4816), 32FF16 (5016)	3300$_{16}$ (00$_{16}$), 3301$_{16}$ (B0$_{16}$)
34FE16 (9016), 34FF16 (5116)	3500$_{16}$ (81$_{16}$), 3501$_{16}$ (B1$_{16}$)
36FE16 (0016), 36FF16 (5216)	3700$_{16}$ (0C$_{16}$), 3701$_{16}$ (B2$_{16}$)
38FE16 (0116), 38FF16 (5316)	3900$_{16}$ (06$_{16}$), 3901$_{16}$ (B3$_{16}$)
3AFE16 (8016), 3AFF16 (5416)	3B00$_{16}$ (00$_{16}$), 3B01$_{16}$ (B4$_{16}$)

■M37272EFSP/FP

<"7F16"> address (test data)	<"8016"> address (test data)
114FE16 (0916), 114FF16 (5116)	11500$_{16}$ (90$_{16}$), 11501$_{16}$ (A1$_{16}$)
116FE16 (0016), 116FF16 (5216)	11700$_{16}$ (00$_{16}$), 11701$_{16}$ (A2$_{16}$)
118FE16 (1216), 118FF16 (5316)	11900$_{16}$ (48$_{16}$), 11901$_{16}$ (A3$_{16}$)
11AFE16 (0016), 11AFF16 (5416)	11B00$_{16}$ (00$_{16}$), 11B01$_{16}$ (A4$_{16}$)
11CFE16 (2416), 11CFF16 (5516)	11D00$_{16}$ (24$_{16}$), 11D01$_{16}$ (A5$_{16}$)
11EFE16 (0016), 11EFF16 (5616)	11F00$_{16}$ (00$_{16}$), 11F01$_{16}$ (A6$_{16}$)
120FE16 (8816), 120FF16 (5716)	12100$_{16}$ (12$_{16}$), 12101$_{16}$ (A7$_{16}$)
122FE16 (0016), 122FF16 (5816)	12300$_{16}$ (00$_{16}$), 12301$_{16}$ (A8$_{16}$)
124FE16 (9016), 124FF16 (5916)	12500$_{16}$ (09$_{16}$), 12501$_{16}$ (A9$_{16}$)
126FE16 (4816), 126FF16 (5A16)	12700$_{16}$ (00$_{16}$), 12701$_{16}$ (AA$_{16}$)
128FE16 (2416), 128FF16 (5B16)	12900$_{16}$ (81$_{16}$), 12901$_{16}$ (AB$_{16}$)
12AFE16 (0016), 12AFF16 (5C16)	12B00$_{16}$ (18$_{16}$), 12B01$_{16}$ (AC$_{16}$)
12CFE16 (2416), 12CFF16 (5D16)	12D00$_{16}$ (00$_{16}$), 12D01$_{16}$ (AD$_{16}$)
12EFE16 (4816), 12EFF16 (5E16)	12F00$_{16}$ (42$_{16}$), 12F01$_{16}$ (AE$_{16}$)
130FE16 (0016), 130FF16 (5F16)	13100$_{16}$ (24$_{16}$), 13101$_{16}$ (AF$_{16}$)
132FE16 (4816), 132FF16 (5016)	13300$_{16}$ (00$_{16}$), 13301$_{16}$ (B0$_{16}$)
134FE16 (9016), 134FF16 (5116)	13500$_{16}$ (81$_{16}$), 13501$_{16}$ (B1$_{16}$)
136FE16 (0016), 136FF16 (5216)	13700$_{16}$ (0C$_{16}$), 13701$_{16}$ (B2$_{16}$)
138FE16 (0116), 138FF16 (5316)	13900$_{16}$ (06$_{16}$), 13901$_{16}$ (B3$_{16}$)
13AFE16 (8016), 13AFF16 (5416)	13B00$_{16}$ (00$_{16}$), 13B01$_{16}$ (B4$_{16}$)

2 : The character code "0916" is used for "transparent space" when displaying Closed Caption.
Therefore, set "0016" to the 40-byte addresses corresponding to the character code "0916."

<Transparent space font data storing area>
■ M37272M6H/M8H-XXXSP/FP, M37272E8SP/FP
addresses 1000_{16} + (4 + 2n) × 100_{16} + 12_{16} to
1000_{16} + (4 + 2n) × 100_{16} + 13_{16}
(n = 0 to 19)

[addresses 1412$_{16}$ and 1413$_{16}$
addresses 1612$_{16}$ and 1613$_{16}$
⋮
addresses 3812$_{16}$ and 3813$_{16}$
addresses 3A12$_{16}$ and 3A13$_{16}$]

■ M37272MAH/MFH-XXXSP/FP, M37272EFSP/FP
addresses 11000_{16} + (4 + 2n) × 100_{16} + 12_{16} to
11000_{16} + (4 + 2n) × 100_{16} + 13_{16}
(n = 0 to 19)

[addresses 11412$_{16}$ and 11413$_{16}$
addresses 11612$_{16}$ and 11613$_{16}$
⋮
addresses 13812$_{16}$ and 13813$_{16}$
addresses 13A12$_{16}$ and 13A13$_{16}$]

(2) OSD RAM

The RAM for OSD is allocated at addresses 0800_{16} to $087F_{16}$, and is divided into a display character code specification part, color code 1 specification part, and color code 2 specification part for each block. Table 8.11.3 shows the contents of the OSD RAM.


For example, to display 1 character position (the left edge) in block 1, write the character code in address 0800_{16}, write the color code 1 at 0820_{16}.

The structure of the OSD RAM is shown in Figure 8.11.16.

Table 8.11.3 Contents of OSD RAM

Block	Display Position (from left)	Character Code Specification	Color Code Specification
Block 1	1st character	0800_{16}	0820_{16}
	2nd character	0801_{16}	0821_{16}
	3rd character : 30th character	0802_{16} : $081D_{16}$	0822_{16} : $083D_{16}$
	31st character	$081E_{16}$	$083E_{16}$
	32nd character	$081F_{16}$	$083F_{16}$
Block 2	1st character	0840_{16}	0860_{16}
	2nd character	0841_{16}	0861_{16}
	3rd character : 30th character	0842_{16} : $085D_{16}$	0862_{16} : $087D_{16}$
	31st character	$085E_{16}$	$087E_{16}$
	32nd character	$085F_{16}$	$087F_{16}$

Blocks 1, 2



Bit	CC mode		OSD mode	
	Bit name	Function	Bit name	Function
RF0	Character code	Character code in OSD ROM	Character code	Character code in OSD ROM
RF1				
RF2				
RF3				
RF4				
RF5				
RF6				
RF7				
RA0	Control of character color R	0: Color signal output OFF 1: Color signal output ON	Control of character color R	0: Color signal output OFF 1: Color signal output ON
RA1	Control of character color G		Control of character color G	
RA2	Control of character color B		Control of character color B	
RA3	OUT1/OUT2 control	(See note 2)	OUT1/OUT2 control	(See note 2)
RA4	Flash control	0: Flash OFF 1: Flash ON	Control of background color R	0: Color signal output OFF 1: Color signal output ON
RA5	Underline control	0: Underline OFF 1: Underline ON	Control of background color G	
RA6	Italic control	0: Italic OFF 1: Italic ON	Control of background color B	

Notes 1: Read value of bits 7 of the color code is “0.”
2: For OUT1/OUT2 control, refer to “8.11.8 OUT1/OUT2 signal.”
3: “$7F_{16}$” and “80_{16}” cannot be used as character code.

Fig. 8.11.16 Bit structure of OSD RAM

8.11.6 Character color

The color for each character is displayed by the color code.
<7 kinds>
Specified by bits 0 (R), 1 (G), and 2 (B) of the color code

8.11.7 Character background color


The character background color can be displayed in the character display area only in the OSD mode. The character background color for each character is specified by the color code.
<7 kinds>
Specified by bits 4 (R), 5 (G), and 6 (B) of the color code

Note : The character background color is displayed in the following part : (character display area)–(character font)–(border).
Accordingly, the character background color does not mix with these color signal.

8.11.8 OUT1, OUT2 signals

The OUT1, OUT2 signals are used to control the luminance of the video signal. The output waveform of the OUT1, OUT2 signals is controlled by display mode, bit 5 of the block control register i (refer to Figure 8.11.4) and RA3 of OSD RAM. The setting values for controlling OUT1, OUT2 and the corresponding output waveform is shown in Figure 8.11.17.

Note : When OUT2 signal is output, set bit 7 of OSD port control register (refer to Figure 8.11.28) to "1."



Display Mode	Block Control Register i OUT1/OUT2 Output Control Bit (b5)	OUT1/OUT2 Control RA3 of OSD RAM	Output Waveform (A-A')
OSD	0 (OUT1 output is controlled by RA3)	0	OUT1 = FONT/BORDER OUT2 = "L"
		1	OUT1 = AREA OUT2 = "L"
	1 (OUT2 output is controlled by RA3)	0	OUT1 = FONT/BORDER OUT2 = "L"
		1	OUT1 = FONT/BORDER OUT2 = AREA
CC	0 (OUT1 output is controlled by RA3)	0	OUT1 = FONT OUT2 = "L"
		1	OUT1 = AREA OUT2 = "L"
	1 (OUT2 output is controlled by RA3)	0	OUT1 = FONT OUT2 = "L"
		1	OUT1 = FONT OUT2 = AREA

Notes 1 : FONT/BORDER.....In the OSD mode (Border ON), OUT1 outputs to the area of font and border.
In the OSD mode (Border OFF), OUT1 outputs to only the font area.
AREA.....OUT1/OUT2 outputs to entire display area of character.
FONT.....In the CC mode, OUT1 outputs to font area.
2 : When the automatic solid space function is OFF in the CC mode, AREA outputs according to bit 3 of color code. When it is ON, the solid space is automatically output by a character code regardless of RA3.

Fig. 8.11.17 Setting Value for Controlling OUT1, OUT2 and Corresponding Output Waveform

8.11.9 Attribute

The attributes (border, flash, underline, italic) are controlled to the character font. The attributes to be controlled are different depending on each mode.

CC mode ..... Flash, underline, italic (per character unit)
OSD mode ..... Border (per character unit)

(1) Under line

The underline is output at the 23th and 24th dots in vertical direction only in the CC mode. The underline is controlled by RA5 of OSD RAM. The color of underline is the same color as that of the character font.

(2) Flash

The character font and the underline are flashed only in the CC mode. The flash is controlled by RA4 of OSD RAM. As for character font part, the character output part is flashed, the character background part is not flashed. The flash cycle bases on the VSYNC count.


- VSYNC cycle × 48 ≈ 800 ms (at display ON)
- VSYNC cycle × 16 ≈ 267 ms (at display OFF)

(3) Italic

The italic is made by slanting the font stored in OSD ROM to the right only in the CC mode. The italic is controlled by RA6 of OSD RAM.


The display example of the italic and underline is shown in Figure 8.11.8. In this case, “R” is displayed.

Notes 1: When setting both the italic and the flash, the italic character flashes.
2: The boundary of character color is displayed in italic. However, the boundary of character background color is not affected by the italic (refer to Figure 8.11.19).
3: The adjacent character (one side or both side) to an italic character is displayed in italic even when the character is not specified to display in italic (refer to Figure 8.11.19).




Color code	
Bit 6 (RA6)	Bit 5 (RA5)
0	0

(a) Ordinary




Color code	
Bit 6 (RA6)	Bit 5 (RA5)
1	0

(b) Under line




Color code	
Bit 6 (RA6)	Bit 5 (RA5)
0	1

(c) Italic (pre-divide ratio = 1)



Color code	
Bit 6 (RA6)	Bit 5 (RA5)
0	1


(d) Italic (pre-divide ratio = 2)



Color code		
Bit 6 (RA6)	Bit 5 (RA5)	Bit 4 (RA4)
1	1	1

(e) Under line amd Italic and flash

Fig. 8.11.18 Example of Attribute Display (in CC Mode)



Notes 1 : The dotted line is the boundary of character color.
2 : When bit 1 of OSD control register is “0.”

Fig. 8.11.19 Example of Italic Display

(4) Border

The border is output around of character font (all bordered) in the OSD mode. The border ON/OFF is controlled by bit 0 and 1 of the block control register i (refer to Figure 8.11.4).

The OUT1 signal is used for border output.

The horizontal size (x) of border is 1Tc (OSD clock cycle divided in pre-divide circuit) regardless of the character font dot size. The vertical size (y) different depending on the screen scan mode and the vertical dot size of character font.

Notes 1 : The border dot area is the shaded area as shown in Figure 8.11.20.
2 : When the border dot overlaps on the next character font, the character font has priority (refer to Figure 8.11.22 A).
When the border dot overlaps on the next character back ground, the border has priority (refer to Figure 8.11.22 B).
3 : The border in vertical out of character area is not displayed (refer to Figure 8.11.22).





Fig. 8.11.20 Example of Border Display



Border dot size \ Vertical dot size of character font	1/2H	1H, 2H, 3H
Horizontal size (x)	1Tc (OSD clock cycle divided in pre-divide circuit)	
Vertical size (y)	1/2H	1H

Fig. 8.11.21 Horizontal and Vertical Size of Border




Fig. 8.11.22 Border Priority

8.11.10 Multiline Display

This microcomputer can ordinarily display 2 lines on the CRT screen by displaying 2 blocks at different vertical positions. In addition, it can display up to 16 lines by using OSD interrupts.

An OSD interrupt request occurs at the point at which display of each block has been completed. In other words, when a scanning line reaches the point of the display position (specified by the vertical position registers) of a certain block, the character display of that block starts, and an interrupt occurs at the point at which the scanning line exceeds the block.

Notes 1: An OSD interrupt does not occur at the end of display when the block is not displayed. In other words, if a block is set to off display by the display control bit of the block control register (addresses $00D2_{16}$, $00D3_{16}$), an OSD interrupt request does not occur (refer to Figure 8.11.23 (A)).

2: When another block display appears while one block is displayed, an OSD interrupt request occurs only once at the end of the another block display (refer to Figure 8.11.23 (B)).

3: On the screen setting window, an OSD interrupt occurs even at the end of the CC mode block (off display) out of window (refer to Figure 8.11.23 (C)).




Fig. 8.11.23 Note on Occurence of OSD Interrupt

8.11.11 Automatic Solid Space Function

This function generates automatically the solid space (OUT1 or OUT2 blank output) of the character area in the CC mode.

The solid space is output in the following area :

• Any character area except character code "09_{16} "

• Character area on the left and right sides of the above character

This function is turned on and off by bit 1 of the OSD control register (refer to Figure 8.11.3).

Notes : The character code "09_{16}" is used for "transparent space" when displaying Closed Caption.
Therefore, set "00_{16}" to the 40-byte addresses corresponding to the character code "09_{16}."

<Transparent space font data storing area>

■ M37272M6H/M8H-XXXSP/FP, M37272E8SP/FP

addresses 1000_{16} + (4 + 2n) × 100_{16} + 12_{16} to
1000_{16} + (4 + 2n) × 100_{16} + 13_{16}
(n = 0 to 19)

[addresses 1412_{16} and 1413_{16}
addresses 1612_{16} and 1613_{16}
⋮
addresses 3812_{16} and 3813_{16}
addresses $3A12_{16}$ and $3A13_{16}$]

■ M37272MAH/MFH-XXXSP/FP, M37272EFSP/FP

addresses 11000_{16} + (4 + 2n) × 100_{16} + 12_{16} to
11000_{16} + (4 + 2n) × 100_{16} + 13_{16}
(n = 0 to 19)

[addresses 11412_{16} and 11413_{16}
addresses 11612_{16} and 11613_{16}
⋮
addresses 13812_{16} and 13813_{16}
addresses $13A12_{16}$ and $13A13_{16}$]




Fig. 8.11.24 Display Screen Example of Automatic Solid Space

8.11.12 Window Function

This function sets the top and bottom boundary of display limit on a screen. The window function is valid only in the CC mode. The top boundary is set by the window registers 1 and bit 7 of block control register 1. The bottom boundary is set by window registers 1 and bit 7 of block control register 2. This function is turned on and off by bit 2 of the OSD control register (refer to Figure 8.11.3).
The window registers 1 and 2 is shown in Figures 8.11.26 and 8.11.27.





Fig. 8.11.25 Example of Window Function

Window Register 1




Window register 1 (WN1) [Address $00D6_{16}$]

B	Name	Functions	After reset	R	W
0 to 7	Window top boundary control bits (WN10 to WN17)	Window top border position = $T_H \times (BC17 \times 16^2 + n)$ (n: setting value, T_H: H_{SYNC} cycle, BC17: bit 7 of block control register 1)	Inderterminate	R	W

Notes 1: Set values except 00_{16} to WN1 when BC17 is 0.
2: Set values fit for the following condition: WN1 < WN2.

Fig. 8.11.26 Window Register 1

Window Register 2



Window register 2 (WN2) [Address $00D7_{16}$]

B	Name	Functions	After reset	R	W
0 to 7	Window bottom boundary control bits (WN20 to WN27)	Window bottom border position = $T_H \times (BC27 \times 16^2 + n)$ (n: setting value, T_H: H_{SYNC} cycle, BC27: bit 7 of block control register 2)	Inderterminate	R	W

Note: Set values fit for the following condition: WN1 < WN2.

Fig. 8.11.27 Window Register 2

8.11.13 OSD Output Pin Control

The OSD output pins R, G, B and OUT1 can also function as ports $P5_2$–$P5_5$. Set corresponding bit of the OSD port control register (address $00CB_{16}$) to "0" to specify these pins as OSD output pins, or set it to "1" to specify it as a general-purpose port P5.

The OUT2 can also function as port $P1_0$. Set bit 0 of the port P1 direction register (address $00C3_{16}$) to "1" (output mode). After that, set bit 7 of the OSD port control register to "1" to specify the pin as OSD output pin, or set it to "0" to specify as port $P1_0$.

The input polarity of the HSYNC, VSYNC and output polarity of signals R, G, B, OUT1 and OUT2 can be specified with the I/O polarity control register (address 00D8) . Set a bit to "0" to specify positive polarity; set it to "1" to specify negative polarity (refer to Figure 8.11.13).

The structure of the OSD port control register is shown in Figure 8.11.28.

OSD Port Control Register

b7 b6 b5 b4 b3 b2 b1 b0

0 0

OSD port control register (PF) [Address $00CB_{16}$]

B	Name	Functions	After reset	R	W
0, 1	Fix these bits to 0.		0	R	
2	Port $P5_2$ output signal selection bit (PF2)	0 : R signal output 1 : Port $P5_2$ output	0	R	W
3	Port $P5_3$ output signal selection bit (PF3)	0 : G signal output 1 : Port $P5_3$ output	0	R	W
4	Port $P5_4$ output signal selection bit (PF4)	0 : B signal output 1 : Port $P5_4$ output	0	R	W
5	Port $P5_5$ output signal selection bit (PF5)	0 : OUT1 signal output 1 : Port $P5_3$ output	0	R	W
6	Nothing is assigned. This bit is write disable bit. When this bit is read out, the value is 0.		0	R	
7	Port $P1_0$ output signal selection bit (PF7)	0 : Port $P1_0$ output 1 : OUT2 signal output	0	R	W

Fig. 8.11.28 OSD Port Control Register

8.11.14 Raster Coloring Function

An entire screen (raster) can be colored by setting the bits 4 to 0 of the raster color register. Since each of the R, G, B, OUT1, and OUT2 pins can be switched to raster coloring output, 8 raster colors can be obtained.

When the character color/the character background color overlaps with the raster color, the color (R, G, B, OUT1, OUT2), specified for the character color/the character background color, takes priority of the raster color. This ensures that character color/character background color is not mixed with the raster color.

The raster color register is shown in Figure 8.11.29, the example of raster coloring is shown in Figure 8.11.30.

Raster Color Register

b7 b6 b5 b4 b3 b2 b1 b0

0 0

Raster color register (RC) [Address 00D9 16]

B	Name	Functions	After reset	R	W
0	Raster color R control bit (RC0)	0 : No output 1 : Output	0	R	W
1	Raster color G control bit (RC1)	0 : No output 1 : Output	0	R	W
2	Raster color B control bit (RC2)	0 : No output 1 : Output	0	R	W
3	Raster color OUT1 control bit (RC3)	0 : No output 1 : Output	0	R	W
4	Raster color OUT2 control bit (RC4)	0 : No output 1 : Output	0	R	W
5, 6	Fix these bits to “0.”		0	R	W
7	Port function selection bit (RC7)	0 : OSC1/X_{CIN}, OSC2/X_{COUT} 1 : $P2_6$, $P2_7$	0	R	W

Note: Either OSD clock source or 32 kHz oscillating clock is selected by bits 5 and 6 of the OSD control register.

Fig. 8.11.29 Raster Color Register




Fig. 8.11.30 Example of Raster Coloring

8.12 SOFTWARE RUNAWAY DETECT FUNCTION

This microcomputer has a function to decode undefined instructions to detect a software runaway.

When an undefined op-code is input to the CPU as an instruction code during operation, the following processing is done.

① The CPU generates an undefined instruction decoding signal.

② The device is internally reset because of occurrence of the undefined instruction decoding signal.

③ As a result of internal reset, the same reset processing as in the case of ordinary reset operation is done, and the program restarts from the reset vector.

Note, however, that the software runaway detecting function cannot be invalid.




Fig.8.12.1 Sequence at Detecting Software Runaway Detection

8.13. RESET CIRCUIT

When the oscillation of a quartz-crystal oscillator or a ceramic resonator is stable and the power source voltage is 5 V ± 10 %, hold the $\overline{\text{RESET}}$ pin at LOW for 2 μs or more, then return is to HIGH. Then, as shown in Figure 8.13.2, reset is released and the program starts form the address formed by using the content of address FFFF16 as the high-order address and the content of the address FFFE16 as the low-order address. The internal state of microcomputer at reset are shown in Figures 8.2.3 to 8.2.6.

An example of the reset circuit is shown in Figure 8.13.1.

The reset input voltage must be kept 0.9 V or less until the power source voltage surpasses 4.5 V.




Fig.8.13.1 Example of Reset Circuit




Fig.8.13.2 Reset Sequence

8.14 CLOCK GENERATING CIRCUIT

This microcomputer has 2 built-in oscillation circuits. An oscillation circuit can be formed by connecting a resonator between XIN and XOUT (XCIN and XCOUT). Use the circuit constants in accordance with the resonator manufacturer's recommended values. No external resistor is needed between XIN and XOUT since a feed-back resistor exists on-chip. However, an external feed-back resistor is needed between XCIN and XCOUT. When using XCIN-XCOUT as sub-clock, clear bits 5 and 6 of the OSD control register to "0." To supply a clock signal externally, input it to the XIN (XCIN) pin and make the XOUT (XCOUT) pin open. When not using XCIN clock, connect the XCIN to VSS and make the XCOUT pin open.

After reset has completed, the internal clock ϕ is half the frequency of XIN. Immediately after poweron, both the XIN and XCIN clock start oscillating. To set the internal clock ϕ to low-speed operation mode, set bit 7 of the CPU mode register to "1."

8.14.1 OSCILLATION CONTROL

(1) Stop Mode

The built-in clock generating circuit is shown in Figure 120. When the STP instruction is executed, the internal clock ϕ stops at HIGH. At the same time, timers 3 and 4 are connected by hardware and "FF16" is set in timer 3 and "0716" is set in timer 4. Select f(XIN)/16 or f(XCIN)/16 as the timer 3 count source (set both bit 0 of the timer mode register 2 and bit 6 at address 00C716 to "0" before the execution of the STP instruction). Moreover, set the timer 3 and timer 4 interrupt enable bits to disabled ("0") before execution of the STP instruction. The oscillator restarts when external interrupt is accepted. However, the internal clock ϕ keeps its HIGH level until timer 4 overflows, allowing time for oscillation stabilization when a ceramic resonator or a quartz-crystal oscillator is used.

(2) Wait Mode

When the WIT instruction is executed, the internal clock ϕ stops in the HIGH level but the oscillator continues running. This wait state is released at reset or when an interrupt is accepted (See note). Since the oscillator does not stop, the next instruction can be executed at once.

Note: In the wait mode, the following interrupts are invalid.
- VSYNC interrupt
- OSD interrupt
- All timer interrupts using external clock input from port pin as count source
- All timer interrupts using f(XIN)/2 or f(XCIN)/2 as count source
- All timer interrupts using f(XIN)/4096 or f(XCIN)/4096 as count source
- f(XIN)/4096 interrupt
- Multi-master I^2C-BUS interface interrupt
- Data slicer interrupt
- A-D conversion interrupt

(3) Low-speed Mode

If the internal clock is generated from the sub-clock (XCIN), a low power consumption operation can be realized by stopping only the main clock XIN. To stop the main clock, set bit 6 (CM6) of the CPU mode register (00FB16) to "1." When the main clock XIN is restarted, the program must allow enough time to for oscillation to stabilize.

Note that in low-power-consumption mode the XCIN-XCOUT drivability can be reduced, allowing even lower power consumption. To reduce the XCIN-XCOUT drivability, clear bit 5 (CM5) of the CPU mode register (00FB16) to "0." At reset, this bit is set to "1" and strong drivability is selected to help the oscillation to start. When an STP instruction is executed, set this bit to "1" by software before executing.




Fig.8.14.1 Ceramic Resonator Circuit Example






Fig.8.14.2 External Clock Input Circuit Example



Notes 1 : The value at reset is "0."
2 : Refer to timer mode register 2.
3 : Refer to the CPU mode register.
4 : Refer to the OSD control register.

Fig.8.14.3 Clock Generating Circuit Block Diagram



The example assumes that 8 MHz is being applied to the XINpin and 32 kHz to the XCINpin. The ϕ indicates the internal clock.

Notes 1: When the STP state is ended, a delay of approximately 4 ms is automatically generated by timer 3 and timer 4.
2: The delay after the STP state ends is approximately 1s.
3: When the internal clock ϕdivided by 8 is used as the timer count source, the frequency of the count source is 2 kHz.

Fig.8.14.4 State Transitions of System Clock

8.15 DISPLAY OSCILLATION CIRCUIT

The OSD oscillation circuit has a built-in clock oscillation circuits, so that a clock for OSD can be obtained simply by connecting an LC, a ceramic resonator, or a quartz-crystal oscillator across the pins OSC1 and OSC2. Which of the sub-clock or the OSD oscillation circuit is selected by setting bits 5 and 6 of the OSD control register (address $00D0_{16}$).





Fig.8.15.1 Display Oscillation Circuit

8.16 AUTO-CLEAR CIRCUIT

When a power source is supplied, the auto-clear function will operate by connecting the following circuit to the $\overline{\text{RESET}}$ pin.



Note : Make the level change from "L" to "H" at the point at which the power source voltage exceeds the specified voltage.

Fig.8.16.1 Auto-clear Circuit Example

8.17 ADDRESSING MODE

The memory access is reinforced with 17 kinds of addressing modes. Refer to SERIES 740 <Software> User's Manual for details.

8.18 MACHINE INSTRUCTIONS

There are 71 machine instructions. Refer to SERIES 740 <Soft- ware> User's Manual for details.

9. PROGRAMMING NOTES

- The divide ratio of the timer is 1/(n+1).
- Even though the BBC and BBS instructions are executed immediately after the interrupt request bits are modified (by the program), those instructions are only valid for the contents before the modification. At least one instruction cycle is needed (such as an NOP) between the modification of the interrupt request bits and the execution of the BBC and BBS instructions.
- After the ADC and SBC instructions are executed (in the decimal mode), one instruction cycle (such as an NOP) is needed before the SEC, CLC, or CLD instruction is executed.
- An NOP instruction is needed immediately after the execution of a PLP instruction.
- In order to avoid noise and latch-up, connect a bypass capacitor (≈ 0.1μF) directly between the V_{CC} pin–V_{SS} pin, AV_{CC} pin–V_{SS} pin, and the V_{CC} pin–CNV_{SS} pin, using a thick wire.
- M37272M6H/M8H/MAH/MFH-XXXSP/FP and M37272E8SP/FP, M37272EFSP/FP are compatible, but please attention differences as follows:

Parameter		M37272E8/EF		M37272MXH	
Spec of1 4th pins		AVcc		NC (Non connection)	
Power souce voltage When System operate $f(X_{IN})$: 8MFz		Normal	Max.	Normal	Max.
	OSD : OFF Data slicer : OFF	15 mA	30 mA	10 mA	25 mA
	OSD : ON Data slicer : ON	30mA	45 mA	25 mA	40 mA

✻ Need to apply 5V±10%(Typical), because 14th pin of M37272E8SP/FP, M37272EFSP/FP is AVcc pin.
14 pin of M37272M6H/M8H/MAH/MFH-XXXSP/FP is the non connection pin, but it is not connect in IC. You can apply voltage.

10. ABSOLUTE MAXIMUM RATINGS

Symbol	Parametear	Conditions	Ratings	Unit
V_{CC} (AV_{CC})	Power source voltage V_{CC} (AV_{CC}...M37272E8SP/FP, M37272EFSP/FP)	All voltages are based on V_{SS}. Output transistors are cut off.	–0.3 to 6	V
V_I	Input voltage CNVSS		–0.3 to 6	V
V_I	Input voltage $P0_0$–$P0_7$, $P1_0$–$P1_7$, $P2_0$–$P2_7$, $P3_0$, $P3_1$, $P5_0$, $P5_1$, X_{IN}, $\overline{RESET}$, CV_{IN}		–0.3–V_{CC} + 0.3	V
V_O	Output voltage $P0_6$, $P0_7$, $P1_0$–$P1_7$, $P2_0$–$P2_7$, $P3_0$, $P3_1$, $P5_2$–$P5_5$, X_{OUT}		–0.3–V_{CC} + 0.3	V
V_O	Output voltage $P0_0$–$P0_5$		–0.3 to 13	V
I_{OH}	Circuit current $P1_0$–$P1_7$, $P2_0$–$P2_7$, $P3_0$, $P3_1$ $P5_2$–$P5_5$		0 to 1 (See note 1)	mA
I_{OL1}	Circuit current $P0_6$, $P0_7$, $P1_0$, $P1_5$–$P1_7$, $P2_0$–$P2_3$, $P2_6$, $P2_7$, $P5_2$–$P5_5$		0 to 2 (See note 2)	mA
I_{OL2}	Circuit current $P1_1$–$P1_4$		0 to 6 (See note 2)	mA
I_{OL3}	Circuit current $P0_0$–$P0_5$		0 to 1 (See note 2)	mA
I_{OL4}	Circuit current $P2_4$, $P2_5$, $P3_0$, $P3_1$		0 to 10 (See note 3)	mA
P_d	Power dissipation	T_a = 25 °C	550	mW
T_{opr}	Operating temperature		–10 to 70	°C
T_{stg}	Storage temperature		–40 to 125	°C

11. RECOMMENDED OPERATING CONDITIONS (T_a = –10 °C to 70 °C, V_{CC} = 5 V ± 10 %, unless otherwise noted)

Symbol	Parametear	Limits			Unit
		Min.	Typ.	Max.	
V_{CC} (AV_{CC})	Power source voltage (See note 4) (AV_{CC}...M37272E8SP/FP, M37272EFSP/FP)	4.5	5.0	5.5	V
V_{SS}	Power source voltage	0	0	0	V
V_{IH1}	HIGH Input voltage $P0_0$–$P0_7$, $P1_0$–$P1_7$, $P2_0$–$P2_7$, $P3_0$, $P3_1$, $P5_0$, $P5_1$, $\overline{RESET}$, X_{IN}	0.8 V_{CC}		V_{CC}	V
V_{IH2}	HIGH Input voltage SCL1, SCL2, SDA1, SDA2 (When using I^2C-BUS)	0.7 V_{CC}		V_{CC}	V
V_{IL1}	LOW Input voltage $P0_0$–$P0_7$, $P1_0$–$P1_7$, $P2_0$–$P2_7$, $P3_0$, $P3_1$	0		0.4 V_{CC}	V
V_{IL2}	LOW Input voltage SCL1, SCL2, SDA1, SDA2 (When using I^2C-BUS)	0		0.3 V_{CC}	V
V_{IL3}	LOW Input voltage (See note 6) $P5_0$, $P5_1$, $\overline{RESET}$, X_{IN}, OSC1, TIM2, TIM3, INT1, INT2, INT3, S_{IN}, S_{CLK}	0		0.2 V_{CC}	V
I_{OH}	HIGH average output current (See note1) $P1_0$–$P1_7$, $P2_0$–$P2_7$, $P3_0$, $P3_1$, $P5_2$–$P5_5$			1	mA
I_{OL1}	LOW average output current (See note 2) $P0_6$, $P0_7$, $P1_0$, $P1_5$–$P1_7$, $P2_0$–$P2_3$, $P2_6$, $P2_7$, $P5_2$–$P5_5$			2	mA
I_{OL2}	LOW average output current (See note 2) $P1_1$–$P1_4$			6	mA
I_{OL3}	LOW average output current (See note 2) $P0_0$–$P0_5$			1	mA
I_{OL4}	LOW average output current (See note 3) $P2_4$, $P2_5$, $P3_0$, $P3_1$			10	mA
f(X_{IN})	Oscillation frequency (for CPU operation) (See note 5) X_{IN}	7.9	8.0	8.1	MHz
f(X_{CIN})	Oscillation frequency (for sub-clock operation) X_{CIN}	29	32	35	kHz
f_{OSC}	Oscillation frequency (for OSD) OSC1	26.5	27.0	27.0	MHz
f_{hs1}	Input frequency TIM2, TIM3, INT1, INT2, INT3			100	kHz
f_{hs2}	Input frequency S_{CLK}			1	MHz
f_{hs3}	Input frequency SCL1, SCL2			400	kHz
f_{hs4}	Input frequency Horizontal sync. signal of video signal	15.262	15.734	16.206	kHz
V_I	Input amplitude video signal CV_{IN}	1.5	2.0	2.5	V

12. ELECTRIC CHARACTERISTICS (V_{CC} = 5 V ± 10 %, V_{SS} = 0 V, f(X_{IN}) = 8 MHz, T_a = –10 °C to 70 °C, unless otherwise noted)

Symbol	Parametear		Test conditions		Limits Min.	Limits Typ.	Limits Max.	Unit	Test circuit
I_{CC}	Power source current	System operation	V_{CC} = 5.5V, f(X_{IN}) = 8MHz	OSD OFF Data slicer OFF		10 (15)	25 (30)	mA	1
			Upper row...M37272M* (Lower row...M37272E8/EF)	OSD ON Data slicer ON		25 (30)	40 (45)		
			V_{CC} = 5.5V, f(X_{IN}) = 0, f(X_{CIN}) = 32kHz, OSD OFF, Data slicer OFF, Low-power dissipation mode set (CM5 = "0", CM6 = "1")			60	200	μA	
		Wait mode	V_{CC} = 5.5 V, f(X_{IN}) = 8 MHz			2	4	mA	
			V_{CC} = 5.5 V, f(X_{IN}) = 0, f(X_{CIN}) = 32 kHz, Low-power dissipation mode set (CM5 = "0", CM6 = "1")			25	100	μA	
		Stop mode	V_{CC} = 5.5V, f(X_{IN}) = 0, f(X_{CIN}) = 0			1	10		
V_{OH}	HIGH output voltage	$P1_0$–$P1_7$, $P2_0$–$P2_7$, $P3_0$, $P3_1$, $P5_2$–$P5_5$	V_{CC} = 4.5 V, I_{OH} = –0.5 mA		2.4			V	2
V_{OL}	LOW output voltage	$P0_0$–$P0_7$, $P1_0$, $P1_5$–$P1_7$, $P2_0$–$P2_3$, $P2_6$, $P2_7$, $P5_2$–$P5_5$	V_{CC} = 4.5 V, I_{OL} = 0.5 mA				0.4	V	
	LOW output voltage	$P2_4$, $P2_5$, $P3_0$, $P3_1$	V_{CC} = 4.5 V, I_{OL} = 10.0 mA				3.0		
	LOW output voltage	$P1_1$–$P1_4$	V_{CC} = 4.5 V	I_{OL} = 3 mA			0.4		
				I_{OL} = 6 mA			0.6		
V_{T+} –V_{T-}	Hysteresis (See note 6) $\overline{RESET}$, $P5_0$, $P5_1$, INT1, INT2, INT3, TIM2, TIM3, S_{IN}, S_{CLK}, SCL1, SCL2, SDA1, SDA2		V_{CC} = 5.0 V			0.5	1.3	V	3
I_{IZH}	HIGH input leak current $P0_6$, $P0_7$, $P1_0$–$P1_7$, $P2_0$–$P2_7$, $P3_0$, $P3_1$, $\overline{RESET}$, $P5_0$, $P5_1$,		V_{CC} = 5.5 V, V_I = 5.5 V				5	μA	4
I_{IZL}	HIGH input leak current $P0_0$–$P0_7$, $P1_0$–$P1_7$, $P2_0$–$P2_7$, $P3_0$, $P3_1$, $P5_0$, $P5_1$, $\overline{RESET}$		V_{CC} = 5.5 V, V_I = 0 V				5	μA	4
I_{OZH}	HIGH output leak current $P0_0$–$P0_5$		V_{CC} = 5.5 V, V_I = 12 V				10	μA	5
R_{BS}	I^2C-BUS • BUS switch connection resistor (between SCL1 and SCL2, SDA1 and SDA2)		V_{CC} = 4.5 V				130	Ω	6

Notes 1: The total current that flows out of the IC must be 20 mA or less.

2: The total input current to IC (I_{OL1} + I_{OL2} + I_{OL3}) must be 30 mA or less.

3: The total average input current for ports $P3_0$, $P3_1$, $P2_4$ and $P2_5$ and AV_{CC}–V_{SS} to IC must be 20 mA or less.

4: Connect 0.1 μF or more capacitor externally between the power source pins V_{CC}–V_{SS} so as to reduce power source noise.When use M37272E8SP/FP and M37272EFSP/FP, connect 0.1 μF or more capacitor externally between the pins AV_{CC}–V_{SS} so as to reduce power source noise. Also connect 0.1 μF or more capacitor externally between the pins V_{CC}–CNV_{SS}.

5: Use a quartz-crystal oscillator or a ceramic resonator for the CPU oscillation circuit. When using the data slicer, use 8 MHz.

6: $P0_6$, $P0_7$, $P1_5$, $P2_3$, $P2_4$ have the hysteresis when these pins are used as interrupt input pins or timer input pins. $P1_1$–$P1_4$ have the hysteresis when these pins are used as multi-master I^2C-BUS interface ports. $P2_0$–$P2_2$ have the hysteresis when these pins are used as serial I/O pins.


7: Pin names in each parameter is described as below.

(1) Dedicated pins: dedicated pin names.

(2) Duble-/triple-function ports


- When the same limits: I/O port name.
- When the limits of functins except ports are different from I/O port limits: function pin name.

1




Pin V_{CC} is made the operation state and is measured the current, with a ceramic resonator.

2




After setting each output pin to HIGH level when measuring V_{OH} and to LOW level when measuring V_{OL}, each pin is measured.


3



4




5



After setting each output pin OFF state, each pin is measured

6



$R_{BS} = V_{BS}/I_{BS}$

Fig.12.1 Measure Circuits

13. A-D CONVERTER CHARACTERISTICS

(V_{CC} = 5 V ± 10 %, V_{SS} = 0 V, f(X_{IN}) = 8 MHz, T_a = –10 °C to 70 °C, unless otherwise noted)

Symbol	Parameter	Test conditions	Limits			Unit
			Min.	Typ.	Max.	
—	Resolution				6	bits
—	Non-linearity error				±1	LSB
—	Differencial non-linearity error				±0.9	LSB
V_{0T}	Zero transition error	I_{OL} (SUM) = 0 mA			2	LSB
V_{FST}	Full-scale transition error				–2	LSB

14. MULTI-MASTER I²C-BUS BUS LINE CHARACTERISTICS

Symbol	Parameter	Standard clock mode		High-speed clock mode		Unit
		Min.	Max.	Min.	Max.	
t_{BUF}	Bus free time	4.7		1.3		µs
$t_{HD;STA}$	Hold time for START condition	4.0		0.6		µs
t_{LOW}	LOW period of SCL clock	4.7		1.3		µs
t_R	Rising time of both SCL and SDA signals		1000	20+0.1C_b	300	ns
$t_{HD;DAT}$	Data hold time	0		0	0.9	µs
t_{HIGH}	HIGH period of SCL clock	4.0		0.6		µs
t_F	Falling time of both SCL and SDA signals		300	20+0.1C_b	300	ns
$t_{SU;DAT}$	Data set-up time	250		100		ns
$t_{SU;STA}$	Set-up time for repeated START condition	4.7		0.6		µs
$t_{SU;STO}$	Set-up time for STOP condition	4.0		0.6		µs

Note: C_b = total capacitance of 1 bus line




Fig.14.1 Definition Diagram of Timing on Multi-master I²C-BUS

15. PROM PROGRAMMING METHOD

The built-in PROM of the One Time PROM version (blank) and the built-in EPROM version can be read or programmed with a general-purpose PROM programmer using a special programming adapter.

Product	Name of Programming Adapter
M37272EFSP	PCA7429G02
M37272E8SP	PCA7429G02
M37272E8FP, M37272EFFP	PCA7427G02

The PROM of the One Time PROM version (blank) is not tested or screened in the assembly process nor any following processes. To ensure proper operation after programming, the procedure shown in Figure 15.1 is recommended to verify programming.




Fig. 15.1 Programming and Testing of One Time PROM Version

16. DATA REQUIRED FOR MASK ORDERS

The following are necessary when ordering a mask ROM production:

- Mask ROM Order Confirmation Form
- Mark Specification Form
- Data to be written to ROM, in EPROM form (three identical copies) or FDK

When using EPROM:


<M37272M6H/M8H-XXXSP/FP, M37272E8SP/FP>

28-pin DIP Type 27512


<M37272MAH/MFH-XXXSP/FP, M37272EFSP/FP>

32-pin DIP Type 27C101


17. ONE TIME PROM VERSION M37272E8SP/FP, M37272EFSP/FP MARKING




XXXXXXX is mitsubishi lot number



XXXXXXX is mitsubishi lot number




XXXXXXX is mitsubishi lot number



XXXXXXX is mitsubishi lot number


18. APPENDIX

Pin Configuration (TOP VIEW)



Outline 42P4B

Note: Only 14th pin is NC pin of M37272M6H/M8H/MAH/MFH-XXXSP. This pin is AVcc pin of M37272E8/EFSP. But NC pin of M37272M6H/M8H/MAH/MFH-XXX SP is not connect in the IC. You can apply to Vcc.




Outline 42P2R-A/E

Note: Only 14th pin is NC pin of M37272M6H/M8H/MAH/MFH-XXXFP. This pin is AVcc pin of M37272E8/EFSP. But NC pin of M37272M6H/M8H/MAH/MFH-XXX SP is not connect in the IC. You can apply to Vcc.


Memory Map

■ M37272M6H/M8H-XXXSP/FP, M37272E8SP/FP



Note: Refer to Table 8.11.3 OSD RAM.

■ M37272MAH/MFH-XXXSP/FP, M37272EFSP/FP



Note: Refer to Table 8.11.3 OSD RAM.

Memory Map of Special Function Register (SFR)

<Bit allocation>

: } Function bit

Name : } Function bit

: No function bit

0 : Fix this bit to "0" (do not write "1")

1 : Fix this bit to "1" (do not write "0")

<State immediately after reset>

0 : "0" immediately after reset

1 : "1" immediately after reset

? : Indeterminate immediately after reset

Address	Register	Bit allocation b7 b6 b5 b4 b3 b2 b1 b0	State immediately after reset b7 b6 b5 b4 b3 b2 b1 b0
$C0_{16}$	Port P0 (P0)		?
$C1_{16}$	Port P0 direction register (D0)		00_{16}
$C2_{16}$	Port P1 (P1)		?
$C3_{16}$	Port P1 direction register (D1)		00_{16}
$C4_{16}$	Port P2 (P2)		?
$C5_{16}$	Port P2 direction register (D2)		00_{16}
$C6_{16}$	Port P3 (P3)	P31 P30	0 0 0 0 0 0 ? ?
$C7_{16}$	Port P3 direction register (D3)	T3SC P31C P30C P31D P30D	00_{16}
$C8_{16}$			?
$C9_{16}$			?
CA_{16}	Port P5 (P5)		?
CB_{16}	OSD port control register (PF)	PF7 PF5 PF4 PF3 PF2 0 0	00_{16}
CC_{16}		00_{16}	00_{16}
CD_{16}			?
CE_{16}	Caption data register 3 (CD3)	CDL27 CDL26 CDL25 CDL24 CDL23 CDL22 CDL21 CDL20	?
CF_{16}	Caption data register 4 (CD4)	CDH27 CDH26 CDH25 CDH24 CDH23 CDH22 CDH21 CDH20	?
$D0_{16}$	OSD control register (OC)	0 OC6 OC5 OC4 OC3 OC2 OC1 OC0	00_{16}
$D1_{16}$	Horizontal position register (HP)	HP6 HP5 HP4 HP3 HP2 HP1 HP0	00_{16}
$D2_{16}$	Block control register 1 (BC1)	BC17 BC16 BC15 BC14 BC13 BC12 BC11 BC10	?
$D3_{16}$	Block control register 2 (BC2)	BC27 BC26 BC25 BC24 BC23 BC22 BC21 BC20	?
$D4_{16}$	Vertical position register 1 (VP1)	VP17 VP16 VP15 VP14 VP13 VP12 VP11 VP10	?
$D5_{16}$	Vertical position register 2 (VP2)	VP27 VP26 VP25 VP24 VP23 VP22 VP21 VP20	?
$D6_{16}$	Window register 1 (WN1)	WN17 WN16 WN15 WN14 WN13 WN12 WN11 WN10	?
$D7_{16}$	Window register 2 (WN2)	WN27 WN26 WN25 WN24 WN23 WN22 WN21 WN20	?
$D8_{16}$	I/O polarity control register (PC)	0 PC6 PC5 PC4 PC3 PC2 PC1 PC0	40_{16}
$D9_{16}$	Raster color register (RC)	RC7 0 0 RC4 RC3 RC2 RC1 RC0	00_{16}
DA_{16}			?
DB_{16}			?
DC_{16}	Interrupt input polarity control register (RE)	INT3 INT2 INT1	00_{16}
DD_{16}		00_{16}	00_{16}
DE_{16}		00_{16}	00_{16}
DF_{16}		00_{16} (See note 1)	00_{16} (See note 2)

Notes 1: This is only M37272MAH/MFH-XXXSP/FP, M37272EFSP/FP.

2: As for M37272M6H/M8H-XXXSP/FP and M37272E8SP/FP, the reset value is ? (indeterminate).

■ SFR1 Area (addresses $E0_{16}$ to FF_{16})

<Bit allocation>

: Function bit

: No function bit

0 : Fix this bit to "0" (do not write "1")

1 : Fix this bit to "1" (do not write "0")

<State immediately after reset>

0 : "0" immediately after reset

1 : "1" immediately after reset

? : Indeterminate immediately after reset

Address	Register	Bit allocation b7							b0	State immediately after reset b7							b0
$E0_{16}$	Data slicer control register 1 (DSC1)	0	1	1	0	0	DSC12	DSC11	DSC10	00_{16}							
$E1_{16}$	Data slicer control register 2 (DSC2)		0	DSC25	DSC24	DSC23		1	DSC20	?	0	?	0	?	?	0	?
$E2_{16}$	Caption data register 1 (CD1)	CDL17	CDL16	CDL15	CDL14	CDL13	CDL12	CDL11	CDL10	00_{16}							
$E3_{16}$	Caption data register 2 (CD2)	CDH17	CDH16	CDH15	CDH14	CDH13	CDH12	CDH11	CDH10	00_{16}							
$E4_{16}$	Clock run-in detect register (CRD)	CRD7	CRD6	CRD5	CRD4	CRD3				00_{16}							
$E5_{16}$	Data clock position register (DPS)	DPS7	DPS6	DPS5	DPS4	DPS3	0	1	0	09_{16}							
$E6_{16}$	Caption position register (CPS)	CPS7	CPS6	CPS5	CPS4	CPS3	CPS2	CPS1	CPS0	0	0	?	0	0	0	0	0
$E7_{16}$	Data slicer test register 2									00_{16}							
$E8_{16}$	Data slicer test register 1									00_{16}							
$E9_{16}$	Synchronous signal counter register			HC5	HC4	HC3	HC2	HC1	HC0	00_{16}							
EA_{16}	Serial I/O register (SIO)									?							
EB_{16}	Serial I/O mode register (SM)	0	SM6	SM5	0	SM3	SM2	SM1	SM0	00_{16}							
EC_{16}	A-D control register 1 (AD1)				ADC14		ADC12	ADC11	ADC10	0	0	0	?	0	0	0	0
ED_{16}	A-D control register 2 (AD2)			ADC25	ADC24	ADC23	ADC22	ADC21	ADC20	00_{16}							
EE_{16}	Timer 5 (T5)									07_{16}							
EF_{16}	Timer 6 (T6)									FF_{16}							
$F0_{16}$	Timer 1 (T1)									FF_{16}							
$F1_{16}$	Timer 2 (T2)									07_{16}							
$F2_{16}$	Timer 3 (T3)									FF_{16}							
$F3_{16}$	Timer 4 (T4)									07_{16}							
$F4_{16}$	Timer mode register 1 (TM1)	TM17	TM16	TM15	TM14	TM13	TM12	TM11	TM10	00_{16}							
$F5_{16}$	Timer mode register 2 (TM2)	TM27	TM26	TM25	TM24	TM23	TM22	TM21	TM20	00_{16}							
$F6_{16}$	I^2C data shift register (S0)	D7	D6	D5	D4	D3	D2	D1	D0	?							
$F7_{16}$	I^2C address register (S0D)	SAD6	SAD5	SAD4	SAD3	SAD2	SAD1	SAD0	RBW	00_{16}							
$F8_{16}$	I^2C status register (S1)	MST	TRX	BB	PIN	AL	AAS	AD0	LRB	0	0	0	1	0	0	0	?
$F9_{16}$	I^2C control register (S1D)	BSEL1	BSEL0	10BIT SAD	ALS	ESO	BC2	BC1	BC0	00_{16}							
FA_{16}	I^2C clock control register (S2)	ACK	ACK BIT	FAST MODE	CCR4	CCR3	CCR2	CCR1	CCR0	00_{16}							
FB_{16}	CPU mode register (CPUM)	CM7	CM6	CM5	1	1	CM2	0	0	$3C_{16}$							
FC_{16}	Interrupt request register 1 (IREQ1)		IN3R	VSCR	OSDR	TM4R	TM3R	TM2R	TM1R	00_{16}							
FD_{16}	Interrupt request register 2 (IREQ2)	0	TM56R	IICR	IN2R	CKR	S1R	DSR	IN1R	00_{16}							
FE_{16}	Interrupt control register 1 (ICON1)		IN3E	VSCE	OSDE	TM4E	TM3E	TM2E	TM1E	00_{16}							
FF_{16}	Interrupt control register 2 (ICON2)	TM56C	TM56E	IICE	IN2E	CKE	S1E	DSE	IN1E	00_{16}							

■ SFR2 Area (addresses 200_{16} to $20F_{16}$)

<Bit allocation>

: Function bit
Name : Function bit
: No function bit
0 : Fix this bit to "0" (do not write "1")
1 : Fix this bit to "1" (do not write "0")

<State immediately after reset>

0 : "0" immediately after reset
1 : "1" immediately after reset
? : Indeterminate immediately after reset

Address	Register	Bit allocation b7 b6 b5 b4 b3 b2 b1 b0	State immediately after reset b7 b6 b5 b4 b3 b2 b1 b0
200_{16}	PWM0 register (PWM0)		? ? ? ? ? ? ? ?
201_{16}	PWM1 register (PWM1)		? ? ? ? ? ? ? ?
202_{16}	PWM2 register (PWM2)		? ? ? ? ? ? ? ?
203_{16}	PWM3 register (PWM3)		? ? ? ? ? ? ? ?
204_{16}	PWM4 register (PWM4)		? ? ? ? ? ? ? ?
205_{16}	PWM5 register (PWM5)		? ? ? ? ? ? ? ?
206_{16}		00_{16}	? ? ? ? ? ? ? ?
207_{16}		00_{16}	? ? ? ? ? ? ? ?
208_{16}	PWM mode register 1 (PM1)	PM13 PM10	? ? ? ? 0 ? ? 0
209_{16}	PWM mode register 2 (PM2)	0 0 PM25 PM24 PM23 PM22 PM21 PM20	00_{16}
$20A_{16}$	ROM correction address 1 (high-order)		00_{16}
$20B_{16}$	ROM correction address 1 (low-order)		00_{16}
$20C_{16}$	ROM correction address 2 (high-order)		00_{16}
$20D_{16}$	ROM correction address 2 (low-order)		00_{16}
$20E_{16}$	ROM correction enable register (RCR)	RC1 RC0	00_{16}
$20F_{16}$			?

Internal State of Processor Status Register and Program Counter at Reset

<Bit allocation>

: } Function bit
Name :

: No function bit

0 : Fix to this bit to "0" (do not write to "1")

1 : Fix to this bit to "1" (do not write to "0")

<State immediately after reset>

0 : "0" immediately after reset

1 : "1" immediately after reset

? : Indeterminate immediately after reset


Register	Bit allocation								State immediately after reset							
	b7							b0	b7							b0
Processor status register (PS)	N	V	T	B	D	I	Z	C	?	?	?	?	?	1	?	?
Program counter (PCH)									Contents of address FFFF16							
Program counter (PCL)									Contents of address FFFE16							

Structure of Register

The figure of each register structure describes its functions, contents at reset, and attributes as follows:

<Example>

CPU Mode Register



Bit position **Bit attributes** (Note 2)
Values immediately after reset release (Note 1)

CPU mode register (CPUM) (CM) [Address $00FB_{16}$]

B	Name	Functions	After reset	R	W
0, 1	Processor mode bits (CM0, CM1)	b1 b0 0 0: Single-chip mode 0 1: } Not available 1 0: } 1 1: }	0	R	W
2	Stack page selection bit (See note) (CM2)	0: 0 page 1: 1 page	1	R	W
3, 4	Fix these bits to "1."		1	R	W
5	Nothing is assigned. This bit is write disable bit. When this bit is read out, the value is "1."		1	R	W
6, 7	Clock switch bits (CM6, CM7)	b7 b6 0 0: f(X_{IN}) = 8 MHz 0 1: f(X_{IN}) = 12 MHz 1 0: f(X_{IN}) = 16 MHz 1 1: Do not set	0	R	W

: Bit in which nothing is assigned

Notes 1: Values immediately after reset release
0 ••••••••••••••••••"0" after reset release
1 ••••••••••••••••••"1" after reset release
Indeterminate•••Indeterminate after reset release


2: Bit attributes••••••The attributes of control register bits are classified into 3 types : read-only, write-only and read and write. In the figure, these attributes are represented as follows :

R••••••Read
R ••••••Read enabled
– ••••••Read disabled

W••••••Write
W ••••••Write enabled
– ••••••Write disabled
✻ ••••••"0" can be set by software, but "1" cannot be set.

Address $00C1_{16}$, $00C3_{16}$, $00C5_{16}$

Port Pi Direction Register




Port Pi direction register (PiD) (i=0,1,2) [Addresses $00C1_{16}$, $00C3_{16}$, $00C5_{16}$]

B	Name	Functions	After reset	R	W
0	Port Pi direction register	0 : Port Pi_0 input mode 1 : Port Pi_0 output mode	0	R	W
1		0 : Port Pi_1 input mode 1 : Port Pi_1 output mode	0	R	W
2		0 : Port Pi_2 input mode 1 : Port Pi_2 output mode	0	R	W
3		0 : Port Pi_3 input mode 1 : Port Pi_3 output mode	0	R	W
4		0 : Port Pi_4 input mode 1 : Port Pi_4 output mode	0	R	W
5		0 : Port Pi_5 input mode 1 : Port Pi_5 output mode	0	R	W
6		0 : Port Pi_6 input mode 1 : Port Pi_6 output mode	0	R	W
7		0 : Port Pi_7 input mode 1 : Port Pi_7 output mode	0	R	W

Address $00C7_{16}$

Port P3 Direction Register



Port P3 direction register (P3D) [Address $00C7_{16}$]

B	Name	Functions	After reset	R	W
0	Port P3 direction register	0 : Port $P3_0$ input mode 1 : Port $P3_0$ output mode	0	R	W
1		0 : Port $P3_1$ input mode 1 : Port $P3_1$ output mode	0	R	W
2	Port $P3_0$ output structure selection bit (P30C)	0 : CMOS output 1 : N-channel open-drain output	0	R	W
3	Port $P3_1$ output structure selection bit (P30C)	0 : CMOS output 1 : N-channel open-drain output	0	R	W
4, 5, 7	Nothing is assigned. These bits are write disable bits. When these bits are read out, the values are 0.		0	R	
6	Timer 3 count source selection bit (T3SC)	Refer to Timer section.	0	R	W

Address 00CB16

OSD Port Control Register

b7 b6 b5 b4 b3 b2 b1 b0

0 0

OSD port control register (PF) [Address 00CB16]

B	Name	Functions	After reset	R	W
0, 1	Fix these bits to 0.		0	R	
2	Port P52 output signal selection bit (PF2)	0 : R signal output 1 : Port P52 output	0	R	W
3	Port P53 output signal selection bit (PF3)	0 : G signal output 1 : Port P53 output	0	R	W
4	Port P54 output signal selection bit (PF4)	0 : B signal output 1 : Port P54 output	0	R	W
5	Port P55 output signal selection bit (PF5)	0 : OUT1 signal output 1 : Port P53 output	0	R	W
6	Nothing is assigned. This bit is write disable bit. When this bit is read out, the value is 0.		0	R	
7	Port P10 output signal selection bit (PF7)	0 : Port P10 output 1 : OUT2 signal output	0	R	W

Address 00D016

OSD Control Register

b7 b6 b5 b4 b3 b2 b1 b0

0


OSD control register (OC) [Address 00D0 16]

B	Name	Functions	After reset	R	W
0	OSD control bit (OC0) (See note)	0 : All-blocks display off 1 : All-blocks display on	0	R	W
1	Automatic solid space control bit (OC1)	0 : OFF 1 : ON	0	R	W
2	Window control bit (OC2)	0 : OFF 1 : ON	0	R	W
3	CC mode clock selection bit (OC3)	0 : Data slicer clock 1 : Clock from OSC1 pin	0	R	W
4	OSD mode clock selection bit (OC4)	0 : Data slicer clock 1 : Clock from OSC1 pin	0	R	W
5, 6	OSC1 clock selection bit (OC5, OC6)	b6 b5 0 0: 32 kHz oscillating 0 1: Do not set. 1 0: LC oscillating, Ceramic oscillating 1 1: Do not set.	0	R	W
7	Fix this bit to 0.		0	R	W

Note: Even this bit is switched during display, the display screen remains unchanged until a rising (falling) of the next V SYNC.

Address 00D1$_{16}$

Horizontal Position Register




Horizontal position register (HP) [Address 00D1 $_{16}$]

B	Name	Functions	After reset	R	W
0 to 6	Horizontal display start position control bits (HP0 to HP6)	Horizontal display start positions 128 steps (00$_{16}$ to 7F$_{16}$) (1 step is 4T$_{OSC}$)	0	R	W
7	Nothing is assigned. This bit is a write disable bit. When this bit is read out, the value is "0."		0	R	—

Note: The setting value synchronizes with the V $_{SYNC}$.

Address 00D2$_{16}$, 00D3$_{16}$

Block Control register i




Block control register i (BCi) (i=1, 2) [Addresses 00D2 $_{16}$ and 00D3$_{16}$]

B	Name	Functions	After reset	R	W
0, 1	Display mode selection bits (BCi0, BCi1) (See note 1)	b1 b0 0 0: Display OFF 0 1: CC mode 1 0: OSD mode (Border OFF) 1 1: OSD mode (Border ON)	Indeterminate	R	W
2, 3	Dot size selection bits (BCi2, BCi3)	b4 = 0, Pre-divide Ratio × 2: b3 b2 = 0 0: 1Tc × 1/2H b3 b2 = 0 1: 1Tc × 1H b3 b2 = 1 0: 2Tc × 2H b3 b2 = 1 1: 3Tc × 3H	Indeterminate	R	W
4	Pre-divide ratio selection bit (BCi4)	b4 = 1, Pre-divide Ratio × 3: b3 b2 = 0 0: 1Tc × 1/2H b3 b2 = 0 1: 1Tc × 1H b3 b2 = 1 0: 2Tc × 2H b3 b2 = 1 1: 3Tc × 3H	Indeterminate	R	W
5	OUT1/OUT2 output control bit (BCi5) (See note 1)	0: OUT1 output control 1: OUT2 output control	Indeterminate	R	W
6	Vertical display start position control bit (BCi6)	BC16: Block 1 BC26: Block 1	Indeterminate	R	W
7	Window top/bottom boundary control bit (BCi7)	BC17: Window top boundary BC27: Window bottom boundary	Indeterminate	R	W

Notes 1: Bit RA3 of OSD RAM controls OUT1 output when bit 5 is "0."
Bit RA3 of OSD RAM controls OUT2 output when bit 5 is "1."
2: Tc is OSD clock cycle divided in pre-divide circuit.
3: H is H$_{SYNC}$.

Address $00D4_{16}$, $00D5_{16}$

Vertical Position Register i




Vertical position register i (VPi) (i = 1 and 2) [Addresses $00D4_{16}$, $00D5_{16}$]

B	Name	Functions	After reset	R	W
0 to 7	Vertical display start position control bits (VPi0 to VPi7) (See note)	Vertical display start position = $T_H \times (BCi6 \times 16^2 + n)$ (n: setting value, T_H: H_{SYNC} cycle, BCi6: bit 6 of block control register i)	Inderterminate	R	W

Note: Set values except 00_{16} to VPi when BCi6 is 0.

Address $00D6_{16}$

Window Register 1




Window register 1 (WN1) [Address $00D6_{16}$]

B	Name	Functions	After reset	R	W
0 to 7	Window top boundary control bits (WN10 to WN17)	Window top border position = $T_H \times (BC17 \times 16^2 + n)$ (n: setting value, T_H: H_{SYNC} cycle, BC17: bit 7 of block control register 1)	Inderterminate	R	W

Notes 1: Set values except 00_{16} to WN1 when BC17 is 0.
2: Set values fit for the following condition: WN1 < WN2.

Address $00D7_{16}$

Window Register 2



Window register 2 (WN2) [Address $00D7_{16}$]

B	Name	Functions	After reset	R	W
0 to 7	Window bottom boundary control bits (WN20 to WN27)	Window bottom border position = $T_H \times (BC27 \times 16^2 + n)$ (n: setting value, T_H: H_{SYNC} cycle, BC27: bit 7 of block control register 2)	Inderterminate	R	W

Note: Set values fit for the following condition: WN1 < WN2.

Address 00D8$_{16}$

I/O Polarity Control Register

b7 b6 b5 b4 b3 b2 b1 b0
0

I/O polarity control register (PC) [Address 00D8 $_{16}$]

B	Name	Functions	After reset	R	W
0	HSYNC input polarity switch bit (PC0)	0 : Positive polarity input 1 : Negative polarity input	0	R	W
1	VSYNC input polarity switch bit (PC1)	0 : Positive polarity input 1 : Negative polarity input	0	R	W
2	R, G, B output polarity switch bit (PC2)	0 : Positive polarity output 1 : Negative polarity output	0	R	W
3	OUT1 output polarity switch bit (PC3)	0 : Positive polarity output 1 : Negative polarity output	0	R	W
4	OUT2 output polarity switch bit (PC4)	0 : Positive polarity output 1 : Negative polarity output	0	R	W
5	Display dot line selection bit (PC5) (See note)	0 : "□" at even field "▨" at odd field 1 : "▨" at even field "□" at odd field	0	R	W
6	Field determination flag (PC6)	0 : Even field 1 : Odd field	1	R	—
7	Fix this bit to "0."		0	R	W

Note: Refer to the corresponding figure (8.11.14).

Address 00D9$_{16}$

Raster Color Register

b7 b6 b5 b4 b3 b2 b1 b0
0 0


Raster color register (RC) [Address 00D9 $_{16}$]

B	Name	Functions	After reset	R	W
0	Raster color R control bit (RC0)	0 : No output 1 : Output	0	R	W
1	Raster color G control bit (RC1)	0 : No output 1 : Output	0	R	W
2	Raster color B control bit (RC2)	0 : No output 1 : Output	0	R	W
3	Raster color OUT1 control bit (RC3)	0 : No output 1 : Output	0	R	W
4	Raster color OUT2 control bit (RC4)	0 : No output 1 : Output	0	R	W
5, 6	Fix these bits to "0."		0	R	W
7	Port function selection bit (RC7)	0 : OSC1/XCIN, OSC2/XCOUT 1 : P26, P27	0	R	W

Note: Either OSD clock source or 32 kHz oscillating clock is selected by bits 5 and 6 of the OSD control register.

Address 00DC16

Interrupt Input Polarity Register




Interrupt input polarity register (RE) [Address 00DC16]

B	Name	Functions	After reset	R	W
0	INT1 polarity switch bit (INT1)	0 : Positive polarity 1 : Negative polarity	0	R	W
4	INT2 polarity switch bit (INT2)	0 : Positive polarity 1 : Negative polarity	0	R	W
5	INT3 polarity switch bit (INT3)	0 : Positive polarity 1 : Negative polarity	0	R	W
4 to 7	Nothing is assigned. These bits are write disable bits. When these bits are read out, the values are “0.”		0	R	—

Address 00E016


Data Slicer Control Register 1



Data slicer control register 1(DSC1) [Address 00E016]

B	Name	Functions	After reset	R	W
0	Data slicer and timing signal generating circuit control bit (DSC10)	0: Stopped 1: Operating	0	R	W
1	Selection bit of data slice reference voltage generating field (DSC11)	0: F2 1: F1	0	R	W
2	Reference clock source selection bit (DSC12)	0: Video signal 1: HSYNC signal	0	R	W
3, 4	Fix these bits to “0.”		0	R	W
5, 6	Fix these bits to “1.”		0	R	W
7	Fix this bit to “0.”		0	R	W

Definition of fields 1 (F1) and 2 (F2)



Address 00E1$_{16}$

Data Slicer Control Register 2


b7 b6 b5 b4 b3 b2 b1 b0

0					1		

Data slicer control register 2 (DSC2) [Address 00E1$_{16}$]

B	Name	Functions	After reset	R	W
0	Caption data latch completion flag 1 (DSC20)	0: Data is not latched yet and a clock-run-in is not determined. 1: Data is latched and a clock-run-in is determined.	Indeterminate	R	—
1	Fix this bit to "1."		0	R	W
2	Test bit	Read-only	Indeterminate	R	—
3	Field determination flag(DSC23)	0: F2 1: F1	Indeterminate	R	—
4	Vertical synchronous signal (V_{sep}) generating method selection bit (DSC24)	0: Method (1) 1: Method (2)	0	R	W
5	V-pulse shape determination flag (DSC25)	0: Match 1: Mismatch	Indeterminate	R	—
6	Fix this bit to "o."		0	R	W
7	Test bit	Read-only	Indeterminate	R	—

Definition of fields 1 (F1) and 2 (F2)



Address 00E4$_{16}$

Clock Run-in Detect Register


b7 b6 b5 b4 b3 b2 b1 b0

Clock run-in detect register (CRD) [Address 00E4$_{16}$]

B	Name	Functions	After reset	R	W
0 to 2	Test bits	Read-only	0	R	—
3 to 7	Clock run-in detection bit (CRD3 to CRD7)	Number of reference clocks to be counted in one clock run-in pulse period.	0	R	—

Address 00E5$_{16}$

Data Clock Position Register




Data clock position register (DPS) [Address 00E5$_{16}$]

B	Name	Functions	After reset	R	W
0	Fix this bit to "0."		1	R	W
1	Fix this bit to "1."		0	R	W
2	Fix this bit to "0."		0	R	W
3	Data clock position set bits (DPS3 to DPS7)		1	R	W
4 to 7			0		

Address 00E6$_{16}$

Caption Position Register




Caption Position Register (CPS) [Address 00E6$_{16}$]

B	Name	Functions	After reset	R	W
0 to 4	Caption position bits(CPS0 to CPS4)		0	R	W
5	Caption data latch completion flag 2 (CPS5)	0: Data is not latched yet and a clock-run-in is not determined. 1: Data is latched and a clock-run-in is determined.	Indeterminate	R	
6, 7	Slice line mode specification bits (in 1 field) (CPS6, CPS7)	Refer to the corresponding Table (Table 8.10.1).	0	R	W

Address 00E9$_{16}$

Sync Pulse Counter Register



Sync pulse counter register (HC) [Address 00E9$_{16}$]

B	Name	Functions	After reset	R	W
0 to 4	Count value (HC0 to HC4)		0	R	
5	Count source (HC5)	0: H_{SYNC} signal 1: Composite sync signal	0	R	W
6, 7	Nothing is assigned. These bits are write disable bits. When these bits are read out, the values are 0.		0	R	

Address 00EB16

Serial I/O Mode Register

b7 b6 b5 b4 b3 b2 b1 b0

0 _ _ 0 _ _ _ _

Serial I/O mode register (SM) [Address 00EB16]

B	Name	Functions	After reset	R	W
0, 1	Internal synchronous clock selection bits (SM0, SM1)	b1 b0 0 0: f(XIN)/4 or f(XCIN)/4 0 1: f(XIN)/16 or f(XCIN)/16 1 0: f(XIN)/32 or f(XCIN)/32 1 1: f(XIN)/64 or f(XCIN)/64	0	R	W
2	Synchronous clock selection bit (SM2)	0: External clock 1: Internal clock	0	R	W
3	Port function selection bit (SM3)	0: P20, P21 1: SCLK, SOUT	0	R	W
4	Fix this bit to "0."		0	R	W
5	Transfer direction selection bit (SM5)	0: LSB first 1: MSB first	0	R	W
6	Transfer clock input pin selection bit (SM6)	0: Input signal from SIN pin 1: Input signal from SOUT pin	0	R	W
7	Fix this bit to "0."		0	R	W

Address 00EC16

A-D Control Register 1


b7 b6 b5 b4 b3 b2 b1 b0

A-D control register 1 (AD1) [Address 00EC16]

B	Name	Functions	After reset	R	W
0 to 2	Analog input pin selection bits (ADC10 to ADC12)	b2 b1 b0 0 0 0 : AD1 0 0 1 : AD2 0 1 0 : AD3 0 1 1 : AD4 1 0 0 : AD5 1 0 1 : AD6 1 1 0 : } Do not set. 1 1 1 : }	0	R	W
3	This bit is a write disable bit. When this bit is read out, the value is "0."		0	R	—
4	Storage bit of comparison result (ADC14)	0: Input voltage < reference voltage 1: Input voltage > reference voltage	Indeterminate	R	W
5 to 7	Nothing is assigned. This bits are write disable bits. When these bits are read out, the values are "0."		0	R	—

Address 00ED16

A-D Control Register 2




A-D control register 2 (AD2) [Address 00ED16]

B	Name	Functions	After reset	R	W
0 to 5	D-A converter set bits (ADC20 to ADC25)	b5 b4 b3 b2 b1 b0 0 0 0 0 0 0 : 1/128Vcc 0 0 0 0 0 1 : 3/128Vcc 0 0 0 0 1 0 : 5/128Vcc ⋮ 1 1 1 1 0 1 : 123/128Vcc 1 1 1 1 1 0 : 125/128Vcc 1 1 1 1 1 1 : 127/128Vcc	0	R	W
6, 7	Nothing is assigned. These bits are write disable bits. When these bits are reed out, the values are 0.		0	R	

Address 00F416

Timer Mode Register 1



Timer mode register 1 (TM1) [Address 00F4 16]

B	Name	Functions	After reset	R	W
0	Timer 1 count source selection bit 1 (TM10)	0: f(XIN)/16 or f(XCIN)/16 (See note) 1: Count source selected by bit 5 of TM1	0	R	W
1	Timer 2 count source selection bit 1 (TM11)	0: Count source selected by bit 4 of TM1 1: External clock from TIM2 pin	0	R	W
2	Timer 1 count stop bit (TM12)	0: Count start 1: Count stop	0	R	W
3	Timer 2 count stop bit (TM13)	0: Count start 1: Count stop	0	R	W
4	Timer 2 count source selection bit 2 (TM14)	0: f(XIN)/16 or f(XCIN)/16 (See note) 1: Timer 1 overflow	0	R	W
5	Timer 1 count source selection bit 2 (TM15)	0: f(XIN)/4096 or f(XCIN)/4096 (See note) 1: External clock from TIM2 pin	0	R	W
6	Timer 5 count source selection bit 2 (TM16)	0: Timer 2 overflow 1: Timer 4 overflow	0	R	W
7	Timer 6 internal count source selection bit (TM17)	0: f(XIN)/16 or f(XCIN)/16 (See note) 1: Timer 5 overflow	0	R	W

Note: Either f(XIN) or f(XCIN) is selected by bit 7 of the CPU mode register.

Address 00F5$_{16}$

Timer Mode Register 2

b7 b6 b5 b4 b3 b2 b1 b0

Timer mode register 2 (TM2) [Address 00F5 $_{16}$]

B	Name	Functions	After reset	R	W
0	Timer 3 count source selection bit (TM20)	(b6 at address 00C7 $_{16}$) ↓ b0 0 0 : f(XIN)/16 or f(XCIN)/16 (See note) 0 1 : f(XCIN) 1 0 : 1 1 : } External clock from TIM3 pin	0	R	W
1, 4	Timer 4 count source selection bits (TM21, TM24)	b4 b1 0 0 : Timer 3 overflow signal 0 1 : f(XIN)/16 or f(XCIN)/16 (See note) 1 0 : f(XIN)/2 or f(XCIN)/2 (See note) 1 1 : f(XCIN)	0	R	W
2	Timer 3 count stop bit (TM22)	0: Count start 1: Count stop	0	R	W
3	Timer 4 count stop bit (TM23)	0: Count start 1: Count stop	0	R	W
5	Timer 5 count stop bit (TM25)	0: Count start 1: Count stop	0	R	W
6	Timer 6 count stop bit (TM26)	0: Count start 1: Count stop	0	R	W
7	Timer 5 count source selection bit 1 (TM27)	0: f(XIN)/16 or f(XCIN)/16 (See note) 1: Count source selected by bit 6 of TM1	0	R	W

Note: Either f(XIN) or f(XCIN) is selected by bit 7 of the CPU mode register.

Address 00F6$_{16}$

I^{2}C Data Shift Register

b7 b6 b5 b4 b3 b2 b1 b0

I^{2}C data shift register1(S0) [Address 00F6$_{16}$]

B	Name	Functions	After reset	R	W
0 to 7	D0 to D7	This is an 8-bit shift register to store receive data and write transmit data.	Indeterminate	R	W

Note: To write data into the I^{2}C data shift register after setting the MST bit to "0" (slave mode), keep an interval of 8 machine cycles or more.

Address 00F7$_{16}$

I^{2}C Address Register

b7 b6 b5 b4 b3 b2 b1 b0

I^{2}C address register (S0D) [Address 00F7$_{16}$]

B	Name	Functions	After reset	R	W
0	Read/write bit (RBW)	<Only in 10-bit addressing (in slave) mode> The last significant bit of address data is compared. 0: Wait the first byte of slave address after START condition (read state) 1: Wait the first byte of slave address after RESTART condition (write state)	0	R	—
1 to 7	Slave address (SAD0 to SAD6)	<In both modes> The address data is compared.	0	R	W

Address 00F8$_{16}$

I^{2}C Status Register

b7 b6 b5 b4 b3 b2 b1 b0


I^{2}C status register (S1) [Address 00F8$_{16}$]

B	Name	Functions	After reset	R	W
0	Last receive bit (LRB) (See note)	0 : Last bit = "0 " 1 : Last bit = "1 " (See note)	Indeterminate	R	—
1	General call detecting flag (AD0) (See note)	0 : No general call detected 1 : General call detected (See note)	0	R	—
2	Slave address comparison flag (AAS) (See note)	0 : Address mismatch 1 : Address match (See note)	0	R	—
3	Arbitration lost detecting flag (AL) (See note)	0 : Not detected 1 : Detected (See note)	0	R	—
4	I^{2}C-BUS interface interrupt request bit (PIN)	0 : Interrupt request issued 1 : No interrupt request issued	1	R	W
5	Bus busy flag (BB)	0 : Bus free 1 : Bus busy	0	R	W
6, 7	Communication mode specification bits (TRX, MST)	b7 b6 0 0 : Slave recieve mode 0 1 : Slave transmit mode 1 0 : Master recieve mode 1 1 : Master transmit mode	0	R	W

Note : These bits and flags can be read out, but cannnot be written.

Address 00F9$_{16}$

I^{2}C Control Register




I^{2}C control register (S1D address 00F9$_{16}$)

B	Name	Functions	After reset	R	W
0 to 2	Bit counter (Number of transmit/recieve bits) (BC0 to BC2)	b2 b1 b0 0 0 0 : 8 0 0 1 : 7 0 1 0 : 6 0 1 1 : 5 1 0 0 : 4 1 0 1 : 3 1 1 0 : 2 1 1 1 : 1	0	R	W
3	I^{2}C-BUS interface use enable bit (ESO)	0 : Disabled 1 : Enabled	0	R	W
4	Data format selection bit(ALS)	0 : Addressing mode 1 : Free data format	0	R	W
5	Addressing format selection bit (10BIT SAD)	0 : 7-bit addressing format 1 : 10-bit addressing format	0	R	W
6, 7	Connection control bits between I^{2}C-BUS interface and ports	b7 b6 Connection port (See note) 0 0 : None 0 1 : SCL1, SDA1 1 0 : SCL2, SDA2 1 1 : SCL1, SDA1 SCL2, SDA2	0	R	W

Note: When using ports P11-P14 as I^{2}C-BUS interface, the output structure changes automatically from CMOS output to N-channel open-drain output.

Address 00FA$_{16}$

I^{2}C Clock Control Register




I^{2}C clock control register (S2 : address 00FA$_{16}$)

B	Name	Functions			After reset	R	W
0 to 4	SCL frequency control bits (CCR0 to CCR4)	Setup value of CCR4–CCR0	Standard clock mode	High speed clock mode	0	R	W
		00 to 02	Setup disabled	Setup disabled			
		03	Setup disabled	333			
		04	Setup disabled	250			
		05	100	400 (See note)			
		06	83.3	166			
		⋮	500/CCR value	1000/CCR value			
		1D	17.2	34.5			
		1E	16.6	33.3			
		1F	16.1	32.3			
		(at ϕ = 4 MHz, unit : kHz)					
5	SCL mode specification bit (FAST MODE)	0: Standard clock mode 1: High-speed clock mode			0	R	W
6	ACK bit (ACK BIT)	0: ACK is returned. 1: ACK is not returned.			0	R	W
7	ACK clock bit (ACK)	0: No ACK clock 1: ACK clock			0	R	W

Note: At 4000kHz in the high-speed clock mode, the duty is as below .
"0" period : "1" period = 3 : 2
In the other cases, the duty is as below.
"0" period : "1" period = 1 : 1

Address 00FB16

CPU Mode Register




CPU mode register (CM) [Address 00FB16]

B	Name	Functions	After reset	R	W
0, 1	Processor mode bits (CM0, CM1)	b1 b0 0 0: Single-chip mode 0 1: } Not available 1 0: } 1 1: }	0	R	W
2	Stack page selection bit (CM2) (See note)	0: 0 page 1: 1 page	1	R	W
3, 4	Fix these bits to 1.		1	R	W
5	XCOUT drivability selection bit (CM5)	0: LOW drive 1: HIGH drive	1	R	W
6	Main Clock (XIN—XOUT) stop bit (CM6)	0: Oscillating 1: Stopped	0	R	W
7	Internal system clock selection bit (CM7)	0: XIN—XOUT selected (high-speed mode) 1: XCIN—XCOUT selected (high-speed mode)	0	R	W

Note: This bit is set to 1 after the reset release.

Address 00FC16

Interrupt Request Register 1




Interrupt request register 1 (IREQ1) [Address 00FC16]

B	Name	Functions	After reset	R	W
0	Timer 1 interrupt request bit (TM1R)	0 : No interrupt request issued 1 : Interrupt request issued	0	R	✻
1	Timer 2 interrupt request bit (TM2R)	0 : No interrupt request issued 1 : Interrupt request issued	0	R	✻
2	Timer 3 interrupt request bit (TM3R)	0 : No interrupt request issued 1 : Interrupt request issued	0	R	✻
3	Timer 4 interrupt request bit (TM4R)	0 : No interrupt request issued 1 : Interrupt request issued	0	R	✻
4	OSD interrupt request bit (OSDR)	0 : No interrupt request issued 1 : Interrupt request issued	0	R	✻
5	VSYNC interrupt request bit (VSCR)	0 : No interrupt request issued 1 : Interrupt request issued	0	R	✻
6	INT3 external interrupt request bit (VSCR)	0 : No interrupt request issued 1 : Interrupt request issued	0	R	✻
7	Nothing is assigned. This bit is a write disable bit. When this bit is read out, the value is “0.”		0	R	—

✻: “0” can be set by software, but “1” cannot be set.

Address 00FD16

Interrupt Request Register 2




Interrupt request register 2 (IREQ2) [Address 00FD16]

B	Name	Functions	After reset	R	W
0	INT1 external interrupt request bit (INIR)	0 : No interrupt request issued 1 : Interrupt request issued	0	R	✻
1	Data slicer interrupt request bit (DSR)	0 : No interrupt request issued 1 : Interrupt request issued	0	R	✻
2	Serial I/O interrupt request bit (S1R)	0 : No interrupt request issued 1 : Interrupt request issued	0	R	✻
3	f(XIN)/4096 interrupt request bit (CKR)	0 : No interrupt request issued 1 : Interrupt request issued	0	R	✻
4	INT2 external interrupt request bit (IN2R)	0 : No interrupt request issued 1 : Interrupt request issued	0	R	✻
5	Multi-master I2C-BUS interrupt request bit (IICR)	0 : No interrupt request issued 1 : Interrupt request issued	0	R	✻
6	Timer 5 • 6 interrupt request bit (TM56R)	0 : No interrupt request issued 1 : Interrupt request issued	0	R	✻
7	Fix this bit to “0.”		0	R	W

✻: “0” can be set by software, but “1” cannot be set.

Address 00FE16

Interrupt Control Register 1




Interrupt control register 1 (ICON1) [Address 00FE16]

B	Name	Functions	After reset	R	W
0	Timer 1 interrupt enable bit (TM1E)	0 : Interrupt disabled 1 : Interrupt enabled	0	R	W
1	Timer 2 interrupt enable bit (TM2E)	0 : Interrupt disabled 1 : Interrupt enabled	0	R	W
2	Timer 3 interrupt enable bit (TM3E)	0 : Interrupt disabled 1 : Interrupt enabled	0	R	W
3	Timer 4 interrupt enable bit (TM4E)	0 : Interrupt disabled 1 : Interrupt enabled	0	R	W
4	OSD interrupt enable bit (OSDE)	0 : Interrupt disabled 1 : Interrupt enabled	0	R	W
5	VSYNC interrupt enable bit (VSCE)	0 : Interrupt disabled 1 : Interrupt enabled	0	R	W
6	INT3 external interrupt enable bit (IN3E)	0 : Interrupt disabled 1 : Interrupt enabled	0	R	W
7	Nothing is assigned. This bit is a write disable bit. When this bit is read out, the value is “0.”		0	R	—

Address 00FF16

Interrupt Control Register 2




Interrupt control register 2 (ICON2) [Address 00FF16]

B	Name	Functions	After reset	R	W
0	INT1 external interrupt enable bit (IN1E)	0 : Interrupt disabled 1 : Interrupt enabled	0	R	W
1	Data slicer interrupt enable bit (DSE)	0 : Interrupt disabled 1 : Interrupt enabled	0	R	W
2	Serial I/O interrupt enable bit (S1E)	0 : Interrupt disabled 1 : Interrupt enabled	0	R	W
3	f(XIN)/4096 interrupt enable bit (CKE)	0 : Interrupt disabled 1 : Interrupt enabled	0	R	W
4	INT2 external interrupt enable bit (IN2E)	0 : Interrupt disabled 1 : Interrupt enabled	0	R	W
5	Multi-master I2C-BUS interface interrupt enable bit (IICE)	0 : Interrupt disabled 1 : Interrupt enabled	0	R	W
6	Timer 5 • 6 interrupt enable bit (TM56E)	0 : Interrupt disabled 1 : Interrupt enabled	0	R	W
7	Timer 5 • 6 interrupt switch bit (TM56C)	0 : Timer 5 1 : Timer 6	0	R	W

Address 020816

PWM Mode Register 1




PWM mode register 1 (PM1) [Address 0208$_{16}$]

B	Name	Functions	After reset	R	W
0	PWM counts source selection bit (PM10)	0 : Count source supply 1 : Count source stop	0	R	W
1, 2	Nothing is assigned. These bits are write disable bits. When these bits are read out, the values are 0.		Indeterminate	R	
3	PWM output polarity selection bit (PM13)	0 : Positive polarity 1 : Negative polarity	0	R	W
4 to 7	Nothing is assigned. These bits are write disable bits. When these bits are read out, the values are 0.		Indeterminate	R	

Address 0209$_{16}$

PWM Mode Register 2




PWM mode register 2 (PM2) [Address 0209$_{16}$]

B	Name	Functions	After reset	R	W
0	P0$_0$/PWM0 output selection bit (PM20)	0 : P0$_0$ output 1 : PWM0 output	0	R	W
1	P0$_1$/PWM1 output selection bit (PM21)	0 : P0$_1$ output 1 : PWM1 output	0	R	W
2	P0$_2$/PWM2 output selection bit (PM22)	0 : P0$_2$ output 1 : PWM2 output	0	R	W
3	P0$_3$/PWM3 output selection bit (PM23)	0 : P0$_3$ output 1 : PWM3 output	0	R	W
4	P0$_4$/PWM4 output selection bit (PM24)	0 : P0$_4$ output 1 : PWM4 output	0	R	W
5	P0$_5$/PWM5 output selection bit (PW25)	0: P0$_5$ output 1: PWM5 output	0	R	W
6, 7	Fix these bits to 0.		0	R	W

Address 020E$_{16}$

ROM Correction Enable Register



ROM correction enable register (RCR) [Address 020E $_{16}$]


B	Name	Functions	After reset	R	W
0	Vector 1 enable bit (RC0)	0: Disabled 1: Enabled	0	R	W
1	Vector 2 enable bit (RC1)	0: Disabled 1: Enabled	0	R	W
2 to 7	Nothing is assigned. These bits are write disable bits. When these bits are read out, the values are “0.”		0	R	—


19. PACKAGE OUTLINE

42P4B

Plastic 42pin 600mil SDIP

EIAJ Package Code	JEDEC Code	Weight(g)	Lead Material
SDIP42-P-600-1.78	–	4.1	Alloy 42/Cu Alloy







Symbol	Dimension in Millimeters		
	Min	Nom	Max
A	–	–	5.5
A1	0.51	–	–
A2	–	3.8	–
b	0.35	0.45	0.55
b1	0.9	1.0	1.3
b2	0.63	0.73	1.03
c	0.22	0.27	0.34
D	36.5	36.7	36.9
E	12.85	13.0	13.15
e	–	1.778	–
e1	–	15.24	–
L	3.0	–	–
θ	0°	–	15°


42P2R-A/E

Plastic 42pin 450mil SSOP


EIAJ Package Code	JEDEC Code	Weight(g)	Lead Material
SSOP42-P-450-0.80	–	0.63	Alloy 42









Detail G





Detail F



Recommended Mount Pad

Symbol	Dimension in Millimeters		
	Min	Nom	Max
A	–	–	2.4
A1	0.05	–	–
A2	–	2.0	–
b	0.25	0.3	0.4
c	0.13	0.15	0.2
D	17.3	17.5	17.7
E	8.2	8.4	8.6
e	–	0.8	–
HE	11.63	11.93	12.23
L	0.3	0.5	0.7
L1	–	1.765	–
z	–	0.75	–
Z1	–	–	0.9
y	–	–	0.15
θ	0°	–	10°
b2	–	0.5	–
e1	–	11.43	–
l2	1.27	–	–

M37272M6H/M8H/MAH/MFH–XXXSP/FP
M37272E8SP/FP, M37272EFSP/FP

SINGLE-CHIP 8-BIT CMOS MICROCOMPUTER with CLOSED CAPTION DECODER
and ON-SCREEN DISPLAY CONTROLLER

MITSUBISHI ELECTRIC CORPORATION
HEAD OFFICE: 2-2-3, MARUNOUCHI, CHIYODA-KU, TOKYO 100-8310, JAPAN

Keep safety first in your circuit designs!

- Mitsubishi Electric Corporation puts the maximum effort into making semiconductor products better and more reliable, but there is always the possibility that trouble may occur with them. Trouble with semiconductors may lead to personal injury, fire or property damage. Remember to give due consideration to safety when making your circuit designs, with appropriate measures such as (i) placement of substitutive, auxiliary circuits, (ii) use of non-flammable material or (iii) prevention against any malfunction or mishap.

Notes regarding these materials

- These materials are intended as a reference to assist our customers in the selection of the Mitsubishi semiconductor product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Mitsubishi Electric Corporation or a third party.
- Mitsubishi Electric Corporation assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.
- All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Mitsubishi Electric Corporation without notice due to product improvements or other reasons. It is therefore recommended that customers contact Mitsubishi Electric Corporation or an authorized Mitsubishi Semiconductor product distributor for the latest product information before purchasing a product listed herein.
  The information described here may contain technical inaccuracies or typographical errors. Mitsubishi Electric Corporation assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors.
  Please also pay attention to information published by Mitsubishi Electric Corporation by various means, including the Mitsubishi Semiconductor home page (http://www.mitsubishichips.com).
- When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Mitsubishi Electric Corporation assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.
- Mitsubishi Electric Corporation semiconductors are not designed or manufactured for use in a device or system that is used under circumstances in which human life is potentially at stake. Please contact Mitsubishi Electric Corporation or an authorized Mitsubishi Semiconductor product distributor when considering the use of a product contained herein for any specific purposes, such as apparatus or systems for transportation, vehicular, medical, aerospace, nuclear, or undersea repeater use.
- The prior written approval of Mitsubishi Electric Corporation is necessary to reprint or reproduce in whole or in part these materials.
- If these products or technologies are subject to the Japanese export control restrictions, they must be exported under a license from the Japanese government and cannot be imported into a country other than the approved destination.
  Any diversion or reexport contrary to the export control laws and regulations of Japan and/or the country of destination is prohibited.
- Please contact Mitsubishi Electric Corporation or an authorized Mitsubishi Semiconductor product distributor for further details on these materials or the products contained therein.

© 2001 MITSUBISHI ELECTRIC CORP.
New publication, effective March. 2001.
Specifications subject to change without notice.

MITSUBISHI ELECTRIC

REVISION DESCRIPTION LIST	M37272M6/M8-XXXSP/FP, M37272MA-XXXSP, M37272E8SP/FP, M37272EFSP DATA SHEET

Rev. No.	Revision Description	Rev. date
1.0	First Edition of PDF File	0103