19-3976; Rev 0; 1/06

1.8W, Filterless, Ultra-Low EMI, Stereo Class D Audio Power Amplifier

General Description

The MAX9773 3rd-generation, ultra-low EMI, stereo, Class D audio power amplifier provides Class AB performance with Class D efficiency. The MAX9773 delivers 1.8W per channel into a 4Ω load, and offers efficiencies above 90%. Active emissions limiting (AEL) circuitry greatly reduces EMI by actively controlling the output FET gate transitions under all possible transient conditions. AEL controls high-frequency emissions resulting from conventional Class D free-wheeling behavior in the presence of an inductive load. Zero-dead-time (ZDT) technology maintains state-of-the-art efficiency and THD+N performance by allowing the output FETs to switch simultaneously without cross conduction. A spread-spectrum modulation scheme eliminates the need for output filtering found in traditional Class D devices. These design concepts reduce component count and extend battery life.

The MAX9773 offers two modulation schemes: a fixed-frequency (FFM) mode, and a spread-spectrum (SSM) mode that reduces EMI-radiated emissions. The MAX9773 oscillator can be synchronized to an external clock through the SYNC input, allowing synchronization of multiple Maxim Class D amplifiers. The sync output (SYNC_OUT) can be used for a master-slave application where more channels are required. The MAX9773 features a fully differential architecture, a full bridge-tied load (BTL) output, and comprehensive click-and-pop suppression. The device features internally set gains of 12dB, 15.6dB, 20dB, and 26dB selected through two gain-select inputs, further reducing external component count.

The MAX9773 features high 80dB PSRR, less than 0.1% THD+N, and SNR in excess of 88dB. Short-circuit and thermal-overload protection prevent the device from being damaged during a fault condition. The MAX9773 is available in 24-pin thin QFN-EP (4mm x 4mm x 0.8mm), and 20-bump UCSP™ (2mm x 2.5mm x 0.6mm) packages. The MAX9773 is specified over the extended -40°C to +85°C temperature range.

Applications

Cellular/Multimedia Phones

Notebooks

Handheld Gaming Consoles

MP3 Players

Pin Configurations and Gain Selection appear at end of data sheet.

UCSP is a trademark of Maxim Integrated Products, Inc.

Features


- **Filterless Amplifier Passes FCC-Radiation Emissions Standards with 6in of Cable**
- **Unique Spread-Spectrum Mode and Active Emissions Limiting Achieves Better than 15dB Margin Under FCC Limit**
- **Zero Dead Time (ZDT) H-Bridge Maintains Good THD+N Performance**
- **Single-Supply Operation (2.5V to 5.5V)**
- **Stereo Output (4Ω, V_{DD} = 5V, THD+N = 1%, P_{OUT} = 1.8W)**
- **No LC Output Filter Required**
- **85% Efficiency (R_L = 8Ω, P_O = 600mW)**
- **Less Than 0.1% THD+N**
- **High 80dB PSRR**
- **Fully Differential Inputs**
- **Integrated Click-and-Pop Suppression**
- **Low-Power Shutdown Mode (0.1µA)**
- **Short-Circuit and Thermal-Overload Protection**
- **Pin-for-Pin Compatible with the MAX9701**
- **Available in Thermally Efficient, Space-Saving Packages**
  - **24-Pin TQFN-EP (4mm x 4mm x 0.8mm)**
  - **20-Bump UCSP (2mm x 2.5mm x 0.6mm)**

Ordering Information

PART	TEMP RANGE	PIN-PACKAGE	PKG CODE
MAX9773EBP-T	-40°C to +85°C	20 UCSP-20	B20-1
MAX9773ETG+	-40°C to +85°C	24 TQFN-EP*	T2444-4

+Denotes lead-free package.
**EP = Exposed paddle.*

Block Diagram



For pricing, delivery, and ordering information, please contact Maxim/Dallas Direct! at 1-888-629-4642, or visit Maxim's website at www.maxim-ic.com.

1.8W, Filterless, Ultra-Low EMI, Stereo Class D Audio Power Amplifier

ABSOLUTE MAXIMUM RATINGS

V_{DD} to GND 6V
V_{DD} to PV_{DD} .....-0.3V to +0.3V
PV_{DD} to PGND 6V
GND to PGND .....-0.3V to +0.3V
All Other Pins to GND .....-0.3V to (V_{DD} + 0.3V)
Continuous Current In/Out of PV_{DD}, PGND, OUT_ .....±800mA
Continuous Input Current (all other pins) .....±20mA
Duration of OUT_ Short Circuit to V_{DD}/GND/PV_{DD}/PGND .....Continuous
Duration of Short Circuit Between OUT+ and OUT- .....Continuous
Continuous Power Dissipation (T_A = +70°C)
20-Bump UCSP (derate 10mW/°C above +70°C) 800mW
24-Pin Thin QFN (derate 20.8mW/°C above +70°C) 1666.7mW
Junction Temperature .....+150°C
Operating Temperature Range .....-40°C to +85°C
Storage Temperature Range .....-65°C to +150°C
Bump Temperature (soldering) Reflow .....+235°C
Lead Temperature (soldering, 10s) .....+300°C

Stresses beyond those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated in the operational sections of the specifications is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

ELECTRICAL CHARACTERISTICS

(V_{DD} = V_{PVDD} = $V_{\overline{SHDN}}$ = 3.3V, V_{GND} = V_{PGND} = 0V, SYNC = 0V (FFM), gain = 12dB (GAIN1 = 1, GAIN2 = 1), R_L connected between OUT+ and OUT-, R_L = ∞, T_A = T_{MIN} to T_{MAX}, unless otherwise noted. Typical values are at T_A = +25°C.) (Notes 1, 2)

PARAMETER	SYMBOL	CONDITIONS			MIN	TYP	MAX	UNITS
GENERAL								
Supply Voltage Range	V_{DD}	Inferred from PSRR test			2.6		5.5	V
Quiescent Current	I_{DD}	Per channel				5.5	7.5	mA
Shutdown Current	I_{SHDN}					0.1	10	µA
Common-Mode Rejection Ratio	CMRR	f_{IN} = 1kHz				66		dB
Input Bias Voltage	V_{BIAS}				1.125	1.25	1.375	V
Turn-On Time	t_{ON}					80		ms
Output Offset Voltage	V_{OS}	T_A = +25°C				±10	±50	mV
Power-Supply Rejection Ratio	PSRR	V_{DD} = 2.5V to 5.5V, V_{IN} = 0V, T_A = +25°C			59	80		dB
		T_{MIN} < T_A < T_{MAX}			56			
		100mV_{P-P} ripple, V_{IN} = 0V	f_{RIPPLE} = 217Hz			72		
			f_{RIPPLE} = 20kHz			50		
Output Power (Note 3)	P_{OUT}	THD+N = 1%, T_A = +25°C	V_{DD} = 3.3V	R_L = 8Ω		500		mW
				R_L = 4Ω		750		
			V_{DD} = 5V	R_L = 8Ω		1300		
				R_L = 4Ω		1800		
Total Harmonic Distortion Plus Noise (Note 3)	THD+N	R_L = 8Ω (P_{OUT} = 400mW), f = 1kHz				0.04		%
		R_L = 4Ω (P_{OUT} = 600mW), f = 1kHz				0.08		
Signal-to-Noise Ratio	SNR	V_{OUT} = 1V_{RMS}	BW = 22Hz to 22kHz	FFM		86		dB
				SSM		86		
			A-weighted	FFM		88.5		
				SSM		88.5		
Oscillator Frequency	f_{OSC}	SYNC = GND, T_A = +25°C			950	1100	1250	kHz
		SYNC = unconnected, T_A = +25°C			1200	1400	1600	
		SYNC = V_{DD}, T_A = +25°C				1200 ±60		
Minimum On-Time	t_{MIN}					200		ns
SYNC Frequency Lock Range	f_{SYNC}				1000		2000	kHz

ELECTRICAL CHARACTERISTICS (continued)

(V_{DD} = V_{PVDD} = $V_{\overline{SHDN}}$ = 3.3V, V_{GND} = V_{PGND} = 0V, SYNC = 0V (FFM), gain = 12dB (GAIN1 = 1, GAIN2 = 1), R_L connected between OUT+ and OUT-, R_L = ∞, T_A = T_{MIN} to T_{MAX}, unless otherwise noted. Typical values are at T_A = +25°C.) (Notes 1, 2)

PARAMETER	SYMBOL	CONDITIONS		MIN	TYP	MAX	UNITS
SYNC_OUT Capacitance Drive	C_{SYNC_OUT}				100		pF
Capacitive Drive	C_L	Bridge-tied capacitance			200		pF
		Single ended			400		
Click-and-Pop Level	K_{CP}	Peak reading, A-weighted, 32 samples per second (Note 4)	Into shutdown		-50		dBV
			Out of shutdown		-50		
Efficiency	η	P_{OUT} = 600mW per channel, f_{IN} = 1kHz, R_L = 8Ω			85		%
Input Resistance	R_{IN}	GAIN1 = 0, GAIN2 = 0		10	16		kΩ
		GAIN1 = 1, GAIN2 = 0			30		
		GAIN1 = 0, GAIN2 = 1			45		
		GAIN1 = 1, GAIN2 = 1			60		
Gain	A_V	GAIN1 = 0, GAIN2 = 0			26		dB
		GAIN1 = 1, GAIN2 = 0			20		
		GAIN1 = 0, GAIN2 = 1			15.6		
		GAIN1 = 1, GAIN2 = 1			12		
Channel-to-Channel Gain Tracking					1		%
Crosstalk		L to R, R to L, f = 10kHz, R_L = 8Ω, P_{OUT} = 300mW			80		dB
DIGITAL INPUTS ($\overline{SHDN}$, SYNC, GAIN1, GAIN2)							
Input-Voltage High	V_{INH}			2			V
Input-Voltage Low	V_{INL}					0.8	V
Input Leakage Current ($\overline{SHDN}$, GAIN1, GAIN2)						±1	µA
Input Leakage Current (SYNC)		V_{SYNC} = GND, normal operation		-15	-7		µA
		V_{SYNC} = V_{DD}, normal operation			12	25	
DIGITAL OUTPUTS (SYNC_OUT)							
Output-Voltage High	V_{OH}	I_{OH} = 3mA, V_{DD} = 3.3V		2.4			V
Output-Voltage Low	V_{OL}	I_{OL} = 3mA				0.4	V

Note 1: All devices are 100% production tested at +25°C. All temperature limits are guaranteed by design.

Note 2: Testing performed with a resistive load in series with an inductor to simulate an actual speaker load. For R_L = 4Ω, L = 33µH. For R_L = 8Ω, L = 68µH.

Note 3: When driving speakers below 4Ω with large signals, exercise care to avoid violating the absolute maximum rating for continuous output current.


Note 4: Testing performed with 8Ω resistive load in series with 68µH inductive load connected across the BTL output. Mode transitions are controlled by $\overline{SHDN}$. K_{CP} level is calculated as: 20 x log[(peak voltage during mode transition, no input signal)]. Units are expressed in dBV.

1.8W, Filterless, Ultra-Low EMI, Stereo Class D Audio Power Amplifier


Typical Operating Characteristics

(V_{DD} = V_{PVDD} = $V_{\overline{SHDN}}$ = 3.3V, V_{GND} = V_{PGND} = 0V, SYNC = V_{DD} (SSM), gain = 12dB (GAIN1 = 1, GAIN2 = 1)).


TOTAL HARMONIC DISTORTION PLUS NOISE vs. FREQUENCY




TOTAL HARMONIC DISTORTION PLUS NOISE vs. FREQUENCY




TOTAL HARMONIC DISTORTION PLUS NOISE vs. FREQUENCY




TOTAL HARMONIC DISTORTION PLUS NOISE vs. FREQUENCY




TOTAL HARMONIC DISTORTION PLUS NOISE vs. FREQUENCY




TOTAL HARMONIC DISTORTION PLUS NOISE vs. OUTPUT POWER




TOTAL HARMONIC DISTORTION PLUS NOISE vs. OUTPUT POWER



TOTAL HARMONIC DISTORTION PLUS NOISE vs. OUTPUT POWER




TOTAL HARMONIC DISTORTION PLUS NOISE vs. OUTPUT POWER




Typical Operating Characteristics (continued)

(V_{DD} = V_{PVDD} = $V_{\overline{SHDN}}$ = 3.3V, V_{GND} = V_{PGND} = 0V, SYNC = V_{DD} (SSM), gain = 12dB (GAIN1 = 1, GAIN2 = 1)).


TOTAL HARMONIC DISTORTION PLUS NOISE vs. OUTPUT POWER




EFFICIENCY vs. OUTPUT POWER




EFFICIENCY vs. OUTPUT POWER




OUTPUT POWER vs. SUPPLY VOLTAGE



OUTPUT POWER vs. SUPPLY VOLTAGE



OUTPUT POWER vs. LOAD RESISTANCE




1.8W, Filterless, Ultra-Low EMI, Stereo Class D Audio Power Amplifier


Typical Operating Characteristics (continued)

(V_{DD} = V_{PVDD} = $V_{\overline{SHDN}}$ = 3.3V, V_{GND} = V_{PGND} = 0V, SYNC = V_{DD} (SSM), gain = 12dB (GAIN1 = 1, GAIN2 = 1)).


OUTPUT POWER vs. LOAD RESISTANCE




POWER-SUPPLY REJECTION RATIO vs. FREQUENCY




COMMON-MODE REJECTION RATIO vs. FREQUENCY




CROSSTALK vs. FREQUENCY




CROSSTALK vs. INPUT AMPLITUDE



OUTPUT FREQUENCY SPECTRUM




OUTPUT FREQUENCY SPECTRUM




Typical Operating Characteristics (continued)

(V_{DD} = V_{PVDD} = $V_{\overline{SHDN}}$ = 3.3V, V_{GND} = V_{PGND} = 0V, SYNC = V_{DD} (SSM), gain = 12dB (GAIN1 = 1, GAIN2 = 1)).


WIDEBAND OUTPUT SPECTRUM (FFM MODE)




WIDEBAND OUTPUT SPECTRUM (SSM MODE (SPEAKER MODE))




TURN-ON/TURN-OFF RESPONSE



SUPPLY CURRENT vs. SUPPLY VOLTAGE



SHUTDOWN CURRENT vs. SUPPLY VOLTAGE




1.8W, Filterless, Ultra-Low EMI, Stereo Class D Audio Power Amplifier

Pin Description

PIN		NAME	FUNCTION
TQFN	UCSP		
1	A2	$\overline{SHDN}$	Active-Low Shutdown. Connect to V_{DD} for normal operation.
2	B3	SYNC	Frequency Select and External Clock Input: SYNC = GND: Fixed-frequency mode with f_S = 1100kHz. SYNC = Unconnected: Fixed-frequency mode with f_S = 1400kHz. SYNC = V_{DD}: Spread-spectrum mode with f_S = 1200kHz ±60kHz. SYNC = Clocked: Fixed-frequency mode with f_S = external clock frequency.
3, 8, 11, 16	—	N.C.	No Connection. Not internally connected.
4	A3	OUTL+	Left-Channel Amplifier Output Positive Phase
5, 14	A4, D4	PV_{DD}	H-Bridge Power Supply. Connect to V_{DD}. Bypass with a 0.1µF capacitor to PGND.
6, 13	B4, C4	PGND	Power Ground
7	A5	OUTL-	Left-Channel Amplifier Output Negative Phase
9, 22	B1, B5	GND	Analog Ground
10	C5	SYNC_OUT	Clock Signal Output
12	D5	OUTR-	Right-Channel Amplifier Output Negative Phase
15	D3	OUTR+	Right-Channel Amplifier Output Positive Phase
17	C3	GAIN1	Gain-Select Input 1
18	D2	GAIN2	Gain-Select Input 2
19	D1	INR-	Right-Channel Inverting Input
20	C2	INR+	Right-Channel Noninverting Input
21	C1	V_{DD}	Analog Power Supply. Connect to PV_{DD}. Bypass with a 10µF capacitor to GND.
23	B2	INL+	Left-Channel Noninverting Input
24	A1	INL-	Left-Channel Inverting Input
EP	—	EP	Exposed Pad. Connect the exposed thermal pad to the GND plane (see the *Supply Bypassing, Layout, and Grounding* section).

Functional Diagram



*BULK CAPACITANCE.

1.8W, Filterless, Ultra-Low EMI, Stereo Class D Audio Power Amplifier




Figure 1. MAX9773 Outputs with an Input Signal Applied

Detailed Description

The MAX9773 ultra-low EMI, filterless, stereo Class D audio power amplifier incorporates several improvements to switch-mode amplifier topology. The MAX9773 features output-driver AEL circuitry to reduce EMI. Zero dead time technology maintains state-of-the art efficiency and THD+N performance by allowing the output FETs to switch simultaneously without cross conduction. The MAX9773 offers Class AB performance with Class D efficiency, while occupying minimal board space. A unique, filterless modulation scheme, synchronizable switching frequency, and spread-spectrum switching mode create a compact, flexible, low-noise, efficient audio power amplifier. The differential input architecture reduces common-mode noise pickup, and can be used without input-coupling capacitors. The inputs can also be configured to accept a single-ended input signal.

Comparators monitor the MAX9773 inputs and compare the complementary input voltages to the sawtooth waveform. The comparators trip when the input magnitude of the sawtooth exceeds their corresponding input voltage. Both comparators reset at a fixed time after the rising edge of the second comparator trip point, generating a minimum-width pulse ($t_{ON(MIN)}$) at the output of the second comparator (Figure 1). As the input voltage increases or decreases, the duration of the pulse at one output increases while the other output pulse duration remains the same. This causes the net voltage across the speaker (V_{OUT+} - V_{OUT-}) to change. The minimum-width pulse helps the device to achieve high levels of linearity.




Figure 2. MAX9773 Outputs with an Input Signal Applied (SSM Mode)

Operating Modes

Fixed-Frequency (FFM) Mode

The MAX9773 features two fixed-frequency modes. Connect SYNC to GND to select a 1.1MHz switching frequency. Leave SYNC unconnected to select a 1.4MHz switching frequency. The frequency spectrum of the MAX9773 consists of the fundamental switching frequency and its associated harmonics (see the Wideband FFT graph in the *Typical Operating Characteristics*). Program the switching frequency so the harmonics do not fall within a sensitive frequency band (Table 1). Audio reproduction is not affected by changing the switching frequency.

Table 1. Operating Modes

SYNC	MODE
GND	FFM with f_{OSC} = 1100kHz
Unconnected	FFM with f_{OSC} = 1400kHz
V_{DD}	SSM with f_{OSC} = 1200kHz ±60kHz
Clocked	FFM with f_{OSC} = external clock frequency

1.8W, Filterless, Ultra-Low EMI, Stereo Class D Audio Power Amplifier

Spread-Spectrum (SSM) Mode

The MAX9773 features a unique spread-spectrum mode that flattens the wideband spectral components, improving EMI emissions that may be radiated by the speaker and cables. This mode is enabled by connecting SYNC to V_{DD} (Table 1). In SSM mode, the switching frequency varies randomly by ±60kHz around the center frequency (1.2MHz). The modulation scheme remains the same, but the period of the sawtooth waveform changes from cycle to cycle (Figure 2). Instead of a large amount of spectral energy present at multiples of the switching frequency, the energy is now spread over a bandwidth that increases with frequency. Above a few megahertz, the wideband spectrum looks like white noise for EMI purposes (Figure 3). A proprietary amplifier topology ensures this does not corrupt the noise floor in the audio bandwidth.

Synchronous Switching Mode

SYNC

The SYNC input allows the MAX9773 to be synchronized to a user-defined clock, or another Maxim Class D amplifier, creating a fully synchronous system, minimizing clock intermodulation, and allocating spectral components of the switching harmonics to insensitive frequency bands. Applying a TTL clock signal between 1000kHz and 2000kHz to SYNC synchronizes the MAX9773. The period of the SYNC clock can be randomized, allowing the MAX9773 to be synchronized to another Maxim Class D amplifier operating in SSM mode.

SYNC_OUT

SYNC_OUT allows several MAX9773s as well as other Class D amplifiers (such as the MAX9700) to be cascaded. The synchronized output minimizes interference due to clock intermodulation caused by the switching spread between single devices. Using SYNC_OUT, the modulation scheme remains the same and audio reproduction is not affected by changing the switching frequency.

Filterless Modulation/Common-Mode Idle

The MAX9773 uses Maxim's unique modulation scheme that eliminates the LC filter required by traditional Class D amplifiers, improving efficiency, reducing component count, conserving board space and system cost. Conventional Class D amplifiers output a 50% duty cycle, 180° out-of-phase square wave when no signal is present. With no filter, the square wave appears across the load as a DC voltage, resulting in finite load current, which increases power consumption especially when idling. When no signal is present at the input of the MAX9773, the amplifiers output an in-phase square wave as shown in Figure 4. Because the MAX9773 drives the speaker differentially, the two outputs cancel each other, resulting in no net idle mode voltage across the speaker, minimizing power consumption.




Figure 3. EMI Spectrum of MAX9773 with 6in of Twisted-Pair Speaker Cable with TDK Ferrite Beads MPZ1608S300A




Figure 4. MAX9773 Outputs with No Input Signal




Figure 5. MAX9773 Efficiency vs. Class AB Efficiency

Efficiency

Efficiency of a Class D amplifier is due to the switching operation of the output stage transistors. In a Class D amplifier, the output transistors act as current-steering switches and consume negligible additional power. Any power loss associated with the Class D output stage is mostly due to the I*R loss of the MOSFET on-resistance, and quiescent-current overhead.

The theoretical best efficiency of a linear amplifier is 78%; however, that efficiency is only exhibited at peak output powers. Under normal operating levels (typical music reproduction levels), efficiency falls below 30%, whereas the MAX9773 still exhibits >80% efficiencies under the same conditions (Figure 5).

Shutdown

The MAX9773 has a shutdown mode that reduces power consumption and extends battery life. Driving $\overline{SHDN}$ low places the MAX9773 in a low-power (0.1µA) shutdown mode. Connect $\overline{SHDN}$ to V_{DD} for normal operation.

Click-and-Pop Suppression

The MAX9773 features comprehensive click-and-pop suppression that eliminates audible transients on startup and shutdown. While in shutdown, the H-bridge is in a high-impedance state. During startup, or power-up, the input amplifiers are muted and an internal loop sets the modulator bias voltages to the correct levels, preventing clicks and pops when the H-bridge is subsequently enabled. For 80ms following startup, a soft-start function gradually unmutes the input amplifiers.

Applications Information

Filterless Operation

Traditional Class D amplifiers require an output filter to recover the audio signal from the amplifier's PWM output. The filters add cost, increase the solution size of the amplifier, and can decrease efficiency. The traditional PWM scheme uses large differential output swings (2 x $V_{DD(P-P)}$) and causes large ripple currents. Any parasitic resistance in the filter components results in a loss of power, lowering the efficiency.

The MAX9773 does not require an output filter. The device relies on the inherent inductance of the speaker coil and the natural filtering of both the speaker and the human ear to recover the audio component of the square-wave output. Eliminating the output filter results in a smaller, less costly, more efficient solution.

Because the frequency of the MAX9773 output is well beyond the bandwidth of most speakers, voice coil movement due to the square-wave frequency is very small. Although this movement is small, a speaker not designed to handle the additional power can be damaged. For optimum results, use a speaker with a series inductance >10µH. Typical 8Ω speakers, for portable audio applications, exhibit series inductances in the range of 20µH to 100µH.

Output Offset

Unlike a Class AB amplifier, the output offset voltage of a Class D amplifier does not noticeably increase quiescent current draw when a load is applied. This is due to the power conversion of the Class D amplifier. For example, an 8mV DC offset across an 8Ω load results in 1mA extra current consumption in a Class AB device. In the Class D case, an 8mV offset into 8Ω equates to an additional power drain of 8µW. Due to the high efficiency of the Class D amplifier, this represents an additional quiescent current draw of: $8\mu W/(V_{DD} / 100 \times \eta)$, which is on the order of a few µA.

1.8W, Filterless, Ultra-Low EMI, Stereo Class D Audio Power Amplifier

Table 2. Gain Settings (V_{DD} = 3.3V, THD+N = 10%)

GAIN1	GAIN2	GAIN (dB)	INPUT (V_{RMS})	R_L (Ω)	P_{OUT} (mW)
0	0	+26	0.097699	4	950
1	0	+20	0.194936	4	950
0	1	+15.6	0.323513	4	950
1	1	12	0.489657	4	950
0	0	+26	0.114288	8	650
1	0	+20	0.228035	8	650
0	1	+15.6	0.378444	8	650
1	1	12	0.572798	8	650

Selectable Gain

The MAX9773 features four selectable gain settings, minimizing external component count. Gains of 12dB, 15.6dB, 20dB, and 26dB are set through gain-select inputs, GAIN1 and GAIN2. GAIN1 and GAIN2 can be hardwired or digitally controlled. Table 2 shows the suggested gain settings to attain a maximum output power from a given peak input voltage and given load at V_{DD} = 3.3V and THD+N = 10%.

Custom Gain Settings

The MAX9773 can be set up with any gain setting by adding three external resistors per amplifier. Figure 6 shows the required circuit for setting up custom gain. Table 3 displays a list of the components to use for several gain settings.

Table 3. Custom Gain Components

GAIN_ SETTINGS		GAIN (dB)	R1 (Ω)	R2 (Ω)	C_{IN} (µF)	GAIN TOLERANCE (dB)
GAIN1	GAIN2					
0	0	26	—	—	1	—
0	0	25	750	20k	1	+0.12/-0.07
0	0	24	1k	10k	1.5	+0.14/-0.08
0	0	23	1k	6k	2.2	+0.13/-0.08
0	0	22	1.5k	6k	2.2	+0.16/-0.1
0	0	21	2k	6k	2	+0.19/-0.12
1	0	20	—	—	1	—
1	0	19	1.2k	30k	1	+0.1/-0.06
1	0	18	2k	20k	1	+0.15/-0.09
1	0	17	2k	10k	1.2	+0.12/-0.07
1	0	16	2.5k	10k	1.2	+0.15/-0.09
0	1	15	1k	40k	0.86	+0.06/-0.03
0	1	14	2.8k	40k	0.68	+0.15/-0.09
0	1	13	2.8k	20k	0.86	+0.14/-0.08
1	1	12	—	—	1	—
1	1	11	1.8k	40k	0.86	+0.08/-0.05
1	1	10	4k	40k	0.68	+0.15/-0.09
1	1	9	5k	30k	0.68	+0.17/-0.1
1	1	8	5k	20k	0.68	+0.15/-0.09
1	1	7	5.5k	16k	0.68	+0.15/-0.09
1	1	6	7k	16k	0.68	+0.17/-0.1
1	1	5	8k	14k	0.68	+0.17/-0.1
1	1	4	8k	12k	0.68	+0.16/-0.1
1	1	3	10k	12k	0.68	+0.17/-0.1
1	1	2	11k	10k	0.68	+0.16/-0.1
1	1	1	12k	10k	0.58	+0.16/-0.1
1	1	0	14k	10k	0.47	+0.17/-0.1




Figure 6. Custom Gain Setting




Figure 7. Single-Ended Input

The internal input resistance, R_{IN}, changes with each gain setting. The R1 resistors attenuate the gain and resistors R2 compensate for R_{IN}'s tolerance, which can be as high as 25%. C_{IN} must be adjusted to compensate for the total change in input impedance or the low-frequency roll-off point shifts.

Input Amplifier

Differential Input

The MAX9773 features a differential input structure, making it compatible with many CODECs and offers improved noise immunity over a single-ended input amplifier. In devices such as cellular phones, high-frequency signals from the RF transmitter can be picked up by the amplifier's input traces. The signals appear at the amplifier's inputs as common-mode noise. A differential input amplifier amplifies the difference of the two inputs, any signal common to both inputs is canceled.

Single-Ended Input

The MAX9773 can be configured as a single-ended input amplifier by capacitively coupling either input to GND, and driving the other input (Figure 7).

Component Selection

Input Filter


An input capacitor, C_{IN}, in conjunction with the MAX9773 input impedance (R_{IN}) forms a highpass filter that removes the DC bias from an incoming signal. The AC-coupling capacitor allows the amplifier to automatically bias the signal to an optimum DC level. Assuming zero-source impedance, the -3dB point of the highpass filter is given by:

$$f_{-3dB} = \frac{1}{2\pi R_{IN} C_{IN}}$$

Choose C_{IN} so f_{-3dB} is well below the lowest frequency of interest. Use capacitors whose dielectrics have low-voltage coefficients, such as tantalum or aluminum electrolytic. Capacitors with high-voltage coefficients, such as ceramics, may result in increased distortion at low frequencies.

Other considerations when designing the input filter include the constraints of the overall system and the actual frequency band of interest. Although high-fidelity audio calls for a flat-gain response between 20Hz and 20kHz, portable voice-reproduction devices such as cellular phones and two-way radios need only concentrate on the frequency range of the spoken human voice (typically 300Hz to 3.5kHz). In addition, speakers used in portable devices typically have a poor response below 300Hz. Taking these two factors into consideration, the input filter may not need to be designed for a 20Hz to 20kHz response, saving both board space and cost due to the use of smaller capacitors.

1.8W, Filterless, Ultra-Low EMI, Stereo Class D Audio Power Amplifier



NOTE: VALUES SHOWN ARE FOR A LOWPASS CUTOFF OF 2Hz AND A BASS GAIN OF -1V/V.
FFM MODE WITH f_{OSC} = 1100kHz.

Figure 8. 2.1 Channel Application Circuit

Output Filter

The MAX9773 does not require an output filter. The device passes FCC emissions standards with 6in of unshielded speaker cables. However, output filtering can be used if a design is failing radiated emissions due to board layout or cable length, or if the circuit is near EMI-sensitive devices. Use a ferrite bead filter when radiated frequencies above 10MHz are of concern. Use an LC filter or a common-mode choke when radiated emissions below 10MHz are of concern, or when long leads (>6in) connect the amplifier to the speaker.

2.1 Channel Configuration

The typical 2.1 channel application circuit (Figure 8) shows the MAX9773 configured as a mid/high-frequency amplifier and the MAX9705 configured as a mono bass amplifier. Input capacitors (C_{IN}) set the highpass cutoff frequency according to the following equation:

$$f = \frac{1}{2\pi \times R_{IN} \times C_{IN}}$$

where R_{IN} is the typical input resistance of the MAX9773. The 10µF capacitors on the output of the MAX9773 ensure a two-pole highpass filter.

Low frequencies are summed through a two-pole lowpass filter and sent to the MAX9705 mono speaker amplifier. The passband gain of the lowpass filter is unity for in-phase stereo signals:

$$A_{VLP} = \frac{-2 \times R3}{R1}$$

where R1 = R2 and R3 = R1//R2. The cutoff frequency of the lowpass filter is set by the following equation:

$$f_{LP} = \frac{1}{2\pi} \times \sqrt{\frac{1}{C1 \times C2 \times R3 \times R4}}$$

Supply Bypassing, Layout, and Grounding

Proper layout and grounding are essential for optimum performance. Use large traces for the power-supply inputs and amplifier outputs to minimize losses due to parasitic trace resistance. Large traces also aid in moving heat away from the package. Proper grounding improves audio performance, minimizes crosstalk between channels, and prevents any switching noise from coupling into the audio signal. Connect PGND and GND together at a single point on the PC board. Route all traces that carry switching transients away from GND and the traces/components in the audio signal path.

Bypass V_{DD} with a 0.1µF capacitor to GND and PV_{DD} with a 10µF capacitor to PGND. Place the bypass capacitors as close to the MAX9773 as possible. Use large, low-resistance output traces. Current drawn from the outputs increases as load impedance decreases. High-output trace resistance decreases the power delivered to the load. Large output, supply, and GND traces allow more heat to move from the MAX9773 to the air, decreasing the thermal impedance of the circuit.


The MAX9773 thin QFN-EP package features an exposed thermal pad on its underside. This pad lowers the package's thermal impedance by providing a direct heat conduction path from the die to the PC board. Connect the exposed thermal pad to the GND plane.

UCSP Applications Information

For the latest application details on UCSP construction, dimensions, tape carrier information, printed circuit board techniques, bump-pad layout, and recommended reflow temperature profile, as well as the latest information on reliability testing results, refer to Application Note: *UCSP—A Wafer-Level Chip-Scale Package* available on Maxim's website at www.maxim-ic.com/ucsp.


1.8W, Filterless, Ultra-Low EMI, Stereo Class D Audio Power Amplifier

System Diagram




1.8W, Filterless, Ultra-Low EMI, Stereo Class D Audio Power Amplifier

Pin Configurations



TQFN



UCSP

Gain Selection

GAIN SELECTION	GAIN (dB)
GAIN1 = 0, GAIN2 = 0	26
GAIN1 = 1, GAIN2 = 0	20
GAIN1 = 0, GAIN2 = 1	15.6
GAIN1 = 1, GAIN2 = 1	12


Chip Information

PROCESS: BiCMOS

1.8W, Filterless, Ultra-Low EMI, Stereo Class D Audio Power Amplifier

Package Information

(The package drawing(s) in this data sheet may not reflect the most current specifications. For the latest package outline information, go to **www.maxim-ic.com/packages**.)



COMMON DIMENSIONS

PKG	12L 4x4			16L 4x4			20L 4x4			24L 4x4			28L 4x4		
REF.	MIN.	NOM.	MAX.	MIN.	NOM.	MAX.	MIN.	NOM.	MAX.	MIN.	NOM.	MAX.	MIN.	NOM.	MAX.
A	0.70	0.75	0.80	0.70	0.75	0.80	0.70	0.75	0.80	0.70	0.75	0.80	0.70	0.75	0.80
A1	0.0	0.02	0.05	0.0	0.02	0.05	0.0	0.02	0.05	0.0	0.02	0.05	0.0	0.02	0.05
A2	0.20 REF			0.20 REF			0.20 REF			0.20 REF			0.20 REF		
b	0.25	0.30	0.35	0.25	0.30	0.35	0.20	0.25	0.30	0.18	0.23	0.30	0.15	0.20	0.25
D	3.90	4.00	4.10	3.90	4.00	4.10	3.90	4.00	4.10	3.90	4.00	4.10	3.90	4.00	4.10
E	3.90	4.00	4.10	3.90	4.00	4.10	3.90	4.00	4.10	3.90	4.00	4.10	3.90	4.00	4.10
e	0.80 BSC.			0.65 BSC.			0.50 BSC.			0.50 BSC.			0.40 BSC.		
k	0.25	-	-	0.25	-	-	0.25	-	-	0.25	-	-	0.25	-	-
L	0.45	0.55	0.65	0.45	0.55	0.65	0.45	0.55	0.65	0.30	0.40	0.50	0.30	0.40	0.50
N	12			16			20			24			28		
ND	3			4			5			6			7		
NE	3			4			5			6			7		
JEDEC VAR.	WGGB			WGGC			WGGD-1			WGGD-2			WGGE		

EXPOSED PAD VARIATIONS

PKG. CODES	D2			E2			DOWN BONDS ALLOWED
	MIN.	NOM.	MAX.	MIN.	NOM.	MAX.	
T1244-3	1.95	2.10	2.25	1.95	2.10	2.25	YES
T1244-4	1.95	2.10	2.25	1.95	2.10	2.25	NO
T1644-3	1.95	2.10	2.25	1.95	2.10	2.25	YES
T1644-4	1.95	2.10	2.25	1.95	2.10	2.25	NO
T2044-2	1.95	2.10	2.25	1.95	2.10	2.25	YES
T2044-3	1.95	2.10	2.25	1.95	2.10	2.25	NO
T2444-2	1.95	2.10	2.25	1.95	2.10	2.25	YES
T2444-3	2.45	2.60	2.63	2.45	2.60	2.63	YES
T2444-4	2.45	2.60	2.63	2.45	2.60	2.63	NO
T2844-1	2.50	2.60	2.70	2.50	2.60	2.70	NO

NOTES:

1. DIMENSIONING & TOLERANCING CONFORM TO ASME Y14.5M-1994.
2. ALL DIMENSIONS ARE IN MILLIMETERS. ANGLES ARE IN DEGREES.
3. N IS THE TOTAL NUMBER OF TERMINALS.
4. THE TERMINAL #1 IDENTIFIER AND TERMINAL NUMBERING CONVENTION SHALL CONFORM TO JESD 95-1 SPP-012. DETAILS OF TERMINAL #1 IDENTIFIER ARE OPTIONAL, BUT MUST BE LOCATED WITHIN THE ZONE INDICATED. THE TERMINAL #1 IDENTIFIER MAY BE EITHER A MOLD OR MARKED FEATURE.
5. DIMENSION b APPLIES TO METALLIZED TERMINAL AND IS MEASURED BETWEEN 0.25 mm AND 0.30 mm FROM TERMINAL TIP.
6. ND AND NE REFER TO THE NUMBER OF TERMINALS ON EACH D AND E SIDE RESPECTIVELY.
7. DEPOPULATION IS POSSIBLE IN A SYMMETRICAL FASHION.
8. COPLANARITY APPLIES TO THE EXPOSED HEAT SINK SLUG AS WELL AS THE TERMINALS.
9. DRAWING CONFORMS TO JEDEC MO220, EXCEPT FOR T2444-3, T2444-4 AND T2844-1.
10. MARKING IS FOR PACKAGE ORIENTATION REFERENCE ONLY.
11. COPLANARITY SHALL NOT EXCEED 0.08mm
12. WARPAGE SHALL NOT EXCEEND 0.10mm
13. LEAD CENTERLINES TO BE AT TRUE POSITION AS DEFINED BY BASIC DIMENSION "e", ±0.05.
14. NUMBER OF LEADS SHOWN ARE FOR REFERENCE ONLY

-DRAWING NOT TO SCALE-


DALLAS SEMICONDUCTOR MAXIM
TITLE PACKAGE OUTLINE, 12, 16, 20, 24, 28L THIN QFN, 4x4x0.8mm
APPROVAL
DOCUMENT CONTROL NO. 21-0139
REV. E
2/2

MAX9773 Package Code: T2444-4

Package Information (continued)

(The package drawing(s) in this data sheet may not reflect the most current specifications. For the latest package outline information, go to **www.maxim-ic.com/packages**.)

5x4 UCSP.EPS




TOP VIEW


COMMON DIMENSIONS	
A	0.62±0.05–0.08
A1	0.29±0.02
A2	0.33 REF.
b	ø0.35±0.03
D1	1.50 BASIC
E1	2.00 BASIC
e	0.50 BASIC
SD	0.25 BASIC
SE	0.00 BASIC

PKG. CODE	VARIABLE DIMENSIONS		DEPOPULATED SOLDER BALLS
	D	E	
B20-1	2.03±0.08	2.54±0.08	NONE
B20-2	2.03±0.08	2.54±0.08	B2, B3, B4
B20-4	2.03±0.08	2.54±0.08	B2, B3, B4, C2, C4
B20-5	2.03±0.08	2.54±0.08	B2, B3, B4, C2, C3, C4
B20-6	2.16±0.08	2.54±0.08	B2, B3, B4

NOTES:
1. ALL DIMENSIONS ARE IN MILLIMETERS.
2. PRODUCT MARKING: NUMBER OF CHARACTERS AND LINES VARY PER PRODUCT.



BOTTOM VIEW



SIDE VIEW

DALLAS SEMICONDUCTOR MAXIM
PROPRIETARY INFORMATION

TITLE: PACKAGE OUTLINE, 5x4 UCSP

APPROVAL	DOCUMENT CONTROL NO.	REV.	
	21-0095	I	1/1

MAX9773 Package Code: B20-1

Maxim cannot assume responsibility for use of any circuitry other than circuitry entirely embodied in a Maxim product. No circuit patent licenses are implied. Maxim reserves the right to change the circuitry and specifications without notice at any time.

© 2006 Maxim Integrated Products Printed USA MAXIM is a registered trademark of Maxim Integrated Products, Inc.