



MCP1603

Tiny Reference Design

Note the following details of the code protection feature on Microchip devices:

- Microchip products meet the specification contained in their particular Microchip Data Sheet.
- Microchip believes that its family of products is one of the most secure families of its kind on the market today, when used in the intended manner and under normal conditions.
- There are dishonest and possibly illegal methods used to breach the code protection feature. All of these methods, to our knowledge, require using the Microchip products in a manner outside the operating specifications contained in Microchip's Data Sheets. Most likely, the person doing so is engaged in theft of intellectual property.
- Microchip is willing to work with the customer who is concerned about the integrity of their code.
- Neither Microchip nor any other semiconductor manufacturer can guarantee the security of their code. Code protection does not mean that we are guaranteeing the product as "unbreakable."

Code protection is constantly evolving. We at Microchip are committed to continuously improving the code protection features of our products. Attempts to break Microchip's code protection feature may be a violation of the Digital Millennium Copyright Act. If such acts allow unauthorized access to your software or other copyrighted work, you may have a right to sue for relief under that Act.

Information contained in this publication regarding device applications and the like is provided only for your convenience and may be superseded by updates. It is your responsibility to ensure that your application meets with your specifications. MICROCHIP MAKES NO REPRESENTATIONS OR WARRANTIES OF ANY KIND WHETHER EXPRESS OR IMPLIED, WRITTEN OR ORAL, STATUTORY OR OTHERWISE, RELATED TO THE INFORMATION, INCLUDING BUT NOT LIMITED TO ITS CONDITION, QUALITY, PERFORMANCE, MERCHANTABILITY OR FITNESS FOR PURPOSE. Microchip disclaims all liability arising from this information and its use. Use of Microchip devices in life support and/or safety applications is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless Microchip from any and all damages, claims, suits, or expenses resulting from such use. No licenses are conveyed, implicitly or otherwise, under any Microchip intellectual property rights.

Trademarks

The Microchip name and logo, the Microchip logo, Accuron, dsPIC, KEELOQ, KEELOQ logo, MPLAB, PIC, PICmicro, PICSTART, rfPIC, SmartShunt and UNI/O are registered trademarks of Microchip Technology Incorporated in the U.S.A. and other countries.

FilterLab, Linear Active Thermistor, MXDEV, MXLAB, SEEVAL, SmartSensor and The Embedded Control Solutions Company are registered trademarks of Microchip Technology Incorporated in the U.S.A.

Analog-for-the-Digital Age, Application Maestro, CodeGuard, dsPICDEM, dsPICDEM.net, dsPICworks, dsSPEAK, ECAN, ECONOMONITOR, FanSense, In-Circuit Serial Programming, ICSP, ICEPIC, Mindi, MiWi, MPASM, MPLAB Certified logo, MPLIB, MPLINK, mTouch, PICkit, PICDEM, PICDEM.net, PICTail, PIC³² logo, PowerCal, PowerInfo, PowerMate, PowerTool, REAL ICE, rfLAB, Select Mode, Total Endurance, WiperLock and ZENA are trademarks of Microchip Technology Incorporated in the U.S.A. and other countries.

SQTP is a service mark of Microchip Technology Incorporated in the U.S.A.

All other trademarks mentioned herein are property of their respective companies.

© 2008, Microchip Technology Incorporated, Printed in the U.S.A., All Rights Reserved.

 Printed on recycled paper.

QUALITY MANAGEMENT SYSTEM
CERTIFIED BY DNV
== ISO/TS 16949:2002 ==

Microchip received ISO/TS-16949:2002 certification for its worldwide headquarters, design and wafer fabrication facilities in Chandler and Tempe, Arizona; Gresham, Oregon and design centers in California and India. The Company's quality system processes and procedures are for its PIC® MCUs and dsPIC® DSCs, KEELOQ® code hopping devices, Serial EEPROMs, microperipherals, nonvolatile memory and analog products. In addition, Microchip's quality system for the design and manufacture of development systems is ISO 9001:2000 certified.

Table of Contents

Preface	1
Chapter 1. Product Overview	
1.1 Introduction	5
1.2 What is the MCP1603 Tiny Reference Design Board?	6
1.3 What the MCP1603 Tiny Reference Design Board Kit Includes?	6
Chapter 2. Installation and Operation	
2.1 Introduction	7
2.2 Features	7
2.3 Getting Started	7
2.3.1 Power Input and Output Connection	7
Appendix A. Schematics and Layouts	
A.1 Introduction and Highlights	9
A.2 Board - Schematic	10
A.3 Board - Top Pads and Silk-Screen	11
A.4 Board - Top Pads and Trace	11
A.5 Board - Bottom Trace	11
Appendix B. Bill of Materials (BOM)	
Worldwide Sales and Service	14

Preface

NOTICE TO CUSTOMERS

All documentation becomes dated, and this manual is no exception. Microchip tools and documentation are constantly evolving to meet customer needs, so some actual dialogs and/or tool descriptions may differ from those in this document. Please refer to our web site (www.microchip.com) to obtain the latest documentation available.

Documents are identified with a “DS” number. This number is located on the bottom of each page, in front of the page number. The numbering convention for the DS number is “DSXXXXA”, where “XXXX” is the document number and “A” is the revision level of the document.

For the most up-to-date information on development tools, see the MPLAB® IDE on-line help. Select the Help menu, and then Topics to open a list of available on-line help files.

INTRODUCTION

This chapter contains general information that will be useful to know before using the MCP1603 Tiny Reference Design. Items discussed in this chapter include:

- Document Layout
- Conventions Used in this Guide
- Recommended Reading
- The Microchip Web Site
- Customer Support
- Document Revision History

DOCUMENT LAYOUT

This document describes how to use the MCP1603 Tiny Reference Design as a development tool to emulate and debug firmware on a target board. The manual layout is as follows:

- **Chapter 1. “Product Overview”** – Important information about the MCP1603 Tiny Reference Design
- **Chapter 2. “Installation and Operation”** – Includes instructions on how to get started with this reference design board and a description of the reference design board operation.
- **Appendix A. “Schematics and Layouts”** – Shows the schematic and layout diagrams for the MCP1603 Tiny Reference Design.
- **Appendix B. “Bill of Materials (BOM)”** - Lists the parts used to build the MCP1603 Tiny Reference Design.

MCP1603 Tiny Reference Design

CONVENTIONS USED IN THIS GUIDE

This manual uses the following documentation conventions:

DOCUMENTATION CONVENTIONS

Description	Represents	Examples
Arial font:		
Italic characters	Referenced books	<i>MPLAB[®] IDE User's Guide</i>
	Emphasized text	...is the <i>only</i> compiler...
Initial caps	A window	the Output window
	A dialog	the Settings dialog
	A menu selection	select Enable Programmer
Quotes	A field name in a window or dialog	"Save project before build"
Underlined, italic text with right angle bracket	A menu path	<u><i>File>Save</i></u>
Bold characters	A dialog button	Click OK
	A tab	Click the Power tab
N'Rnnnn	A number in verilog format, where N is the total number of digits, R is the radix and n is a digit.	4'b0010, 2'hF1
Text in angle brackets < >	A key on the keyboard	Press <Enter>, <F1>
Courier New font:		
Plain Courier New	Sample source code	#define START
	Filenames	autoexec.bat
	File paths	c:\mcc18\h
	Keywords	_asm, _endasm, static
	Command-line options	-Opa+, -Opa-
	Bit values	0, 1
	Constants	0xFF, 'A'
Italic Courier New	A variable argument	<i>file.o</i> , where <i>file</i> can be any valid filename
Square brackets []	Optional arguments	mcc18 [options] <i>file</i> [options]
Curly brackets and pipe character: { }	Choice of mutually exclusive arguments; an OR selection	errorlevel {0 1}
Ellipses...	Replaces repeated text	var_name [, var_name...]
	Represents code supplied by user	void main (void) { ... }

RECOMMENDED READING

This user's guide describes how to use MCP1603 Tiny Reference Design. Other useful documents are listed below. The following Microchip document is available and recommended as supplemental reference resources:

- **MCP1603 Data Sheet, "2.0 MHz, 500 mA Synchronous Buck Regulator", DS22042**
- **AN793 - "Power Management in Portable Applications: Understanding the Buck Switchmode Power Converter", DS00793**
- **MCP1603 Buck Converter Evaluation Board User's Guide, DS51652**

THE MICROCHIP WEB SITE

Microchip provides online support via our web site at www.microchip.com. This web site is used as a means to make files and information easily available to customers. Accessible by using your favorite Internet browser, the web site contains the following information:

- **Product Support** – Data sheets and errata, application notes and sample programs, design resources, user's guides and hardware support documents, latest software releases and archived software
- **General Technical Support** – Frequently Asked Questions (FAQs), technical support requests, online discussion groups, Microchip consultant program member listing
- **Business of Microchip** – Product selector and ordering guides, latest Microchip press releases, listing of seminars and events, listings of Microchip sales offices, distributors and factory representatives

CUSTOMER SUPPORT

Users of Microchip products can receive assistance through several channels:

- Distributor or Representative
- Local Sales Office
- Field Application Engineer (FAE)
- Technical Support

Customers should contact their distributor, representative or field application engineer (FAE) for support. Local sales offices are also available to help customers. A listing of sales offices and locations is included in the back of this document.

Technical support is available through the web site at: <http://support.microchip.com>

DOCUMENT REVISION HISTORY

Revision A (October 2008)

- Initial Release of this Document.

MCP1603 Tiny Reference Design

NOTES:

Chapter 1. Product Overview

1.1 INTRODUCTION

Step-down converter choices include a variety of linear and switching regulators. The MCP1603 500 mA synchronous buck regulator provides a low profile, cost effective, and efficient solution for devices like cellular telephones, USB-powered devices and hand held instruments. The device provides a solution with minimal board space because of the high-frequency operation, which reduces the size requirements of the external inductor and capacitor and the 1 mm maximum height TSOT package. The MCP1603 switches at a fixed frequency of 2.0 MHz when operating at a heavy load. This provides a low-noise, small size solution. When operating at light loads, the MCP1603 automatically changes operation to a pulse frequency modulation (PFM) mode to minimize quiescent current drawn from the input source. No intervention is necessary for smooth transition from one mode to another.

This chapter covers the following topics:

- What is the MCP1603 Tiny Reference Design?
- What the MCP1603 Tiny Reference Design Kit includes?




FIGURE 1-1: MCP1603 Tiny Reference Design Block Diagram.

MCP1603 Tiny Reference Design

1.2 WHAT IS THE MCP1603 TINY REFERENCE DESIGN BOARD?

The MCP1603 Tiny Reference Design demonstrates the use of Microchip's MCP1603 device in a step-down application. The evaluation board is a fully functional platform to evaluate the MCP1603 buck regulator over the input voltage, output voltage and current range of the device. The evaluation board is designed to show off one of the main advantages of MCP1603 - its small size.

Test points are provided to allow easy connection of the input voltage source and the output load.




FIGURE 1-2: MCP1603 Tiny Reference Design Board Size.

1.3 WHAT THE MCP1603 TINY REFERENCE DESIGN BOARD KIT INCLUDES?

This MCP1603 Tiny Reference Design kit includes:

- Three separate MCP1603 Tiny Reference Design boards with the following output voltage options:
 - Fixed 3.3V using the MCP1603T-330I/OS
 - Fixed 1.8V using the MCP1603T-180I/OS
 - Fixed 1.2V using the MCP1603T-120I/OS
- Analog and Interface Products Demonstration Boards CD-ROM
 - MCP1603 Tiny Reference Design (DS51750)

Chapter 2. Installation and Operation

2.1 INTRODUCTION

The MCP1603 Tiny Reference Design is designed to demonstrate Microchip's MCP1603 in a fixed output voltage configuration. The board is designed to demonstrate how to generate both positive and negative rails using the MCP1603. The MCP1603 is a 500 mA synchronous buck regulator that features both Pulse Frequency Modulation (PFM) and Pulse Width Modulation (PWM). The PFM mode is used at light loads to improve system efficiency while the 2.0 MHz PWM mode is entered at heavy loads. The transition between PFM and PWM modes automatically occurs without any external intervention. The MCP1603 is available in both adjustable parts that require an external divider to set the output voltage and fixed output voltage parts. The high switching speed and TSOT package (1 mm maximum height) make the MCP1603 ideal for space constrained applications that require an efficient stepped down voltage.

2.2 FEATURES

The MCP1603 Tiny Reference Design has the following features:

- Ultra compact size and low profile 500 mA converter design
- Wide Input voltage range from 2.7V to 5.5V
- Fixed output voltages: 3.3V, 1.2V, 1.8V as well as -1.2V and -1.8V (from 3.3V supply)
- Test points for connecting input voltage source and external load

2.3 GETTING STARTED

The MCP1603 Tiny Reference Design is fully assembled and tested for evaluating the MCP1603 device. The board requires the use of an external input voltage source of 2.7V to 5.5V and an external load capable of 500 mA.

2.3.1 Power Input and Output Connection

Powering the MCP1603 Tiny Reference Design (Positive Output Voltage Configuration)

1. Connect the positive side of the input source (+) to V_{IN} .
2. Connect the negative or return side (-) of input source to GND. Refer to Figure 2-1. The input voltage must be within the range of 2.7V to 5.5V.

MCP1603 Tiny Reference Design




FIGURE 2-1: Positive Output Voltage Setup Configuration Diagram.

Powering the MCP1603 Tiny Reference Design (Negative Output Configuration)

1. Connect the positive side of the input source (+) to V_{IN} .
2. Connect the negative or return side (-) of input source to V_{OUT} . Refer to Figure 2-2. In this configuration the output voltage will appear between the V_{OUT} terminal and GND terminal of the board.

Note: For negative voltage generation the following condition must be met:
 $V_{IN} - V_{OUT} < 5.5V$. For example, if generating -1.2V output,
 $V_{IN} - (-1.2V) < 5.5V$, therefore, $V_{IN} < 4.3V$.

The MCP1603 device will be able to provide full load current in this configuration.




FIGURE 2-2: Negative Output Voltage Setup Configuration Diagram.

Applying Load to MCP1603 Tiny Reference Design Board (Positive Output Configuration)

1. Connect the positive side of the load (+) to V_{OUT} .
2. Connect the negative side of the load (-) to GND. Refer to Figure 2-1 and Figure 2-2. The maximum load current should not exceed 500 mA.

As an alternative, a resistor can be connected between GND and V_{OUT} . The value of this resistor must be sized such that the maximum load current does not exceed 500 mA for the selected output voltage.

Appendix A. Schematics and Layouts


A.1 INTRODUCTION AND HIGHLIGHTS

This appendix contains the following schematics and layouts for the MCP1603 Tiny Reference Design:


- Board - Schematic
- Board - Top Silk Layer
- Board - Top Metal Layer
- Board - Bottom Metal Layer

MCP1603 Tiny Reference Design


A.2 BOARD - SCHEMATIC




A.3 BOARD - TOP PADS AND SILK-SCREEN



A.4 BOARD - TOP PADS AND TRACE



A.5 BOARD - BOTTOM TRACE



MCP1603 Tiny Reference Design

NOTES:

Appendix B. Bill of Materials (BOM)

TABLE B-1: BILL OF MATERIALS (BOM)

Qty	Designator	Description	Manufacturer	Part Number
2	C1, C2	10uF, 6.3V, 0603 Ceramic Capacitor	Panasonic® - ECG	ECJ-1VB0J106M
1	L1	4.7uH, 740mA Inductor	TDK Corporation	VLF3012AT-4R7MR74
1	PCB	RoHS Compliant Bare PCB, MCP1603 Tiny Reference Design Board	Microchip Technology Inc.	104-00220
4	TP1, TP2, TP3, TP4	PC Test Point Compact SMT	Keystone Electronics®	5016
1	U1	500 mA Synchronous Buck Regulator in SOT23-5 Package	Microchip Technology Inc.	MCP1603T-120I/OS
1	U1	500 mA Synchronous Buck Regulator in SOT23-5 Package	Microchip Technology Inc.	MCP1603T-180I/OS
1	U1	500 mA Synchronous Buck Regulator in SOT23-5 Package	Microchip Technology Inc.	MCP1603T-330I/OS

Note 1: The components listed in this Bill of Materials are representative of the PCB assembly. The released BOM used in manufacturing uses all RoHS-compliant components.



WORLDWIDE SALES AND SERVICE

AMERICAS

Corporate Office

2355 West Chandler Blvd.
Chandler, AZ 85224-6199
Tel: 480-792-7200
Fax: 480-792-7277
Technical Support:
<http://support.microchip.com>
Web Address:
www.microchip.com

Atlanta

Duluth, GA
Tel: 678-957-9614
Fax: 678-957-1455

Boston

Westborough, MA
Tel: 774-760-0087
Fax: 774-760-0088

Chicago

Itasca, IL
Tel: 630-285-0071
Fax: 630-285-0075

Dallas

Addison, TX
Tel: 972-818-7423
Fax: 972-818-2924

Detroit

Farmington Hills, MI
Tel: 248-538-2250
Fax: 248-538-2260

Kokomo

Kokomo, IN
Tel: 765-864-8360
Fax: 765-864-8387

Los Angeles

Mission Viejo, CA
Tel: 949-462-9523
Fax: 949-462-9608

Santa Clara

Santa Clara, CA
Tel: 408-961-6444
Fax: 408-961-6445

Toronto

Mississauga, Ontario,
Canada
Tel: 905-673-0699
Fax: 905-673-6509

ASIA/PACIFIC

Asia Pacific Office

Suites 3707-14, 37th Floor
Tower 6, The Gateway
Harbour City, Kowloon
Hong Kong
Tel: 852-2401-1200
Fax: 852-2401-3431

Australia - Sydney

Tel: 61-2-9868-6733
Fax: 61-2-9868-6755

China - Beijing

Tel: 86-10-8528-2100
Fax: 86-10-8528-2104

China - Chengdu

Tel: 86-28-8665-5511
Fax: 86-28-8665-7889

China - Hong Kong SAR

Tel: 852-2401-1200
Fax: 852-2401-3431

China - Nanjing

Tel: 86-25-8473-2460
Fax: 86-25-8473-2470

China - Qingdao

Tel: 86-532-8502-7355
Fax: 86-532-8502-7205

China - Shanghai

Tel: 86-21-5407-5533
Fax: 86-21-5407-5066

China - Shenyang

Tel: 86-24-2334-2829
Fax: 86-24-2334-2393

China - Shenzhen

Tel: 86-755-8203-2660
Fax: 86-755-8203-1760

China - Wuhan

Tel: 86-27-5980-5300
Fax: 86-27-5980-5118

China - Xiamen

Tel: 86-592-2388138
Fax: 86-592-2388130

China - Xian

Tel: 86-29-8833-7252
Fax: 86-29-8833-7256

China - Zhuhai

Tel: 86-756-3210040
Fax: 86-756-3210049

ASIA/PACIFIC

India - Bangalore

Tel: 91-80-4182-8400
Fax: 91-80-4182-8422

India - New Delhi

Tel: 91-11-4160-8631
Fax: 91-11-4160-8632

India - Pune

Tel: 91-20-2566-1512
Fax: 91-20-2566-1513

Japan - Yokohama

Tel: 81-45-471- 6166
Fax: 81-45-471-6122

Korea - Daegu

Tel: 82-53-744-4301
Fax: 82-53-744-4302

Korea - Seoul

Tel: 82-2-554-7200
Fax: 82-2-558-5932 or
82-2-558-5934

Malaysia - Kuala Lumpur

Tel: 60-3-6201-9857
Fax: 60-3-6201-9859

Malaysia - Penang

Tel: 60-4-227-8870
Fax: 60-4-227-4068

Philippines - Manila

Tel: 63-2-634-9065
Fax: 63-2-634-9069

Singapore

Tel: 65-6334-8870
Fax: 65-6334-8850

Taiwan - Hsin Chu

Tel: 886-3-572-9526
Fax: 886-3-572-6459

Taiwan - Kaohsiung

Tel: 886-7-536-4818
Fax: 886-7-536-4803

Taiwan - Taipei

Tel: 886-2-2500-6610
Fax: 886-2-2508-0102

Thailand - Bangkok

Tel: 66-2-694-1351
Fax: 66-2-694-1350

EUROPE

Austria - Wels

Tel: 43-7242-2244-39
Fax: 43-7242-2244-393

Denmark - Copenhagen

Tel: 45-4450-2828
Fax: 45-4485-2829

France - Paris

Tel: 33-1-69-53-63-20
Fax: 33-1-69-30-90-79

Germany - Munich

Tel: 49-89-627-144-0
Fax: 49-89-627-144-44

Italy - Milan

Tel: 39-0331-742611
Fax: 39-0331-466781

Netherlands - Drunen

Tel: 31-416-690399
Fax: 31-416-690340

Spain - Madrid

Tel: 34-91-708-08-90
Fax: 34-91-708-08-91

UK - Wokingham

Tel: 44-118-921-5869
Fax: 44-118-921-5820