SCR SERIES

Universal Lamp Alarm Relay

(SCR430T only)



Description


The SCR series is a universal lamp alarm relay designed to sense the failure of flashing or steady incandescent beacon lamps or steady side lights. The toroidal current sensor provides isolation and allows monitoring of more than one line at a time. The SCR Series energizes when one or more lamps fail. It will monitor the operation of one to four side lights and up to four beacon lamps.

Operation

When a lamp fails, the SCR Series senses a decrease in current flow. After a fixed time delay, the LED glows and the two alarm outputs energize. The outputs and the LED are reset when the failed lamps are replaced and the current returns to the nominal setting, or when the input voltage is removed. The SCR will sense an open flasher, it will not sense a continuously ON flasher (see FB Series).

Wiring Diagram


BEACON LAMP CONNECTION DIAGRAM



V = Voltage
B = Beacon Lamps
SS = Selector Switch
T = Toroid
F = Flasher
AXL = Auxiliary Load/Alarm

Relay contacts are isolated.

OBSTRUCTION LAMP CONNECTION DIAGRAM



V = Voltage
SS = Selector Switch
T = Toroid
AXL = Auxiliary Load/Alarm
OL = Obstruction Lamps

Relay contacts are isolated.

Features & Benefits

FEATURES	BENEFITS
Toroidal current sensing	Provides isolation from the lighting circuit and allows monitoring of multiple lines simultaneously
Monitors 1-4 side lights or up to 4 beacon lamps	Senses failed incandescent flashing beacon or steady obstruction lamps
Isolated, 10A, SPDT alarm output plus one 1A, solid-state line voltage alarm output	Provides alarm indication and can also be used for remote monitoring of the lighting system
Fixed trip delay (6s)	Prevents nuisance alarms
Switch selectable number, voltage, and wattage of lamps	User selectable to meet wide application needs with one relay

Ordering Information


MODEL	INPUT	LAMP TYPE
SCR430T	120VAC	Incandescent
SCR630T	230VAC	Incandescent

If you don't find the part you need, call us for a custom product 800-843-8848

© 2016 Littelfuse Protection Relays & Controls


SCR SERIES

Selection Range



a. Lamp Wattage - Select the lamp wattage of the lamps in use.
b. Lamp Voltage - Select the lamp voltage shown on the lamp (SCR430T)
c. Lamps ON - Select the number of lamps on during normal operation. Only one lamp switch at a time may be transferred to the right.

Programming Example



Example Shown: SCR430T-620 watts at 120 VAC lamps, two lamps are ON during normal operation.

STEP
1. Select lamp wattage: 116 or 620 watts
2. Select the number of lamps ON (1 thru 4) during normal operation. Only one lamp switch may be ON (RIGHT) at any time.

Specifications

Operation

Lamp Monitoring				
Capacity (in lamps)	**100W**	**116W**	**620W**	**700W**
SCR430T 120VAC Lamps	4	4	4	n/a
SCR630T 230VAC Lamps	n/a	4	n/a	4

Time Delay

Trip Delay	Factory fixed ≅ 6s

Input

Input Voltage/Tolerance	SCR430T - 120VAC ±10% SCR630T - 230VAC ±10%
AC Line Frequency	50/60Hz

Output

Line Voltage Output (Solid-state Rated)	≤ 125W @ 120VAC ≤ 250W @ 240VAC
Isolated Alarm Output (SPDT)	10A @ 240VAC or 30VDC resistive; 1/4 hp @ 125VAC; 1/2 hp @ 250VAC

Mechanical

Mounting	Two #6 (M3.5 x 0.6) screws
Dimensions	**H** 88.9 mm (3.5"); **W** 63.5 mm (2.5"); **D** 44.5 mm (1.75")
Termination	Screws with captive clamps for up to 14 AWG (2.45 mm^2) wire

Protection

Circuitry	Encapsulated

Environmental

Operating Temperature	-55° to 65°C
Weight	≅ 6.8 oz (193 g)

© 2016 Littelfuse Protection Relays & Controls