The Wideband IC Line

RF LDMOS Wideband Integrated Power Amplifier

MHVIC2114R2

2100 MHz, 27 V, 23 dBm
SINGLE W-CDMA
RF LDMOS WIDEBAND
INTEGRATED POWER AMPLIFIER


The MHVIC2114R2 wideband integrated circuit is designed for base station applications. It uses Motorola's newest High Voltage (26 to 28 Volts) LDMOS IC technology and integrates a multi-stage structure. Its wideband On-Chip matching design makes it usable from 1600 to 2600 MHz. The linearity performances cover all modulation formats for cellular applications: CDMA and W-CDMA. The device is in a PFP-16 flat pack package that provides excellent thermal performance through a solderable backside contact.

Final Application


- Typical Two-Tone Performance: V_{DD} = 27 Volts, I_{DQ1} = 95 mA, I_{DQ2} = 204 mA, I_{DQ3} = 111 mA, P_{out} = 15 Watts PEP, Full Frequency Band
  Power Gain — 32 dB
  IMD — -30 dBc

Driver Application


- Typical Single-Channel W-CDMA Performance: V_{DD} = 27 Volts, I_{DQ1} = 96 mA, I_{DQ2} = 204 mA, I_{DQ3} = 111 mA, P_{out} = 23 dBm, 2110-2170 MHz, 3GPP Test Model 1, Measured in a 3.84 MHz BW @ 5 MHz Offset, 64 DTCH, Peak/Avg. = 8.5 dB @ 0.01% Probability on CCDF.
  Power Gain — 32 dB
  ACPR — -58 dBc
- P1dB = 14 Watts, Gain Flatness = 0.2 dB from 2110 to 2170 MHz
- Capable of Handling 3:1 VSWR, @ 27 Vdc, 2140 MHz, 15 Watts CW Output Power
- Characterized with Series Equivalent Large-Signal Impedance Parameters and Common Source Scattering Parameters
- On-Chip Matching (50 Ohm Input, DC Blocked, >5 Ohm Output)
- Integrated Temperature Compensation with Enable/Disable Function
- Integrated ESD Protection
- In Tape and Reel. R2 Suffix = 1,500 Units per 16 mm, 13 inch Reel.



CASE 978-03
PFP-16



PIN CONNECTIONS



(Top View)

NOTE: Exposed backside flag is source terminal for transistors.

Freescale Semiconductor, Inc.

© Motorola, Inc. 2004

MOTOROLA intelligence everywhere™ digital dna™

For More Information On This Product,
Go to: www.freescale.com

MAXIMUM RATINGS

Rating	Symbol	Value	Unit
Drain-Source Voltage	V_{DSS}	65	Vdc
Gate-Source Voltage	V_{GS}	-0.5, +15	Vdc
Storage Temperature Range	T_{stg}	- 65 to +150	°C
Operating Junction Temperature	T_J	150	°C
Input Power	P_{in}	5	dBm

THERMAL CHARACTERISTICS

Characteristic		Symbol	Value (1)	Unit
Thermal Resistance, Junction to Case		$R_{\theta JC}$		°C/W
Driver Application (P_{out} = +0.2 W CW)	Stage 1, 27 Vdc, I_{DQ1} = 96 mA		11.5	
	Stage 2, 27 Vdc, I_{DQ2} = 204 mA		7.52	
	Stage 3, 27 Vdc, I_{DQ3} = 111 mA		5.52	

ESD PROTECTION CHARACTERISTICS

Test Conditions	Class
Human Body Model	1 (Minimum)
Machine Model	M1 (Minimum)
Charge Device Model	C2 (Minimum)

MOISTURE SENSITIVITY LEVEL

Test Methodology	Rating
Per JESD 22-A113	3


ELECTRICAL CHARACTERISTICS (T_C = 25°C unless otherwise noted)

Characteristic	Symbol	Min	Typ	Max	Unit
W-CDMA CHARACTERISTICS (In Motorola Test Fixture, 50 ohm system) V_{DD} = 27 Vdc, I_{DQ1} = 96 mA, I_{DQ2} = 204 mA, I_{DQ3} = 111 mA, P_{out} = 23 dBm, 2110-2170 MHz, Single-Carrier W-CDMA, 3.84 MHz Channel Bandwidth Carrier. ACPR measured in 3.84 MHz Channel Bandwidth @ ±5 MHz Offset. Peak/Avg. = 8.5 dB @ 0.01% Probability on CCDF.					
Power Gain	G_{ps}	29	32	36	dB
Gain Flatness	G_F	—	0.3	0.5	dB
Input Return Loss	IRL	—	-13	-10	dB
Adjacent Channel Power Ratio	ACPR	—	-60	-57	dBc
Group Delay	Delay	—	1.7	—	ns
Phase Linearity	—	—	0.2	—	°

(1) Refer to AN1955/D, *Thermal Measurement Methodology of RF Power Amplifiers.* Go to http://www.motorola.com/semiconductors/rf. Select Documentation/Application Notes - AN1955.

Freescale Semiconductor, Inc.

For More Information On This Product,
Go to: www.freescale.com



Z1	0.323″ x .055″ 50 Ω Microstrip
Z2	0.196″ x .176″ Microstrip
Z3	0.286″ x .055″ Microstrip
Z4	0.150″ x .018″ Microstrip
Z5	0.363″ x .055″ Microstrip
PCB	Arlon, 0.021″, ε_r = 2.55

Figure 1. MHVIC2114R2 Test Circuit Schematic

Table 1. MHVIC2114R2 Test Circuit Component Designations and Values

Part	Description	Part Number	Manufacturer
C1, C5, C8, C12, C14, C19	1 μF Tantalum Chip Capacitors	TAJA105K035R	Kemet
C2, C3, C4, C7, C11, C18	0.01 μF Chip Capacitors	0805C103K5RACTR	Vishay
C6, C10, C17	6.8 pF Chip Capacitors (ACCU-P)	AVX08051J6R8BBT	AVX
C9	1.5 pF Chip Capacitor (ACCU-P)	AVX08051J1R5BBT	AVX
C15, C16	2.2 pF Chip Capacitors (ACCU-P)	AVX08051J2R2BBT	AVX
C22	1.0 pF Chip Capacitor (ACCU-P)	AVX08051J1R0BBT	AVX
C13, C20, C21	330 μF Electrolytic Capacitors	MCR35V337M10X16	Multicomp
R1, R2, R3	1 kΩ Chip Resistors (0805)	P1.00KCCT-ND	Panasonic

Freescale Semiconductor, Inc.

For More Information On This Product,
Go to: www.freescale.com




Figure 2. MHVIC2114R2 Test Circuit Component Layout

Freescale Semiconductor, Inc.

For More Information On This Product,
Go to: www.freescale.com

TYPICAL CHARACTERISTICS




Figure 3. Broadband Frequency Response




Figure 4. Delay versus Frequency




Figure 5. Power Gain versus Frequency




Figure 6. Input Return Loss versus Frequency




Figure 7. Power Gain versus Output Power




Figure 8. S21 Phase versus Output Power

Freescale Semiconductor, Inc.

TYPICAL CHARACTERISTICS




Figure 9. W-CDMA ACPR versus Output Power




Figure 10. Two-Tone Intermodulation Distortion Products versus Frequency




Figure 11. Two-Tone Intermodulation Distortion Products versus Tone Spacing




Figure 12. Fixture Bias versus Temperature





Figure 13. Gate Bias versus Temperature

Freescale Semiconductor, Inc.

For More Information On This Product,
Go to: www.freescale.com



V_{DD} = 27 Vdc, I_{DQ1} = 96 mA, I_{DQ2} = 204 mA, I_{DQ3} = 111 mA, P_{out} = 23 dBm

f MHz	Z_{in} Ω	Z_{load} Ω
2110	57.9 - j12.1	1.1 + j2.7
2140	50.6 - j18.9	1.1 + j3.4
2170	42.3 - j21.1	1.2 + j3.7

Z_{in} = Device input impedance as measured from gate to ground.

Z_{load} = Test circuit impedance as measured from drain to ground.






Figure 14. Series Equivalent Source and Load Impedance

Freescale Semiconductor, Inc.


PACKAGE DIMENSIONS







BOTTOM VIEW

NOTES:
1. CONTROLLING DIMENSION: MILLIMETER.
2. DIMENSIONS AND TOLERANCES PER ASME Y14.5M, 1994.
3. DATUM PLANE -H- IS LOCATED AT BOTTOM OF LEAD AND IS COINCIDENT WITH THE LEAD WHERE THE LEAD EXITS THE PLASTIC BODY AT THE BOTTOM OF THE PARTING LINE.
4. DIMENSIONS D AND E1 DO NOT INCLUDE MOLD PROTRUSION. ALLOWABLE PROTRUSION IS 0.250 PER SIDE. DIMENSIONS D AND E1 DO INCLUDE MOLD MISMATCH AND ARE DETERMINED AT DATUM PLANE -H-.
5. DIMENSION b DOES NOT INCLUDE DAMBAR PROTRUSION. ALLOWABLE DAMBAR PROTRUSION IS 0.127 TOTAL IN EXCESS OF THE b DIMENSION AT MAXIMUM MATERIAL CONDITION.
6. DATUMS -A- AND -B- TO BE DETERMINED AT DATUM PLANE -H-.





SECT W-W



DETAIL Y

	MILLIMETERS	
DIM	MIN	MAX
A	2.000	2.300
A1	0.025	0.100
A2	1.950	2.100
D	6.950	7.100
D1	4.372	5.180
E	8.850	9.150
E1	6.950	7.100
E2	4.372	5.180
L	0.466	0.720
L1	0.250 BSC	
b	0.300	0.432
b1	0.300	0.375
c	0.180	0.279
c1	0.180	0.230
e	0.800 BSC	
h	---	0.600
θ	0°	7°
aaa	0.200	
bbb	0.200	
ccc	0.100	

CASE 978-03
ISSUE B
PFP-16

Information in this document is provided solely to enable system and software implementers to use Motorola products. There are no express or implied copyright licenses granted hereunder to design or fabricate any integrated circuits or integrated circuits based on the information in this document.

Motorola reserves the right to make changes without further notice to any products herein. Motorola makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does Motorola assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. “Typical” parameters that may be provided in Motorola data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including “Typicals”, must be validated for each customer application by customer’s technical experts. Motorola does not convey any license under its patent rights nor the rights of others. Motorola products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the Motorola product could create a situation where personal injury or death may occur. Should Buyer purchase or use Motorola products for any such unintended or unauthorized application, Buyer shall indemnify and hold Motorola and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that Motorola was negligent regarding the design or manufacture of the part.

MOTOROLA and the Stylized M Logo are registered in the US Patent and Trademark Office. All other product or service names are the property of their respective owners. Motorola, Inc. is an Equal Opportunity/Affirmative Action Employer.

© Motorola Inc. 2004

HOW TO REACH US:

USA/EUROPE/LOCATIONS NOT LISTED:
Motorola Literature Distribution
P.O. Box 5405, Denver, Colorado 80217
1-800-521-6274 or 480-768-2130

JAPAN: Motorola Japan Ltd.; SPS, Technical Information Center,
3-20-1, Minami-Azabu, Minato-ku, Tokyo 106-8573, Japan
81-3-3440-3569

ASIA/PACIFIC: Motorola Semiconductors H.K. Ltd.; Silicon Harbour Centre,
2 Dai King Street, Tai Po Industrial Estate, Tai Po, N.T., Hong Kong
852-26668334

HOME PAGE: http://motorola.com/semiconductors

MOTOROLA

◊For More Information On This Product,
Go to: www.freescale.com

Freescale Semiconductor, Inc.