19-4194; Rev 5; 10/08

Single/Dual/Quad, 28MHz, Low-Noise, Low-Voltage, Precision Op Amps

General Description

The MAX410/MAX412/MAX414 single/dual/quad op amps set a new standard for noise performance in high-speed, low-voltage systems. Input voltage-noise density is guaranteed to be less than 2.4nV/√Hz at 1kHz. A unique design not only combines low noise with ±5V operation, but also consumes 2.5mA supply current per amplifier. Low-voltage operation is guaranteed with an output voltage swing of 7.3VP-P into 2kΩ from ±5V supplies. The MAX410/MAX412/MAX414 also operate from supply voltages between ±2.4V and ±5V for greater supply flexibility.

Unity-gain stability, 28MHz bandwidth, and 4.5V/µs slew rate ensure low-noise performance in a wide variety of wideband and measurement applications. The MAX410/MAX412/MAX414 are available in DIP and SO packages in the industry-standard single/dual/quad op amp pin configurations. The single comes in an ultra-small TDFN package (3mm × 3mm).

Applications

Low-Noise Frequency Synthesizers


Infrared Detectors

High-Quality Audio Amplifiers

Ultra Low-Noise Instrumentation Amplifiers

Bridge Signal Conditioning

Typical Operating Circuit



LOW-NOISE INSTRUMENTATION AMPLIFIER

Features

- ♦ **Voltage Noise: 2.4nV/√Hz (max) at 1kHz**
- ♦ **2.5mA Supply Current Per Amplifier**
- ♦ **Low Supply Voltage Operation: ±2.4V to ±5V**
- ♦ **28MHz Unity-Gain Bandwidth**
- ♦ **4.5V/µs Slew Rate**
- ♦ **250µV (max) Offset Voltage (MAX410/MAX412)**
- ♦ **115dB (min) Voltage Gain**
- ♦ **Available in an Ultra-Small TDFN Package**

Ordering Information


PART	TEMP RANGE	PIN-PACKAGE
MAX410CPA	0°C to +70°C	8 Plastic DIP
MAX410BCPA	0°C to +70°C	8 Plastic DIP
MAX410CSA	0°C to +70°C	8 SO
MAX410BCSA	0°C to +70°C	8 SO
MAX410EPA	-40°C to +85°C	8 Plastic DIP
MAX410BEPA	-40°C to +85°C	8 Plastic DIP
MAX410ESA	-40°C to +85°C	8 SO
MAX410BESA	-40°C to +85°C	8 SO
MAX410ETA	-40°C to +85°C	8 TDFN-EP*
MAX410MSA/PR	-55°C to +125°C	8 SO**
MAX410MSA/PR-T	-55°C to +125°C	8 SO**

*EP—Exposed paddle. Top Mark—AGQ.

**Contact factory for availability.

Ordering Information continued at end of data sheet.

Pin Configurations



Pin Configurations continued at end of data sheet.

For pricing, delivery, and ordering information, please contact Maxim Direct at 1-888-629-4642, or visit Maxim's website at www.maxim-ic.com.

Single/Dual/Quad, 28MHz, Low-Noise, Low-Voltage, Precision Op Amps

ABSOLUTE MAXIMUM RATINGS

Supply Voltage 12V
Differential Input Current (Note 1) .....±20mA
Input Voltage Range.....V+ to V-
Common-Mode Input Voltage .....(V+ + 0.3V) to (V- - 0.3V)
Short-Circuit Current Duration.....Continuous
Continuous Power Dissipation (T_A = +70°C)
MAX410/MAX412
8-Pin Plastic DIP (derate 9.09mW/°C above +70°C) ...727mW
8-Pin SO (derate 5.88mW/°C above +70°C).....471mW
8-Pin TDFN (derate 24.4mW/°C above +70°C) 1951mW
MAX414
14-Pin Plastic DIP (derate 10.00mW/°C above +70°C)800mW
14-Pin SO (derate 8.33mW/°C above +70°C).....667mW
Operating Temperature Ranges:
MAX41_C_ _ .....0°C to +70°C
MAX41_E_ _.....-40°C to +85°C
Storage Temperature Range .....-65°C to +150°C
Lead Temperature (soldering, 10s) .....+300°C

Note 1: The amplifier inputs are connected by internal back-to-back clamp diodes. In order to minimize noise in the input stage, current-limiting resistors are not used. If differential input voltages exceeding ±1.0V are applied, limit input current to 20mA.

Stresses beyond those listed under "Absolute Maximum Ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated in the operational sections of the specifications is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

ELECTRICAL CHARACTERISTICS

(V+ = 5V, V- = -5V, **T_A = +25°C**, unless otherwise noted.)

PARAMETER	SYMBOL	CONDITIONS		MIN	TYP	MAX	UNITS
Input Offset Voltage	V_{OS}	MAX410, MAX410B, MAX412, MAX412B			±120	±250	µV
		MAX414, MAX414B			±150	±320	
Input Bias Current	I_B				±80	±150	nA
Input Offset Current	I_{OS}				±40	±80	nA
Differential Input Resistance	$R_{IN(Diff)}$				20		kΩ
Common-Mode Input Resistance	$R_{IN(CM)}$				40		MΩ
Input Capacitance	C_{IN}				4		pF
Input Noise-Voltage Density	e_n	MAX410, MAX412, MAX414	10Hz		7		nV/√Hz
			1000Hz (Note 2)		1.5	2.4	
		MAX410B, MAX412B, MAX414B	1000Hz (Note 2)		2.4	4.0	
Input Noise-Current Density	i_n	f_O = 10Hz			2.6		pA/√Hz
		f_O = 1000Hz			1.2		
Common-Mode Input Voltage	V_{CM}			±3.5	+3.7/ -3.8		V
Common-Mode Rejection Ratio	CMRR	V_{CM} = ±3.5V		115	130		dB
Power-Supply Rejection Ratio	PSRR	V_S = ±2.4V to ±5.25V		96	103		dB
Large-Signal Gain	A_{VOL}	R_L = 2kΩ, V_O = ±3.6V		115	122		dB
		R_L = 600Ω, V_O = ±3.5V		110	120		
Output Voltage Swing	V_{OUT}	R_L = 2kΩ		+3.6 -3.7	+3.7/ -3.8		V
Short-Circuit Output Current	I_{SC}				35		mA
Slew Rate	SR	10kΩ ll 20pF load			4.5		V/µs
Unity-Gain Bandwidth	GBW	10kΩ ll 20pF load			28		MHz
Settling Time	t_S	To 0.1%			1.3		µs
Channel Separation	C_S	f_O = 1kHz			135		dB

ELECTRICAL CHARACTERISTICS (continued)

(V+ = 5V, V- = -5V, **T_A = +25°C**, unless otherwise noted.)

PARAMETER	SYMBOL	CONDITIONS	MIN	TYP	MAX	UNITS
Operating Supply-Voltage Range	V_S		±2.4		±5.25	V
Supply Current	I_S	Per amplifier		2.5	2.7	mA

ELECTRICAL CHARACTERISTICS

(V+ = 5V, V- = -5V, **T_A = 0°C to +70°C**, unless otherwise noted.)

PARAMETER	SYMBOL	CONDITIONS	MIN	TYP	MAX	UNITS
Input Offset Voltage	V_{OS}			±150	±350	µV
Offset Voltage Tempco	$\Delta V_{OS}/\Delta T$	Over operating temperature range		±1		µV/°C
Input Bias Current	I_B			±100	±200	nA
Input Offset Current	I_{OS}			±80	±150	nA
Common-Mode Input Voltage	V_{CM}		±3.5	+3.7/ -3.8		V
Common-Mode Rejection Ratio	CMRR	V_{CM} = ±3.5V	105	121		dB
Power-Supply Rejection Ratio	PSRR	V_S = ±2.4V to ±5.25V	90	97		dB
Large-Signal Gain	A_{VOL}	R_L = 2kΩ, V_O = ±3.6V	110	120		dB
		R_L = 600Ω, V_O = ±3.5V	90	119		
Output Voltage Swing	V_{OUT}	R_L = 2kΩ	±3.5	+3.7/ -3.6		V
Supply Current	I_S	Per amplifier			3.3	mA

ELECTRICAL CHARACTERISTICS

(V+ = 5V, V- = -5V, **T_A = -40°C to +85°C**, unless otherwise noted.) (Note 3)

PARAMETER	SYMBOL	CONDITIONS	MIN	TYP	MAX	UNITS
Input Offset Voltage	V_{OS}	MAX410, MAX410B, MAX412, MAX412B		±200	±400	µV
		MAX414, MAX414B		±200	±450	
Offset Voltage Tempco	$\Delta V_{OS}/\Delta T$	Over operating temperature range		±1		µV/°C
Input Bias Current	I_B			±130	±350	nA
Input Offset Current	I_{OS}			±100	±200	nA
Common-Mode Input Voltage	V_{CM}		±3.5	+3.7/ -3.6		V
Common-Mode Rejection Ratio	CMRR	V_{CM} = ±3.5V	105	120		dB
Power-Supply Rejection Ratio	PSRR	V_S = ±2.4V to ±5.25V	90	94		dB
Large-Signal Gain	A_{VOL}	R_L = 2kΩ, V_O = ±3.6V	110	118		dB
		R_L = 600Ω, V_O = +3.4V to -3.5V	90	114		
Output Voltage Swing	V_{OUT}	R_L = 2kΩ	±3.5	+3.7/ -3.6		V
Supply Current	I_S	Per amplifier			3.3	mA


Note 2: Guaranteed by design.
Note 3: All TDFN devices are 100% tested at T_A = +25°C. Limits over temperature for thin TDFNs are guaranteed by design.

Single/Dual/Quad, 28MHz, Low-Noise, Low-Voltage, Precision Op Amps


Typical Operating Characteristics

(V+ = 5V, V- = -5V, T_A = +25°C, unless otherwise noted.)


VOLTAGE-NOISE DENSITY vs. FREQUENCY




CURRENT-NOISE DENSITY vs. FREQUENCY




1kHz VOLTAGE NOISE DISTRIBUTION




0.1Hz TO 10Hz VOLTAGE NOISE




WIDEBAND NOISE DC TO 20kHz




OPEN-LOOP GAIN vs. TEMPERATURE



SHORT-CIRCUIT OUTPUT CURRENT vs. TEMPERATURE




OUTPUT VOLTAGE SWING vs. TEMPERATURE




Typical Operating Characteristics (continued)

(V+ = 5V, V- = -5V, T_A = +25°C, unless otherwise noted.)


SUPPLY CURRENT vs. TEMPERATURE




SLEW RATE vs. TEMPERATURE



UNITY-GAIN BANDWIDTH vs. TEMPERATURE




LARGE-SIGNAL TRANSIENT RESPONSE




AV = +1, RF = 499Ω, RL = 2kΩ II 20pF, VS = ±5V, TA = +25°C

SMALL-SIGNAL TRANSIENT RESPONSE




AV = +1, RF = 499Ω, RL = 2kΩ II 20pF, VS = ±5V, TA = +25°C


WIDEBAND VOLTAGE NOISE (0.1Hz TO FREQUENCY INDICATED)



TOTAL NOISE DENSITY vs. MATCHED SOURCE RESISTANCE



TOTAL NOISE DENSITY vs. UNMATCHED SOURCE RESISTANCE




Single/Dual/Quad, 28MHz, Low-Noise, Low-Voltage, Precision Op Amps


Typical Operating Characteristics (continued)

(V+ = 5V, V- = -5V, T_A = +25°C, unless otherwise noted.)


TOTAL HARMONIC DISTORTION PLUS NOISE vs. FREQUENCY




PERCENTAGE OVERSHOOT vs. CAPACITIVE LOAD




MAX412/MAX414 CHANNEL SEPARATION vs. FREQUENCY



GAIN AND PHASE vs. FREQUENCY



GAIN AND PHASE vs. FREQUENCY



Applications Information

The MAX410/MAX412/MAX414 provide low voltage-noise performance. Obtaining low voltage noise from a bipolar op amp requires high collector currents in the input stage, since voltage noise is inversely proportional to the square root of the input stage collector current. However, op amp current noise is proportional to the square root of the input stage collector current, and the input bias current is proportional to the input stage collector current. Therefore, to obtain optimum low-noise performance, DC accuracy, and AC stability, minimize the value of the feedback and source resistance.

Total Noise Density vs. Source Resistance

The standard expression for the total input-referred noise of an op amp at a given frequency is:

$$e_t = \sqrt{e_n^2 + (R_p + R_n)^2\ i_n^2 + 4kT\ (R_p + R_n)}$$

where:

R_n = Inverting input effective series resistance

R_p = Noninverting input effective series resistance

e_n = Input voltage-noise density at the frequency of interest

i_n = Input current-noise density at the frequency of interest

T = Ambient temperature in Kelvin (K)

k = 1.28 x 10^{-23} J/K (Boltzman's constant)

In Figure 1, R_p = R3 and R_n = R1 ll R2. In a real application, the output resistance of the source driving the input must be included with R_p and R_n. The following example demonstrates how to calculate the total output-noise density at a frequency of 1kHz for the MAX412 circuit in Figure 1.

Gain = 1000

4kT at +25°C = 1.64 x 10^{-20}

R_p = 100Ω

R_n = 100Ω ll 100kΩ = 99.9 W

e_n = 1.5nV/√Hz at 1kHz

i_n = 1.2pA/√Hz at 1kHz

$e_t = [(1.5 \times 10^{-9})^2 + (100 + 99.9)^2\ (1.2 \times 10^{-12})^2 + (1.64 \times 10^{-20})\ (100 + 99.9)]^{1/2}$ = 2.36nV/√Hz at 1kHz

Output noise density = (100)e_t = 2.36µV/√Hz at 1kHz.

In general, the amplifier's voltage noise dominates with equivalent source resistances less than 200Ω. As the equivalent source resistance increases, resistor noise becomes the dominant term, eventually making the voltage noise contribution from the MAX410/MAX412/MAX414 negligible. As the source resistance is further increased, current noise becomes dominant. For example, when the equivalent source resistance is greater than 3kΩ at 1kHz, the current noise component is larger than the resistor noise. The graph of Total Noise Density vs. Matched Source Resistance in the *Typical Operating Characteristics* shows this phenomenon. Optimal MAX410/MAX412/MAX414 noise performance and minimal total noise achieved with an equivalent source resistance of less than 10kΩ.

Voltage Noise Testing

RMS voltage-noise density is measured with the circuit shown in Figure 2, using the Quan Tech model 5173 noise analyzer, or equivalent. The voltage-noise density at 1kHz is sample tested on production units. When measuring op-amp voltage noise, only low-value, metal film resistors are used in the test fixture.

The 0.1Hz to 10Hz peak-to-peak noise of the MAX410/MAX412/MAX414 is measured using the test




Figure 1. Total Noise vs. Source Resistance Example




Figure 2. Voltage-Noise Density Test Circuit

Single/Dual/Quad, 28MHz, Low-Noise, Low-Voltage, Precision Op Amps




Figure 3. 0.1Hz to 10Hz Voltage Noise Test Circuit




Figure 4. 0.1Hz to 10Hz Voltage Noise Test Circuit, Frequency Response

circuit shown in Figure 3. Figure 4 shows the frequency response of the circuit. The test time for the 0.1Hz to 10Hz noise measurement should be limited to 10 seconds, which has the effect of adding a second zero to the test circuit, providing increased attenuation for frequencies below 0.1Hz.

Current Noise Testing

The current-noise density can be calculated, once the value of the input-referred noise is determined, by using the standard expression given below:

$$i_n = \frac{\sqrt{e_{no}^2 - \left[(A_{VCL})^2(4kT)(R_n + R_p)\right]}}{(R_n + R_p)(A_{VCL})} \; A/\sqrt{Hz}$$

where:

R_n = Inverting input effective series resistance

R_p= Noninverting input effective series resistance

e_{no} = Output voltage-noise density at the frequency of interest ($V/\sqrt{Hz}$)

i_n = Input current-noise density at the frequency of interest ($A/\sqrt{Hz}$)

A_{VCL} = Closed-loop gain

T = Ambient temperature in Kelvin (K)

k = 1.38×10^{-23} J/K (Boltzman's constant)

R_p and R_n include the resistances of the input driving source(s), if any.

If the Quan Tech model 5173 is used, then the A_{VCL} terms in the numerator and denominator of the equation given above should be eliminated because the Quan




Figure 5. Current-Noise Test Circuit




Figure 6a. Voltage Follower Circuit with 3900pF Load




Figure 6b. Driving 3900pF Load as Shown in Figure 6a

Tech measures input-referred noise. For the circuit in Figure 5, assuming R_p is approximately equal to R_n and the measurement is taken with the Quan Tech model 5173, the equation simplifies to:

$$i_n = \frac{\sqrt{e_{no}^2 - \left[(1.64 \times 10^{-20})(20 \times 10^3)\right]}}{(20 \times 10^3)} \; A/\sqrt{Hz}$$

Input Protection

To protect amplifier inputs from excessive differential input voltages, most modern op amps contain input protection diodes and current-limiting resistors. These resistors increase the amplifier's input-referred noise. They have not been included in the MAX410/MAX412/MAX414, to optimize noise performance. The MAX410/MAX412/MAX414 do contain back-to-back input protection diodes which will protect the amplifier for differential input voltages of ±0.1V. If the amplifier must be protected from higher differential input voltages, add external current-limiting resistors in series with the op amp inputs to limit the potential input current to less than 20mA.

Capacitive-Load Driving

Driving large capacitive loads increases the likelihood of oscillation in amplifier circuits. This is especially true for circuits with high loop gains, like voltage followers. The output impedance of the amplifier and a capacitive load form an RC network that adds a pole to the loop response. If the pole frequency is low enough, as when driving a large capacitive load, the circuit phase margin is degraded.

In voltage follower circuits, the MAX410/MAX412/MAX414 remain stable while driving capacitive loads as great as 3900pF (see Figures 6a and 6b).

When driving capacitive loads greater than 3900pF, add an output isolation resistor to the voltage follower circuit, as shown in Figure 7a. This resistor isolates the load capacitance from the amplifier output and restores the phase margin. Figure 7b is a photograph of the response of a MAX410/MAX412/MAX414 driving a 0.015µF load with a 10Ω isolation resistor

The capacitive-load driving performance of the MAX410/MAX412/MAX414 is plotted for closed-loop gains of -1V/V and -10V/V in the % Overshoot vs. Capacitive Load graph in the *Typical Operating Characteristics*.

Feedback around the isolation resistor RI increases the accuracy at the capacitively loaded output (see Figure 8). The MAX410/MAX412/MAX414 are stable with a 0.01µF load for the values of R_I and C_F shown. In general, for decreased closed-loop gain, increase R_I or C_F. To drive larger capacitive loads, increase the value of C_F.

Single/Dual/Quad, 28MHz, Low-Noise, Low-Voltage, Precision Op Amps




Figure 7a. Capacitive-Load Driving Circuit




Figure 8. Capacitive-Load Driving Circuit with Loop-Enclosed Isolation Resistor




Figure 7b. Driving a 0.015µF Load with a 10Ω Isolation Resistor




Figure 9. MAX410 Offset Null Circuit

TDFN Exposed Paddle Connection

On TDFN packages, there is an exposed paddle that does not carry any current but should be connected to V- (not the GND plane) for rated power dissipation.

Total Supply Voltage Considerations

Although the MAX410/MAX412/MAX414 are specified with ±5V power supplies, they are also capable of single-supply operation with voltages as low as 4.8V. The minimum input voltage range for normal amplifier operation is between V- + 1.5V and V+ - 1.5V. The minimum room-temperature output voltage range (with 2kΩ load) is between V+ - 1.4V and V- + 1.3V for total supply voltages between 4.8V and 10V. The output voltage range, referenced to the supply voltages, decreases slightly over temperature, as indicated in the ±5V *Electrical Characteristics* tables. Operating characteristics at total supply, voltages of less than 10V are guaranteed by design and PSRR tests.


MAX410 Offset Voltage Null

The offset null circuit of Figure 9 provides approximately ±450µV of offset adjustment range, sufficient for zeroing offset over the full operating temperature range.

Ordering Information (continued)

PART	TEMP RANGE	PIN-PACKAGE
MAX412CPA	0°C to +70°C	8 Plastic DIP
MAX412BCPA	0°C to +70°C	8 Plastic DIP
MAX412CSA	0°C to +70°C	8 SO
MAX412BCSA	0°C to +70°C	8 SO
MAX412EPA	-40°C to +85°C	8 Plastic DIP
MAX412BEPA	-40°C to +85°C	8 Plastic DIP
MAX412ESA	-40°C to +85°C	8 SO
MAX412BESA	-40°C to +85°C	8 SO
MAX414CPD	0°C to +70°C	14 Plastic DIP
MAX414BCPD	0°C to +70°C	14 Plastic DIP
MAX414CSD	0°C to +70°C	14 SO
MAX414BCSD	0°C to +70°C	14 SO
MAX414EPD	-40°C to +85°C	14 Plastic DIP
MAX414BEPD	-40°C to +85°C	14 Plastic DIP
MAX414ESD	-40°C to +85°C	14 SO
MAX414BESD	-40°C to +85°C	14 SO

Pin Configurations (continued)



DIP/SO

Chip Information

MAX410 TRANSISTOR COUNT: 132

MAX412 TRANSISTOR COUNT: 262

MAX414 TRANSISTOR COUNT: 2 × 262 (hybrid)

PROCESS: Bipolar


Single/Dual/Quad, 28MHz, Low-Noise, Low-Voltage, Precision Op Amps

Package Information

For the latest package outline information and land patterns, go to **www.maxim-ic.com/packages**.

PACKAGE TYPE	PACKAGE CODE	DOCUMENT NO.
8 Plastic DIP	P8-1	21-0043
8 SO	S8-2	21-0041
8 TDFN-EP	T4833-2	21-0137
14 Plastic DIP	P14-3	21-0043
14 SO	S14-1	21-0041

PDIPN.EPS



	INCHES		MILLIMETERS	
	MIN	MAX	MIN	MAX
A	---	0.180	---	4.572
A1	0.015	---	0.38	---
A2	0.125	0.175	3.18	4.45
A3	0.055	0.080	1.40	2.03
B	0.015	0.022	0.381	0.56
B1	0.045	0.065	1.14	1.65
C	0.008	0.014	0.2	0.355
D1	0.005	0.080	0.13	2.03
E	0.300	0.325	7.62	8.26
E1	0.240	0.310	6.10	7.87
e	0.100 BSC.		2.54 BSC.	
eA	0.300 BSC.		7.62 BSC.	
eB	0.400 BSC.		10.16 BSC.	
L	0.115	0.150	2.921	3.81

	INCHES		MILLIMETERS			
	MIN	MAX	MIN	MAX	N	MS001
D	0.348	0.390	8.84	9.91	8	AB
D	0.735	0.765	18.67	19.43	14	AC
D	0.745	0.765	18.92	19.43	16	AA
D	0.885	0.915	22.48	23.24	18	AD
D	1.015	1.045	25.78	26.54	20	AE
D	1.14	1.265	28.96	32.13	24	AF
D	1.360	1.380	34.54	35.05	28	*5

NOTES:
1. D&E DO NOT INCLUDE MOLD FLASH
2. MOLD FLASH OR PROTRUSIONS NOT TO EXCEED .15mm (.006")
3. CONTROLLING DIMENSION: MILLIMETER
4. MEETS JEDEC MS001-XX AS SHOWN IN ABOVE TABLE
5. SIMILIAR TO JEDEC MO-058AB
6. N = NUMBER OF PINS

MAXIM 120 SAN GABRIEL DR SUNNYVALE CA 94086 FAX (408) 737 7194 PROPRIETARY INFORMATION

TITLE: PACKAGE FAMILY OUTLINE: PDIP .300" | 1/1 | DOCUMENT CONTROL NUMBER 21-0043 D REV

Package Information (continued)


For the latest package outline information and land patterns, go to **www.maxim-ic.com/packages**.

SOICN .EPS


	INCHES		MILLIMETERS	
DIM	MIN	MAX	MIN	MAX
A	0.053	0.069	1.35	1.75
A1	0.004	0.010	0.10	0.25
B	0.014	0.019	0.35	0.49
C	0.007	0.010	0.19	0.25
e	0.050 BSC		1.27 BSC	
E	0.150	0.157	3.80	4.00
H	0.228	0.244	5.80	6.20
L	0.016	0.050	0.40	1.27

VARIATIONS:


	INCHES		MILLIMETERS			
DIM	MIN	MAX	MIN	MAX	N	MS012
D	0.189	0.197	4.80	5.00	8	AA
D	0.337	0.344	8.55	8.75	14	AB
D	0.386	0.394	9.80	10.00	16	AC



TOP VIEW



FRONT VIEW



SIDE VIEW

NOTES:
1. D&E DO NOT INCLUDE MOLD FLASH.
2. MOLD FLASH OR PROTRUSIONS NOT TO EXCEED 0.15mm (.006").
3. LEADS TO BE COPLANAR WITHIN 0.10mm (.004").
4. CONTROLLING DIMENSION: MILLIMETERS.
5. MEETS JEDEC MS012.
6. N = NUMBER OF PINS.

DALLAS SEMICONDUCTOR MAXIM

PROPRIETARY INFORMATION


TITLE: PACKAGE OUTLINE, .150" SOIC

APPROVAL	DOCUMENT CONTROL NO.	REV.	
	21-0041	B	1/1

Single/Dual/Quad, 28MHz, Low-Noise, Low-Voltage, Precision Op Amps

Package Information (continued)

For the latest package outline information and land patterns, go to **www.maxim-ic.com/packages**.



Single/Dual/Quad, 28MHz, Low-Noise, Low-Voltage, Precision Op Amps

Package Information (continued)

For the latest package outline information and land patterns, go to **www.maxim-ic.com/packages**.

COMMON DIMENSIONS		
SYMBOL	MIN.	MAX.
A	0.70	0.80
D	2.90	3.10
E	2.90	3.10
A1	0.00	0.05
L	0.20	0.40
k	0.25 MIN.	
A2	0.20 REF.	

PACKAGE VARIATIONS							
PKG. CODE	N	D2	E2	e	JEDEC SPEC	b	[(N/2)-1] x e
T633-2	6	1.50±0.10	2.30±0.10	0.95 BSC	MO229 / WEEA	0.40±0.05	1.90 REF
T833-2	8	1.50±0.10	2.30±0.10	0.65 BSC	MO229 / WEEC	0.30±0.05	1.95 REF
T833-3	8	1.50±0.10	2.30±0.10	0.65 BSC	MO229 / WEEC	0.30±0.05	1.95 REF
T1033-1	10	1.50±0.10	2.30±0.10	0.50 BSC	MO229 / WEED-3	0.25±0.05	2.00 REF
T1033-2	10	1.50±0.10	2.30±0.10	0.50 BSC	MO229 / WEED-3	0.25±0.05	2.00 REF
T1433-1	14	1.70±0.10	2.30±0.10	0.40 BSC	----	0.20±0.05	2.40 REF
T1433-2	14	1.70±0.10	2.30±0.10	0.40 BSC	----	0.20±0.05	2.40 REF

NOTES:
1. ALL DIMENSIONS ARE IN mm. ANGLES IN DEGREES.
2. COPLANARITY SHALL NOT EXCEED 0.08 mm.
3. WARPAGE SHALL NOT EXCEED 0.10 mm.
4. PACKAGE LENGTH/PACKAGE WIDTH ARE CONSIDERED AS SPECIAL CHARACTERISTIC(S).
5. DRAWING CONFORMS TO JEDEC MO229, EXCEPT DIMENSIONS "D2" AND "E2", AND T1433-1 & T1433-2.
6. "N" IS THE TOTAL NUMBER OF LEADS.
7. NUMBER OF LEADS SHOWN ARE FOR REFERENCE ONLY.
8. MARKING IS FOR PACKAGE ORIENTATION REFERENCE ONLY.

DALLAS SEMICONDUCTOR MAXIM

TITLE: PACKAGE OUTLINE, 6,8,10 & 14L, TDFN, EXPOSED PAD, 3x3x0.80 mm

APPROVAL	DOCUMENT CONTROL NO.	REV.	
	21-0137	I	2/2

-DRAWING NOT TO SCALE-

Single/Dual/Quad, 28MHz, Low-Noise, Low-Voltage, Precision Op Amps

Revision History

REVISION NUMBER	REVISION DATE	DESCRIPTION	PAGES CHANGED
5	10/08	Added rugged plastic product	1, 11

Maxim cannot assume responsibility for use of any circuitry other than circuitry entirely embodied in a Maxim product. No circuit patent licenses are implied. Maxim reserves the right to change the circuitry and specifications without notice at any time.

© 2008 Maxim Integrated Products MAXIM is a registered trademark of Maxim Integrated Products, Inc.