N-Channel Enhancement-Mode Vertical DMOS FET

Ordering Information

BV_{DSS} / BV_{DGS}	$R_{DS(ON)}$ (max)	$I_{D(ON)}$ (min)	Order Number / Package
			Die†
60V	3.0Ω	2.0A	VN01506NW
90V	3.0Ω	2.0A	VN1509NW

† MIL visual screening available.

Features

- ❑ Free from secondary breakdown
- ❑ Low power drive requirement
- ❑ Ease of paralleling
- ❑ Low C_{ISS} and fast switching speeds
- ❑ Excellent thermal stability
- ❑ Integral Source-Drain diode
- ❑ High input impedance and high gain
- ❑ Complementary N- and P-channel devices

Applications

- ❑ Motor controls
- ❑ Converters
- ❑ Amplifiers
- ❑ Switches
- ❑ Power supply circuits
- ❑ Drivers (relays, hammers, solenoids, lamps, memories, displays, bipolar transistors, etc.)

Advanced DMOS Technology

These enhancement-mode (normally-off) transistors utilize a vertical DMOS structure and Supertex's well-proven silicon-gate manufacturing process. This combination produces devices with the power handling capabilities of bipolar transistors and with the high input impedance and positive temperature coefficient inherent in MOS devices. Characteristic of all MOS structures, these devices are free from thermal runaway and thermally-induced secondary breakdown.

Supertex's vertical DMOS FETs are ideally suited to a wide range of switching and amplifying applications where high breakdown voltage, high input impedance, low input capacitance, and fast switching speeds are desired.

Absolute Maximum Ratings

Drain-to-Source Voltage	BV_{DSS}
Drain-to-Gate Voltage	BV_{DGS}
Gate-to-Source Voltage	± 20V
Operating and Storage Temperature	-55°C to +150°C
Soldering Temperature*	300°C

* Distance of 1.6 mm from case for 10 seconds.

03/26/02

Supertex Inc. does not recommend the use of its products in life support applications and will not knowingly sell its products for use in such applications unless it receives an adequate "products liability indemnification insurance agreement." Supertex does not assume responsibility for use of devices described and limits its liability to the replacement of devices determined to be defective due to workmanship. No responsibility is assumed for possible omissions or inaccuracies. Circuitry and specifications are subject to change without notice. For the latest product specifications, refer to the Supertex website: http://www.supertex.com. For complete liability information on all Supertex products, refer to the most current databook or to the Legal/Disclaimer page on the Supertex website.

Electrical Characteristics (@ 25°C unless otherwise specified)

Symbol	Parameter		Min	Typ	Max	Unit	Conditions
BV_{DSS}	Drain-to-Source Breakdown Voltage	VN1509	90			V	V_{GS} = 0V, I_D = 1mA
		VN1506	60				
$V_{GS(th)}$	Gate Threshold Voltage		0.8		2.4	V	V_{GS} = V_{DS}, I_D = 1mA
$\Delta V_{GS(th)}$	Change in $V_{GS(th)}$ with Temperature			-3.8	-5.5	mV/°C	V_{GS} = V_{DS}, I_D = 1mA
I_{GSS}	Gate Body Leakage				100	nA	V_{GS} = ± 20V, V_{DS} = 0V
I_{DSS}	Zero Gate Voltage Drain Current				1	µA	V_{GS} = 0V, V_{DS} = Max Rating
					100		V_{GS} = 0V, V_{DS} = 0.8 Max Rating T_A = 125°C
$I_{D(ON)}$	ON-State Drain Current		0.5	1.0		A	V_{GS} = 5V, V_{DS} = 25V
			2.0	2.5			V_{GS} = 10V, V_{DS} = 25V
$R_{DS(ON)}$	Static Drain-to-Source ON-State Resistance			3.0	5.0	Ω	V_{GS} = 5V, I_D = 250mA
				2.5	3.0		V_{GS} = 10V, I_D = 1A
$\Delta R_{DS(ON)}$	Change in $R_{DS(ON)}$ with Temperature			0.70	1	%/°C	V_{GS} = 10V, I_D = 1A
G_{FS}	Forward Transconductance		300	450		m℧	V_{DS} = 25V, I_D = 0.5A
C_{ISS}	Input Capacitance			55	65	pF	V_{GS} = 0V, V_{DS} = 25V f = 1 MHz
C_{OSS}	Common Source Output Capacitance			20	25		
C_{RSS}	Reverse Transfer Capacitance			5	8		
$t_{d(ON)}$	Turn-ON Delay Time			3	5	ns	V_{DD} = 25V I_D = 1A R_{GEN} = 25Ω
t_r	Rise Time			5	8		
$t_{d(OFF)}$	Turn-OFF Delay Time			6	9		
t_f	Fall Time			5	8		
V_{SD}	Diode Forward Voltage Drop			1.2	1.8	V	V_{GS} = 0V, I_{SD} =1.0A
t_{rr}	Reverse Recovery Time			400		ns	V_{GS} = 0V, I_{SD} =1.0A

Notes:
1. All D.C. parameters 100% tested at 25°C unless otherwise stated. (Pulse test: 300µs pulse, 2% duty cycle.)
2. All A.C. parameters sample tested.

Switching Waveforms and Test Circuit



Supertex inc.
1235 Bordeaux Drive, Sunnyvale, CA 94089
TEL: (408) 744-0100 • FAX: (408) 222-4895
www.supertex.com

©2002 Supertex Inc. All rights reserved. Unauthorized use or reproduction prohibited.