

PRELIMINARY

Notice: This is not a final specification.
Some parametric limits are subject to change.

MITSUBISHI Analog ICs

M65533FP

3ch 8-bit 80MHz A/D Converters

General Description

The M65533FP is a CMOS **3ch 8-bit 80MHz** analog-to-digital converter by sub-ranging architecture for high speed video processing. It can be realized 80MHz operation by using 2 ADCs in parallel. And it has **PLL circuit** generate a stable clock locked to sync signal. It is a type of "AC" connection with internal clamp circuit and variable input range.

Features

- 3ch 8-bit high speed A-D converters
- Maximum conversion rate
- Analog input Level
- Digital input
- Digital output
- Low power dissipation
- Package

- Small input capacitance
- Built-in Reference Voltage
- Built-in Clamp circuit

80 MSPS(min.)

1.0V(Typ) : 0.5 -1.5 V

TTL compatible

VoH=0.7XVcc , VoL=0.3XVcc [V_{inH}=1.4V]
[I_o=4mA]

700mW [CL=10pF]

80 pin QFP package, 0.80mm lead pitch

[PKG size(without lead) =14mm x 20mm]

10 pF

V_{ref}(+)=1.5V+150/-330mV(*) V_{ref}(-)=0.5V

V_{clamp}=0.5V+/-250mV(*)

(*)Controllable by IIC BUS

Applications


- LCD monitor
- High speed video processing

Recommended Operating Condition

- Supply voltage range (typ.=3.3V) 3.15 to 3.45 V
- Supply voltage range (typ.=5.0V) 4.75 to 5.25 V for 5V I/F only

Pin configuration(Top View)

Shown on next page



PRELIMINARY


Notice: This is not a final specification.
Some parametric limits are subject to change.

MITSUBISHI Analog ICs

M65533FP

3ch 8-bit 80MHz A/D Converters

Pin Configuration



PRELIMINARY


Notice: This is not a final specification.
Some parametric limits are subject to change.

MITSUBISHI Analog ICs

M65533FP

3ch 8-bit 80MHz A/D Converters

Block Diagram



(note) Pins for ADC is described for only R signal

Absolute Maximum Ratings (Ta = 25°C, unless otherwise noted.)

Symbol	Parameter	Condition	Ratings	Unit
DVdd	Digital Supply Voltage		0 to 4.0	V
AVdd	Analog Supply Voltage		0 to 4.0	V
Vdd(I/O)	I/O Supply Voltage		0 to 6.0	V
V _{id}	Digital Input Voltage		0 to 4.0	V
I _{OUT}	Analog Output Current		-30 to 0	mA
P _d	Power Dissipation		1600	mW
T _{opr}	Operating Temperature		0 to +70	°C
T _{stg}	Storage Temperature		-40 to +150	°C

In current measurement, (+) and (-) is corresponding to an inflow and an outflow current, respectively.

Recommended Operating Conditions (Ta = 25°C, unless otherwise noted.)

Symbol	Parameter	Limits			Unit
		Min.	Typ.	Max.	
V _{dd}	Supply Voltage	3.15	3.30	3.45	V
V _{dd(I/O)}	Supply Voltage(I/O)	4.75	5.0	5.25	V
V _{IH}	Digital Input Voltage (High)	2.4	-	V _{dd}	V
V _{IL}	Digital Input Voltage (Low)	0	-	0.8	V
t _{WH}	Clock Pulse Width (High)	6.25	-	-	ns
t _{WL}	Clock Pulse Width (Low)	6.25	-	-	ns
t _{su}	Set-up Time	5	-	-	ns
t _h	Hold Time	5	-	-	ns

Electrical Characteristics

(Ta = 25°C, AVdd = DVdd = 3.30V, unless otherwise noted.)

(1) Overall

Symbol	Parameter	Condition	Limits			Unit
			Min.	Typ.	Max.	
AIdD(AD R/G/B)	AD(R/G/B) Analog Supply Current	For R/G/B signal		tbF		mA
DIdD(AD R/G/G)	AD(R/G/G) Digital Supply Current	For R/G/B signal		tbF		mA
DIdD(I/O R/G/G)	I/O block Supply Current	For R/G/B signal		tbF		mA
DIdD(PLL)	PLL block Supply Current			tbF		mA
DIdD(LO)	Logic block Supply Current			tbF		mA
DIdD(I/O 5)	5V I/O block Supply Current			tbF		mA

(2) ADC Block

Symbol	Parameter	Condition	Limits			Unit
			Min.	Typ.	Max.	
Res	Resolution			8		Bits
Vdd	Supply Voltage		3.15	3.30	3.45	V
NL	Integral Nonlinearity	Vref(+)=1.5V, Vref(-)=0.5V			± 1.0	LSB
DNL	Differential Nonlinearity	Vref(+)=1.5V, Vref(-)=0.5V			± 1.0	LSB
VOH	Digital output Voltage "H"		0.7xVdd		Vdd	V
VOL	Digital output Voltage "L"		0		0.3xVdd	V
VinA	Analog input range		0.67	1.00	1.15	Vp-p
Cin	Input Capacitance			10		pF
fCLK	Max. Conversion Rate		80			MHz
Vref(+)	Reference Voltage "High"	Changeable by IIC (16mV step)	1.17	1.5	1.65	V
Vref(M)	Reference Voltage "Middle"		0.84	1.0	1.07	V
Vref(-)	Reference Voltage "Low"			0.5		V
Rref	Reference Resistor			120		Ohms
B.W	Input Bandwidth	-3dB input frequency	70			MHz
tpdLH	Output delay time(L->H)			110	160	ns
tpdHL	Output delay time(H->L)			110	160	ns
tr	Output rise time			tbF		ns
tf	Output fall time			tbF		ns
Vclamp	Clamp Voltage	Changeable by IIC (16mV step)	0.25	0.5	0.73	V

(3) PLL Block

Symbol	Parameter	Condition	Limits			Unit
			Min.	Typ.	Max.	
fH	Horizontal frequency		10	60	100	KHz
fVCO	VCO frequency		20		80	MHz
jPLL	maximum jitter			0.5	1.0	ns
D.R(PLL)	PLL Divider Ratio	from 800 by 1 step	800		1376	-

Pin Description -1

No connection.
 It is grounded during actual use.

Pin No.	Pin Name	I/O	Function	From or To
31,33,35	DVDDX(A/D)		Digital Power supply (R/G/B signal)	3.3V
5,13,21	AVDDX(A/D)		Analog Power supply (R/G/B signal)	3.3V
44,54,64	DVDDX(OUT)		I/O Power supply (R/G/B signal)	3.3V
66,67	VDD(PLL)		PLL Power supply	3.3V
30,32,34	DGNDX (A/D)		Digital ground (R/G/B signal)	GND
4,12,20	AGNDX (A/D)		Analog ground (R/G/B signal)	GND
45,55,65	DGNDX(OUT)		I/O ground (R/G/B signal)	GND
69,70	GND(PLL)		PLL ground	GND
2,10,18	XCIN	I	R/G/B signal Clamp Input	From LPF
7,15,23	XVRT		Reference Voltage(+) Input (R/G/B signal)	Bypass capacitor
6,14,22	XVRM		Reference Voltage(M) Input (R/G/B signal)	Bypass capacitor
1,9,17	XVRB		Reference Voltage(-) Input (R/G/B signal)	Bypass capacitor
8,16,24	XNB		ADC operating current setting BIAS	Bypass capacitor
36 - 43 46 - 53 56 - 63	DoX<7:0>	O	Digital Output (R/G/B signal)	To Logic LSI
74	FH-IN	I	H Sync Input	From Sync Sep. LSI
68	FILTER		PLL filter	(R+C)//C
29	CLK-OUT	O	Clock output	To Logic LSI
79	SDA	I/O	IIC Data Input/Output	From MCU
78	SCL	I/O	IIC CLK Input	From MCU
80	RESET	I	Reset signal Input	To Vdd
77	EXT-CLK IN	I	External Clock input	From PLL LSI
25,26,27	Test<1-3 >	I/O	Test terminal	

Pin Description -2

No connection.
It is grounded during actual use.

[illegible]

Table of Power-down Function(SubAdd=00h, D2-D0) Setting by IIC BUS

Digital input code	Power-down function
"HHH"	power-down
"LLL"	normal operation

Default

Only Clamp=>"HLL"
 Only PLL=>"LHL"
 Only ADC=>"LLH"

Table of CP Function (SubAdd=11h, D0) Setting by IIC BUS

CP signal	CP function
"H"	Clamping
"L"	Hold state

CP signal	Digital input code	CP Polarity
	D0="H"	Inversed
	D0="L"	Not-inversed

Table of Hsync Function(SubAdd=17h, D0) Setting by IIC BUS

Digital input code	Hsync function
 D0="H"	Inversed
 D0="L"	Not-inversed

Default

Table of CLK output Function(SubAdd=13h, D0) Setting by IIC BUS

Digital input code	CLK output function
D0="H"	Inversed (180)
D0="L"	Not-inversed (0)

Default

Table of Internal/External CLK(SubAdd=16h, D5) Setting by IIC BUS

Digital input code	CLK output function
D5="H"	External
D5="L"	Internal

Default

Table of Digital Output R/G/B < 7 : 0 > Function Setting by IIC BUS

Output "HZ" is available at D1="H" of SubAdd=18h "L"=default

Analog input voltage	Digital output code								Note
	7 MSB	6	5	4	3	2	1	0 LSB	
1.500V	1	1	1	1	1	1	1	1	
1.496V	1	1	1	1	1	1	1	0	
⋮	⋮	⋮	⋮	⋮	⋮	⋮	⋮	⋮	
1.000V	1	0	0	0	0	0	0	0	
0.996V	0	1	1	1	1	1	1	1	
⋮	⋮	⋮	⋮	⋮	⋮	⋮	⋮	⋮	
0.504V	0	0	0	0	0	0	0	1	
0.500V	0	0	0	0	0	0	0	0	

**Table of Delay adjustment(SubAdd=16h, D3-D0)
 for External CLK (SubAdd=16h, D5="H")**

Setting by IIC BUS

Digital input code				CLK Delayed Adjustment	
D3	D2	D1	D0		
1	1	1	1	75ns	
1	1	1	0	70ns	
1	1	1	1	70ns	
1	0	0	0	40ns	
0	1	1	1	35ns	
1	1	1	1	70ns	
0	0	0	1	5ns	
0	0	0	0	0ns	Default

**Table of Vref(+) Voltage adjustment
 (SubAdd=0Bh, D4-D0:R 0Ch, D4-D0:G 0Dh, D4-D0:B)**

Setting by IIC BUS

Digital input code					Vref(+) adjustment	Note
D4	D3	D2	D1	D0		
1	1	1	1	1	40LSB	1.5+0.157V
1	1	1	1	0	36LSB	
1	1	1	1	1	70ns	
1	0	1	0	1	0LSB	1.5-0V
1	1	1	1	1	70ns	
1	0	0	0	0	-20LSB	
0	1	1	1	1	-24LSB	
1	1	1	1	1	70ns	
0	0	0	0	1	-80LSB	
0	0	0	0	0	-84LSB	1.5-0.329V

Default

Table of Clamp level adjustment

Setting by IIC BUS

(SubAdd=0Eh, D4-D0:R 0Fh, D4-D0:G 10h, D4-D0:B)

Digital input code					Delay adjustment level	Note
D4	D3	D2	D1	D0		
1	1	1	1	1	60LSB	0.5V+235mV
1	1	1	1	0	56LSB	
1	1	1	0	1		
1	1	1	0	0		
1	0	0	0	0	0LSB	0.5V-0mV
0	1	1	1	1	-4LSB	
0	1	1	1	0		
0	1	1	0	1		
0	1	1	0	0		
0	0	0	0	1	-60LSB	
0	0	0	0	0	-64LSB	0.5V-251mV

Default

Table of CLK output Phase (SubAdd=12h, D4 -D0)

Setting by IIC BUS

Digital input code					CLK output phase
D4	D3	D2	D1	D0	
1	1	1	1	1	division into 32 of 1 period
1	1	1	1	0	
1	1	1	0	1	
1	1	1	0	0	
1	0	0	0	0	
0	1	1	1	1	
0	1	1	1	0	
0	1	1	0	1	
0	0	0	0	1	0 + 0 * 360/32
0	0	0	0	0	

Default

Table of CLK output Phase Function (SubAdd=12h,D5)

Setting by IIC BUS

Digital input code	CLK output Phase Function
D5="H"	OFF
D5="L"	ON

Table of CLK's Pol. for A/D (SubAdd=12h,D6)

Setting by IIC BUS

Digital input code	CLK's Pol.
D6="H"	NEGA
D6="L"	POS

**Table of PLL divider adjustment
 (SubAdd=14h,A6-A0 15h,A3-A0)**


Setting by IIC BUS

Digital input code											Divider adjustment
14h							15h				
A6	A5	A4	A3	A2	A1	A0	A3	A2	A1	A0	
1	0	1	0	1	1	0	0	0	0	0	fH x 1376
1	0	1	0	1	0	1	1	1	1	1	fH x 1375
⋮	⋮	⋮	⋮	⋮	⋮	⋮	⋮	⋮	⋮	⋮	
1	0	0	0	0	0	0	0	0	0	0	fH x 1024
0	1	1	1	1	1	1	1	1	1	1	fH x 1023
⋮	⋮	⋮	⋮	⋮	⋮	⋮	⋮	⋮	⋮	⋮	
0	1	1	0	0	1	0	0	0	0	1	fH x 801
0	1	1	0	0	1	0	0	0	0	0	fH x 800

**Table of PLL divider adjustment
 (SubAdd=15h,A6-A5)**

Setting by IIC BUS

Digital input code	PLL Pre-divider adjustment
D6,5="1 1"	1/6
D6,5="1 0"	1/4
D6,5="0 1"	1/3
D6,5="0 0"	1/2



PRELIMINARY

Notice: This is not a final specification.
Some parametric limits are subject to change.

mitsubishi MITSUBISHI Analog ICs

M65533FP

3ch 8-bit 80MHz A/D Converters

Table of Reset Function (pin 80)

Reset signal	Reset function
"L"	Reset
"H"	normal operation

PRELIMINARY


Notice: This is not a final specification.
Some parametric limits are subject to change.

MITSUBISHI Analog ICs


M65533FP

3ch 8-bit 80MHz A/D Converters

Application Examples



Analog Input / Digital Output Timing Diagram



Notes to the operation

1. Both a ground and a supply planes in a PCB should be as wide as possible for reducing a parasitic inductance and resistance. Especially, for the better performance, the analog plane needs to be much wider.
2. A tantalum or electrolytic capacitor of 10 μ F or more and a ceramic capacitor of 0.01 μ F are tied together, which are connected between a digital supply and ground, also between a analog supply and ground. These capacitors should be placed as close as possible to the IC. They work as bypass capacitors for preventing a degradation in the performance by a supply voltage fluctuation caused by digital signals including a clock and digital inputs and so on.
3. The analog output should be isolated as much as possible from a clock and digital inputs, thus minimizing decoupling and interactive noise.

PRELIMINARY


Notice: This is not a final specification.
Some parametric limits are subject to change.

MITSUBISHI Analog ICs

M65533FP

3ch 8-bit 80MHz A/D Converters

Application Example (M65533FP)




M65533FP IIC-BUS CONTROL TABLE

(1) Slave address :

A6 A5 A4 A3 A2 A1 A0 R/W
 1 0 0 1 1 1 0 0 (=9Ch)

(2) Slave address format :
 read



(3) Sub address byte and Data byte format :
 read

Block	No.	Functions	Bit	Sub Add	Data byte							
					D7	D6	D5	D4	D3	D2	D1	D0
Total	1	Power-down	3	00h	0					A02	A01	A00
ADC	2	Vref(+) Vol (R)	5	0Bh	0			A04	A03	A02	A01	A00
	3	Vref(+) Vol (G)	5	0Ch	0			A04	A03	A02	A01	A00
	4	Vref(+) Vol (B)	5	0Dh	0			A04	A03	A02	A01	A00
	5	Clamp Vol (R)	5	0Eh	0			A04	A03	A02	A01	A00
	6	Clamp Vol (G)	5	0Fh	0			A04	A03	A02	A01	A00
	7	Clamp Vol (B)	5	10h	0			A04	A03	A02	A01	A00
	8	Clamp-in Pol	1	11h	0							A00
CLK /PLL	9	CLK Phase	7	12h	0	A06	A05	A04	A03	A02	A01	A00
	10	CLKOUT Pol	1	13h	0							A00
	11	PLL upper	7	14h	0	A06	A05	A04	A03	A02	A01	A00
	12	PLL lower & Divider	6	15h	0	A06	A05		A03	A02	A01	A00
	13	INT/EXT CLK	5	16h	0		A05		A03	A02	A01	A00
	14	H_Sync Pol	2	17h	0							A00
	15	ADC Output	1	18h	0						A01	
(Note) Blanks should not be defined. Because it may be used for test mode or function check.												