



### SPC56EL60xx- differences between cut 1.0 and cut 2.0

## 1 Introduction

This document describes the differences between SPC56EL60xx cut2 and the predecessor cut1.

**Table 1. Order codes**

| Order codes | Flash/SRAM  | Package       | Speed (MHz) | Other features                          |
|-------------|-------------|---------------|-------------|-----------------------------------------|
| SPC564L60L3 | 1 MB/128 KB | LQFP100 3.3 V | 80          | Single core<br>FlexRay<br>- 40 - 105 °C |
| SPC56EL60L5 | 1 MB/128 KB | LQFP144 3.3 V | 120         | Dual core<br>FlexRay<br>- 40 - 125 °C   |

# Contents

|          |                                                               |          |
|----------|---------------------------------------------------------------|----------|
| <b>1</b> | <b>Introduction .....</b>                                     | <b>1</b> |
| <b>2</b> | <b>Differences cut1 and cut2 .....</b>                        | <b>4</b> |
| 2.1      | Errata fixes .....                                            | 4        |
| 2.2      | Feature enhancements .....                                    | 6        |
| 2.2.1    | Nexus - NXSS .....                                            | 6        |
| 2.2.2    | Nexus - RDY PIN .....                                         | 6        |
| 2.2.3    | Nexus - DDR mode – I/O timing .....                           | 6        |
| 2.2.4    | DSPI - enhanced version .....                                 | 6        |
| 2.2.5    | CRC Unit - support for additional polynomial .....            | 6        |
| 2.2.6    | AIPS MPROT - enhanced protection features .....               | 6        |
| 2.2.7    | MC_RGM - destructive reset can be triggered by software ..... | 7        |
| 2.2.8    | SSCM - easier access to NVM calibration data .....            | 7        |
| 2.3      | Device ID codes .....                                         | 7        |
| 2.4      | Pin muxing .....                                              | 7        |
|          | <b>Appendix A Reference document .....</b>                    | <b>8</b> |
|          | <b>Revision history .....</b>                                 | <b>9</b> |

List of tables

Table 1.    Order codes ..... 1

Table 2.    Errata for cut1 and the fixes for cut2. .... 4

Table 3.    Document revision history ..... 9

## 2 Differences cut1 and cut2

The listed differences between the two revisions of SPC56EL60xx are related to:

- Errata fixes
- Feature enhancements
- ID codes
- Pin muxing

### 2.1 Errata fixes

[Table 2](#) shows the currently known errata for cut1 and the planned fixes for cut2.

Please refer to SPC56EL60L5 - SPC56EL60C3 errata sheet, rev. 2 (see [Appendix A: Reference document](#)).

**Table 2. Errata for cut1 and the fixes for cut2**

| Errata number | Module | Description                                                                                                                                        |
|---------------|--------|----------------------------------------------------------------------------------------------------------------------------------------------------|
| e5299PS       | NEXUS  | Critical signals of Nexus debugger not monitored by FCCU.                                                                                          |
| e5302PS       | JTAG   | Critical signals of JTAG not monitored by FCCU.                                                                                                    |
| e5681PS       | NEXUS  | Nexus interface availability is indicated too early.                                                                                               |
| e6842PS       | DPM    | CPU core 1 in unknown state after HALT0 or STOP0 mode exit when device configured in DPM.                                                          |
| e7292PS       | XOSC   | External oscillator is not controllable.                                                                                                           |
| e7811PS       | ADC1   | Enabling of conversions of shared channels using ADC1.                                                                                             |
| e8521PS       | CTU    | CTU: Invalid Command Error is not detected in case of dual conversion mode on shared ADC channels.                                                 |
| e8826PS       | PMU    | Destructive reset triggered during a mode transition from run mode to safe/halt/stop mode.                                                         |
| e5932PS       | FLASH  | RWW errors not correctly flagged at high system frequencies.                                                                                       |
| e6934IPG      | DSPI   | DSPI: changing CTARs between frames in continuous PCS mode causes error.                                                                           |
| e10483IPG     | DSPI   | DSPI: PCS Continuous Selection Format limitation.                                                                                                  |
| e18427IPG     | DSPI   | DSPI: DSPI Microsecond Bus Limitations.                                                                                                            |
| e8814PS       | ADC    | ADC parameters on negative current injection out of specification.                                                                                 |
| e7764PS       | NEXUS  | Nexus stall feature not supported in lockstep mode.                                                                                                |
| e5455PS       | BAM    | BAM: BookE mode not supported for serial downloads.                                                                                                |
| e6020PS       | BAM    | BAM: autobaud feature is not available.                                                                                                            |
| e3771PS       | RGM    | MC_RGM: FCCU_SOFT is incorrectly configurable to generate a 'long' reset sequence.                                                                 |
| e4107PS       | ME     | MC_CGM and MC_PCU: a data storage exception is not generated on an access to MC_CGM or MC_PCU when the respective peripheral is disabled at MC_ME. |

**Table 2. Errata for cut1 and the fixes for cut2 (continued)**

| Errata number | Module   | Description                                                                                                                                     |
|---------------|----------|-------------------------------------------------------------------------------------------------------------------------------------------------|
| e5301PS       | RGM      | MC_RGM: SAFE mode exit may be possible even though condition causing the SAFE mode request has not been cleared.                                |
| e6041PS       | ME       | MC_ME: peripherals in unknown state after SAFE mode exit.                                                                                       |
| e6440PS       | MC       | SWT interrupt does not cause STOP0 mode exit.                                                                                                   |
| e6699PS       | CGM      | MC_CGM: short glitch may occur on output clock.                                                                                                 |
| e7583 PS      | RGM      | MC_RGM: RGM_FES content incorrect after startup LBIST execution.                                                                                |
| e8291PS       | CGM      | System clock source change may cause a "CMU0 system clock frequency too high or too low event".                                                 |
| e9367PS       | eTimer   | eTimer: configuring an eTimer counter channel in GATED-COUNT mode or in SIGNED-COUNT mode it may cause a possible incorrect counting of 1 tick. |
| e9414PS       | eTimer   | Possible false DMA requests from eTimer.                                                                                                        |
| e6886PS       | NPC      | MCKO clock gating not implemented.                                                                                                              |
| e9376 PS      | PWM      | FlexPWM: configuring the count value to set PWMA/PWMB first low and then high in the same cycle the output signals are low.                     |
| e6309PS       | SSCM     | Debugging functionality could be lost when unsecuring a secured device.                                                                         |
| e6500PS       | ADC      | VREFP and VDD_HV_ADC power up sequencing constraint.                                                                                            |
| e5485PS       | ADC      | ADC: ADC_DMAE[DCLR] should not be used.                                                                                                         |
| e9154 PS      | ADC      | ADC: abort request during last sampling cycle corrupts the data register of next channel conversion.                                            |
| e1685PS       | FMPLL    | FMPLL: FMPLL_CR[UNLOCK_ONCE] wrongly set.                                                                                                       |
| e7220PS       | SWG      | SWG: SGEN_CTRL.NRO bit is reserved *).                                                                                                          |
| e5816PS       | SWG      | SWG: Sinewave generator (SWG) is active during self-test execution.                                                                             |
| e26553IPG     | e200z4   | e200z4: mtlr followed by se_rfi/se_rfc/se_rfdi/se_rfmci can give unexpected results.                                                            |
| e8099 PS      | DMA      | Limitations for DMA access to LINFlex.                                                                                                          |
| e9471 PS      | IPBUS    | CAN Register/Message Buffer Access can reset or block the device if certain clock divider ratios (PeriN: System Clock) are selected.            |
| e7752PS       | Platform | ICache commands ICBTLS and ICBLC do not work as specified.                                                                                      |

## 2.2 Feature enhancements

The list below shows feature enhancements for cut2.

- Nexus - NXSS
- Nexus - RDY PIN
- Nexus – DDR mode – I/O timing
- DSPI enhanced version
- CRC Unit - support for additional polynomial
- AIPS MPROT - enhanced protection features
- MC\_RGM - destructive reset can be triggered by software
- SSCM - easier access to NVM calibration data
- Selftest - reduction of execution time

### 2.2.1 Nexus - NXSS

The Nexus Crossbar Slave Port Data Trace Module for System SRAM allows to trace all DMA/SRAM accesses.

### 2.2.2 Nexus - RDY PIN

To increase the transfer rate of the IEEE 1149.1 port, an additional pin has been implemented to signal when data are ready to be transferred to and from NRRs. This may eliminate the need to poll NRRs for status information for synchronization purposes. This capability becomes especially important when performing read/write access transfers to different speed target memories.

This functionality is only available on BGA257 package (ball K3). RDY is muxed with GPIO (GPIO is default out of reset).

### 2.2.3 Nexus - DDR mode – I/O timing

The I/O timing has been changed so that the MDO / MSEO outputs are valid during the MCKO rising and falling edges.

### 2.2.4 DSPI - enhanced version

Support higher net through put in slave mode by reducing required dead cycles in back to back operation.

### 2.2.5 CRC Unit - support for additional polynomial

An additional 8-bit CRC polynomial has been implemented. The bit field 28:29 of the register CRC\_CFG for each context selects the polynomial preserving compatibility with previous versions of this IP used on cut1.

### 2.2.6 AIPS MPROT - enhanced protection features

The default reset MPROT (Master Protection) configuration for each AIPS bridge is determined via the aips\_rstcfg vector which has been changed.

In general in both modes of operation only the two cores (Instruction Port, Load/Store Port and the Nexus subsystem) have access rights to the IPS peripherals per default configuration.

### 2.2.7 MC\_RGM - destructive reset can be triggered by software

Additional support for software triggerable destructive reset event (D[14]) has been implemented.

### 2.2.8 SSCM - easier access to NVM calibration data

The selftest execution time has been reduced compared to cut1 by appr. 13 ms. The information is documented in the SPC56EL60L3, SPC56EL60L5 datasheet (see [Appendix A: Reference document](#)) as part of the reset sequence specification.

## 2.3 Device ID codes

SPC56EL60xx contains ID codes which identify the device.

- JTAG ID  
Cut1: 0000\_1010\_1110\_1010\_\_0010\_0000\_0100\_0001  
Cut2: 0000\_1010\_1110\_1010\_\_0011\_0000\_0100\_0001
- MCU ID Register 1 (MIDR1)
- MCU ID Register 2 (MIDR2)

The values of these ID codes differ between cut1 and cut2.

## 2.4 Pin muxing

SPC56EL60xx cut2 is pin-compatible with cut1. Cut2 specifies an additional RDY pin for the BGA257 package (ball K3). On cut1 this ball is not connected to any function. The RDY pin on cut2 is muxed with GPIO (GPIO is default out of reset).

## Appendix A      Reference document

1. 32-bit Power Architecture™ microcontroller for automotive SIL3/ASILD chassis and safety applications (SPC56EL60L5 - SPC56EL60C3 errata sheet - Doc ID 16945).
2. 32-bit Power Architecture® microcontroller for automotive SIL3/ASILD chassis and safety applications (SPC56EL60L5 - SPC56EL60C3 datasheet - Doc ID 15457).

## Revision history

**Table 3. Document revision history**

| <b>Date</b> | <b>Revision</b> | <b>Changes</b>      |
|-------------|-----------------|---------------------|
| 03-Jan-2011 | 1               | Initial release.    |
| 18-Sep-2013 | 2               | Updated Disclaimer. |

**Please Read Carefully:**

Information in this document is provided solely in connection with ST products. STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, modifications or improvements, to this document, and the products and services described herein at any time, without notice.

All ST products are sold pursuant to ST's terms and conditions of sale.

Purchasers are solely responsible for the choice, selection and use of the ST products and services described herein, and ST assumes no liability whatsoever relating to the choice, selection or use of the ST products and services described herein.

No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted under this document. If any part of this document refers to any third party products or services it shall not be deemed a license grant by ST for the use of such third party products or services, or any intellectual property contained therein or considered as a warranty covering the use in any manner whatsoever of such third party products or services or any intellectual property contained therein.

**UNLESS OTHERWISE SET FORTH IN ST'S TERMS AND CONDITIONS OF SALE ST DISCLAIMS ANY EXPRESS OR IMPLIED WARRANTY WITH RESPECT TO THE USE AND/OR SALE OF ST PRODUCTS INCLUDING WITHOUT LIMITATION IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE (AND THEIR EQUIVALENTS UNDER THE LAWS OF ANY JURISDICTION), OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT.**

**ST PRODUCTS ARE NOT DESIGNED OR AUTHORIZED FOR USE IN: (A) SAFETY CRITICAL APPLICATIONS SUCH AS LIFE SUPPORTING, ACTIVE IMPLANTED DEVICES OR SYSTEMS WITH PRODUCT FUNCTIONAL SAFETY REQUIREMENTS; (B) AERONAUTIC APPLICATIONS; (C) AUTOMOTIVE APPLICATIONS OR ENVIRONMENTS, AND/OR (D) AEROSPACE APPLICATIONS OR ENVIRONMENTS. WHERE ST PRODUCTS ARE NOT DESIGNED FOR SUCH USE, THE PURCHASER SHALL USE PRODUCTS AT PURCHASER'S SOLE RISK, EVEN IF ST HAS BEEN INFORMED IN WRITING OF SUCH USAGE, UNLESS A PRODUCT IS EXPRESSLY DESIGNATED BY ST AS BEING INTENDED FOR "AUTOMOTIVE, AUTOMOTIVE SAFETY OR MEDICAL" INDUSTRY DOMAINS ACCORDING TO ST PRODUCT DESIGN SPECIFICATIONS. PRODUCTS FORMALLY ESCC, QML OR JAN QUALIFIED ARE DEEMED SUITABLE FOR USE IN AEROSPACE BY THE CORRESPONDING GOVERNMENTAL AGENCY.**

Resale of ST products with provisions different from the statements and/or technical features set forth in this document shall immediately void any warranty granted by ST for the ST product or service described herein and shall not create or extend in any manner whatsoever, any liability of ST.

ST and the ST logo are trademarks or registered trademarks of ST in various countries.

Information in this document supersedes and replaces all information previously supplied.

The ST logo is a registered trademark of STMicroelectronics. All other names are the property of their respective owners.

© 2013 STMicroelectronics - All rights reserved

STMicroelectronics group of companies

Australia - Belgium - Brazil - Canada - China - Czech Republic - Finland - France - Germany - Hong Kong - India - Israel - Italy - Japan - Malaysia - Malta - Morocco - Philippines - Singapore - Spain - Sweden - Switzerland - United Kingdom - United States of America

[www.st.com](http://www.st.com)

