
Remote I/O R9 Series

MULTI POWER MONITORING UNIT

(Clamp-on current sensor CLSE, Modbus/TCP)

Functions & Features

• Multi Power Monitoring Unit for Modbus/TCP (Ethernet)
• By using clamp-on current sensors, there is no need of current transformers.
• Up to 8 circuits can be measured. (Common voltage measurement)
• Current sensors are easy to install in existing systems. Wide input range of 5 to 600 A is availabe.
• All measured values, counter values, display mode, setting data are stored in the non-volatile memory when power is off.
• By using SD card, data logging of current and power etc. with calendar is available.



MODEL: R9EWTU-2001-AD4[1]

ORDERING INFORMATION

• Code number: R9EWTU-2001-AD4[1]
Specify a code from below for [1].
(e.g. R9EWTU-2001-AD4/Q)
• Specify the specification for option code /Q
(e.g. /C01/SET)

CONFIGURATION

2: Single-phase/2-wire, 3-phase/3-wire, single-phase/3-wire; 8 circuits

CONNECTION

0: Terminal block

I/O

0: Without

EXTENSION UNIT

1: With connection

AUXILIARY POWER SUPPLY

AD4: universal
100 – 240 V AC (Operational range 85 – 264 V, 50 / 60 Hz) /
110 – 240 V DC (Operational range 99 – 264 V,
ripple 10 %p-p max)

[1] OPTIONS

blank: none
/Q: With options (specify the specification)

SPECIFICATIONS OF OPTION: Q (multiple selections)

COATING (For the detail, refer to M-System's web site.)
/C01: Silicone coating
/C02: Polyurethane coating
/C03: Rubber coating

EX-FACTORY SETTING
/SET: Preset according to the Ordering Information Sheet (No. ESU-6224)

RELATED PRODUCTS

• Discrete I/O extension unit (model: R9WTU-ED)
• Multi power monitoring extension unit (model: R9WTU-EP)
• PC configurator software (model: PMCFG)
Downloadable at M-System's web site.
A dedicated cable is required to connect the module to the PC. Please refer to the internet software download site or the users manual for the PC configurator for applicable cable types.
• Clamp-on current sensor (model: CLSE)
The clamp-on current sensors, not included in this product package, must be ordered separately. Required number depends upon the system configuration.
• SD card
A SD card is required to store data in the unit.
Use the specified model number of memory card.
Available for purchase from M-System. Consult M-System.
- Hagiwara Solutions NSD6-004GH(B21SEI
(NSD6-004GH(A00SDI, NSDA-004GT,
NSDA-004GL ... discontinued)
- Apacer Technology AP-ISD04GIS4B-3T
(AP-ISD04GIS4B-T ... discontinued)


GENERAL SPECIFICATIONS

Construction: Stand-alone
Degree of protection: IP20
Connection
Auxiliary power or voltage input: M3.5 screw terminals


(torque 0.8 N·m)
Current input: M3 screw terminals (torque 0.5 N·m)
Ethernet: RJ-45 modular jack
Solderless terminal: Refer to the drawing at the end of the section.
Recommended manufacturer: Japan Solderless Terminal MFG.Co.Ltd, Nichifu Co.,ltd
Applicable wire size
M3 screw terminal: 0.25 to 1.65 mm^2 (AWG 22 to 16)
M3.5 screw terminal: 1.04 to 2.63 mm^2 (AWG 16 to 14)
Configuration: Single-phase/2-wire, single-phase/3-wire, 3-phase/3-wire
Screw terminal: Nickel-plated steel
Housing material: Flame-resistant resin (black)
Isolation: Sensor core to sensor output or current input or voltage input to Ethernet to auxiliary power to FE1

■ **Measured variables**
Voltage: R – N, S – N, T – N, R – S, S – T, T – R
Current: R, S, T, N
Active / reactive / apparent power: R, S, T, Σ
Power factor: R, S, T, Σ
Frequency
Active energy: Incoming
Reactive energy: Incoming lag
Active / reactive / apparent power intervals (demand)
Average (demand) current: R, S, T, N
Harmonic contents: Σ
Voltage: R - N, S - N, T - N, R - S, S - T, T - R
Current: R, S, T, N
Max. and min. values
Calendar log (inserting SD card): Voltage, Current, power, electric energy, power factor
Operating mode setting: Connection, clamp-on sensor selection
Status indicators: Power, SD Card, RUN

■**Recommended solderless terminal size - M3**



■**Recommended solderless terminal size - M3.5**



ETHERNET COMMUNICATION

Communication Standard: IEEE 802.3u
Transmission: 10BASE-T, 100BASE-TX
Baud rate: 10/100 Mbps (Auto Negotiation function)
Protocol: Modbus/TCP
Data: RTU (Binary)
Max. number of socket connections: 2
Transmission media: 10BASE-T (STP, Category 5) 100BASE-TX (STP, Category 5e)
Max. length of fieldbus segment: 100 meters
IP address: 192.168.0.1 (factory setting);
Selectable with PC Configurator Software (model: PMCFG)
Port No.: 502
Ethernet indicator LED: Link, Link100, COL

INPUT SPECIFICATIONS

Frequency: 50 / 60 Hz (45 – 65 Hz)
• **Voltage Input**
Rated voltage
•**Between lines**: 400 V AC
•**Line-neutral (phase voltage)**: 230 V (single-phase / 2-wire and 3-wire)
Input burden: ≤ U_{LN}^2 / 300 kΩ / phase
Overload capacity: 200 % of rating for 10 sec., 120 % continuous
Selectable primary voltage range: 50 – 400 000 V
• **Current Input**
CLSE-R5: 0 – 5 A AC
CLSE-05: 0 – 50 A AC
CLSE-10: 0 – 100 A AC
CLSE-20: 0 – 200 A AC
CLSE-40: 0 – 400 A AC
CLSE-60: 0 – 600 A AC
Overload capacity: 120 % continous, 500 % for 10 sec.
Note: Use for the circuit not exceed 480 V
Selectable primary current range: 1 – 20 000 A (Using CLSE-R5 the unit is configurable only with configurator software.)
Operational range
Current: 0 – 120 % of the rating
Voltage: 10 – 120 % of the rating
Apparent power: ≤ 120 % of the rating
Active/reactive power: ±120 % of the rating
Frequency: 45 – 65 Hz
Power factor: ±1

INSTALLATION

Auxiliary power supply
•**AC**: < 9 VA
•**DC**: < 3 W
Operating temperature: -10 to +55°C (14 to 131°F)
Operating humidity: 30 to 90 %RH (non-condensing)


Atmosphere: No corrosive gas or heavy dust
Mounting: Surface or DIN rail
Weight: 500 g (1.1 lb)

PERFORMANCE


Accuracy (at 10 - 35°C or 50 - 95°F, 45 – 65 Hz)[*1]
Add the accuracy of the current sensor for overall values.
Voltage: ±0.5 % of the rating[*2]
Current: ±0.5 % of the rating[*2]
Power: ±0.5 % of the rating[*2]
Power factor: ±1.5 %
Frequency: ±0.1 % of the rating[*2]
Energy: ±1 %
Harmonic contents: ±2 % of the rating[*2]
*1. Sensor error margin not included
*2. The described accuracy levels are ensured at the input 1% or more for neutral current in a 1-phase/3-wire circuit and phase-S current in an unbalanced 3-phase/3-wire circuit.
Data update period:
Harmonic contents and frequency: ≤ 1 sec.
Other: ≤ 500 msec.
Calendar clock: (with battery backup)
Accuracy: Monthly deviation 3 minutes at 25°C
Back up period: Approx. 2 years at 25°C without power
With the power on, no battery drain
Battery: Primary lithium battery (non-removable)
Insulation resistance: ≥ 100 MΩ with 500 V DC
Dielectric strength: 1500 V AC @ 1 minute (current input or voltage input to Ethernet to auxiliary power to FE1)

EXTERNAL VIEW

■**TOP VIEW**



■**FRONT VIEW**







TERMINAL CONNECTIONS

Use the model CLSE clamp sensor for current inputs.

The figure below shows only one circuit.


A maximum of eight (8) current sensor inputs can be connected (Ch. 1 through Ch. 8).

Grounding is not required for low voltage circuits.

System / Application	Terminal	System / Application	Terminal
Single-phase / 2-wire		Three-phase / 3-wire balanced load	
Single-phase / 3-wire		Three-phase / 3-wire unbalanced load	


TERMINAL ASSIGNMENTS

• Auxiliary Power Supply, Voltage Input




No.	ID	FUNCTION
1	U(+)	Auxiliary power (+)
2	V(–)	Auxiliary power (–)
3	FE1	Power ground
4	P1	Voltage input P1
5	P2	Voltage input P2
6	P3	Voltage input P3
7	N	Voltage input N

• Current Input 2




No.	ID	FUNCTION	No.	ID	FUNCTION
1	5ch 1L	Ch.5, Current input 1L	10	5ch 1K	Ch.5, Current input 1K
2	5ch 3L	Ch.5, Current input 3L	11	5ch 3K	Ch.5, Current input 3K
3	6ch 1L	Ch.6, Current input 1L	12	6ch 1K	Ch.6, Current input 1K
4	6ch 3L	Ch.6, Current input 3L	13	6ch 3K	Ch.6, Current input 3K
5	7ch 1L	Ch.7, Current input 1L	14	7ch 1K	Ch.7, Current input 1K
6	7ch 3L	Ch.7, Current input 3L	15	7ch 3K	Ch.7, Current input 3K
7	8ch 1L	Ch.8, Current input 1L	16	8ch 1K	Ch.8, Current input 1K
8	8ch 3L	Ch.8, Current input 3L	17	8ch 3K	Ch.8, Current input 3K
9	T2	Unused	18	T1	Unused

• Current Input 1




No.	ID	FUNCTION	No.	ID	FUNCTION
1	NC	Unused	10	NC	Unused
2	1ch 1L	Ch.1, Current input 1L	11	1ch 1K	Ch.1, Current input 1K
3	1ch 3L	Ch.1, Current input 3L	12	1ch 3K	Ch.1, Current input 3K
4	2ch 1L	Ch.2, Current input 1L	13	2ch 1K	Ch.2, Current input 1K
5	2ch 3L	Ch.2, Current input 3L	14	2ch 3K	Ch.2, Current input 3K
6	3ch 1L	Ch.3, Current input 1L	15	3ch 1K	Ch.3, Current input 1K
7	3ch 3L	Ch.3, Current input 3L	16	3ch 3K	Ch.3, Current input 3K
8	4ch 1L	Ch.4, Current input 1L	17	4ch 1K	Ch.4, Current input 1K
9	4ch 3L	Ch.4, Current input 3L	18	4ch 3K	Ch.4, Current input 3K

EXTERNAL DIMENSIONS unit: mm (inch)




MOUNTING REQUIREMENTS unit: mm (inch)


■ **SINGLE MOUNTING**



■ **BASIC + EXTENSION UNIT**



SCHEMATIC CIRCUITRY & CONNECTION DIAGRAM



⚠ Specifications are subject to change without notice.