

Profile sensor
S9132

High-speed frame rate sensor capable of acquiring two-dimensional projection data

The profile sensor S9132 is a high-performance CMOS area sensor particularly intended to acquire projection data. A projection profile in the X and Y directions has very small amounts of data compared to normal area sensors and therefore allows high-speed position detection and moving object detection. S9132 also has advantages over convensional 2D PSDs (Position Sensitive Detectors) that the output linearity is improved, multiple light spots can be detected and external circuits are simplified. A timing generator, bias voltage generator and 10-bit AD converter circuits are all integrated on the same chip, allowing operations with a very simple external driver circuit and external signal processing circuit.

Features

- Sensor for acquiring 2D projection data
- High-speed frame rate: 3200 frames/s Max. (8-bit)
  1600 frames/s Max. (10-bit)
- Low power consumption
- Digital video output
- 10-bit/8-bit switchable ADC

Applications

- Light spot position detection (printers, FA inspection equipment, amusement machines)
- Moving object detection (FA inspection equipment, amusement machines)
- 3D measurement (FA inspection equipment, medical measurement)

■ Conceptual view of light spot detection



KMPDC0168EA

■ Absolute maximum ratings

Parameter	Symbol	Value	Unit
Analog supply voltage	Vdd (A)	-0.3 to +6	V
Digital supply voltage	Vdd (D)	-0.3 to +6	V
Gain selection terminal voltage	Vg	-0.3 to +6	V
AD mode selection voltage	Vsel	-0.3 to +6	V
Clock pulse voltage	V (CLK)	-0.3 to +6	V
Start pulse voltage	V (ST)	-0.3 to +6	V
Operating temperature *1	Topr	-5 to +65	°C
Storage temperature	Tstg	-10 to +85	°C

*1: No condensation

■ Shape specifications

Parameter	Value	Unit
Number of pixels	256 × 256	-
Pixel pitch	7.8	μm
Active area	1.9968 × 1.9968	mm
Package	20-pin LCC package	-
Package size	7.6 × 7.6	mm

SOLID STATE DIVISION

■ Recommended terminal voltage

Parameter		Symbol	Min.	Typ.	Max.	Unit
Analog supply voltage		Vdd (A)	4.75	5	5.25	V
Digital supply voltage *2		Vdd (D)	3	5	Vdd (A)	V
Gain selection terminal voltage	High gain	Vg	0	-	0.4	V
	Low gain		Vdd (A) -0.25	Vdd (A)	Vdd (A) +0.25	
AD mode selection voltage	10-bit MODE	Vsel	Vdd (A) -0.25	Vdd (A)	Vdd (A) +0.25	V
	8-bit MODE		0	-	0.4	
Clock pulse voltage	High level	V (CLK)	Vdd (D) -0.25	Vdd (D)	Vdd (D) +0.25	V
	Low level		0	-	0.4	
Start pulse voltage	High level	V (ST)	Vdd (D) -0.25	Vdd (D)	Vdd (D) +0.25	V
	Low level		0	-	0.4	

*2: When the latter-stage digital processing circuit is a 3.3 V family, the high level of digital output signal is 3.3 V when operated at Vdd (A)=5 V, Vdd (D)=3.3 V.

■ Electrical characteristics (Ta=25 °C)

Parameter		Symbol	Min.	Typ.	Max.	Unit
Clock pulse frequency *3	10-bit MODE	f (CLK)	500	-	5 M	Hz
	8-bit MODE		500	-	10 M	
Start pulse intervals		T (ST)	3101/f (CLK)	-	-	s
Video data rate		VR	-	f (CLK)/12	-	Hz
Digital output voltage	High level	VDO (H)	Vdd (D)-0.15	-	-	V
	Low level	VDO (L)	-	-	0.15	
Digital output rise time (10 to 90 %)*4	CL=10 pF	tr	-	-	30	ns
	CL=30 pF		-	-	60	
Digital output fall time (10 to 90 %)*4	CL=10 pF	tf	-	-	30	ns
	CL=30 pF		-	-	60	
Power consumption *5		P	-	75	-	mW

*3: Vdd (A)=Vdd (D)=5 V, V (CLK)=V (ST)=5 V, Vg=5 V (Low gain)
*4: CL: Load capacitance of digital output terminal
*5: Vdd (A)=Vdd (D)=5 V, V (CLK)=V (ST)=V (ST)=5 V, f (CLK)=5 MHz, f (ST)=1.5 kHz

■ Electrical and optical characteristics [Ta=25 °C, Vdd (A)=Vdd (D)=5 V, V (CLK)=V (ST)=5 V]

Parameter		Symbol	Min.	Typ.	Max.	Unit
Spectral response range		λ	380 to 1000			nm
Peak sensitivity wavelength		λp	-	500	-	nm
Photo sensitivity *6	High gain	RES	-	40	-	V/nJ
	Low gain		-	8	-	
Dark current		ID	-	0.2	0.6	pA
Saturation charge		Qsat	-	8	-	pC
Feedback capacitance of charge amplifier *7	High gain	Cf	-	0.2	-	pF
	Low gain		-	1	-	
Dark output voltage *8	High gain	Vd	-	100	300	mV
	Low gain		-	20	60	
Saturation output voltage	High gain	Vsat	2.5	3.5	-	V
	Low gain		2.5	3	-	
Photo response non-uniformity *9		PRNU	-	-	±10	%

*6: Vg=5 V (Low gain), Vg=0 V (High gain)
*7: λ=780 nm
*8: Storage time Ts=100 ms
*9: Uniformity is defined under the condition that the device is uniformly illuminated by light which is 50 % of the saturation exposure level and using 254 pixels excluding both ends pixels as follows:
PRNU=ΔV/V × 100 (%)
X: the average output of all pixels, ΔX: the difference from the maximum or minimum output and X

■ Spectral response (typical example)



■ A/D converter characteristics (Ta=25 °C)

Parameter		Symbol	Value	Unit
Digital output format			Serial output	
Resolution *10	10-bit MODE	RESO	10	bit
	8-bit MODE		8	
Conversion time		tCON	12/f (CLK)	s/ch
Frame readout time		FR	3100/f (CLK)	s/f
Conversion voltage range *11			0 to 3.8	V

*10: Vsel=5 V (10-bit mode), Vsel=0 V (8-bit mode)

*11: Digital output is available from MSB as serial output.
10-bit mode: D9 to D0
8-bit mode: D7 to D0

■ Timing chart



Parameter	Symbol	Min.	Typ.	Max.	Unit
Clock pulse width	tpw (CLK)	40	-	-	ns
Clock pulse rise and fall time	tr (CLK), tf (CLK)	0	20	30	ns
Start pulse width	tpw (ST)	90	-	-	ns
Start pulse rise and fall time	tr (ST), tr (ST)	0	20	30	ns

NOTE) Operation in the X and Y directions can be performed independently.
The internal timing circuit starts operating at the fall timing of the clock pulse immediately after the start pulse goes "low". It doesn't matter how many times the clock pulse goes “low” during the "Low" period of the start pulse.
The storage time is determined by the start pulse intervals. However, scince the charge storage of each pixel is carried out between the signal readout of that pixel and the next signal readout of the same pixel, the start time of charge storage differs depending on each pixel. In addition, the next start pulse cannot be input until signal readout from all pixels is completed.

8-bit mode

● In the neighborhood of start pixel



● In the neighborhood of last pixel



KMPDC0173EA

10-bit mode

● In the neighborhood of start pixel



● In the neighborhood of last pixel



KMPDC0174EA

■ Block diagram



KMPDC0175EA

■ Connection examples



KMPDC0176EB

■ Dimensional outline (unit: mm)



■ Pin connection

Pin No.	Symbol	I/O	Function
1	Vsel (X)	I	AD mode selection voltage
2	Vg (X)	I	Gain selection voltage
3	ST (X)	I	Start pulse
4	CLK (X)	I	Clock pulse
5	EOS (X)	O	End of scan pulse
6	CLK (Y)	I	Clock pulse
7	ST (Y)	I	Start pulse
8	Vdd (A)	I	Analog supply voltage
9	Vg (Y)	I	Gain selection voltage
10	Vsel (Y)	I	AD mode selection voltage
11	Vss (A)	I	Analog ground
12	Vss (D)	I	Digital ground
13	Trig (Y)	O	Trigger pulse
14	DO (Y)	O	Digital output
15	Vdd (D)	I	Digital supply voltage
16	NC		No connection
17	DO (X)	O	Digital output
18	Trig (X)	O	Trigger pulse
19	EOC (X)	O	End of conversion pulse
20	Vss (A)	I	Analog ground

Profile sensor mounted on terminal pitch conversion board S9132-01

S9132-01 is a profile sensor mounted on a terminal pitch conversion board having 1-inch (2.54 mm) pitch output terminals.

■ Dimensional outline (unit: mm)



HAMAMATSU

Information furnished by HAMAMATSU is believed to be reliable. However, no responsibility is assumed for possible inaccuracies or omissions.
Specifications are subject to change without notice. No patent rights are granted to any of the circuits described herein. ©2004 Hamamatsu Photonics K.K.

HAMAMATSU PHOTONICS K.K., Solid State Division
1126-1 Ichino-cho, Higashi-ku, Hamamatsu City, 435-8558 Japan, Telephone: (81) 53-434-3311, Fax: (81) 53-434-5184, http://www.hamamatsu.com
U.S.A.: Hamamatsu Corporation: 360 Foothill Road, P.O.Box 6910, Bridgewater, N.J. 08807-0910, U.S.A., Telephone: (1) 908-231-0960, Fax: (1) 908-231-1218
Germany: Hamamatsu Photonics Deutschland GmbH: Arzbergerstr. 10, D-82211 Herrsching am Ammersee, Germany, Telephone: (49) 08152-3750, Fax: (49) 08152-2658
France: Hamamatsu Photonics France S.A.R.L.: 19, Rue du Saule Trapu, Parc du Moulin de Massy, 91882 Massy Cedex, France, Telephone: 33-(1) 69 53 71 00, Fax: 33-(1) 69 53 71 10
United Kingdom: Hamamatsu Photonics UK Limited: 2 Howard Court, 10 Tewin Road, Welwyn Garden City, Hertfordshire AL7 1BW, United Kingdom, Telephone: (44) 1707-294888, Fax: (44) 1707-325777
North Europe: Hamamatsu Photonics Norden AB: Smidesvägen 12, SE-171 41 Solna, Sweden, Telephone: (46) 8-509-031-00, Fax: (46) 8-509-031-01
Italy: Hamamatsu Photonics Italia S.R.L.: Strada della Moia, 1/E, 20020 Arese, (Milano), Italy, Telephone: (39) 02-935-81-733, Fax: (39) 02-935-81-741

Cat. No. KMPD1075E05
Dec. 2004 DN