PCM1789 24-Bit, 192-kHz Sampling, Enhanced Multi-Level ΔΣ, Stereo, Audio Digital-to-Analog Converter

1 Features

- Enhanced Multi-Level Delta-Sigma DAC:
  - High Performance: Differential, f_S = 48 kHz
  - THD+N: –94 dB
  - SNR: 113 dB
  - Dynamic Range: 113 dB
  - Sampling Rate: 8 kHz to 192 kHz
  - System Clock: 128 f_S, 192 f_S, 256 f_S, 384 f_S, 512 f_S, 768 f_S, 1152 f_S
  - Differential Voltage Output: 8 V_{PP}
  - Analog Low-Pass Filter Included
  - 4x/8x Oversampling Digital Filter:
    - Passband Ripple: ±0.0018 dB
    - Stop Band Attenuation: –75 dB
  - Zero Flags (16-, 20-, 24-Bits)
- Flexible Audio Interface:
  - I/F Format: I^2S, Left-/Right-Justified, DSP
  - Data Length: 16, 20, 24, 32 Bits
- Flexible Mode Control:
  - 3-Wire SPI, 2-Wire I^2C-Compatible Serial Control Interface, or Hardware Control
  - Connect Up To 4 Devices on One SPI Bus
- Multi Functions via SPI or I^2C I/F:
  - Audio I/F Format Select: I^2S, Left-Justified, Right-Justified, DSP
  - Digital Attenuation and Soft Mute
  - Digital De-Emphasis: 32kHz, 44.1kHz, 48kHz
  - Data Polarity Control
  - Power-Save Mode
- Multi Functions via Hardware Control:
  - Audio I/F Format Select: I^2S, Left-Justified
  - Digital De-Emphasis Filter: 44.1kHz
- Analog Mute by Clock Halt Detection
- External Reset Pin
- Power Supplies:
  - 5 V for Analog and 3.3 V for Digital
- Package: TSSOP-24
- Operating Temperature Range: –40°C to 85°C

2 Applications

- Blu-ray Disc™ Players
- DVD Players
- AV Receivers
- Home Theaters
- Car Audio External Amplifiers
- Car Audio AVN Applications

3 Description

The PCM1789 is a high-performance, single-chip, 24-bit, stereo, audio digital-to-analog converter (DAC) with differential outputs. The two-channel, 24-bit DAC employs an enhanced multi-level, delta-sigma (ΔΣ) modulator, and supports 8 kHz to 192 kHz sampling rates and a 16-, 20-, 24-, 32-bit width digital audio input word on the audio interface. The audio interface of PCM1789 supports a 24-bit, DSP format in addition to I^2S, left-justified, and right-justified formats.


The PCM1789 can be controlled through a three-wire, SPI-compatible or two-wire, I^2C-compatible serial interface in software, which provides access to all functions including digital attenuation, soft mute, de-emphasis, and so forth. Also, hardware control mode provides two user-programmable functions through two control pins. The PCM1789 is available in a 24-pin TSSOP package.

Device Information(1)

PART NUMBER	PACKAGE	BODY SIZE (NOM)
PCM1789	TSSOP (24)	4.40 mm x 7.80 mm

(1) For all available packages, see the orderable addendum at the end of the data sheet.

PCM1789 Typical Application



An IMPORTANT NOTICE at the end of this data sheet addresses availability, warranty, changes, use in safety-critical applications, intellectual property matters and other important disclaimers. PRODUCTION DATA.

Table of Contents

1 Features ... 1
2 Applications ... 1
3 Description ... 1
4 Revision History ... 2
5 Pin Configuration and Functions ... 3
6 Specifications ... 4
6.1 Absolute Maximum Ratings ... 4
6.2 ESD Ratings ... 4
6.3 Recommended Operating Conditions ... 4
6.4 Thermal Information ... 5
6.5 Electrical Characteristics: Digital Input/Output ... 5
6.6 Electrical Characteristics: DAC ... 6
6.7 Electrical Characteristics: Power-Supply Requirements ... 7
6.8 System Clock Timing Requirements ... 7
6.9 Audio Interface Timing Requirements ... 7
6.10 Three-Wire Timing Requirements ... 8
6.11 SCL and SDA Timing Requirements ... 8
6.12 Typical Characteristics ... 9
7 Detailed Description ... 13
7.1 Overview ... 13
7.2 Functional Block Diagram ... 13
7.3 Feature Description ... 13
7.4 Device Functional Modes ... 18
7.5 Register Maps ... 23
8 Application and Implementation ... 29
8.1 Application Information ... 29
8.2 Typical Application ... 31
8.3 Application Curve ... 32
9 Power Supply Recommendations ... 32
10 Layout ... 33
10.1 Layout Guidelines ... 33
10.2 Layout Example ... 33
11 Device and Documentation Support ... 34
11.1 Documentation Support ... 34
11.2 Community Resources ... 34
11.3 Trademarks ... 34
11.4 Electrostatic Discharge Caution ... 34
11.5 Glossary ... 34
12 Mechanical, Packaging, and Orderable Information ... 34

4 Revision History

NOTE: Page numbers for previous revisions may differ from page numbers in the current version.

Changes from Revision A (January 2009) to Revision B **Page**

- Added *ESD Ratings* table, *Feature Description* section, *Device Functional Modes* section, *Application and Implementation* section, *Power Supply Recommendations* section, *Layout* section, *Device and Documentation Support* section, and *Mechanical, Packaging, and Orderable Information* section. ... 1


Changes from Original (October 2008) to Revision A **Page**

- Changed Figure 39 ... 31

Copyright © 2008–2015, Texas Instruments Incorporated

5 Pin Configuration and Functions

PW Package
24-Pin TSSOP
Top View



Pin Functions

PIN		I/O	PULL-DOWN	5-V TOLERANT	DESCRIPTION
NAME	NO.				
LRCK	1	I	Yes	No	Audio data word clock input
BCK	2	I	Yes	No	Audio data bit clock input
DIN	3	I	No	No	Audio data input
RST	4	I	Yes	Yes	Reset and power-down control input with active low
SCKI	5	I	No	Yes	System clock input
VDD	6	—	—	—	Digital power supply, +3.3 V
DGND	7	—	—	—	Digital ground
VCC1	8	—	—	—	Analog power supply 1, +5 V
VCOM	9	—	—	—	Voltage common decoupling
AGND1	10	—	—	—	Analog ground 1
VOUTL–	11	O	No	No	Negative analog output from DAC left channel
VOUTL+	12	O	No	No	Positive analog output from DAC left channel
VOUTR+	13	O	No	No	Positive analog output from DAC right channel
VOUTR–	14	O	No	No	Negative analog output from DAC right channel
AGND2	15	—	—	—	Analog ground 2
VCC2	16	—	—	—	Analog power supply 2, +5 V
AMUTEI	17	I	No	Yes	Analog mute control input with active low
ZERO2/AMUTEO	18	O	No	No	Zero detect flag output 2/Analog mute control output(1) with active low
ZERO1	19	O	No	No	Zero detect flag output 1
MODE	20	I	No	No	Control port mode selection. Tied to VDD: SPI, ADR6 = 1, pull-up: SPI, ADR6 = 0, pull-down: H/W auto mode, tied to DGND: I^2C
MD/SDA/DEMP	21	I/O	No	Yes	Input data for SPI, data for I^2C(1), de-emphasis control for hardware control mode
MC/SCL/FMT	22	I	No	Yes	Clock for SPI, clock for I^2C, format select for hardware control mode
MS/ADR0/RSV	23	I	Yes	Yes	Chip Select for SPI, address select 0 for I^2C, reserve (set low) for hardware control mode
ADR5/ADR1/RSV	24	I	No	Yes	Address select 5 for SPI, address select 1 for I^2C, reserve (set low) for hardware control mode

(1) Open-drain configuration in out mode.

Copyright © 2008–2015, Texas Instruments Incorporated

6 Specifications

6.1 Absolute Maximum Ratings

over operating free-air temperature range (unless otherwise noted)(1)

		MIN	MAX	UNIT
Supply voltage	VCC1, VCC2	–0.3	6.5	V
	VDD	–0.3	4.0	
Ground voltage differences	AGND1, AGND2, DGND		±0.1	V
Supply voltage differences	VCC1, VCC2		0.1	V
Digital input voltage	RST, ADR5, MS, MC, MD, SCKI, AMUTEI	–0.3	6.5	V
	BCK, LRCK, DIN, MODE, ZERO1, ZERO2	–0.3	(VDD + 0.3) < +4.0	
Analog input voltage	VCOM, VOUTL±, VOUTR±	–0.3	(VCC + 0.3) < +6.5	V
Input current (all pins except supplies)			±10	mA
Ambient temperature under bias		–40	125	°C
Junction temperature			150	°C
Package temperature (IR reflow, peak)			260	°C
Storage temperature, T_{stg}		–55	150	°C

(1) Stresses beyond those listed under *Absolute Maximum Ratings* may cause permanent damage to the device. These are stress ratings only, which do not imply functional operation of the device at these or any other conditions beyond those indicated under *Recommended Operating Conditions*. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

6.2 ESD Ratings

			VALUE	UNIT
$V_{(ESD)}$	Electrostatic discharge	Human-body model (HBM), per ANSI/ESDA/JEDEC JS-001(1)	±1000	V
		Charged-device model (CDM), per JEDEC specification JESD22-C101(2)	±250	

(1) JEDEC document JEP155 states that 500-V HBM allows safe manufacturing with a standard ESD control process.
(2) JEDEC document JEP157 states that 250-V CDM allows safe manufacturing with a standard ESD control process.

6.3 Recommended Operating Conditions

over operating free-air temperature range (unless otherwise noted)

		MIN	NOM	MAX	UNIT
Analog supply voltage, VCC		4.5	5.0	5.5	V
Digital supply voltage, VDD		3.0	3.3	3.6	V
Digital Interface		LVTTL-compatible			
Digital input clock frequency	Sampling frequency, LRCK	8		192	kHz
	System clock frequency, SCKI	2.048		36.864	MHz
Analog output voltage	Differential		8		V_{PP}
Analog output load resistance	To ac-coupled GND	5			kΩ
	To dc-coupled GND	15			
Analog output load capacitance				50	pF
Digital output load capacitance				20	pF
Operating free-air temperature	PCM1789 consumer grade	–40	25	85	°C

Copyright © 2008–2015, Texas Instruments Incorporated

6.4 Thermal Information

THERMAL METRIC(1)		PCM1789 PW (TSSOP) 24 PINS	UNIT
$R_{\theta JA}$	Junction-to-ambient thermal resistance	87.8	°C/W
$R_{\theta JC(top)}$	Junction-to-case (top) thermal resistance	19.3	°C/W
$R_{\theta JB}$	Junction-to-board thermal resistance	42.6	°C/W
ψ_{JT}	Junction-to-top characterization parameter	0.5	°C/W
ψ_{JB}	Junction-to-board characterization parameter	42.1	°C/W
$R_{\theta JC(bot)}$	Junction-to-case (bottom) thermal resistance	n/a	°C/W

(1) For more information about traditional and new thermal metrics, see the *Semiconductor and IC Package Thermal Metrics* application report, SPRA953.

6.5 Electrical Characteristics: Digital Input/Output

All specifications at T_A = +25°C, VCC1 = VCC2 = 5 V, VDD = 3.3 V, f_S = 48 kHz, SCKI = 512 f_S, 24-bit data, and Sampling mode = Auto, unless otherwise noted.

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
DATA FORMAT						
f_S	Sampling frequency		8	48	192	kHz
	System clock frequency	128 f_S, 192 f_S, 256 f_S, 384 f_S, 512 f_S, 768 f_S, 1152 f_S	2.048		36.864	MHz
INPUT LOGIC						
	LOGIC FAMILY					
V_{IH}	Input logic level, high (BCK, LRCK, and DIN)		2.0		VDD	VDC
V_{IL}	Input logic level, low (BCK, LRCK, and DIN)				0.8	VDC
V_{IH}	Input logic current, high (SCKI, ADR5/ADR1/RSV, MC/SCL/FMT, MD/SDA?DEMP, and AMUTEI)		2.0		5.5	VDC
V_{IL}	Input logic current, low (SCKI, ADR5/ADR1/RSV, MC/SCL/FMT, MD/SDA/DEMP, and AMUTEI)				0.8	VDC
I_{IH}	Input logic current, high (DIN, SCKI, ADR5/ADR1/RSV, MC/SCL/FMT, MD/SDA/DEMP, and AMUTEI)	V_{IN} = VDD			±10	µA
I_{IL}	Input logic current, low (DIN, SCKI, ADR5/ADR1/RSV, MC/SCL/FMT, MD/SDA/DEMP, and AMUTEI)	V_{IN} = 0 V			±10	µA
I_{IH}	Input logic current, high (BCK, LRCK, RST, MS/ADR0/RSV)	V_{IN} = VDD		+65	+100	µA
	Input logic current, low (BCK, LRCK, RST, MS/ADR0/RSV)	V_{IN} = 0 V			±10	µA
OUTPUT LOGIC						
V_{OH}	Output logic level, high (ZERO1 and ZERO2)	I_{OUT} = –4 mA	2.4			VDC
V_{OL}	Output logic level, high (ZERO1 and ZERO2)	I_{OUT} = +4 mA			0.4	VDC
REFERENCE OUTPUT						
	VCOM output voltage			0.5 × VCC1		V
	VCOM output impedance			7.5		kΩ
	Allowable VCOM output source/sink current				1	µA

Copyright © 2008–2015, Texas Instruments Incorporated

6.6 Electrical Characteristics: DAC

All specifications at T_A = +25°C, VCC1 = VCC2 = 5 V, VDD = 3.3 V, f_S = 48 kHz, SCKI = 512 f_S, 24-bit data, and Sampling mode = Auto, unless otherwise noted.

PARAMETER		TEST CONDITIONS		MIN	TYP	MAX	UNIT
RESOLUTION				16	24		Bits
DC ACCURACY							
	Gain mismatch channel-to-channel			x	±2.0	±6.0	% of FSR
	Gain error				±2.0	±6.0	% of FSR
	Bipolar zero error				±1.0		% of FSR
DYNAMIC PERFORMANCE(1) (2)							
THD+N	Total harmonic distortion + noise	V_{OUT} = 0 dB	f_S = 48 kHz		–94	–88	dB
			f_S = 96 kHz		–94		dB
			f_S = 192 kHz		–94		dB
	Dynamic range	f_S = 48 kHz, EIAJ, A-weighted		106	113		dB
		f_S = 96 kHz, EIAJ, A-weighted			113		dB
		f_S = 192 kHz, EIAJ, A-weighted			113		dB
SNR	Signal-to-noise ratio	f_S = 48 kHz, EIAJ, A-weighted		106	113		dB
		f_S = 96 kHz, EIAJ, A-weighted			113		dB
		f_S = 192 kHz, EIAJ, A-weighted			113		dB
	Channel separation	f_S = 48 kHz		103	109		dB
		f_S = 96 kHz			109		dB
		f_S = 192 kHz			108		dB
ANALOG OUTPUT							
	Output voltage	Differential			1.6 × VCC1		V_{PP}
	Center voltage				0.5 × VCC1		V
	Load impedance	To ac-coupled GND(3)		5			kΩ
		To dc-coupled GND(3)		15			kΩ
	LPF frequency response	f = 20 kHz			–0.04		dB
		f = 44 kHz			–0.18		dB
DIGITAL FILTER PERFORMANCE WITH SHARP ROLL-OFF							
	Passband (single, dual)	Except SCKI = 128 f_S and 192 f_S				0.454 × f_S	Hz
		SCKI = 128 f_S and 192 f_S				0.432 × f_S	Hz
	Passband (quad)					0.432 × f_S	Hz
	Stop band (single, dual)	Except SCKI = 128 f_S and 192 f_S		0.546 × f_S			Hz
		SCKI = 128 f_S and 192 f_S		0.569 × f_S			Hz
	Stop band (quad)			0.569 × f_S			Hz
	Passband ripple	< 0.454 × f_S, 0.432 × f_S				±0.0018	dB
	Stop band attenuation	> 0.546 × f_S, 0.569 × f_S		–75			dB
DIGITAL FILTER PERFORMANCE WITH SLOW ROLL-OFF							
	Passband					0.328 × f_S	Hz
	Stop band			0.673 × f_S			Hz
	Passband ripple	< 0.328 × f_S				±0.0013	dB
	Stop band attenuation	> 0.673 × f_S		–75			dB
DIGITAL FILTER PERFORMANCE							
	Group delay time (single, dual)	Except SCKI = 128 f_S and 192 f_S			28/f_S		sec
		SCKI = 128 f_S and 192 f_S			19/f_S		sec
	Group delay time (quad)				19/f_S		sec
	De-emphasis error				±0.1		dB

(1) In differential mode at VOUTx± pin, f_{OUT} = 1 kHz, using Audio Precision System II, Average mode with 20-kHz LPF and 400-Hz HPF.
(2) f_S = 48 kHz: SCKI = 512 f_S (single), f_S = 96 kHz : SCKI = 256 f_S (dual), f_S = 192 kHz : SCKI = 128 f_S (quad).
(3) Allowable minimum input resistance of differential-to-single-ended converter with D-to-S gain = G is calculated as (1 + 2G)/(1 + G) × 5k for ac-coupled, and (1+ 0.9G)/(1 + G) × 15k for dc-coupled connection; refer to Figure 37 and Figure 38.

Copyright © 2008–2015, Texas Instruments Incorporated

6.7 Electrical Characteristics: Power-Supply Requirements

All specifications at T_A = +25°C, VCC1 = VCC2 = 5 V, VDD = 3.3 V, f_S = 48 kHz, SCKI = 512 f_S, 24-bit data, and Sampling mode = Auto, unless otherwise noted.

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
POWER-SUPPLY REQUIREMENTS						
VCC1/2	Voltage range		4.5	5.0	5.5	VDC
VDD			3.0	3.3	3.6	VDC
I_{CC}	Supply current	f_S = 48 kHz		19	28	mA
		f_S = 192 kHz		19		mA
		Full power-down(1)		170		µA
I_{DD}		f_S = 48 kHz		18	30	mA
		f_S = 192 kHz		22		mA
		Full power-down(1)		60		µA
	Power dissipation	f_S = 48 kHz		154	239	mW
		f_S = 192 kHz		168		mW
		Full power-down(1)		1.05		mW
TEMPERATURE RANGE						
	Operating temperature	PCM1789 consumer grade	–40		+85	°C
θ_{JA}	Thermal resistance	TSSOP-24		115		°C/W

(1) SCKI, BCK, and LRCK stopped.

6.8 System Clock Timing Requirements

(see Figure 19)

		MIN	NOM	MAX	UNIT
t_{SCY}	System clock cycle tiime	27			ns
t_{SCH}	Syst4em clock width high	10			ns
t_{SCL}	System clock width low	10			ns
—	System clock duty cycle	40%	60%		

6.9 Audio Interface Timing Requirements

(see Figure 35)

		MIN	NOM	MAX	UNIT
t_{BCY}	BCK cycle time	75			ns
t_{BCH}	BCK pulse width high	35			ns
t_{BCL}	BCK pulse width low	35			ns
t_{LRW}	LRCK pulse width high (LJ, RJ and I^2S formats)	1/(2 × f_S)		1/(2 × f_S)	s
	LRCK pulse width high (DSP format)	t_{BCY}		t_{BCY}	s
t_{LRS}	LRCK setup time to BCK rising edge	10			ns
t_{LRH}	LRCK hold time to BCK rising edge	10			ns
t_{DIS}	DIN setup time to BCK rising edge	10			ns
t_{DIH}	DIN hold time to BCK rising edge	10			ns

Copyright © 2008–2015, Texas Instruments Incorporated

6.10 Three-Wire Timing Requirements

(See Figure 24)

		MIN	NOM	MAX	UNIT
t_{MCY}	MC pulse cycle time	100			ns
t_{MCL}	MC low-level time	40			ns
t_{MCH}	MC high-level time	40			ns
t_{HCH}	MS high-level time	t_{MCY}			ns
t_{MSS}	MS falling edge to MC rising edge	30			ns
t_{MHS}	MS rising edge from MC rising edge for LSB	15			ns
t_{MDH}	MS hold time	15			ns
t_{MDS}	MD setup time	15			ns

6.11 SCL and SDA Timing Requirements

(See Figure 1)

		STANDARD MODE		FAST MODE		UNIT
		MIN	MAX	MIN	MAX	
f_{SCL}	SCL clock frequency		100		400	kHz
t_{BUF}	Bus free time between STOP and START condition	4.7		1.3		µs
t_{LOW}	Low period of the SCL clock	4.7		1.3		µs
t_{HI}	High period of the SCL clock	4.0		0.6		µs
t_{S-SU}	Setup time for START/Repeated START condition	4.7		0.6		µs
t_{S-HD}	Hold time for START/Repeated START condition	4.0		0.6		µs
t_{D-SU}	Data setup time	250		100		ns
t_{D-HD}	Data hold time	0	3450	0	900	ns
t_{SCL-R}	Rise time of SCL signal		1000	20 + 0.1 C_B	300	ns
t_{SCL-F}	Fall time of SCL signal		1000	20 + 0.1 C_B	300	ns
t_{SDA-R}	Rise time of SDA signal		1000	20 + 0.1 C_B	300	ns
t_{SDA-F}	Fall time of SDA signal		1000	20 + 0.1 C_B	300	ns
t_{P-SU}	Setup time for STOP condition	4.0		0.6		µs
t_{GW}	Allowable glitch width		N/A		50	ns
C_B	Capacitive load for SDA and SCL line		400		100	pF
V_{NH}	Noise margin at high level for each connected device(including hysteresis)	0.2 × VDD		0.2 × VDD		V
V_{NL}	Noise margin at low level for each connected device (including hysteresis)	0.1 × VDD		0.1 × VDD		V
V_{HYS}	Hysteresis of Schmitt trigger input	N/A		0.05 × VDD		V




Figure 1. SCL and SDA Control Interface Timing

Copyright © 2008–2015, Texas Instruments Incorporated

6.12 Typical Characteristics

6.12.1 Digital Filter

All specifications at T_A = 25°C, VCC1 = VCC2 = 5 V, VDD = 3.3 V, f_S = 48 kHz, SCKI = 512 f_S, 24-bit data, and Sampling mode = Auto, unless otherwise noted.




Figure 2. Frequency Response (Single Rate)




Figure 3. Frequency Response Passband (Single Rate)




Figure 4. Frequency Response (Dual Rate)




Figure 5. Frequency Response Passband (Dual Rate)




Figure 6. Frequency Response (Quad Rate)





Figure 7. Frequency Response Passband (Quad Rate)

Copyright © 2008–2015, Texas Instruments Incorporated


6.12.2 Digital De-Emphasis Filter

All specifications at T_A = +25°C, VCC1 = VCC2 = 5 V, VDD = 3.3 V, f_S = 48 kHz, SCKI = 512 f_S, 24-bit data, and Sampling mode = Auto, unless otherwise noted.




f_S = 48 kHz

Figure 8. De-emphasis Characteristic



f_S = 44.1 kHz

Figure 9. De-emphasis Characteristic



f_S = 32 kHz

Figure 10. De-emphasis Characteristic




Figure 11. Analog Filter Characteristic

Copyright © 2008–2015, Texas Instruments Incorporated

6.12.3 Dynamic Performance

All specifications at T_A = +25°C, VCC1 = VCC2 = 5 V, VDD = 3.3 V, f_S = 48 kHz, SCKI = 512 f_S, 24-bit data, and Sampling mode = Auto, unless otherwise noted.




Figure 12. Total Harmonic Distortion + Noise vs Temperature




Figure 13. Dynamic Range and Signal-to-Noise Ratio vs Temperature




Figure 14. Total Harmonic Distortion + Noise vs Supply Voltage





Figure 15. Dynamic Range and Signal-to-Noise Ratio vs Supply Voltage

Copyright © 2008–2015, Texas Instruments Incorporated


6.12.4 Output Spectrum

All specifications at T_A = +25°C, VCC1 = VCC2 = 5 V, VDD = 3.3 V, f_S = 48 kHz, SCKI = 512 f_S, 24-bit data, and Sampling mode = Auto, unless otherwise noted.




0 dB, N = 32768

Figure 16. Output Spectrum



–60 dB, N = 32768

Figure 17. Output Spectrum



BPZ, N = 32768

Figure 18. Output Spectrum

Copyright © 2008–2015, Texas Instruments Incorporated


7 Detailed Description

7.1 Overview

The PCM1789 is a high-performance stereo DAC targeted for consumer audio applications such as Blu-ray Disc players and DVD players, as well as home multi-channel audio applications (such as home theater and A/V receivers). The PCM1789 consists of a two-channel DAC. The DAC output type is fixed with a differential configuration. The PCM1789 supports 16-, 20-, 24-, 32-bit linear PCM input data in I^2S and left-justified audio formats, and 24-bit linear PCM input data in right-justified and DSP formats with various sampling frequencies from 8 kHz to 192 kHz. The PCM1789 offers three modes for device control: two-wire I^2C software, three-wire SPI software, and hardware.

- **Audio data interface formats:** I^2S, LJ, RJ, DSP
- **Audio data word length:** 16, 20, 24, 32 Bits
- **Audio data format:** MSB first, twos complement

7.2 Functional Block Diagram



7.3 Feature Description

7.3.1 Analog Outputs

The PCM1789 includes a two-channel DAC, with a pair of differential voltage outputs pins. The full-scale output voltage is (1.6 × VCC1) V_{PP} in differential output mode. A dc-coupled load is allowed in addition to an ac-coupled load, if the load resistance conforms to the specification. These balanced outputs are each capable of driving 0.8 VCC1 (4 V_{PP}) typical into a 5-kΩ ac-coupled or 15-kΩ dc-coupled load with VCC1 = +5 V. The internal output amplifiers for VOUTL and VOUTR are biased to the dc common voltage, equal to 0.5 VCC1.

The output amplifiers include an RC continuous-time filter that helps to reduce the out-of-band noise energy present at the DAC outputs as a result of the noise shaping characteristics of the PCM1789 delta-sigma (ΔΣ) DACs. The frequency response of this filter is shown in the *Analog Filter Characteristic* (Figure 11) of the *Typical Characteristics*. By itself, this filter is not enough to attenuate the out-of-band noise to an acceptable level for most applications. An external low-pass filter is required to provide sufficient out-of-band noise rejection. Further discussion of DAC post-filter circuits is provided in the *Application Information* section.

Copyright © 2008–2015, Texas Instruments Incorporated

Feature Description (continued)

7.3.2 Voltage Reference VCOM

The PCM1789 includes a pin for the common-mode voltage output, VCOM. This pin should be connected to the analog ground via a decoupling capacitor. This pin can also be used to bias external high-impedance circuits, if they are required.

7.3.3 System Clock Input

The PCM1789 requires an external system clock input applied at the SCKI input for DAC operation. The system clock operates at an integer multiple of the sampling frequency, or f_S. The multiples supported in DAC operation include 128 f_S, 192 f_S, 256 f_S, 384 f_S, 512 f_S, 768 f_S, and 1152 f_S. Details for these system clock multiples are shown in Table 1. The *System Clock Timing Requirements* table shows the SCKI timing requirements.

Table 1. System Clock Frequencies for Common Audio Sampling Rates

DEFAULT SAMPLING MODE	SAMPLING FREQUENCY, f_S (kHz)	SYSTEM CLOCK FREQUENCY (MHz)						
		128 f_S	192 f_S	256 f_S	384 f_S	512 f_S	768 f_S	1152 f_S
Single rate	8	N/A	N/A	2.0480	3.0720	4.0960	6.1440	9.2160
	16	2.0480	3.0720	4.0960	6.1440	8.1920	12.2880	18.4320
	32	4.0960	6.1440	8.1920	12.2880	16.3840	24.5760	36.8640
	44.1	5.6448	8.4672	11.2896	16.9344	22.5792	33.8688	N/A
	48	6.1440	9.2160	12.2880	18.4320	24.5760	36.8640	N/A
Dual rate	88.2	11.2896	16.9344	22.5792	33.8688	N/A	N/A	N/A
	96	12.2880	18.4320	24.5760	36.8640	N/A	N/A	N/A
Quad rate	176.4	22.5792	33.8688	N/A	N/A	N/A	N/A	N/A
	192	24.5760	36.8640	N/A	N/A	N/A	N/A	N/A




Figure 19. System Clock Timing Diagram

7.3.4 Reset Operation

The PCM1789 has both an internal power-on reset circuit and an external reset circuit. The sequences for both reset circuits are shown in Figure 20 and Figure 21. Figure 20 illustrates the timing at the internal power-on reset. Initialization is triggered automatically at the point where VDD exceeds 2.2 V typical, and the internal reset is released after 3846 SCKI clock cycles from power-on, if RST is held high and SCKI is provided. VOUTx from the DAC is forced to the VCOM level initially (that is, 0.5 × VCC1) and settles at a specified level according to the rising VCC. If synchronization among SCKI, BCK, and LRCK is maintained, VOUT provides an output that corresponds to DIN after 3846 SCKI clocks from power-on. If the synchronization is not held, the internal reset is not released, and both operating modes are maintained at reset and power-down states. After synchronization forms again, the DAC returns to normal operation with the previous sequences.

Figure 21 illustrates a timing diagram at the external reset. RST accepts an externally-forced reset with RST low, and provides a device reset and power-down state that achieves the lowest power dissipation state available in the PCM1789. If RST goes from high to low under synchronization among SCKI, BCK, and LRCK, the internal reset is asserted, all registers and memory are reset, and finally, the PCM1789 enters into all power-down states. At the same time, VOUT is immediately forced into the AGND1 level. To begin normal operation again, toggle RST high; the same power-up sequence is performed as the power-on reset shown in Figure 20.

Copyright © 2008–2015, Texas Instruments Incorporated

The PCM1789 does not require particular power-on sequences for VCC and VDD; it allows VDD on and then VCC on, or VCC on and then VDD on. From the viewpoint of the *Absolute Maximum Ratings*, however, simultaneous power-on is recommended for avoiding unexpected responses on VOUTx. Figure 20 illustrates the response for VCC on with VDD on.




Figure 20. Power-On-Reset Timing Requirements




Figure 21. External Reset Timing Requirements

7.3.5 ZERO Flag

The PCM1789 has two ZERO flag pins (ZERO1 and ZERO2) that can be assigned to the combinations shown in Table 2. Zero flag combinations are selected through the AZRO bit in control register 22 (16h). If the input data of all the assigned channels remain at '0' for 1024 sampling periods (LRCK clock periods), the ZERO1/2 bits are set to a high level, logic '1' state. Furthermore, if the input data of any of the assigned channels read '1', the ZERO1/2 are set to a low level, logic '0' state, immediately. Zero data detection is supported for 16-/20-/24-bit data width, but is not supported for 32-bit data width.

The active polarity of the zero flag output can be inverted through the ZREV bit in control register 22 (16h). The reset default is active high for zero detection.

In parallel hardware control mode, ZERO1 and ZERO2 are fixed with combination *A*, shown in Table 2.

Table 2. Zero Flag Outputs Combination

ZERO FLAG COMBINATION	ZERO1	ZERO2
A	Left channel	Right channel
B	Left channel or right channel	Left channel and right channel

Copyright © 2008–2015, Texas Instruments Incorporated

Note that the ZERO2 pin is multiplexed with AMUTEO pin. Selection of ZERO2 or AMUTEO can be changed through the MZSEL bit in control register 22 (16h). The default setting after reset is the selection of ZERO2.

7.3.6 AMUTE Control

The PCM1789 has an AMUTE control input, status output pins, and functionality. AMUTEI is the input control pin of the internal analog mute circuit. An AMUTEI low input causes the DAC output to cut-off from the digital input and forces it to the center level (0.5 VCC1). AMUTEO is the status output pin of the internal analog mute circuit. AMUTEO low indicates the analog mute control circuit is active because of a programmed condition (such as an SCKI halt, asynchronous detect, zero detect, or by the DAC disable command) that forces the DAC outputs to a center level. Because AMUTEI is not terminated internally and AMUTEO is an open-drain output, pull-ups by the appropriate resistors are required for proper operation.

Note that the AMUTEO pin is multiplexed with the ZERO2 pin. The desired pin is selected through the MZSEL bit in control register 22 (16h). The default setting is the selection of the ZERO2 pin.

Additionally, because the AMUTEI pin control and power-down control in register (OPEDA when high, PSMDA when low) do not function together, AMUTEI takes priority over power-down control. Therefore, power-down control is ignored during AMUTEI low, and AMUTEI low forces the DAC output to a center level (0.5 VCC1) even if power-down control is asserted.

7.3.7 Three-Wire (SPI) Serial Control

The PCM1789 includes an SPI-compatible serial port that operates asynchronously with the audio serial interface. The control interface consists of MD/SDA/DEMP, MC/SCL/FMT, and MS/ADR0/RSV. MD is the serial data input used to program the mode control registers. MC is the serial bit clock that shifts the data into the control port. MS is the select input used to enable the mode control port.

7.3.8 Control Data Word Format

All single write operations via the serial control port use 16-bit data words. Figure 22 shows the control data word format. The first bit (fixed at '0') is for write operation. After the first bit are seven other bits, labeled ADR[6:0], that set the register address for the write operation. ADR6 is determined by the status of the MODE pin. ADR5 is determined by the state of the ADR5/ADR1/RSV pin. A maximum of four PCM1789s can be connected on the same bus at any one time. Each PCM1789 responds when receiving its own register address. The eight least significant bits (LSBs), D[7:0] on MD, contain the data to be written to the register address specified by ADR[6:0].





Figure 22. Control Data Word Format for MD

7.3.9 Register Write Operation

Figure 23 shows the functional timing diagram for single write operations on the serial control port. MS is held at a high state until a register is to be written to. To start the register write cycle, MS is set to a low state. 16 clocks are then provided on MC, corresponding to the 16 bits of the control data word on MD. After the 16th clock cycle has been completed, MS is set high to latch the data into the indexed mode control register.

In addition to single write operations, the PCM1789 also supports multiple write operations, which can be performed by sending the N-bytes (where N ≤ 9) of the 8-bit register data that follow after the first 16-bit register address and register data, while keeping the MC clocks and MS at a low state. Ending a multiple write operation can be accomplished by setting MS to a high state.

Copyright © 2008–2015, Texas Instruments Incorporated



(1) X = don't care.

Figure 23. Register Write Operation

7.3.10 Timing Requirements

Figure 24 shows a detailed timing diagram for the three-wire serial control interface. These timing parameters are critical for proper control port operation.




Figure 24. Three-Wire Serial Control Interface Timing

7.3.11 Two-wire (I^2C) Serial Control

The PCM1789 supports an I^2C-compatible serial bus and data transmission protocol for fast mode configured as a slave device. This protocol is explained in the I^2C specification 2.0.

The PCM1789 has a 7-bit slave address, as shown in Figure 25. The first five bits are the most significant bits (MSBs) of the slave address and are factory-preset to 10011. The next two bits of the address byte are selectable bits that can be set by MS/ADR0/RSV and ADR5/ADR1/RSV. A maximum of four PCM1789s can be connected on the same bus at any one time. Each PCM1789 responds when it receives its own slave address.





Figure 25. Slave Address

7.3.12 Packet Protocol

A master device must control the packet protocol, which consists of a start condition, a slave address with the read/write bit, data if a write operation is required, an acknowledgment if a read operation is required, and a stop condition. The PCM1789 supports both slave receiver and transmitter functions. Details about DATA for both write and read operations are described in Figure 26.

Copyright © 2008–2015, Texas Instruments Incorporated



(1) R/$\overline{W}$: Read operation if 1; write operation otherwise.

(2) ACK: Acknowledgment of a byte if 0, not Acknowledgment of a byte if 1.

(3) DATA: Eight bits (byte); details are described in the *Write Operation* and *Read Operation* sections.

Figure 26. I^2C Packet Control Protocol

7.3.13 Write Operation

The PCM1789 supports a receiver function. A master device can write to any PCM1789 register using single or multiple accesses. The master sends a PCM1789 slave address with a write bit, a register address, and the data. If multiple access is required, the address is that of the starting register, followed by the data to be transferred. When valid data are received, the index register automatically increments by one. When the register address reaches &h4F, the next value is &h40. When undefined registers are accessed, the PCM1789 does not send an acknowledgment. Figure 27 illustrates a diagram of the write operation. The register address and write data are in 8-bit, MSB-first format.

Transmitter	M	M	M	S	M	S	M	S	M	S		S	M
Data Type	St	Slave Address	$\overline{W}$	ACK	Reg Address	ACK	Write Data 1	ACK	Write Data 2	ACK		ACK	Sp

NOTE: M = Master device, S = Slave device, St = Start condition, $\overline{W}$ = Write, ACK = Acknowledge, and Sp = Stop condition.

Figure 27. Framework for Write Operation

7.3.14 Read Operation

A master device can read the registers of the PCM1789. The value of the register address is stored in an indirect index register in advance. The master sends the PCM1789 slave address with a read bit after storing the register address. Then the PCM1789 transfers the data that the index register points to. Figure 28 shows a diagram of the read operation.

Transmitter	M	M	M	S	M	S	M	M	M	S	S	M	M
Data Type	St	Slave Address	$\overline{W}$	ACK	Reg Address	ACK	Sr	Slave Address(1)	R	ACK	Read Data	NACK	Sp

(1) The slave address after the repeated start condition must be the same as the previous slave address.

NOTE: M = Master device, S = Slave device, St = Start condition, Sr = Repeated start condition, $\overline{W}$ = Write, R = Read, ACK = Acknowledge, NACK = Not acknowledge, and Sp = Stop condition.

Figure 28. Framework for Read Operation

7.4 Device Functional Modes

7.4.1 Sampling Mode

The PCM1789 supports three sampling modes (single rate, dual rate, and quad rate) in DAC operation. In single rate mode, the DAC operates at an oversampling frequency of x128 (except when SCKI = 128 f_S and 192 f_S); this mode is supported for sampling frequencies less than 50 kHz. In dual rate mode, the DAC operates at an oversampling frequency of x64; this mode is supported for sampling frequencies less than 100 kHz. In quad rate mode, the DAC operates at an oversampling frequency of x32. The sampling mode is automatically selected according to the ratio of system clock frequency and sampling frequency by default (that is, single rate for 512 f_S, 768 f_S, and 1152 f_S; dual rate for 256 f_S and 384 f_S; and quad rate for 128 f_S and 192 f_S), but manual selection is also possible for specified combinations through the serial mode control register.

Copyright © 2008–2015, Texas Instruments Incorporated

Device Functional Modes (continued)

Table 3 and Figure 29 show the relationship among the oversampling rate (OSR) of the digital filter and ΔΣ modulator, the noise-free shaped bandwidth, and each sampling mode setting.

Table 3. Digital Filter OSR, Modulator OSR, and Noise-Free Shaped Bandwidth for Each Sampling Mode

SAMPLING MODE REGISTER SETTING	SYSTEM CLOCK FREQUENCY (xf_S)	NOISE-FREE SHAPED BANDWIDTH[1] (kHz)			DIGITAL FILTER OSR	MODULATOR OSR
		f_S = 48 kHz	f_S = 96 kHz	f_S = 192 kHz		
Auto	512, 768, 1152	40	N/A	N/A	×8	x128
	256, 384	20	40	N/A	x8	x64
	128, 192[2]	10	20	40	x4	x32
Single	512, 768, 1152	40	N/A	N/A	x8	x128
	256, 384	40	N/A	N/A	x8	x128
	128, 192[2]	20	N/A	N/A	x4	x64
Dual	256, 384	20	40	N/A	x8	x64
	128, 192[2]	20	40	N/A	x4	x64
Quad	128, 192[2]	10	20	40	x4	x32

(1) Bandwidth in which noise is shaped out.
(2) Quad mode filter characteristic is applied.




Figure 29. ΔΣ Modulator and Digital Filter Characteristic

7.4.2 Audio Serial Port Operation

The PCM1789 audio serial port consists of three signals: BCK, LRCK, and DIN. BCK is a bit clock input. LRCK is a left/right word clock or frame synchronization clock input. DIN is the audio data input for VOUTL/R.

7.4.3 Audio Data Interface Formats and Timing

The PCM1789 supports six audio data interface formats: 16-/20-/24-/32-bit I^2S, 16-/20-/24-/32-bit left-justified, 24-bit right-justified, 16-bit right-justified, 24-bit left-justified mode DSP, and 24-bit I^2S mode DSP. In the case of I^2S, left-justified, and right-justified data formats, 64 BCKs, 48 BCKs, and 32 BCKs per LRCK period are supported; however, 48 BCKs are limited to 192/384/768 f_S SCKI, and 32 BCKs are limited to 16-bit right-justified only. The audio data formats are selected by MC/SCL/FMT in hardware control mode and by the FMTDA[2:0] bits in control register 17 (11h) in software control mode. All data must be in binary twos complement and MSB first.

Table 4 summarizes the applicable formats and describes the relationships among them and the respective restrictions with mode control. Figure 30 through Figure 34 show six audio interface data formats.

Copyright © 2008–2015, Texas Instruments Incorporated

Table 4. Audio Data Interface Formats and Sampling Rate, Bit Clock, and System Clock Restrictions

CONTROL MODE	FORMAT	DATA BITS	MAX LRCK FREQUENCY (f_S)	SCKI RATE (xf_S)	BCK RATE (xf_S)
Software control	I^2S/Left-Justified	16/20/24/32(1)	192 kHz	128 to 1152(2)	64, 48
	Right-Justified	24, 16	192 kHz	128 to 1152(2)	64, 48, 32 (16 bit)(3)
	I^2S/Left-Justified DSP	24	192 kHz	128 to 768	64
Hardware control	I^2S/Left-Justified	16/20/24/32(1)	192 kHz	128 to 1152(2)	64, 48

(1) 32-bit data length is acceptable only for BCK = 64 f_S and when using I^2S or Left-Justified format.
(2) 1152 f_S is acceptable only for f_S = 32 kHz, BCK = 64 f_S, and when using I^2S, Left-Justified, or 24-bit Right-Justified format.
(3) BCK = 32 f_S is supported only for 16-bit data length.




Figure 30. Audio Data Format: 16-/20-/24-/32-Bit I^2S (N = 15/19/23/31, M = 14/18/22/30, and L = 13/17/21/29)




Figure 31. Audio Data Format: 16-/20-/24-/32-Bit Left-Justified (N = 15/19/23/31, M = 14/18/22/30, and L = 13/17/21/29)




Figure 32. Audio Data Format: 24-Bit Right-Justified




Figure 33. Audio Data Format: 16-Bit Right-Justified

Copyright © 2008–2015, Texas Instruments Incorporated




Figure 34. Audio Data Format: 24-Bit DSP Format

7.4.4 Audio Interface Timing

Figure 35 and *Audio Interface Timing Requirements* describe the detailed audio interface timing specifications.




Figure 35. Audio Interface Timing Diagram for Left-Justified, Right-Justified, I²S, and DSP Data Formats

7.4.5 Synchronization with the Digital Audio System

The PCM1789 operates under the system clock (SCKI) and the audio sampling rate (LRCK). Therefore, SCKI and LRCK must have a specific relationship. The PCM1789 does not need a specific phase relationship between the audio interface clocks (LRCK, BCK) and the system clock (SCKI), but does require a specific frequency relationship (ratiometric) between LRCK, BCK, and SCKI.

If the relationship between SCKI and LRCK changes more than ±2 BCK clocks because of jitter, sampling frequency change, etc., the DAC internal operation stops within $1/f_S$, and the analog output is forced into VCOM (0.5 VCC1) until re-synchronization among SCKI, LRCK, and BCK completes, and then either $38/f_S$ (single, dual rate) or $29/f_S$ (quad rate) passes. In the event the change is less than ±2 BCKs, re-synchronization does not occur, and this analog output control and discontinuity does not occur.

Figure 36 shows the DAC analog output during loss of synchronization. During undefined data periods, some noise may be generated in the audio signal. Also, the transition of normal to undefined data and undefined (or zero) data to normal data creates a discontinuity of data on the analog outputs, which may then generate some noise in the audio signal.

The DAC outputs (VOUTx) hold the previous state if the system clock halts, but the asynchronous and re-synchronization processes will occur after the system clock resumes.

Copyright © 2008–2015, Texas Instruments Incorporated




Figure 36. DAC Outputs During Loss of Synchronization

7.4.6 MODE Control

The PCM1789 includes three mode control interfaces with three oversampling configurations, depending on the input state of the MODE pin, as shown in Table 5. The pull-up and pull-down resistors must be 220 kΩ ±5%.

Table 5. Interface Mode Control Selection

MODE	MODE CONTROL INTERFACE
Tied to DGND	Two-wire (I^2C) serial control, selectable oversampling configuration
Pull-down resistor to DGND	Two-wire parallel control, auto mode oversampling configuration
Pull-up resistor to VDD	Three-wire (SPI) serial control, selectable oversampling configuration, ADR6 = '0'
Tied to VDD	Three-wire (SPI) serial control, selectable oversampling configuration, ADR6 = '1'

The input state of the MODE pin is sampled at the moment of power-on, or during a low-to-high transition of the RST pin, with the system clock input. Therefore, input changes after reset are ignored until the next power-on or reset. From the mode control selection described in Table 5, the functions of four pins are changed, as shown in Table 6.

Table 6. Pin Functions for Interface Mode

PIN	PIN ASSIGNMENTS		
	SPI	I^2C	H/W
21	MD (input)	SDA (input/output)	DEMP (input)
22	MC (input)	SCL (input)	FMT (input)
23	MS (input)	ADR0 (input)	RSV (input, low)
24	ADR5 (input)	ADR1 (input)	RSV (input, low)

In serial mode control, the actual mode control is performed by register writes (and reads) through the SPI- or I^2C-compatible serial control port. In parallel mode control, two specific functions are controlled directly through the high/low control of two specific pins, as described in the following section.

7.4.7 Parallel Hardware Control

The functions shown in Table 7 and Table 8 are controlled by two pins, DEMP and FMT, in parallel hardware control mode. The DEMP pin controls the 44.1-kHz digital de-emphasis function of both channels. The FMT pin controls the audio interface format for both channels.

Table 7. DEMP Functionality

DEMP	DESCRIPTION
Low	De-emphasis off
High	44.1 kHz de-emphasis on

Table 8. FMT Functionality

FMT	DESCRIPTION
Low	16-/20-/24-/32-bit I^2S format
High	16-/20-/24-/32-bit left-justified format

Copyright © 2008–2015, Texas Instruments Incorporated

7.5 Register Maps

7.5.1 Control Register Definitions (Software Mode Only)

The PCM1789 has many user-programmable functions that are accessed via control registers, and are programmed through the SPI or I^2C serial control port. Table 9 shows the available mode control functions along with reset default conditions and associated register addresses. Table 10 lists the register map.

Table 9. User-Programmable Mode Control Functions

FUNCTION	RESET DEFAULT	REGISTER(1)	LABEL
Mode control register reset	Normal operation	16	MRST
System reset	Normal operation	16	SRST
Analog mute function control	Mute disabled	16	AMUTE[3:0]
Sampling mode selection	Auto	16	SRDA[1:0]
Power-save mode selection	Power save	17	PSMDA
Audio interface format selection	I^2S	17	FMTDA[2:0]
Operation control	Normal operation	18	OPEDA
Digital filter roll-off control	Sharp roll-off	18	FLT
Output phase selection	Normal	19	REVDA[2:1]
Soft mute control	Mute disabled	20	MUTDA[2:1]
Zero flag	Not detected	21	ZERO[2:1]
Digital attenuation mode	0 dB to –63 dB, 0.5-dB step	22	DAMS
Digital de-emphasis function control	Disabled	22	DEMP[1:0]
AMUTEO/ZERO flag selection	ZERO2	22	MZSEL
Zero flag function selection	ZERO1: left-channel ZERO2: right-channel	22	AZRO
Zero flag polarity selection	High for detection	22	ZREV
Digital attenuation level setting	0 dB, no attenuation	24, 25	ATDAx[7:0]

(1) If ADR6 or ADR5 is high, the register address must be changed to the number shown + offset; offset is 32, 64 and 96 according to state of ADR6, 5 (01, 10 and 11).

Table 10. Register Map

ADR[6:0](1)		DATA[7:0]							
DEC	HEX	B7	B6	B5	B4	B3	B2	B1	B0
16	10	MRST	SRST	AMUTE3	AMUTE2	AMUTE1	AMUTE0	SRDA1	SRDA0
17	11	PSMDA	RSV(2)	RSV(2)	RSV(2)	RSV(2)	FMTDA2	FMTDA1	FMTDA0
18	12	RSV(2)	RSV(2)	RSV(2)	OPEDA	RSV(2)	RSV(2)	RSV(2)	FLT
19	13	RSV(2)	RSV(2)	RSV(2)	RSV(2)	RSV(2)	RSV(2)	REVDA2	REVDA1
20	14	RSV(2)	RSV(2)	RSV(2)	RSV(2)	RSV(2)	RSV(2)	MUTDA2	MUTDA1
21	15	RSV(2)	RSV(2)	RSV(2)	RSV(2)	RSV(2)	RSV(2)	ZERO2	ZERO1
22	16	DAMS	RSV(2)	DEMP1	DEMP0	MZSEL	RSV(2)	AZRO	ZREV
23	17	RSV(2)	RSV(2)	RSV(2)	RSV(2)	RSV(2)	RSV(2)	RSV(2)	RSV(2)
24	18	ATDA17	ATDA16	ATDA15	ATDA14	ATDA13	ATDA12	ATDA11	ATDA10
25	19	ATDA27	ATDA26	ATDA25	ATDA24	ATDA23	ATDA22	ATDA21	ATDA20

(1) If ADR6 or ADR5 is high, the register address must be changed to the number shown + offset; offset is 32, 64 and 96 according to state of ADR6, 5 (01, 10 and 11).
(2) RSV must be set to '0'.

Copyright © 2008–2015, Texas Instruments Incorporated

7.5.2 Register Definitions

DEC	HEX	B7	B6	B5	B4	B3	B2	B1	B0
16	10	MRST	SRST	AMUTE3	AMUTE2	AMUTE1	AMUTE0	SRDA1	SRDA0

MRST

Mode control register reset

This bit sets the mode control register reset to the default value. Pop noise may be generated. Returning the MRST bit to '1' is unnecessary because it is automatically set to '1' after the mode control register is reset.

Default value = 1.

MRST	Mode control register reset
0	Set default value
1	Normal operation (default)

SRST

System reset

This bit controls the system reset, which includes the resynchronization between the system clock and sampling clock, and DAC operation restart. The mode control register is not reset and the PCM1789 does not go into a power-down state. Returning the SRST bit to '1' is unnecessary; it is automatically set to '1' after triggering a system reset.

Default value = 1.

SRST	System reset
0	Resynchronization
1	Normal operation (default)

AMUTE[3:0]

Analog mute function control

These bits control the enabling/disabling of each source event that triggers the analog mute control circuit.

Default value = 0000.

AMUTE	Analog mute function control
xxx0	Disable analog mute control by SCKI halt
xxx1	Enable analog mute control by SCKI halt
xx0x	Disable analog mute control by asynchronous detect
xx1x	Enable analog mute control by asynchronous detect
x0xx	Disable analog mute control by ZERO1 and ZERO2 detect
x1xx	Enable analog mute control by ZERO1 and ZERO2 detect
0xxx	Disable analog mute control by DAC disable command
1xxx	Enable analog mute control by DAC disable command

SRDA[1:0]

Sampling mode selection

These bits control the sampling mode of DAC operation. In Auto mode, the sampling mode is automatically set according to multiples between the system clock and sampling clock: single rate for 512 f_S, 768 f_S, and 1152 f_S, dual rate for 256 f_S or 384 f_S, and quad rate for 128 f_S and 192 f_S.

Default value = 00.

SRDA	Sampling mode selection
00	Auto (default)
01	Single rate
10	Dual rate
11	Quad rate

DEC	HEX	B7	B6	B5	B4	B3	B2	B1	B0
17	11	PSMDA	RSV	RSV	RSV	RSV	FMTDA2	FMTDA1	FMTDA0

PSMDA

Power-save mode selection

This bit selects the power-save mode for the OPEDA function. When PSMDA = 0, OPEDA controls the power-save mode and normal operation. When PSMDA = 1, OPEDA functions controls the DAC disable (not power-save mode) and normal operation.

Default value: 0.

PSMDA	Power-save mode selection
0	Power-save enable mode (default)
1	Power-save disable mode

Copyright © 2008–2015, Texas Instruments Incorporated

RSV	**Reserved** Reserved; do not use.
FMTDA[2:0]	**Audio interface format selection** These bits control the audio interface format for DAC operation. Details of the format and any related restrictions with the system clock are described in the *Audio Data Interface Formats and Timing* section. Default value: 0000 (16-/20-/24-/32-bit I^2S format).

FMTDA	Audio interface format selection
000	16-/20-/24-/32-bit I^2S format (default)
001	16-/20-/24-/32-bit left-justified format
010	24-bit right-justified format
011	16-bit right-justified format
100	24-bit I^2S mode DSP format
101	24-bit left-justified mode DSP format
110	Reserved
111	Reserved

DEC	HEX	B7	B6	B5	B4	B3	B2	B1	B0
18	12	RSV	RSV	RSV	OPEDA	RSV	RSV	RSV	FLT

RSV	**Reserved** Reserved; do not use.
OPEDA	**Operation control** This bit controls the DAC operation mode. In operation disable mode, the DAC output is cut off from DIN and the internal DAC data are reset. If PSMDA = 1, the DAC output is forced into VCOM. If PSMDA = 0, the DAC output is forced into AGND and the DAC goes into a power-down state. For normal operating mode, this bit must be '0'. The serial mode control is effective during operation disable mode. Default value: 0.

OPEDA	Operation control
0	Normal operation
1	Operation disable with or without power save

FLT	**Digital filter roll-off control** This bit allows users to select the digital filter roll-off that is best suited to their applications. Sharp and slow filter roll-off selections are available. The filter responses for these selections are shown in the *Typical Characteristics* sections of this data sheet. Default value: 0.

FLT	Digital filter roll-off control
0	Sharp roll-off
1	Slow roll-off

DEC	HEX	B7	B6	B5	B4	B3	B2	B1	B0
19	13	RSV	RSV	RSV	RSV	RSV	RSV	REVDA2	REVDA1

RSV	**Reserved** Reserved; do not use.
REVDA[2:1]	**Output phase selection** These bits are used to control the phase of the DAC analog signal outputs. Default value: 00.

REVDA	Output phase selection
x0	Left channel normal output
x1	Left channel inverted output
0x	Right channel normal output
1x	Right channel inverted output

Copyright © 2008–2015, Texas Instruments Incorporated

DEC	HEX	B7	B6	B5	B4	B3	B2	B1	B0
20	14	RSV	RSV	RSV	RSV	RSV	RSV	MUTDA2	MUTDA1

RSV	**Reserved** Reserved; do not use.
MUTDA[2:1]	**Soft Mute control** These bits are used to enable or disable the Soft Mute function for the corresponding DAC outputs, VOUTx. The Soft Mute function is incorporated into the digital attenuators. When mute is disabled (MUTDA[2:1] = 0), the attenuator and DAC operate normally. When mute is enabled by setting MUTDA[2:1] = 1, the digital attenuator for the corresponding output is decreased from the current setting to infinite attenuation. By setting MUTDA[2:1] = 0, the attenuator is increased to the last attenuation level in the same manner as it is for decreasing levels. This configuration reduces *pop and zipper noise* during muting of the DAC output. This Soft Mute control uses the same resource of digital attenuation level setting. Mute control has priority over the digital attenuation level setting. Default value: 00.

MUTDA	Soft Mute control
x0	Left channel mute disabled
x1	Left channel mute enabled
0x	Right channel mute disabled
1x	Right channel mute enabled

DEC	HEX	B7	B6	B5	B4	B3	B2	B1	B0
21	15	RSV	RSV	RSV	RSV	RSV	RSV	ZERO2	ZERO1

RSV	**Reserved** Reserved; do not use.
ZERO[2:1]	**Zero flag (read-only)** These bits indicate the present status of the zero detect circuit for each DAC channel; these bits are read-only.

ZERO	Zero flag
x0	Left channel zero input not detected
x1	Left channel zero input detected
0x	Right channel zero input not detected
1x	Right channel zero input detected

DEC	HEX	B7	B6	B5	B4	B3	B2	B1	B0
22	16	DAMS	RSV	DEMP1	DEMP0	MZSEL	RSV	AZRO	ZREV

DAMS	**Digital attenuation mode** This bit selects the attenuation mode. Default value: 0.

DAMS	Digital attenuation mode
0	Fine step: 0.5-dB step for 0 dB to –63 dB range (default)
1	Wide range: 1-dB step for 0 dB to –100 dB range

RSV	**Reserved** Reserved; do not use.
DEMP[1:0]	**Digital de-emphasis function/sampling rate control** These bits are used to disable and enable the various sampling frequencies of the digital de-emphasis function. Default value: 00.

DEMP	Digital de-emphasis function/sampling rate control
00	Disable (default)
01	48 kHz enable
10	44.1 kHz enable
11	32 kHz enable

MZSEL	**AMUTEO/ZERO flag selection** This bit is used to select the function of the ZERO2 pin.

Copyright © 2008–2015, Texas Instruments Incorporated

	Default value: 0.	
	MZSEL	**AMUTEO/ZERO flag selection**
	0	The ZERO2 pin functions as ZERO2 (default).
	1	The ZERO2 pin functions as AMUTEO.
AZRO	**Zero flag channel combination selection** This bit is used to select the zero flag channel combination for ZERO1 and ZERO2. Default value: 0.	
	AZRO	**Zero flag combination selection**
	0	Combination A: ZERO1 = left channel, ZERO2 = right channel (default)
	1	Combination B: ZERO1 = left channel or right channel, ZERO2 = left channel and right channel
ZREV	**Zero flag polarity selection** This bit controls the polarity of the zero flag pin. Default value: 0.	
	ZREV	**Zero flag polarity selection**
	0	High for zero detect (default)
	1	Low for zero detect

DEC	HEX	B7	B6	B5	B4	B3	B2	B1	B0
23	17	RSV	RSV	RSV	RSV	RSV	RSV	RSV	RSV
24	18	ATDA17	ATDA16	ATDA15	ATDA14	ATDA13	ATDA12	ATDA11	ATDA10
25	19	ATDA27	ATDA26	ATDA25	ATDA24	ATDA23	ATDA22	ATDA21	ATDA20

RSV	**Reserved** Reserved; do not use.
ATDAx[7:0]	**Digital attenuation level setting** Where *x* = 1 to 2, corresponding to the DAC output (VOUTx). Both DAC outputs (VOUTL and VOUTR) have a digital attenuation function. The attenuation level can be set from 0 dB to R dB, in S-dB steps. Changes in attenuator levels are made by incrementing or decrementing one step (S dB) for every $8/f_S$ time interval until the programmed attenuator setting is reached. Alternatively, the attenuation level can be set to infinite attenuation (or mute). R (range) and S (step) is –63 and 0.5 for DAMS = 0, and –100 and 1.0 for DAMS = 1, respectively. The DAMS bit is defined in register 22 (16h). Table 11 shows attenuation levels for various settings. The attenuation level for each channel can be set individually using the following formula: Attenuation level (dB) = S × (ATDAx[7:0]$_{DEC}$ – 255) where ATDAx[7:0]$_{DEC}$ = 0 through 255. For ATDAx[7:0]$_{DEC}$ = 0 through 128 with DAMS = 0, or 0 through 154 with DAMS = 1, attenuation is set to infinite attenuation (mute). Default value: 1111 1111.

Copyright © 2008–2015, Texas Instruments Incorporated

Table 11. Attenuation Levels for Various Settings

ATDAx[7:0]		ATTENUATION LEVEL SETTING	
BINARY	DECIMAL	DAMS = 0	DAMS = 1
1111 1111	255	0 dB, no attenuation (default)	0 dB, no attenuation (default)
1111 1110	254	–0.5 dB	–1 dB
1111 1101	253	–1.0 dB	–2 dB
...	...	...	...
1001 1100	156	–45.9 dB	–99 dB
1001 1011	155	–50.0 dB	–100 dB
1001 1010	154	–50.5 dB	Mute
...	...	...	...
1000 0010	130	–62.5 dB	Mute
1000 0001	129	–63.0 dB	Mute
0000 0000	128	Mute	Mute
...	...	...	...
0000 0000	0	Mute	Mute

Copyright © 2008–2015, Texas Instruments Incorporated

8 Application and Implementation

NOTE

Information in the following applications sections is not part of the TI component specification, and TI does not warrant its accuracy or completeness. TI's customers are responsible for determining suitability of components for their purposes. Customers should validate and test their design implementation to confirm system functionality.

8.1 Application Information

8.1.1 Connection Diagrams

A basic connection diagram is shown in Figure 39, with the necessary power-supply bypassing and decoupling components. Texas Instruments' PLL170X is used to generate the system clock input at SCKI, as well as to generate the clock for the audio signal processor. The use of series resistors (22 Ω to 100 Ω) are recommended for SCKI, LRCK, BCK, and DIN for electromagnetic interference (EMI) reduction.

8.1.2 Power Supply and Grounding

The PCM1789 requires +5 V for the analog supply and +3.3 V for the digital supply. The +5-V supply is used to power the DAC analog and output filter circuitry, and the +3.3-V supply is used to power the digital filter and serial interface circuitry. For best performance, it is recommended to use a linear regulator (such as the REG101-5/33, REG102-5/33, or REG103-5/33) with the +5-V and +3.3-V supplies.

Five capacitors are required for supply bypassing, as shown in Figure 39. These capacitors should be located as close as possible to the PCM1789 package. The 10-µF capacitors are aluminum electrolytic, while the three 1-µF capacitors are ceramic.

8.1.3 Low-Pass Filter and Differential-to-Single-Ended Converter For DAC Outputs


ΔΣ DACs use noise-shaping techniques to improve in-band signal-to-noise ratio (SNR) performance at the expense of generating increased out-of-band noise above the Nyquist frequency, or $f_S/2$. The out-of-band noise must be low-pass filtered in order to provide optimal converter performance. This filtering is accomplished by a combination of on-chip and external low-pass filters.

Figure 37 and Figure 38 show the recommended external differential-to-single-ended converter with low-pass active filter circuits for ac-coupled and dc-coupled applications. These circuits are second-order Butterworth filters using a multiple feedback (MFB) circuit arrangement that reduces sensitivity to passive component variations over frequency and temperature. For more information regarding MFB active filter designs, please refer to Applications Bulletin SBAA055, *Dynamic Performance Testing of Digital Audio D/A Converters*, available from the TI web site (www.ti.com) or your local Texas Instruments' sales office.

Because the overall system performance is defined by the quality of the DACs and the associated analog output circuitry, high-quality audio op amps are recommended for the active filters. Texas Instruments' OPA2134, OPA2353, and NE5532A dual op amps are shown in Figure 37 and Figure 38, and are recommended for use with the PCM1789.


Copyright © 2008–2015, Texas Instruments Incorporated

Application Information (continued)



NOTE: Amplifier is an NE5532A x 1/2 or OPA2134 x1/2; R_1 = 7.5 kΩ; R_2 = 5.6 kΩ; R_3 = 360 Ω; C_1 = 3300 pF; C_2 = 680 pF; Gain = 0.747;
$f_{-3\ dB}$ = 53 kHz.

Figure 37. AC-Coupled, Post-LPF and Differential to Single-Ended Buffer




NOTE: Amplifier is an NE5532A x 1/2 or OPA2134 x1/2; R_1 = 15 kΩ; R_2 = 11 kΩ; R_3 = 820 Ω; C_1 = 1500 pF; C_2 = 330 pF; Gain = 0.733;
$f_{-3\ dB}$ = 54 kHz.

Figure 38. DC-Coupled, Post-LPF and Differential to Single-Ended Buffer

Copyright © 2008–2015, Texas Instruments Incorporated

8.2 Typical Application



NOTE: C_1 through C_3 are 1-µF ceramic capacitors. C_4 through C_6 are 10-µF electrolytic capacitors. R_1 through R_4 are 22-Ω to 100-Ω resistors. R_5 is a resistor appropriate for pull-up. R_6 is a 220-kΩ resistor, ±5%. An appropriate resistor is required for pull-up, if ZERO2/AMUTEO pin is used as AMUTEO.

Figure 39. Basic Connection Diagram

8.2.1 Design Requirements

- Control: Hardware, I^2C, or SPI
- Audio Input: PCM Serial Data, TDM, or DSP
- Audio Output: (1.6 × VCC1) Vpp Analog Audio Biased to (0.5 × VCC1) V
- Master Clock: PLL170X IC

8.2.2 Detailed Design Procedure

8.2.2.1 Hardware Control Method

There are 3 ways to control the PCM1789, hardware control, SPI, or I^2C. Hardware control will provide a limited access to control features available in the PCM1789 but can be implemented with pull up and pull downs, or with GPIO of a microcontroller. Control via SPI or I^2C will provide access to all control registers and features but will require a digital device that can implement SPI or I^2C.

Typical Application (continued)

8.2.2.2 Audio Input

For Audio Input there are 3 options, PCM serial data, TDM, or DSP. All three will support the same quality of audio data, but having these 3 options to match the audio sources available outputs allows for greater flexibility. This selection is made by configuring the MODE pin which is detailed in Table 9 and shown in .

8.2.2.3 Audio Output

The output of the PCM1789 will produce a differential (1.6 × VCC1) Vpp signal at full scale into a 5-kΩ load, that should be filtered before being sent to an amplifier. Outputs V_{OUT1} through V_{OUT8} will be biased at (0.5 × VCC1) V.

8.2.2.4 Master Clock

The master clock can come from wither a dedicated IC such as the PLL170X series, a crystal or the audio source IC. What is important is that the audio source and the PCM1789 are driven from the same source so that the audio clocks will be synchronous.

8.3 Application Curve




Figure 40. Frequency Response (Single Rate)

9 Power Supply Recommendations

The PCM1789 requires 5 V for the analog supply and 3.3 V for the digital supply. The +5-V supply is used to power the DAC analog and output filter circuitry, and the +3.3-V supply is used to power the digital filter and serial interface circuitry. For best performance, it is recommended to use a linear regulator (such as the REG101-5/33, REG102-5/33, or REG103-5/33) with the +5-V and +3.3-V supplies.

Five capacitors are required for supply bypassing, as shown in Figure 39. These capacitors should be located as close as possible to the PCM1789 package. The 10-µF capacitors are aluminum electrolytic, while the three 1-µF capacitors are ceramic.

Copyright © 2008–2015, Texas Instruments Incorporated

10 Layout

10.1 Layout Guidelines

A typical printed circuit board (PCB) layout for the PCM1789 is shown in Figure 41. A ground plane is recommended, with the analog and digital sections being isolated from one another using a split or cut in the circuit board. The PCM1789 should be oriented with the digital I/O pins facing the ground plane split/cut to allow for short, direct connections to the digital audio interface and control signals originating from the digital section of the board.

Separate power supplies are recommended for the digital and analog sections of the board. This configuration prevents the switching noise present on the digital supply from contaminating the analog power supply and degrading the dynamic performance of the PCM1789.

10.2 Layout Example




Figure 41. Recommended PCB Layout

11 Device and Documentation Support

11.1 Documentation Support

11.1.1 Related Documentation

For related documentation, see the following:

- *Dynamic Performance Testing of Digital Audio D/A Converters*, SBAA055
- PLL1700 *3.3-V Dual-PLL Multiclock Generator*, SBOS096
- REG101 *DMOS 100 mA Low-Dropout Regulator*, SBVS026
- REG102 *DMOS 250 mA Low-Dropout Regulator*, SBVS024
- REG103 *DMOS 500 mA Low-Dropout Regulator*, SBVS010
- OPAx134 *SoundPlus™ High Performance Audio Operational Amplifiers*, SBOS058
- OPAx353 *High-Speed, Single-Supply, Rail-to-Rail Op Amps MicroAmplifier™ Series*, SBOS103
- *NE5532x, SA5532x Dual Low-Noise Operational Amplifiers*, SLOS075

11.2 Community Resources

The following links connect to TI community resources. Linked contents are provided "AS IS" by the respective contributors. They do not constitute TI specifications and do not necessarily reflect TI's views; see TI's Terms of Use.

TI E2E™ Online Community ***TI's Engineer-to-Engineer (E2E) Community.*** Created to foster collaboration among engineers. At e2e.ti.com, you can ask questions, share knowledge, explore ideas and help solve problems with fellow engineers.

Design Support ***TI's Design Support*** Quickly find helpful E2E forums along with design support tools and contact information for technical support.

11.3 Trademarks

E2E is a trademark of Texas Instruments.
Blu-ray Disc is a trademark of Blu-ray Disc Association.
All other trademarks are the property of their respective owners.

11.4 Electrostatic Discharge Caution



These devices have limited built-in ESD protection. The leads should be shorted together or the device placed in conductive foam during storage or handling to prevent electrostatic damage to the MOS gates.

11.5 Glossary

SLYZ022 — *TI Glossary*.

This glossary lists and explains terms, acronyms, and definitions.

12 Mechanical, Packaging, and Orderable Information

The following pages include mechanical, packaging, and orderable information. This information is the most current data available for the designated devices. This data is subject to change without notice and revision of this document. For browser-based versions of this data sheet, refer to the left-hand navigation.

Copyright © 2008–2015, Texas Instruments Incorporated

PACKAGING INFORMATION

Orderable Device	Status (1)	Package Type	Package Drawing	Pins	Package Qty	Eco Plan (2)	Lead/Ball Finish (6)	MSL Peak Temp (3)	Op Temp (°C)	Device Marking (4/5)	Samples
PCM1789PW	ACTIVE	TSSOP	PW	24	60	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-2-260C-1 YEAR	-40 to 85	PCM1789	Samples
PCM1789PWG4	ACTIVE	TSSOP	PW	24	60	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-2-260C-1 YEAR	-40 to 85	PCM1789	Samples
PCM1789PWR	ACTIVE	TSSOP	PW	24	2000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-2-260C-1 YEAR	-40 to 85	PCM1789	Samples
PCM1789PWRG4	ACTIVE	TSSOP	PW	24	2000	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-2-260C-1 YEAR	-40 to 85	PCM1789	Samples

(1) The marketing status values are defined as follows:
ACTIVE: Product device recommended for new designs.
LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.
NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.
PREVIEW: Device has been announced but is not in production. Samples may or may not be available.
OBSOLETE: TI has discontinued the production of the device.

(2) Eco Plan - The planned eco-friendly classification: Pb-Free (RoHS), Pb-Free (RoHS Exempt), or Green (RoHS & no Sb/Br) - please check http://www.ti.com/productcontent for the latest availability information and additional product content details.
TBD: The Pb-Free/Green conversion plan has not been defined.
Pb-Free (RoHS): TI's terms "Lead-Free" or "Pb-Free" mean semiconductor products that are compatible with the current RoHS requirements for all 6 substances, including the requirement that lead not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, TI Pb-Free products are suitable for use in specified lead-free processes.
Pb-Free (RoHS Exempt): This component has a RoHS exemption for either 1) lead-based flip-chip solder bumps used between the die and package, or 2) lead-based die adhesive used between the die and leadframe. The component is otherwise considered Pb-Free (RoHS compatible) as defined above.
Green (RoHS & no Sb/Br): TI defines "Green" to mean Pb-Free (RoHS compatible), and free of Bromine (Br) and Antimony (Sb) based flame retardants (Br or Sb do not exceed 0.1% by weight in homogeneous material)

(3) MSL, Peak Temp. - The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

(4) There may be additional marking, which relates to the logo, the lot trace code information, or the environmental category on the device.

(5) Multiple Device Markings will be inside parentheses. Only one Device Marking contained in parentheses and separated by a "~" will appear on a device. If a line is indented then it is a continuation of the previous line and the two combined represent the entire Device Marking for that device.

(6) Lead/Ball Finish - Orderable Devices may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead/Ball Finish values may wrap to two lines if the finish value exceeds the maximum column width.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

OTHER QUALIFIED VERSIONS OF PCM1789 :


- Automotive: PCM1789-Q1

NOTE: Qualified Version Definitions:


- Automotive - Q100 devices qualified for high-reliability automotive applications targeting zero defects

TAPE AND REEL INFORMATION

REEL DIMENSIONS




TAPE DIMENSIONS



A0	Dimension designed to accommodate the component width
B0	Dimension designed to accommodate the component length
K0	Dimension designed to accommodate the component thickness
W	Overall width of the carrier tape
P1	Pitch between successive cavity centers


QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
PCM1789PWR	TSSOP	PW	24	2000	330.0	16.4	6.95	8.3	1.6	8.0	16.0	Q1


TAPE AND REEL BOX DIMENSIONS



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
PCM1789PWR	TSSOP	PW	24	2000	367.0	367.0	38.0


PW (R–PDSO–G24) PLASTIC SMALL OUTLINE



4040064–6/G 02/11

NOTES:
A. All linear dimensions are in millimeters. Dimensioning and tolerancing per ASME Y14.5M–1994.
B. This drawing is subject to change without notice.
C. Body length does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0,15 each side.
D. Body width does not include interlead flash. Interlead flash shall not exceed 0,25 each side.
E. Falls within JEDEC MO–153

PW (R–PDSO–G24) PLASTIC SMALL OUTLINE



NOTES:
A. All linear dimensions are in millimeters.
B. This drawing is subject to change without notice.
C. Publication IPC–7351 is recommended for alternate design.
D. Laser cutting apertures with trapezoidal walls and also rounding corners will offer better paste release. Customers should contact their board assembly site for stencil design recommendations. Refer to IPC–7525 for other stencil recommendations.
E. Customers should contact their board fabrication site for solder mask tolerances between and around signal pads.

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as “components”) are sold subject to TI’s terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI’s terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers’ products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers’ products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI’s goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or “enhanced plastic” are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have ***not*** been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components as meeting ISO/TS16949 requirements, mainly for automotive use. In any case of use of non-designated products, TI will not be responsible for any failure to meet ISO/TS16949.

Products		**Applications**	
Audio	www.ti.com/audio	Automotive and Transportation	www.ti.com/automotive
Amplifiers	amplifier.ti.com	Communications and Telecom	www.ti.com/communications
Data Converters	dataconverter.ti.com	Computers and Peripherals	www.ti.com/computers
DLP® Products	www.dlp.com	Consumer Electronics	www.ti.com/consumer-apps
DSP	dsp.ti.com	Energy and Lighting	www.ti.com/energy
Clocks and Timers	www.ti.com/clocks	Industrial	www.ti.com/industrial
Interface	interface.ti.com	Medical	www.ti.com/medical
Logic	logic.ti.com	Security	www.ti.com/security
Power Mgmt	power.ti.com	Space, Avionics and Defense	www.ti.com/space-avionics-defense
Microcontrollers	microcontroller.ti.com	Video and Imaging	www.ti.com/video
RFID	www.ti-rfid.com		
OMAP Applications Processors	www.ti.com/omap	**TI E2E Community**	e2e.ti.com
Wireless Connectivity	www.ti.com/wirelessconnectivity		

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2015, Texas Instruments Incorporated