

Flexible Termination System (FT-CAP), X7R Dielectric, 6.3 – 100 VDC, VW 80808 Specification

Overview

KEMET's Flexible Termination (FT-CAP) multilayer ceramic capacitor in X7R dielectric incorporates a unique, flexible termination system that is integrated with KEMET's standard termination materials. A conductive silver epoxy is utilized between the base metal and nickel barrier layers of KEMET's standard termination system in order to establish pliability while maintaining terminal strength, solderability and electrical performance. This technology was developed in order to address the primary failure mode of MLCCs— flex cracks, which are typically the result of excessive tensile and shear stresses produced during board flexure and thermal cycling. Flexible termination technology inhibits the transfer of board stress to the rigid ceramic body, therefore mitigating flex cracks which can result in low IR or short circuit failures.

Although this technology does not eliminate the potential for mechanical damage that may propagate during extreme environmental and handling conditions, it does provide superior flex performance over standard termination systems.

Combined with the stability of an X7R dielectric, these flex-robust devices are RoHS Compliant, offer a 5 mm minimum of flex-bend and exhibit a predictable change in capacitance with respect to time and voltage. Capacitance change with reference to ambient temperature is limited to $\pm 15\%$ from -55°C to $+125^{\circ}\text{C}$.

In addition of these devices meeting the Automotive Electronics Council's AEC-Q200 qualification requirements, the VW80808 (VW/AUDI) Specification approval is also part of this robust product offering



Ordering Information

C	1206	X	106	K	4	R	A	C	3316
Ceramic	Case Size (L" x W")	Specification/ Series	Capacitance Code (pF)	Capacitance Tolerance	Rated Voltage (VDC)	Dielectric	Failure Rate/ Design	Termination Finish	Packaging/Grade (C-Spec) ¹
	0603 0805 1206 1210	X = Flexible Termination	Two significant digits + number of zeros	J = $\pm 5\%$ K = $\pm 10\%$ M = $\pm 20\%$	9 = 6.3 8 = 10 4 = 16 3 = 25 5 = 50 1 = 100	R = X7R	A = N/A	C = 100% Matte Sn	3316 = 7" Reel Unmarked 3317 = 13" Reel Unmarked

¹ Additional reeling or packaging options may be available. Contact KEMET for details.

Table 1 – Capacitance Range/Selection Waterfall (0603 – 1210 Case Sizes)

Capacitance Code	0603					0805					1206					1210				
	6.3 V 10 V 16 V	25 V	50 V	100 V	6.3 V 10 V 16 V	25 V	50 V	100 V	6.3 V 10 V 16 V	25 V	50 V	100 V	6.3 V 10 V 16 V	25 V	50 V	100 V	6.3 V 10 V 16 V	25 V	50 V	100 V
Product Availability and Chip Thickness Codes – See Table 2 for Chip Thickness Dimensions																				
100	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
110	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
120	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
130	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
150	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
160	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
180	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
200	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
220	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
240	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
270	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
300	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
330	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
360	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
390	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
430	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
470	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
510	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
560	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
620	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
680	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
750	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
820	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
910	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
101	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
111	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
121	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
131	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
151	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
181	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
221	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
271	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
331	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
391	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
471	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
561	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
681	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
821	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
102	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
122	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
152	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
182	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
222	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
272	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
332	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
392	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
472	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
562	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
682	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
822	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
103	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
123	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
153	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
183	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
223	CD	CD	CD	CD	DR	DR	DR	DR	DR	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
273	CD	CD	CD		DR	DR	DR	DD	DS	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
333	CD	CD	CD		DR	DR	DR	DD	DS	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
393	CD	CD	CD		DR	DR	DR	DD	DS	EQ	EQ	EQ	EQ	EQ	FN	FN	FN	FN	FN	FN
Cap Code	6.3 V 10 V 16 V	25 V	50 V	100 V	6.3 V 10 V 16 V	25 V	50 V	100 V	6.3 V 10 V 16 V	25 V	50 V	100 V	6.3 V 10 V 16 V	25 V	50 V	100 V	6.3 V 10 V 16 V	25 V	50 V	100 V
	0603				0805				1206				1210							

Table 1 – Capacitance Range/Selection Waterfall (0603 – 1210 Case Sizes) cont'd

Capacitance Code	0603					0805					1206					1210				
	6.3 V 10 V 16 V	25 V	50 V	100 V	6.3 V 10 V 16 V	25 V	50 V	100 V	6.3 V 10 V 16 V	25 V	50 V	100 V	6.3 V 10 V 16 V	25 V	50 V	100 V	6.3 V 10 V 16 V	25 V	50 V	100 V
Product Availability and Chip Thickness Codes – See Table 2 for Chip Thickness Dimensions																				
473	CD	CD	CD		DR	DR	DR	DS	DG	EQ	EQ	EQ	ER	ES			FN	FN	FN	FQ
563	CD	CD			DD	DD	DD	DS		EQ	EQ	EQ	EQ	ES			FN	FN	FN	FQ
683	CD	CD			DD	DD	DD	DS		EQ	EQ	EQ	EQ	ES			FN	FN	FN	FQ
823					DD	DD	DD	DS		EQ	EQ	EQ	EQ	ES			FN	FN	FN	FQ
104					DR	DR	DR	DS		EQ	EQ	EQ	EQ	EM			FN	FN	FN	FQ
124					DD	DD	DD	DG		ER	ER	ER	ER	EU			FN	FN	FN	FQ
154					DD	DD	DD	DG		ER	ER	ER	ER	EU			FQ	FQ	FQ	FQ
184					DD	DD	DD			ER	ER	ER	ER	ER			FQ	FQ	FQ	FQ
224					DD	DD	DD			ER	ER	ER	ER				FQ	FQ	FQ	FQ
274					DD	DD	DD			ER	ER	ER	ER	EM			FQ	FQ	FQ	FQ
334					DD	DD	DD			ER	ER	ER	ER	EU			FX	FX	FX	FX
394					DS	DS	DS			ER	ER	ER					FX	FX	FX	FX
474					DS	DS	DS			ER	ER	ER					FX	FX	FX	FX
564					DH	DH	DH			ER	ER	ER					FX	FX	FX	FX
684					DH	DH	DH			ES	ES	ES					FX	FX	FX	FX
824										ES	ES	ES					FA	FA	FA	FA
105										ES	ES	ES					FU	FU	FU	FU
125										EH	EH	EH					FZ	FZ	FZ	FZ
155										EH	EH	EH					FZ	FZ	FZ	FZ
185										EH	EH	EH					FZ	FZ	FZ	FZ
225										EH	EH	EH					FZ	FZ	FZ	FZ
275																	FZ	FZ	FZ	FZ
335																	FM	FM	FM	FM
Cap Code	6.3 V 10 V 16 V	25 V	50 V	100 V	6.3 V 10 V 16 V	25 V	50 V	100 V	6.3 V 10 V 16 V	25 V	50 V	100 V	6.3 V 10 V 16 V	25 V	50 V	100 V	6.3 V 10 V 16 V	25 V	50 V	100 V
	0603				0805				1206				1210							

Table 2 – Chip Thickness/Tape & Reel Packaging Quantities

Thickness Code	Case Size	Thickness ± Range (mm)	Paper Quantity ¹		Plastic Quantity	
			7" Reel	13" Reel	7" Reel	13" Reel
AA	1005		15000			
AB	0201		15000			
BB	0402		15000			
BC	0402		15000			
PA	0508	0.80 ± 0.10			4000	10000
CB	0603	0.80 ± 0.07	4000	10000		
CF	0603	0.80 ± 0.07*	4000	15000		
CC	0603	0.80 ± 0.10	4000	10000		
CG	0603	0.80 ± 0.10*	4000	15000		
CD	0603	0.80 ± 0.15	4000	10000		
CJ	0603	0.80 ± 0.15*	4000	15000		
CH	0603	0.85 ± 0.07	4000	10000		
MA	0612	0.80 ± 0.10			4000	10000
DB	0805	0.60 ± 0.10			4000	10000
DC	0805	0.78 ± 0.10			4000	10000
DR	0805	0.78 ± 0.20			4000	10000
DK	0805	0.80 ± 0.10			4000	10000
DD	0805	0.90 ± 0.10			4000	10000
DL	0805	0.95 ± 0.10			4000	10000
DE	0805	1.00 ± 0.10			2500	10000
DS	0805	1.00 ± 0.20			2500	10000
DF	0805	1.10 ± 0.10			2500	10000
DG	0805	1.25 ± 0.15			2500	10000
DH	0805	1.25 ± 0.20			2500	10000
EB	1206	0.78 ± 0.10	4000	10000	4000	10000
EQ	1206	0.78 ± 0.20	4000	10000	4000	10000
EK	1206	0.80 ± 0.10			2000	8000
EC	1206	0.90 ± 0.10			4000	10000
ER	1206	0.90 ± 0.20			4000	10000
EN	1206	0.95 ± 0.10			4000	10000
ED	1206	1.00 ± 0.10			2500	10000
ES	1206	1.00 ± 0.20			2500	10000
EE	1206	1.10 ± 0.10			2500	10000
ET	1206	1.10 ± 0.20			2500	10000
EF	1206	1.20 ± 0.15			2500	10000
EP	1206	1.20 ± 0.20			2500	10000
EM	1206	1.25 ± 0.15			2500	10000
EL	1206	1.25 ± 0.20			2500	10000
EG	1206	1.60 ± 0.15			2000	8000
EH	1206	1.60 ± 0.20			2000	8000
EU	1206	1.60 ± 0.25			2000	8000
EJ	1206	1.70 ± 0.20			2000	8000
FB	1210	0.78 ± 0.10			4000	10000
FN	1210	0.78 ± 0.20			4000	10000
FC	1210	0.90 ± 0.10			4000	10000
FQ	1210	0.90 ± 0.20			4000	10000
FD	1210	0.95 ± 0.10			4000	10000
Thickness Code	Case Size	Thickness ± Range (mm)	7" Reel	13" Reel	7" Reel	13" Reel
			Paper Quantity ¹		Plastic Quantity	

Table 2 – Chip Thickness/Tape & Reel Packaging Quantities cont'd

Thickness Code	Case Size	Thickness ± Range (mm)	Paper Quantity ¹		Plastic Quantity	
			7" Reel	13" Reel	7" Reel	13" Reel
FX	1210	0.95 ± 0.20			4000	10000
FE	1210	1.00 ± 0.10			2500	10000
FF	1210	1.10 ± 0.10			2500	10000
FA	1210	1.10 ± 0.15			2500	10000
FG	1210	1.25 ± 0.15			2500	10000
FZ	1210	1.25 ± 0.20			2500	10000
FL	1210	1.40 ± 0.15			2000	8000
FO	1210	1.50 ± 0.20			2000	8000
FH	1210	1.55 ± 0.15			2000	8000
FU	1210	1.55 ± 0.20			2000	8000
FP	1210	1.60 ± 0.20			2000	8000
FM	1210	1.70 ± 0.20			2000	8000
FJ	1210	1.85 ± 0.20			2000	8000
FT	1210	1.90 ± 0.20			1500	4000
FY	1210	2.00 ± 0.20			2000	8000
FK	1210	2.10 ± 0.20			2000	8000
FR	1210	2.25 ± 0.20			2000	8000
FS	1210	2.50 ± 0.30			1000	4000
FV	1210	3.35 ± 0.10			600	2000
FW	1210	6.15 ± 0.15			300	1000
Thickness Code	Case Size	Thickness ± Range (mm)	7" Reel	13" Reel	7" Reel	13" Reel
			Paper Quantity ¹		Plastic Quantity	

KEMET Corporation World Headquarters

2835 KEMET Way
Simpsonville, SC 29681

Mailing Address:
P.O. Box 5928
Greenville, SC 29606

www.kemet.com
Tel: 864-963-6300
Fax: 864-963-6521

Corporate Offices
Fort Lauderdale, FL
Tel: 954-766-2800

North America

Northeast
Wilmington, MA
Tel: 978-658-1663

Southeast
Lake Mary, FL
Tel: 407-855-8886

Central
Novi, MI
Tel: 248-994-1030

Irving, TX
Tel: 972-915-6041

West
Milpitas, CA
Tel: 408-433-9950

Mexico
Guadalajara, Jalisco
Tel: 52-33-3123-2141

Europe

Southern Europe
Sasso Marconi, Italy
Tel: 39-051-939111

Skopje, Macedonia
Tel: 389-2-55-14-623

Central Europe
Landsberg, Germany
Tel: 49-8191-3350800

Kamen, Germany
Tel: 49-2307-438110

Northern Europe
Wyboston, United Kingdom
Tel: 44-1480-273082

Espoo, Finland
Tel: 358-9-5406-5000

Asia

Northeast Asia
Hong Kong
Tel: 852-2305-1168

Shenzhen, China
Tel: 86-755-2518-1306

Beijing, China
Tel: 86-10-5877-1075

Shanghai, China
Tel: 86-21-6447-0707

Seoul, South Korea
Tel: 82-2-6294-0550

Taipei, Taiwan
Tel: 886-2-27528585

Southeast Asia
Singapore
Tel: 65-6701-8033

Penang, Malaysia
Tel: 60-4-6430200

Bangalore, India
Tel: 91-806-53-76817

Note: KEMET reserves the right to modify minor details of internal and external construction at any time in the interest of product improvement. KEMET does not assume any responsibility for infringement that might result from the use of KEMET Capacitors in potential circuit designs. KEMET is a registered trademark of KEMET Electronics Corporation.

Disclaimer

All product specifications, statements, information and data (collectively, the "Information") in this datasheet are subject to change. The customer is responsible for checking and verifying the extent to which the Information contained in this publication is applicable to an order at the time the order is placed.

All Information given herein is believed to be accurate and reliable, but it is presented without guarantee, warranty, or responsibility of any kind, expressed or implied.

Statements of suitability for certain applications are based on KEMET Electronics Corporation's ("KEMET") knowledge of typical operating conditions for such applications, but are not intended to constitute – and KEMET specifically disclaims – any warranty concerning suitability for a specific customer application or use. The Information is intended for use only by customers who have the requisite experience and capability to determine the correct products for their application. Any technical advice inferred from this Information or otherwise provided by KEMET with reference to the use of KEMET's products is given gratis, and KEMET assumes no obligation or liability for the advice given or results obtained.

Although KEMET designs and manufactures its products to the most stringent quality and safety standards, given the current state of the art, isolated component failures may still occur. Accordingly, customer applications which require a high degree of reliability or safety should employ suitable designs or other safeguards (such as installation of protective circuitry or redundancies) in order to ensure that the failure of an electrical component does not result in a risk of personal injury or property damage.

Although all product-related warnings, cautions and notes must be observed, the customer should not assume that all safety measures are indicated or that other measures may not be required.