
TOSHIBA Transistor
Silicon NPN Epitaxial Type (PCT Process) Silicon PNP Epitaxial Type (PCT Process)


RN4985

Switching, Inverter Circuit, Interface Circuit
and Driver Circuit Applications

- Including two devices in US6 (ultra super mini type with 6 leads)
- With built-in bias resistors
- Simplify circuit design
- Reduce a quantity of parts and manufacturing process


Equivalent Circuit and Bias Resister Values





R1: 2.2kΩ
R2: 47kΩ
(Q1, Q2 Common)

Unit: mm



JEDEC	—
JEITA	—
TOSHIBA	2-2J1A

Weight: 6.8 mg (typ.)

Q1 Absolute Maximum Ratings (Ta = 25°C)

Characteristic	Symbol	Rating	Unit
Collector-base voltage	V_{CBO}	50	V
Collector-emitter voltage	V_{CEO}	50	V
Emitter-base voltage	V_{EBO}	5	V
Collector current	I_C	100	mA

Q2 Absolute Maximum Ratings (Ta = 25°C)

Characteristic	Symbol	Rating	Unit
Collector-base voltage	V_{CBO}	−50	V
Collector-emitter voltage	V_{CEO}	−50	V
Emitter-base voltage	V_{EBO}	−5	V
Collector current	I_C	−100	mA


Q1, Q2 Common Absolute Maximum Ratings (Ta = 25°C)

Characteristic	Symbol	Rating	Unit
Collector power dissipation	P_C *	200	mW
Junction temperature	T_j	150	°C
Storage temperature range	T_{stg}	−55~150	°C


Note: Using continuously under heavy loads (e.g. the application of high temperature/current/voltage and the significant change in temperature, etc.) may cause this product to decrease in the reliability significantly even if the operating conditions (i.e. operating temperature/current/voltage, etc.) are within the absolute maximum ratings.
Please design the appropriate reliability upon reviewing the Toshiba Semiconductor Reliability Handbook (“Handling Precautions”/“Derating Concept and Methods”) and individual reliability data (i.e. reliability test report and estimated failure rate, etc).

* Total rating

Marking



Equivalent Circuit (Top View)



Q1 Electrical Characteristics (Ta = 25°C)

Characteristic	Symbol	Test Circuit	Test Condition	Min	Typ.	Max	Unit
Collector cut-off current	I_{CBO}	—	V_{CB} = 50V, I_E = 0	—	—	100	nA
	I_{CEO}	—	V_{CE} = 50V, I_B = 0	—	—	500	
Emitter cut-off current	I_{EBO}	—	V_{EB} = 5V, I_C = 0	0.078	—	0.145	mA
DC current gain	h_{FE}	—	V_{CE} = 5V, I_C = 10mA	80	—	—	—
Collector-emitter saturation voltage	$V_{CE\ (sat)}$	—	I_C = 5mA, I_B = 0.25mA	—	0.1	0.3	V
Input voltage (ON)	$V_{I\ (ON)}$	—	V_{CE} = 0.2V, I_C = 5mA	0.6	—	1.1	V
Input voltage (OFF)	$V_{I\ (OFF)}$	—	V_{CE} = 5V, I_C = 0.1mA	0.5	—	0.8	V
Transition frequency	f_T	—	V_{CE} = 10V, I_C = 5mA	—	250	—	MHz
Collector output capacitance	C_{ob}	—	V_{CB} = 10V, I_E = 0, f = 1 MHz	—	3	6	pF


Q2 Electrical Characteristics (Ta = 25°C)


Characteristic	Symbol	Test Circuit	Test Condition	Min	Typ.	Max	Unit
Collector cut-off current	I_{CBO}	—	V_{CB} = −50V, I_E = 0	—	—	−100	nA
	I_{CEO}	—	V_{CE} = −50V, I_B = 0	—	—	−500	
Emitter cut-off current	I_{EBO}	—	V_{EB} = −5V, I_C = 0	−0.078	—	−0.145	mA
DC current gain	h_{FE}	—	V_{CE} = −5V, I_C = −10mA	80	—	—	—
Collector-emitter saturation voltage	$V_{CE\ (sat)}$	—	I_C = −5mA, I_B = −0.25mA	—	−0.1	−0.3	V
Input voltage (ON)	$V_{I\ (ON)}$	—	V_{CE} = −0.2V, I_C = −5mA	−0.6	—	−1.1	V
Input voltage (OFF)	$V_{I\ (OFF)}$	—	V_{CE} = −5V, I_C = −0.1mA	−0.5	—	−0.8	V
Transition frequency	f_T	—	V_{CE} = −10V, I_C = −5mA	—	200	—	MHz
Collector output capacitance	C_{ob}	—	V_{CB} = −10V, I_E = 0	—	3	6	pF


Q1, Q2 Common Electrical Characteristics (Ta = 25°C)

Characteristic	Symbol	Test Circuit	Test Condition	Min	Typ.	Max	Unit
Input resistor	R1	—	—	1.54	2.2	2.86	kΩ
Resistor ratio	R1/R2	—	—	0.0421	0.0468	0.0515	—


Q1



I_C – V_I (ON)
COMMON EMITTER
V_{CE} = 0.2V
Ta = 100°C
25
−25
COLLECTOR CURRENT I_C (mA)
INPUT VOLTAGE $V_{I(ON)}$ (V)
100
50
30
10
5
3
1
0.5
0.3
0.1
0.3
1
3
10
30
100



h_{FE} – I_C
COMMON EMITTER
V_{CE} = 5V
Ta = 100°C
25
−25
DC CURRENT GAIN h_{FE}
COLLECTOR CURRENT I_C (mA)
500
300
100
50
30
10
1
3
10
30
100


I_C – V_I (OFF)
COMMON EMITTER
V_{CE} = 5V
Ta = 100°C
25
−25
COLLECTOR CURRENT I_C (μA)
INPUT VOLTAGE $V_{I(OFF)}$ (V)
10000
5000
3000
1000
500
300
100
50
30
0
0.2
0.4
0.6
0.8
1.0
1.2
1.4

Q2


I_C – V_I (ON)
COMMON EMITTER
V_{CE} = −0.2V
Ta = 100°C
25
−25
COLLECTOR CURRENT I_C (mA)
INPUT VOLTAGE $V_{I(ON)}$ (V)
−100
−50
−30
−10
−5
−3
−1
−0.5
−0.3
−0.1
−0.3
−1
−3
−10
−30
−100


h_{FE} – I_C
COMMON EMITTER
V_{CE} = −5V
Ta = 100°C
25
−25
DC CURRENT GAIN h_{FE}
COLLECTOR CURRENT I_C (mA)
500
300
100
50
30
10
−1
−3
−10
−30
−100


I_C – V_I (OFF)
COMMON EMITTER
V_{CE} = −5V
Ta = 100°C
25
−25
COLLECTOR CURRENT I_C (μA)
INPUT VOLTAGE $V_{I(OFF)}$ (V)
−10000
−5000
−3000
−1000
−500
−300
−100
−50
−30
0
−0.2
−0.4
−0.6
−0.8
−1.0
−1.2
−1.4

RESTRICTIONS ON PRODUCT USE

- Toshiba Corporation, and its subsidiaries and affiliates (collectively “TOSHIBA”), reserve the right to make changes to the information in this document, and related hardware, software and systems (collectively “Product”) without notice.
- This document and any information herein may not be reproduced without prior written permission from TOSHIBA. Even with TOSHIBA’s written permission, reproduction is permissible only if reproduction is without alteration/omission.
- Though TOSHIBA works continually to improve Product’s quality and reliability, Product can malfunction or fail. Customers are responsible for complying with safety standards and for providing adequate designs and safeguards for their hardware, software and systems which minimize risk and avoid situations in which a malfunction or failure of Product could cause loss of human life, bodily injury or damage to property, including data loss or corruption. Before creating and producing designs and using, customers must also refer to and comply with (a) the latest versions of all relevant TOSHIBA information, including without limitation, this document, the specifications, the data sheets and application notes for Product and the precautions and conditions set forth in the “TOSHIBA Semiconductor Reliability Handbook” and (b) the instructions for the application that Product will be used with or for. Customers are solely responsible for all aspects of their own product design or applications, including but not limited to (a) determining the appropriateness of the use of this Product in such design or applications; (b) evaluating and determining the applicability of any information contained in this document, or in charts, diagrams, programs, algorithms, sample application circuits, or any other referenced documents; and (c) validating all operating parameters for such designs and applications. **TOSHIBA ASSUMES NO LIABILITY FOR CUSTOMERS’ PRODUCT DESIGN OR APPLICATIONS.**
- Product is intended for use in general electronics applications (e.g., computers, personal equipment, office equipment, measuring equipment, industrial robots and home electronics appliances) or for specific applications as expressly stated in this document. Product is neither intended nor warranted for use in equipment or systems that require extraordinarily high levels of quality and/or reliability and/or a malfunction or failure of which may cause loss of human life, bodily injury, serious property damage or serious public impact (“Unintended Use”). Unintended Use includes, without limitation, equipment used in nuclear facilities, equipment used in the aerospace industry, medical equipment, equipment used for automobiles, trains, ships and other transportation, traffic signaling equipment, equipment used to control combustions or explosions, safety devices, elevators and escalators, devices related to electric power, and equipment used in finance-related fields. Do not use Product for Unintended Use unless specifically permitted in this document.
- Do not disassemble, analyze, reverse-engineer, alter, modify, translate or copy Product, whether in whole or in part.
- Product shall not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable laws or regulations.
- The information contained herein is presented only as guidance for Product use. No responsibility is assumed by TOSHIBA for any infringement of patents or any other intellectual property rights of third parties that may result from the use of Product. No license to any intellectual property right is granted by this document, whether express or implied, by estoppel or otherwise.
- **ABSENT A WRITTEN SIGNED AGREEMENT, EXCEPT AS PROVIDED IN THE RELEVANT TERMS AND CONDITIONS OF SALE FOR PRODUCT, AND TO THE MAXIMUM EXTENT ALLOWABLE BY LAW, TOSHIBA (1) ASSUMES NO LIABILITY WHATSOEVER, INCLUDING WITHOUT LIMITATION, INDIRECT, CONSEQUENTIAL, SPECIAL, OR INCIDENTAL DAMAGES OR LOSS, INCLUDING WITHOUT LIMITATION, LOSS OF PROFITS, LOSS OF OPPORTUNITIES, BUSINESS INTERRUPTION AND LOSS OF DATA, AND (2) DISCLAIMS ANY AND ALL EXPRESS OR IMPLIED WARRANTIES AND CONDITIONS RELATED TO SALE, USE OF PRODUCT, OR INFORMATION, INCLUDING WARRANTIES OR CONDITIONS OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, ACCURACY OF INFORMATION, OR NONINFRINGEMENT.**
- Do not use or otherwise make available Product or related software or technology for any military purposes, including without limitation, for the design, development, use, stockpiling or manufacturing of nuclear, chemical, or biological weapons or missile technology products (mass destruction weapons). Product and related software and technology may be controlled under the Japanese Foreign Exchange and Foreign Trade Law and the U.S. Export Administration Regulations. Export and re-export of Product or related software or technology are strictly prohibited except in compliance with all applicable export laws and regulations.
- Please contact your TOSHIBA sales representative for details as to environmental matters such as the RoHS compatibility of Product. Please use Product in compliance with all applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive. TOSHIBA assumes no liability for damages or losses occurring as a result of noncompliance with applicable laws and regulations.