

HD29029

Dual CCD Drivers

REJ03D0303-0200Z
(Previous ADE-205-580 (Z))
Rev.2.00
Jul.16.2004

Description


The HD29029 is optimum for CCD drive and has two drivers in a package. The input circuit is operated at TTL level. The outputs are capable of source or sink currents of 0.5 A.

Features

- High-speed operation 7 ns typ in transition times (t_{TLH} , t_{THL}) at $C_L = 200$ pF
- No external components needed because direct drive is available at TTL level inputs
- Output swing voltage: 12 V
- Sink/Source currents: 0.5 A (for each)
- Output cross voltage: 50% typ
- Ordering Information

Part Name	Package Type	Package Code	Package Abbreviation	Taping Abbreviation (Quantity)
HD29029FPEL	SOP-8 pin (JEITA)	FP-8DGV	FP	EL (2,500 pcs/reel)

Pin Arrangement



(Top view)

Function Table

Input A	Output Y
H	L
L	H

H: High level

L: Low level



Absolute Maximum Ratings

Item	Symbol	Ratings	Unit
Supply Voltage	V_{CC}^{*1}	15	V
Input Voltage	V_{IN}	7	V
Output Current	$I_{O(peak)}$	± 0.5	A
Operating Temperature	T_a	-20 to +75	°C
Storage Temperature	T_{stg}	-65 to +150	°C
Junction Temperature	T_J	150	°C
Power Dissipation per Package	P_T^{*2}	0.735	W

Notes: 1. The voltage value is defined with respect to ground terminal unless otherwise noted.

2. The total power dissipation is at $T_a = 25^\circ\text{C}$. When driving large capacity with high frequency radiation is needed. There fore, delating with 5.9 mW/°C must be done as shown below.

3. The absolute maximum ratings are values which must not individually be eceeded, and furthermore, no two of which may be realized at same time.



Recommended Operating Conditions

Item	Symbol	Min	Typ	max	Unit
Supply Voltage	V_{CC}	8.0	9.0	13.0	V
Operating Temperature	T_a	-20	25	75	°C

Electrical Characteristics ($V_{CC} = 8$ to 13 V, $T_a = -20$ to 75°C)


Item	Symbol	Min	Typ	Max	Unit	Conditions
Input Voltage	V_{IH}	2.0	—	—	V	
	V_{IL}	—	—	0.6	V	
Output Voltage	V_{OH}	$V_{CC}-2$	—	—	V	$V_{IL} = 0.6$ V, $I_{OH} = -1$ mA
	V_{OL}	—	—	0.5	V	$V_{IH} = 2.0$ V, $I_{OH} = 1$ mA
Input Current	I_{IH}	—	—	20	μA	$V_I = 2.7$ V
	I_{IL}	—	—	-100	μA	$V_I = 0.4$ V
Supply Current	I_{CCH}	—	—	10	mA	
	I_{CCL}	—	—	25	mA	
Input Current	I_{LI}	—	—	100	μA	$V_I = 7$ V
Input Clamp Voltage	V_{IK}	—	—	-1.5	V	$I_{IN} = -18$ mA

Switching Characteristics ($C_L = 200$ pF, $T_a = 25^{\circ}\text{C}$)


Item	Symbol	Min	Typ	Max	Unit	Conditions
Propagation Delay Time	t_{PHL}	—	4.0	15.0	ns	$V_{CC} = 9$ V
		—	4.0	13.0	ns	$V_{CC} = 12$ V
	t_{PLH}	—	6.0	15.0	ns	$V_{CC} = 9$ V
		—	6.0	13.0	ns	$V_{CC} = 12$ V
Transition Time	t_{THL}	—	8.0	14.0	ns	$V_{CC} = 9$ V
		—	7.0	12.0	ns	$V_{CC} = 12$ V
	t_{TLH}	—	8.0	14.0	ns	$V_{CC} = 9$ V
		—	7.0	12.0	ns	$V_{CC} = 12$ V

Switching Time Test Method

Test circuit




Waveforms




Output Characteristics ($C_L = 200\text{ pF}$, $T_a = 25^\circ\text{C}$)

Item	Symbol	Min	Typ	Max	Unit	Conditions
Output Cross Voltage	V_x	20	50	80	%	$V_{CC} = 9\text{ V}$
		20	50	80	%	$V_{CC} = 12\text{ V}$


Test circuit



Waveforms



Package Dimensions



Renesas Technology Corp. Sales Strategic Planning Div. Nippon Bldg., 2-6-2, Ohte-machi, Chiyoda-ku, Tokyo 100-0004, Japan

Keep safety first in your circuit designs!

1. Renesas Technology Corp. puts the maximum effort into making semiconductor products better and more reliable, but there is always the possibility that trouble may occur with them. Trouble with semiconductors may lead to personal injury, fire or property damage. Remember to give due consideration to safety when making your circuit designs, with appropriate measures such as (i) placement of substitutive, auxiliary circuits, (ii) use of nonflammable material or (iii) prevention against any malfunction or mishap.

Notes regarding these materials

1. These materials are intended as a reference to assist our customers in the selection of the Renesas Technology Corp. product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Renesas Technology Corp. or a third party.
2. Renesas Technology Corp. assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.
3. All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Renesas Technology Corp. without notice due to product improvements or other reasons. It is therefore recommended that customers contact Renesas Technology Corp. or an authorized Renesas Technology Corp. product distributor for the latest product information before purchasing a product listed herein.
The information described here may contain technical inaccuracies or typographical errors.
Renesas Technology Corp. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors.
Please also pay attention to information published by Renesas Technology Corp. by various means, including the Renesas Technology Corp. Semiconductor home page (<http://www.renesas.com>).
4. When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Renesas Technology Corp. assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.
5. Renesas Technology Corp. semiconductors are not designed or manufactured for use in a device or system that is used under circumstances in which human life is potentially at stake. Please contact Renesas Technology Corp. or an authorized Renesas Technology Corp. product distributor when considering the use of a product contained herein for any specific purposes, such as apparatus or systems for transportation, vehicular, medical, aerospace, nuclear, or undersea repeater use.
6. The prior written approval of Renesas Technology Corp. is necessary to reprint or reproduce in whole or in part these materials.
7. If these products or technologies are subject to the Japanese export control restrictions, they must be exported under a license from the Japanese government and cannot be imported into a country other than the approved destination.
Any diversion or reexport contrary to the export control laws and regulations of Japan and/or the country of destination is prohibited.
8. Please contact Renesas Technology Corp. for further details on these materials or the products contained therein.



RENESAS SALES OFFICES

<http://www.renesas.com>

Renesas Technology America, Inc.

450 Holger Way, San Jose, CA 95134-1368, U.S.A
Tel: <1> (408) 382-7500 Fax: <1> (408) 382-7501

Renesas Technology Europe Limited.

Dukes Meadow, Millboard Road, Bourne End, Buckinghamshire, SL8 5FH, United Kingdom
Tel: <44> (1628) 585 100, Fax: <44> (1628) 585 900

Renesas Technology Europe GmbH

Dornacher Str. 3, D-85622 Feldkirchen, Germany
Tel: <49> (89) 380 70 0, Fax: <49> (89) 929 30 11

Renesas Technology Hong Kong Ltd.

7/F., North Tower, World Finance Centre, Harbour City, Canton Road, Hong Kong
Tel: <852> 2265-6688, Fax: <852> 2375-6836

Renesas Technology Taiwan Co., Ltd.

FL 10, #99, Fu-Hsing N. Rd., Taipei, Taiwan
Tel: <886> (2) 2715-2888, Fax: <886> (2) 2713-2999

Renesas Technology (Shanghai) Co., Ltd.

26/F., Ruijin Building, No.205 Maoming Road (S), Shanghai 200020, China
Tel: <86> (21) 6472-1001, Fax: <86> (21) 6415-2952

Renesas Technology Singapore Pte. Ltd.

1, Harbour Front Avenue, #06-10, Keppel Bay Tower, Singapore 098632
Tel: <65> 6213-0200, Fax: <65> 6278-8001