

June 2002

EXAR'S XR88C92/192 COMPARED WITH PHILIPS'S SC26C92

Author: PY

1.0 INTRODUCTION

This application note describes the major difference between Exar's XR88C92/192 with Philips's SC26C92. These devices are very similar, with a few hardware, firmware-related and bus timing differences.

1.1 HARDWARE DIFFERENCES

- The Philips SC26C92 and Exar XR88C92/192 are both available in three footprints: 44-pin PLCC, 44-pin QFP and 40-pin DIP. The Exar and Philips DUARTs are pin-to-pin compatible in all three footprints.
- The Exar's 44-pin TQFP package is the same size and has the same pitch as the Philips' 44-pin QFP package. But they differ in the package thickness and the lead length. See the list below:

	<u>Exar</u>	<u>Philips</u>
Thickness:	1.4mm	1.75mm
Lead Length, Lp:	0.45mm < Lp < 0.75mm	0.55mm < Lp < 0.95mm

1.2 FIRMWARE DIFFERENCES

All the internal registers in the SC26C92 and XR88C92/192 are identical with only one exception:

- Since the XR88C192 has a 16-byte FIFO as compared to a 8-byte FIFO in the SC26C92, the selectable transmit and receive trigger levels are different.

1.3 BUS TIMING DIFFERENCES

- The XR88C92/192 is faster than the SC26C92. For example, the data access time (from -CS low to data valid) during a read is a maximum of 32 ns for the XR88C92/192, whereas it is a maximum of 55 ns for the SC26C92.

1.4 SUMMARY OF DIFFERENCES

In the table below, some differences between the XR88C92/192 and SC26C92 are summarized.

TABLE 1: DIFFERENCES BETWEEN EXAR'S XR88C92/192 WITH PHILIPS'S SC26C92

DIFFERENCES	XR88C92/192	SC26C92
Data Bus Standard	Intel	Intel
Power Supply Operation	3.3 and 5 V	5 V only
Max Operating Current	3 mA @ 3.3 V 6 mA @ 5 V	10 mA @ 5 V
Max Frequency on XTAL1	24 MHz	8 MHz
Max Data Rate	1 Mbps	1 Mbps
Operating Temperature Range	Commercial and Industrial	Commercial and Industrial
Package	44-TQFP, 44-PLCC, 40-PDIP	44-PQFP, 44- PLCC, 40-PDIP
44-(T)QFP package thickness	1.4 mm	1.75 mm
44-(T)QFP package max lead lengths	0.75 mm	0.95 mm
TX FIFO Size	8 (XR88C92) 16 (XR88C192)	8
RX FIFO Size	8 (XR88C92) 16 (XR88C192)	8
TX FIFO Trigger Levels	8, 4, 6, 1 (XR88C92) 16, 8, 12, 1(XR88C192)	8, 4, 6, 1
RX FIFO Trigger Levels	1, 3, 6, 8 (XR88C92) 1, 6, 12, 16 (XR88C192)	1, 3, 6, 8

1.5 REPLACING THE SC26C92 WITH THE XR88C92/192

You can directly replace the Philips SC26C92 with Exar's XR88C92/192 without any hardware changes if using either the 44-TQFP, 44-PLCC or 40-PDIP packages since they are all pin-to-pin compatible.

Since the XR88C192 has a larger Transmit and Receive FIFO, the software will need to be updated to take advantage of the features of the XR88C192. The XR88C92/192 allows the hardware designer to choose either a 5 or 3.3 V power supply instead of being forced to use a 5 V power supply only. Also, the XR88C92/192 has a lower power consumption than the SC26C92.

NOTICE

EXAR Corporation reserves the right to make changes to the products contained in this publication in order to improve design, performance or reliability. EXAR Corporation assumes no responsibility for the use of any circuits described herein, conveys no license under any patent or other right, and makes no representation that the circuits are free of patent infringement. Charts and schedules contained here in are only for illustration purposes and may vary depending upon a user's specific application. While the information in this publication has been carefully checked; no responsibility, however, is assumed for inaccuracies.

EXAR Corporation does not recommend the use of any of its products in life support applications where the failure or malfunction of the product can reasonably be expected to cause failure of the life support system or to significantly affect its safety or effectiveness. Products are not authorized for use in such applications unless EXAR Corporation receives, in writing, assurances to its satisfaction that: (a) the risk of injury or damage has been minimized; (b) the user assumes all such risks; (c) potential liability of EXAR Corporation is adequately protected under the circumstances.

Copyright 2002 EXAR Corporation

June 2002

Send your UART technical inquiry with technical details to hotline: uarttechsupport@exar.com

Reproduction, in part or whole, without the prior written consent of EXAR Corporation is prohibited.
