


National Semiconductor's
SPUSI2
USB Interface Dongle



User's Guide
August 2009

1.0 SPUSI2 USB Interface Dongle

What is the SPUSI2 USB Interface Dongle?


The SPUSI2 USB Interface Dongle is National Semiconductor's platform for interfacing to evaluation boards and reference boards with a Serial Peripheral Interface (SPI).

Examples included National Semiconductor's latest line of sensor boards (SP1202S01, SP1202S02, SP1202S03, SP1202S04, SP1602S01, and SP1602S02). These boards are a subset of the online WEBENCH Sensor Designer tool available at www.national.com.

Packing List

The SPUSI2 Board comes with the following components
SPUSI2 USB Interface Dongle
USB Cable

Picture of the SPUSI2



Component Description

The following table describes both the on-board connectors and the main components on the SPUSI2 board.

Component	Description
J1	USB cable connection
J2	General -use
U1	USB Microcontroller
D1	3.3V Power Indicator
D2	Ready Indicator
D3	Data Flow Indicator
SW1	Reset Switch for Microcontroller

Test Points

Test Point	Description
TP1	PE1
TP2	PE0
TP3	DIN
TP4	SCLK
TP5	CSB
TP6	DOUT
TP7	BKPT
TP10	3P3V (3.3V)
TPG1, TPG2, TPG3, TPG4	Ground


2.0 Power Requirements

The SPUSI2 board requires no external power supply. It is powered by the +5V available on the USB connector. The +5V is regulated down to +3.3V for the Microcontroller. The +5V and +3V are available on connector J2 on pins 14 and 13 respectively.


3.0 Setup Procedure

1. Download Sensor Path Control Panel Software onto your computer prior to connecting board to computer:
<http://www.national.com/analog/webench/sensors/spusi2>

2. Connect board to computer. The **Found New Hardware Wizard** will popup. Select **Yes, this time only** and click **Next**.




3. Select **Install the software automatically (Recommended)** and click **Next**.



4. Wizard begins to install software for Sensor Signal Path 2008 Board. Click ***Continue Anyway*** on the ***Hardware Installation*** pop-up.



5. Click ***Finish***.



5.0 Bill of Materials

Item	Qty	Reference	Part	Source
1	2	C1, C2	12pF, 0805	Panasonic #ECJ-2VC1H120J Digi-Key #PCC120CNTR-ND
2	16	C3, C4, C5, C6, C7, C8, C9, C10, C11, C12, C13, C14, C15, C16, C18, C20	0.1μF, 16V, ±10%, 0805, X7R	Yageo #CC0805KRX7R7BB104 Digi-Key #311-1142-2-ND
3	2	C17, C19	4.7 uF, 16V, Tant, ±20%, size 1206	Vishay/Sprague #293D475X9016A2TE3 Digi-Key #718-1148-2-ND
4	1	D1	LED (RED)	Lite-On #LTST-C930KAKT Digi-Key #160-1461-1-ND
5	1	D2	LED (YEL)	Lite-On #LTST-C930YKT Digi-Key #160-1213-1-ND
6	1	D3	LED (GRN)	Lite-On #LTST-C930GKT Digi-Key #160-1212-1-ND
7	1	J1	USB Connector	Mil-Max 897-43-004-90-000000 Digi-Key #ED90064-ND
8	1	J2	2 x 7 Pin Female Header, R/A	Sullins #PPPC072LJBN-RC Digi-Key #S5560-ND
9	1	L1	1uH	Murata #BLM15AG102SN1 Digi-Key #490-1007-1-ND
10	-	R7, R9, R11	Not Stuffed	n/a
11	4	R8, R10, R12, R16	0Ω, 5%, 1/10W, 0603	Rohm #MCR03EZPJ000 Digi-Key #RHM0.0GTR-ND
12	1	R13	1MΩ, 5%, 1/10W, 0603	Rohm #MCR03EZPJ105 Digi-Key #RHM1.0MGTR-ND
13	2	R14, R15	1.5kΩ, 5%, 1/10W, 0603	Rohm #MCR03EZPJ152 Digi-Key #RHM1.5KGTR-ND
14	3	R17, R18, R20	1kΩ, 5%, 1/10W, 0603	Rohm #MCR03EZPJ102 Digi-Key #RHM1.0KGCT-ND
15	1	R19	100kΩ, 5%, 1/10W, 0603	Rohm #MCR03EZPJ104 Digi-Key #RHM100KGTR-ND
16	1	SW1	Switch, NO	C&K #PTS635SL50 Digi-Key #CKN9102-ND
17	-	TPG1, TPG2, TPG3, TPG4	Not Stuffed	n/a
18	-	TP3, TP4, TP5, TP6, TP8, TP10	Not Stuffed	n/a
19	1	U2	LM3722IM5-2.32	National Semi #LM3722IM5-2.32/NOPB Digi-Key #LM3722IM5-2.32CT-ND
20	1	U3	LM1117MPX-3.3 / SOT-223	National Semi #LM1117MPX-3.3/NOPB Digi-Key #LM1117MPX-3.3CT-ND
21	1	U4	AT24C02 / SO8	Atmel #AT24C02BN-SH-B Digi-Key #AT24C02BN-SH-B-ND
22	1	U7	CY7C68013A-100AXC	Cypress Semi #CY7C68013A-100AXC Digi-Key #428-1667-ND
23	1	Y1	24 MHz	ECS# ECS-240-12-5PX-TR Digi-Key #XC1001TR-ND
24	1		PCB	Advanced Circuits

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products

Audio	www.ti.com/audio
Amplifiers	amplifier.ti.com
Data Converters	dataconverter.ti.com
DLP® Products	www.dlp.com
DSP	dsp.ti.com
Clocks and Timers	www.ti.com/clocks
Interface	interface.ti.com
Logic	logic.ti.com
Power Mgmt	power.ti.com
Microcontrollers	microcontroller.ti.com
RFID	www.ti-rfid.com
OMAP Mobile Processors	www.ti.com/omap
Wireless Connectivity	www.ti.com/wirelessconnectivity

Applications

Automotive and Transportation	www.ti.com/automotive
Communications and Telecom	www.ti.com/communications
Computers and Peripherals	www.ti.com/computers
Consumer Electronics	www.ti.com/consumer-apps
Energy and Lighting	www.ti.com/energy
Industrial	www.ti.com/industrial
Medical	www.ti.com/medical
Security	www.ti.com/security
Space, Avionics and Defense	www.ti.com/space-avionics-defense
Video and Imaging	www.ti.com/video

TI E2E Community Home Page

e2e.ti.com

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2012, Texas Instruments Incorporated