

LTC2311/LTC2310 Single 16-Bit/14-Bit/12-Bit, 5Msps/2Msps, Serial, High Speed SAR ADCs

DESCRIPTION

Demonstration circuit 2425A features the **LTC®2311** family. With up to 5Msps, these differential, single channel, 16-bit, serial, high speed successive approximation register (SAR) ADCs are available in a 16-lead MSOP package. The LTC2311 family has an internal 20ppm/°C maximum drift reference and an SPI-compatible serial interface that supports CMOS and LVDS logic. Note the demo board is configured for CMOS operation by default; see the note under JP3 for LVDS operation. The following text refers to the LTC2311, but applies to all members of the family, the only difference being the sample rate and/or the

number of bits. The DC2425A demonstrates the DC and AC performance of the LTC2311 in conjunction with the DC890 PScope™ data collection board. Alternatively, by connecting the DC2425A into a customer application, the performance of the LTC2311 can be evaluated directly in that circuit.

Design files for this circuit board are available at <http://www.linear.com/demo/DC2425A>

LT, LTC, LTM, Linear Technology and the Linear logo are registered trademarks and PScope is a trademark of Linear Technology Corporation. All other trademarks are the property of their respective owners.

BOARD PHOTO




Figure 1. DC2425A Connection Diagram

dc2425af

DEMO MANUAL DC2425A

ASSEMBLY OPTIONS

Table 1. DC2425A Assembly Options

VERSION	U1 PART NUMBER	MAX CONVERSION RATE	# OF BITS	MAX CLOCK FREQUENCY
DC2425A-A	LTC2311CMSE-16#PBF	5Msps	16	105MHz
DC2425A-B	LTC2310CMSE-16#PBF	2Msps	16	42MHz
DC2425A-C	LTC2311CMSE-14#PBF	5Msps	14	105MHz
DC2425A-D	LTC2310CMSE-14#PBF	2Msps	14	42MHz
DC2425A-E	LTC2311CMSE-12 #PBF	5Msps	12	105MHz
DC2425A-F	LTC2310CMSE-12#PBF	2Msps	12	42MHz

QUICK START PROCEDURE

Demonstration circuit 2425A is easy to set up and evaluate for performance. Refer to Figure 1 and follow the procedure below.

- Connect the DC2425A to a DC890 USB high speed data collection board using edge connector P1.
- Connect the DC890 to a host PC with a standard USB A/B cable.
- Apply a low jitter signal source to J3 to test channel 1. Note that the DC2425A is capable of accepting a differential input signal as well as a single-ended signal. See the Hardware Setup section for the jumper positions that correspond to these configurations.
- As a clock source, apply a low jitter 10dBm sine wave or square wave to connector J5. See Table 1 for maximum clock frequencies. Note that J5 has a 50Ω termination resistor to ground.
- Run the PScope software (Pscope.exe version K73, or later) supplied with the DC890 or download it from www.linear.com/software. Complete software documentation is available from the Help menu. Updates can be downloaded from the Tools menu. Check for updates periodically, as new features may be added. The PScope software should recognize the DC2425A and configure itself automatically.

- Click the Collect button (Figure 2) to begin acquiring data. The Collect button then changes to Pause, which can be used to stop data acquisition.




Figure 2. DC2425A PScope Screenshot

QUICK START PROCEDURE

DRIVE OPTIONS

There are several ways to drive the LTC2311 on the DC2425A.

If a true differential signal source is available, apply the signal to the differential inputs J3 and J4; make the following changes to the DC2425A:

- Remove R27, R38.
- Install 0 Ω 0603 resistors at R39, R47.

If a single-ended signal source is available, the LTC2311 may be driven differentially by applying the signal to J3.

The LTC2311 may be driven in the pseudo-differential bipolar mode by applying the single-ended signal to J3; make the following changes to the DC2425A:

- Move JP5 to the BIP position.
- Install a 10 μ F 0603 capacitor at C56.

The LTC2311 may be driven in the pseudo-differential unipolar mode by applying the single-ended signal to J3; make the following changes to the DC2425A:

- Move JP5 to the UNI position.
- Install a 10 μ F 0603 capacitor at C56.

HARDWARE SETUP

SIGNAL CONNECTIONS

J1 FPGA Program: Factory use only.

J2 JTAG: Factory use only.

J3 AIN+ Input: In the single-ended configuration, this is the signal input. For differential operation, this serves as the positive signal input.

J4 AIN- Input: This input is used only for differential operation. It serves as the negative signal input.

J5 CLK: This input has a 50 Ω termination resistor, and is intended to be driven by a low jitter 10dBm sine or square wave. To achieve the full AC performance of this part, the clock jitter should be kept under 2ps. This input is capacitively coupled so that the input clock can be either 0V to 2.5V or ± 1.25 V. This eliminates the need for level shifting. To run at the maximum conversion rate, apply the frequency specified in the Table 1.

JP1 VCCIO: Use this jumper to select the VCCIO supply voltage. The default setting is **2.5V**. The **1.8V** setting selects a 1.8V supply voltage.

JP2 VDD: Use this jumper to select the VDD supply voltage. The default setting is **5V**. The **3.3V** setting selects a 3.3V supply voltage.

JP3: Use this jumper to select the reference source for the LTC2311. The default setting is DRIVE REFOUT. This setting uses the voltage applied to Pin 3 of the LTC2311 as the reference voltage. The EXT setting will accept a voltage applied to E11 as the reference voltage. If no voltage is applied to E11, the LTC2311 will use its internal reference, which is 4.096V.

JP4 +IN Coupling: Use this jumper to select AC- or DC-coupling of the signal applied to J3. The default setting is **DC**. At very low input frequencies, using AC-coupling may degrade the distortion performance.

JP5 Mode: Use this jumper to select the signal input mode for the LTC2311. The default setting is **DIFF**. The **DIFF** setting accepts a single-ended signal from J3 but applies it as a differential signal to the LTC2311. The **BIP** setting accepts a single-ended signal from J3 and applies it as a single-ended bipolar signal to the LTC2311. The **UNI** setting also accepts a single-ended signal from J3, and applies it as a unipolar signal to the LTC2311. See Drive Options section for more details.

JP6 -IN Coupling: Use this jumper to select AC- or DC-coupling of the signal applied to J4. The default setting is **DC**. At very low input frequencies, using AC-coupling may degrade the distortion performance.

JP7 CM: Use this jumper to set the DC bias point for the signal applied to J3 when JP4 (+IN coupling) is in the AC position. The default setting is 4.096V which sets the common mode voltage at 2.048V. The **EXT** setting allows the use of an externally applied common mode voltage applied at E12 (EXT_CM1).

JP8 Data Out: Use this jumper to select the data output format from the LTC2311. The default setting is **CMOS**. The output data will not be valid if the jumper is moved to the **LVDS** position unless the following changes have been made:

Install 100 Ω 0402 resistors at R26, 75, 76, 99

Reprogram the CPLD through J1 using the programming file LTC2311.pof found at:

<http://www.linear.com/demo/DC2425A>

Move JP8 to the **LVDS** position.

JP9 EEPROM: Factory use only.

JP10 OSC: Use this jumper to enable the onboard encode clock source. The default setting is **OFF**. The **ON** setting energizes this source. Refer to the DC2425A schematic for additional passive elements required to use the onboard source.

PARTS LIST

ITEM	QTY	REFERENCE	PART DESCRIPTION	MANUFACTURER/PART NUMBER
Required Circuit Components				
1	13	C4, C6, C11, C12, C36, C48, C53, C63, C71, C92, C93, C95, C100	CAP, X5R, 10µF, 6.3V 20% 0603	NIC, NMC0603X5R106M6.3TRPF4KF
2	0	C35, C37, C56, C64, C65	CAP, 0603	OPT
3	1	C54	CAP, NP0, 200pF, 50V 5%, 0603	MURATA, GRM1885C1H201JA01D
4	9	C3, C18, C19, C20, C21, C23, C51, C84, C99	CAP, X7R, 1µF, 25V 10%, 0603	TDK, C1608X7R1E105K
5	2	C106, C119	CAP, X5R, 4.7µF, 6.3V 10%, 0603	AVX, 06036D475KAT2A
6	1	C68	CAP, X5R, 2.2µF, 10V 10%, 0603	MURATA, GRM188R61A225KE34D
7	1	C1	CAP, X7R, 47µF, 10V 10%, 1210	MURATA, GRM32ER71A476KE15L
8	5	C7, C8, C9, C10, C13	CAP, X7R, 0.01µF, 6.3V 10%, 0603	MURATA, GRM188R70J103KA01D
9	3	C2, C5, C17	CAP, X7R, 10µF, 10V 10%, 0805	MURATA, GRM21BR71A106KE51L
10	1	C22	CAP, X5R, 3.3µF, 6.3V 10%, 0603	AVX, 06036D335KAT2A
11	40	C14, C26, C31, C32, C33, C34, C42, C44, C45, C46, C49, C50, C52, C55, C57, C58, C59, C60, C61, C62, C66, C67, C69, C70, C72, C73, C74, C75, C76, C79, C81, C85, C86, C87, C88, C89, C90, C94, C96, C97	CAP, X7R, 0.1µF, 16V 10%, 0402	NIC, NMC0402X7R104K16TRPF
12	1	C30	CAP, X5R, 47µF, 6.3V 20%, 0805	TAIYO YUDEN, JMK212BJ476MG-T
13	3	C40, C43, C78	CAP, X7R, 0.01µF, 16V 10%, 0402	NIC, NMC0402X7R103K16TRPF
14	1	C80	CAP, X7R, 1nF, 16V 10%, 0402	AVX, 0402YC102KAT2A
15	3	C28, C82, C83	CAP, X7R, 22nF, 16V 10%, 0402	AVX, 0402YC223KAT2A
16	2	C77, C41	CAP, X7R, 4.7nF, 16V 10%, 0402	AVX, 0402YC472KAT2A
17	4	C15, C16, C24, C25	CAP, NP0, 10pF, 16V 10%, 0402	AVX, 0402YA100KAT2A
18	1	C27	CAP, TANT, 470µF 10V 20%, 7343	AVX, TPSE477M010R0050
19	1	C39	CAP, X7R, 2.2nF, 16V 10%, 0402	AVX, 0402YC222KAT2A
20	4	D1, D2, D3, D4	DIODE, SCHOTTKY 30V 200MW, SOD323	DIODE INC., BAT54WS-7-F
21	9	E4, E5, E6, E7, E8, E9, E10, E11, E12	TEST POINT, TURRET, 0.064"	MILL MAX, 2308-2-00-80-00-00-07-0
22	3	E1, E2, E3	TEST POINT, TURRET, 0.094"	MILL MAX, 2501-2-00-80-00-00-07-0
23	9	JP1, JP2, JP3, JP4, JP6, JP7, JP8, JP9, JP10	HEADER, 1X3, 0.100"	SAMTEC, TSW-103-07-L-S
24	1	JP5	HEADER, 2X3, 0.100"	SAMTEC, TSW-103-07-L-D
25	3	J3, J4, J5	CONN BNC FEM JACK PC MNT STRGHT	AMPHENOL CONNEX, 112404
26	2	J1, J2	HEADER, 2X5, 0.100"	SAMTEC, TSW-105-07-L-D
27	2	L1, L2	IND., FERRITE CHIP 390Ω 2000mA 1206	MURATA, BLM31PG391SN1L
28	10	R2, R8, R9, R10, R11, R23, R38, R58, R72, R73	RES., CHIP, 1k, 1/10W, 1% 0603	PANASONIC, ERJ-3EKF1001V
29	0	R21, R24, R27, R29, R31, R35, R46, R50, R75	RES., CHIP, 0603	OPT
30	1	R53	RES., CHIP, 33Ω, 1/10W, 5% 0603	PANASONIC, ERJ-3GEYJ330V

DEMO MANUAL DC2425A

PARTS LIST

ITEM	QTY	REFERENCE	PART DESCRIPTION	MANUFACTURER/PART NUMBER
31	7	R20, R22, R25, R39, R45, R47, R52	RES., CHIP, 0Ω, 1/10W, 0603	PANASONIC, ERJ-3GEY0R00V
32	2	R30, R33	RES., CHIP, 0Ω, 1/16W, 0402	PANASONIC, ERJ-2GEJ0R00V
33	2	R28, R32	RES., CHIP, 49.9Ω, 1/10W, 1% 0603	PANASONIC, ERJ-3EKF49R9V
34	1	R74	RES., CHIP, 49.9Ω, 1/4W, 1% 1206	PANASONIC, ERJ-8ENF49R9V
35	0	R26, R31	RES., CHIP, 0402	OPT
36	2	R3, R4	RES., CHIP, 3.92k, 1/10W, 1% 0603	PANASONIC, ERJ-3EKF3921V
37	1	R5	RES., CHIP, 499Ω, 1/10W, 1% 0603	PANASONIC, ERJ-3EKF4990V
38	1	R12	RES., CHIP, 866Ω, 1/10W, 1% 0603	PANASONIC, ERJ-3EKF8660V
39	1	R6	RES., CHIP, 3.09k, 1/10W, 1% 0603	PANASONIC, ERJ-3EKF3091V
40	1	R1	RES., CHIP, 4.02k, 1/10W, 1% 0603	PANASONIC, ERJ-3EKF4021V
41	1	R7	RES., CHIP, 1.43k, 1/10W, 1% 0603	PANASONIC, ERJ-3EKF1431V
42	18	R19, R34, R36, R37, R40, R41, R42, R43, R44, R48, R49, R51, R53, R54, R55, R56, R65, R66, R67	RES., CHIP, 33Ω, 1/16W, 5% 0402	PANASONIC, ERJ-2GEJ330X
43	1	R15	RES., CHIP, 1k, 1/16W, 1% 0402	PANASONIC, ERJ-2RK1001X
44	4	R68, R69, R70, R71	RES., CHIP, 4.99k, 1/10W, 1% 0603	PANASONIC, ERJ-3EKF4991V
45	9	R13, R14, R16, R17, R18, R61, R62, R63, R64	RES., CHIP, 10k, 1/16W, 5% 0402	PANASONIC, ERJ-2GEJ103X
46	3	R77, R78, R79	RES., CHIP, 10k, 1/10W, 5% 0603	PANASONIC, ERJ-3GEYJ103V
47	1	R76	RES., CHIP, 100, 1/10W, 1% 0603	PANASONIC, ERJ-3EKF1000V
48	2	U12, U16	IC, INVERTER UHS SINGLE SC70-5	FAIRCHILD, NC7SZ04P5X
49	1	U9	IC, 400MHz AMPLIFIER, MS8	LINEAR TECH., LT1819CMS8#PBF
50	1	U13	IC, FLIP FLOP D-TYPE LOG, US8	ON SEMI., NL17SZ74USG
51	1	U14	IC, VOLTAGE REFERENCE, MSOP8	LINEAR TECH., LTC6655BHMS8-4.096#PBF
52	1	U17	IC, OP-AMP, TSOT23-5	LINEAR TECH., LT6202CS5#PBF
53	4	U2, U3, U4, U7	IC, MICROPOWER REGULATOR, SO8	LINEAR TECH., LT1763CS8#PBF
54	1	U1	IC, MICROPOWER NEG. REGULATOR, SOT-23	LINEAR TECH., LT1964ES5-SD#PBF
55	1	U5	IC, MICROPOWER REGULATOR, SO8	LINEAR TECH., LT1763CS8-2.5#PBF
56	1	U6	IC, LINEAR REGULATOR, SO8	LINEAR TECH., LT3021ES8-1.2#PBF
57	1	U11	IC, CYCLONE III FPGA 5k, EQFP144	ALTERA, EP3C5E144C7N
58	1	U8	IC, CONFIG DEVICE 4MBIT, SO8	ALTERA, EPCS4SI8N
59	1	U15	IC, EEPROM 2kBIT 400kHz, TSSOP8	MICROCHIP, 24LC024-I/ST
60	1	Y1	OSCILLATOR, 106.2500 MHz 3.3V SMD, Y-CB3LV	CTS-FREQUENCY, CB3LV-3I-106M2500
61	10	SHUNTS AS SHOWN ON ASSY DWG	SHUNT, 0.100	SAMTEC, SNT-100-BK-G
62	4	MH1-MH4	STANDOFF, NYLON 0.25"	KEYSTONE, 8831 (SNAP ON)

PARTS LIST

ITEM	QTY	REFERENCE	PART DESCRIPTION	MANUFACTURER/PART NUMBER
DC2425A-A Required Circuit Components				
1	1	DC2425A	General BOM	
2	2	R58, R59	RES., CHIP, 1k, 1/10W, 1% 0402	PANASONIC, ERJ-2EKF1001V
3	0	R57, R60	RES, 0402 DNI	
4	1	U10	I.C., SAR ADC, MSOP-4X5	LINEAR TECH., LTC2311CMSE-16#PBF
DC2425A-B Required Circuit Components				
1	1	DC2425A	General BOM	
2	2	R58, R59	RES., CHIP, 1k, 1/10W, 1% 0402	PANASONIC, ERJ-2EKF1001V
3	0	R57, R60	RES, 0402 DNI	
4	1	U10	I.C., SAR ADC, MSOP-4X5	LINEAR TECH., LTC2310CMSE-16#PBF
DC2425A-C Required Circuit Components				
1	1	DC2425A	General BOM	
2	2	R57, R59	RES., CHIP, 1k, 1/10W, 1% 0402	PANASONIC, ERJ-2EKF1001V
3	0	R58, R60	RES, 0402 DNI	
4	1	U10	I.C., SAR ADC, MSOP-4X5	LINEAR TECH., LTC2311CMSE-14#PBF
DC2425A-D Required Circuit Components				
1	1	DC2425A	General BOM	
2	2	R57, R59	RES., CHIP, 1k, 1/10W, 1% 0402	PANASONIC, ERJ-2EKF1001V
3	0	R58, R60	RES, 0402 DNI	
4	1	U10	I.C., SAR ADC, MSOP-4X5	LINEAR TECH., LTC2310CMSE-14#PBF
DC2425A-E Required Circuit Components				
1	1	DC2425A	General BOM	
2	2	R57, R60	RES., CHIP, 1k, 1/10W, 1% 0402	PANASONIC, ERJ-2EKF1001V
3	0	R58, R59	RES, 0402 DNI	
4	1	U10	I.C., SAR ADC, MSOP-4X5	LINEAR TECH., LTC2311CMSE-12#PBF
DC2425A-F Required Circuit Components				
1	1	DC2425A	General BOM	
2	2	R57, R60	RES., CHIP, 1k, 1/10W, 1% 0402	PANASONIC, ERJ-2EKF1001V
3	0	R58, R59	RES, 0402 DNI	
4	1	U10	I.C., SAR ADC, MSOP-4X5	LINEAR TECH., LTC2310CMSE-12#PBF

DEMO MANUAL DC2425A

SCHEMATIC DIAGRAMS

ECO

REV

0

DESCRIPTION

PRODUCTION

APPROVED

DOUG S.

DATE

08-28-13

1

2

3

4

5

6

7

8

9

10

11

12

13

14

15

16

17

18

19

20

21

22

23

24

25

26

27

28

29

30

31

32

33

34

35

36

37

38

39

40

41

42

43

44

45

46

47

48

49

50

51

52

53

54

55

56

57

58

59

60

61

62

63

64

65

66

67

68

69

70

71

72

73

74

75

76

77

78

79

80

81

82

83

84

85

86

87

88

89

90

91

92

93

94

95

96

97

98

99

100

101

102

103

104

105

106

107

108

109

110

111

112

113

114

115

116

117

118

119

120

121

122

123

124

125

126

127

128

129

130

131

132

133

134

135

136

137

138

139

140

141

142

143

144

145

146

147

148

149

150

151

152

153

154

155

156

157

158

159

160

161

162

163

164

165

166

167

168

169

170

171

172

173

174

175

176

177

178

179

180

181

182

183

184

185

186

187

188

189

190

191

192

193

194

195

196

197

198

199

200

201

202

203

204

205

206

207

208

209

210

211

212

213

214

215

216

217

218

219

220

221

222

223

224

225

226

227

228

229

230

231

232

233

234

235

236

237

238

239

240

241

242

243

244

245

246

247

248

249

250

251

252

253

254

255

256

257

258

259

260

261

262

263

264

265

266

267

268

269

270

271

272

273

274

275

276

277

278

279

280

281

282

283

284

285

286

287

288

289

290

291

292

293

294

295

296

297

298

299

300

301

302

303

304

305

306

307

308

309

310

311

312

313

314

315

316

317

318

319

320

321

322

323

324

325

326

327

328

329

330

331

332

333

334

335

336

337

338

339

340

341

342

343

344

345

346

347

348

349

350

351

352

353

354

355

356

357

358

359

360

361

362

363

364

365

366

367

368

369

370

371

372

373

374

375

376

377

378

379

380

381

382

383

384

385

386

387

388

389

390

391

392

393

394

395

396

397

398

399

400

401

402

403

404

405

406

407

408

409

410

411

412

413

414

415

416

417

418

419

420

421

422

423

424

425

426

427

428

429

430

431

432

433

434

435

436

437

438

439

440

441

442

443

444

445

446

447

448

449

450

451

452

453

454

455

456

457

458

459

460

461

462

463

464

465

466

467

468

469

470

471

472

473

474

475

476

477

478

479

480

481

482

483

484

485

486

487

488

489

490

491

492

493

494

495

496

497

498

499

500

501

502

503

504

505

506

507

508

509

510

511

512

513

514

515

516

517

518

519

520

521

522

523

524

525

526

527

528

529

530

531

532

533

534

535

536

537

538

539

540

541

542

543

544

545

546

547

548

549

550

551

552

553

554

555

556

557

558

559

560

561

562

563

564

565

566

567

568

569

570

571

572

573

574

575

576

577

578

579

580

581

582

583

584

585

586

587

588

589

590

591

592

593

594

595

596

597

598

599

600

601

602

603

604

605

606

607

608

609

610

611

612

613

614

615

616

617

618

619

620

621

622

623

624

625

626

627

628

629

630

631

632

633

634

635

636

637

638

639

640

641

642

643

644

645

646

647

648

649

650

651

652

653

654

655

656

657

658

659

660

661

662

663

664

665

666

667

668

669

670

671

672

673

674

675

676

677

678

679

680

681

682

683

684

685

686

687

688

689

690

691

692

693

694

695

696

697

698

699

700

701

702

703

704

705

706

707

708

709

710

711

712

713

714

715

716

717

718

719

720

721

722

723

724

725

726

727

728

729

730

731

732

733

734

735

736

737

738

739

740

741

742

743

744

745

746

747

748

749

750

751

752

753

754

755

756

757

758

759

760

761

762

763

764

765

766

767

768

769

770

771

772

773

774

775

776

777

778

779

780

781

782

783

784

785

786

787

788

789

790

791

792

793

794

795

796

797

798

799

800

801

802

803

804

805

806

807

808

809

810

811

812

813

814

815

816

817

818

819

820

821

822

823

824

825

826

827

828

829

830

831

832

833

834

835

836

837

838

839

840

841

842

843

844

845

846

847

848

849

850

851

852

853

854

855

856

857

858

859

860

861

862

863

864

865

866

867

868

869

870

871

872

873

874

875

876

877

878

879

880

881

882

883

884

885

886

887

888

889

890

891

892

893

894

895

896

897

898

899

900

901

902

903

904

905

906

907

908

909

910

911

912

913

914

915

916

917

918

919

920

921

922

923

924

925

926

927

928

929

930

931

932

933

934

935

936

937

938

939

940

941

942

943

944

945

946

947

948

949

950

951

952

953

954

955

956

957

958

959

960

961

962

963

964

965

966

967

968

969

970

971

972

973

974

975

976

977

978

979

980

981

982

983

984

985

986

987

988

989

990

991

992

993

994

995

996

997

998

999

1000

1630 McCarty Blvd.
Milpitas, CA 95035
Phone: (408)432-1900 www.linear.com
Fax: (408)434-4307
LTC Confidential-For Customer Use Only

LINEAR

TECHNOLOGY

TITLE: SCHEMATIC

TRUE DIFFERENTIAL INPUT ADC

SIZE B

IC NO. LTC231XIMSE FAMILY

REV. 0

DATE: Thursday, December 03, 2015

SHEET 1 OF 2

CUSTOMER NOTICE

LINEAR TECHNOLOGY HAS MADE A BEST EFFORT TO DESIGN A CIRCUIT THAT MEETS CUSTOMER-SUPPLIED SPECIFICATIONS; HOWEVER, IT REMAINS THE CUSTOMER'S RESPONSIBILITY TO VERIFY PERFORMANCE OF THE CIRCUIT IN THEIR FINAL APPLICATION. COMPONENT SUBSTITUTION AND PRINTED CIRCUIT BOARD LAYOUT MAY SIGNIFICANTLY AFFECT CIRCUIT PERFORMANCE OR RELIABILITY. CONTACT LINEAR TECHNOLOGY APPLICATIONS ENGINEERING FOR ASSISTANCE.

APPROVALS

POB DES. D. STUETZLE

APP ENG. D. STUETZLE

SCALE = NONE

THIS CIRCUIT IS PROPERTY OF LINEAR TECHNOLOGY AND SUPPLIED FOR USE WITH LINEAR TECHNOLOGY PARTS.

* ASST

U1

ENTS

Meqns

R27

R28

R29

R30

-3

LTC231XIMSE-14

14

2

DNI

1K

DNI

-4

LTC231XIMSE-14

14

3

DNI

1K

DNI

-5

LTC231XIMSE-14

14

4

DNI

1K

DNI

-6

LTC231XIMSE-14

14

5

DNI

1K

DNI

-7

LTC231XIMSE-14

14

6

DNI

1K

DNI

-8

LTC231XIMSE-14

14

7

DNI

1K

DNI

-9

LTC231XIMSE-14

14

8

DNI

1K

DNI

-10

LTC231XIMSE-14

14

9

DNI

1K

DNI

-11

LTC231XIMSE-14

14

10

DNI

1K

DNI

-12

LTC231XIMSE-14

14

11

DNI

1K

DNI

-13

LTC231XIMSE-14

14

12

DNI

1K

DNI

-14

LTC231XIMSE-14

14

13

DNI

1K

DNI

-15

LTC231XIMSE-14

14

14

DNI

1K

DNI

-16

LTC231XIMSE-14

14

15

DNI

1K

DNI

-17

LTC231XIMSE-14

14

16

DNI

1K

DNI

-18

LTC231XIMSE-14

14

17

DNI

1K

DNI

-19

LTC231XIMSE-14

14

18

DNI

1K

DNI

-20

LTC231XIMSE-14

14

19

DNI

1K

DNI

-21

LTC231XIMSE-14

14

20

DNI

1K

DNI

-22

LTC231XIMSE-14

14

21

DNI

1K

DNI

-23

LTC231XIMSE-14

14

22

DNI

1K

DNI

-24

LTC231XIMSE-14

14

23

DNI

1K

DNI

-25

LTC231XIMSE-14

14

24

DNI

1K

DNI

-26

LTC231XIMSE-14

14

25

DNI

1K

DNI

-27

LTC231XIMSE-14

14

26

DNI

1K

DNI

-28

LTC231XIMSE-14

14

27

DNI

1K

DNI

-29

LTC231XIMSE-14

14

28

DNI

1K

DNI

-30

LTC231XIMSE-14

14

29

DNI

1K

DNI

-31

LTC231XIMSE-14

14

30

DNI

1K

DNI

-32

LTC231XIMSE-14

14

31

DNI

1K

DNI

-33

LTC231XIMSE-14

14

32

DNI

1K

DNI

-34

LTC231XIMSE-14

14

33

DNI

1K

DNI

-35

LTC231XIMSE-14

14

34

DNI

1K

DNI

-36

LTC231XIMSE-14

14

35

DNI

1K

DNI

-37

LTC231XIMSE-14

14

36

DNI

1K

DNI

-38

LTC231XIMSE-14

14

37

DNI

1K

DNI

-39

LTC231XIMSE-14

14

38

DNI

1K

DNI

-40

LTC231XIMSE-14

14

39

DNI

1K

DNI

-41

LTC231XIMSE-14

14

40

DNI

1K

DNI

-42

LTC231XIMSE-14

14

41

DNI

1K

DNI

-43

LTC231XIMSE-14

14

42

DNI

1K

DNI

-44

LTC231XIMSE-14

14

43

DNI

1K

DNI

-45

LTC231XIMSE-14

14

44

DNI

1K

DNI

-46

LTC231XIMSE-14

14

45

DNI

1K

DNI

-47

LTC231XIMSE-14

14

46

DNI

1K

DNI

-48

LTC231XIMSE-14

14

47

DNI

1K

DNI

-49

LTC231XIMSE-14

14

48

DNI

1K

DNI

-50

LTC231XIMSE-14

14

49

DNI

1K

DNI

-51

LTC231XIMSE-14

14

50

DNI

1K

DNI

-52

LTC231XIMSE-14

14

51

DNI

1K

DNI

-53

LTC231XIMSE-14

14

52

DNI

1K

DNI

-54

LTC231XIMSE-14

14

53

DNI

1K

DNI

-55

LTC231XIMSE-14

14

54

DNI

1K

DNI

-56

LTC231XIMSE-14

14

55

DNI

1K

DNI

-57

LTC231XIMSE-14

14

56

DNI

1K

DNI

-58

LTC231XIMSE-14

14

57

DNI

1K

DNI

-59

LTC231XIMSE-14

14

58

DNI

1K

DNI

-60

LTC231XIMSE-14

14

59

DNI

1K

DNI

-61

LTC231XIMSE-14

14

60

DNI

1K

DNI

-62

LTC231XIMSE-14

14

61

DNI

1K

DNI

-63

LTC231XIMSE-14

14

62

DNI

1K

DNI

-64

LTC231XIMSE-14

14

63

DNI

1K

DNI

-65

LTC231XIMSE-14

14

64

DNI

1K

DNI

-66

LTC231XIMSE-14

14

65

DNI

1K

DNI

-67


LTC231XIMSE-14


14

66

D

SCHEMATIC DIAGRAMS



CUSTOMER NOTICE LINEAR TECHNOLOGY HAS MADE A BEST EFFORT TO DESIGN A CIRCUIT THAT MEETS CUSTOMER-SUPPLIED SPECIFICATIONS. HOWEVER, IT REMAINS THE CUSTOMER'S RESPONSIBILITY TO VERIFY THE CIRCUIT'S PERFORMANCE IN THEIR SPECIFIC APPLICATION. COMPONENT SUBSTITUTION AND PRINTED CIRCUIT BOARD LAYOUT MAY SIGNIFICANTLY AFFECT CIRCUIT PERFORMANCE OR RELIABILITY. CONTACT LINEAR TECHNOLOGY APPLICATIONS ENGINEERING FOR ASSISTANCE.		APPROVALS PCB DES. D. STUETZLE APP. ENG. D. STUETZLE		 LINEAR TECHNOLOGY 1820 McCarty Blvd. Milpitas, CA 95035 Phone: (408) 432-1900 www.linear.com Fax: (408) 434-0037 LTC Confidential-For Customer Use Only	
TRUE DIFFERENTIAL INPUT ADC		IC NO.		REV.	
SIZE		B		0	
DATE:		Thursday, May 07, 2015		0	
SCALE = NONE		LT C231XIMSE FAMILY		DEMO CIRCUIT 2425A	
DATE:		2		OF 2	

DEMO MANUAL DC2425A

DEMONSTRATION BOARD IMPORTANT NOTICE

Linear Technology Corporation (LTC) provides the enclosed product(s) under the following **AS IS** conditions:

This demonstration board (DEMO BOARD) kit being sold or provided by Linear Technology is intended for use for **ENGINEERING DEVELOPMENT OR EVALUATION PURPOSES ONLY** and is not provided by LTC for commercial use. As such, the DEMO BOARD herein may not be complete in terms of required design-, marketing-, and/or manufacturing-related protective considerations, including but not limited to product safety measures typically found in finished commercial goods. As a prototype, this product does not fall within the scope of the European Union directive on electromagnetic compatibility and therefore may or may not meet the technical requirements of the directive, or other regulations.

If this evaluation kit does not meet the specifications recited in the DEMO BOARD manual the kit may be returned within 30 days from the date of delivery for a full refund. THE FOREGOING WARRANTY IS THE EXCLUSIVE WARRANTY MADE BY THE SELLER TO BUYER AND IS IN LIEU OF ALL OTHER WARRANTIES, EXPRESSED, IMPLIED, OR STATUTORY, INCLUDING ANY WARRANTY OF MERCHANTABILITY OR FITNESS FOR ANY PARTICULAR PURPOSE. EXCEPT TO THE EXTENT OF THIS INDEMNITY, NEITHER PARTY SHALL BE LIABLE TO THE OTHER FOR ANY INDIRECT, SPECIAL, INCIDENTAL, OR CONSEQUENTIAL DAMAGES.

The user assumes all responsibility and liability for proper and safe handling of the goods. Further, the user releases LTC from all claims arising from the handling or use of the goods. Due to the open construction of the product, it is the user's responsibility to take any and all appropriate precautions with regard to electrostatic discharge. Also be aware that the products herein may not be regulatory compliant or agency certified (FCC, UL, CE, etc.).

No License is granted under any patent right or other intellectual property whatsoever. **LTC assumes no liability for applications assistance, customer product design, software performance, or infringement of patents or any other intellectual property rights of any kind.**

LTC currently services a variety of customers for products around the world, and therefore this transaction **is not exclusive**.

Please read the DEMO BOARD manual prior to handling the product. Persons handling this product must have electronics training and observe good laboratory practice standards. **Common sense is encouraged.**

This notice contains important safety information about temperatures and voltages. For further safety concerns, please contact a LTC application engineer.

Mailing Address:

Linear Technology
1630 McCarthy Blvd.
Milpitas, CA 95035

Copyright © 2004, Linear Technology Corporation