

Errata sheet

LPC54018JxM_LPC54S018JxM

Errata sheet LPC54018JxM_LPC54S018JxM

Rev. 1.0 — 27 January 2019

Errata sheet

Document information

Info	Content
Keywords	LPC54018J2MET180, LPC54018J4MET180, LPC54S018J2MET180, LPC54S018J4MET180
Abstract	LPC54018JxM and LPC54S018JxM errata



Revision history

Rev	Date	Description
v.1	20190127	<ul style="list-style-type: none">Initial version.

Contact information

For more information, please visit: <http://www.nxp.com>

For sales office addresses, please send an email to: salesaddresses@nxp.com

1. Product identification

The LPC54018JxM_LPC54S018JxM TFBGA180 package have the following top-side marking:

- First line: LPC54018JxM_LPC54S018JxM
- Second line: ET180
- Third line: xxxxxxxxxxxx
- Fourth line: xxxyywwx[R]x
 - yyww: Date code with yy = year and ww = week.
 - xR = boot code version and device revision.

Table 1. Device revision table

Revision identifier (R)	Revision description
1B	Initial device revision with Boot ROM version 21.1

2. Errata overview

Table 2. Functional problems table

Functional problems	Short description	Revision identifier	Detailed description
USB.2	In USB full-speed device mode, the ROOT2 endpoint test fails.	1B	Section 3.1
ADC.1	High current consumption in reduced low power modes when using ADC.	1B	Section 3.2
SHA.1	Using MEMCTRL after DIGEST Ready to include more blocks via Mastering does not clear DIGEST bit.	1B	Section 3.3

Table 3. AC/DC deviations table

AC/DC deviations	Short description	Revision identifier	Detailed description
n/a	n/a	n/a	n/a

Table 4. Errata notes

Note	Short description	Revision identifier	Detailed description
n/a	n/a	n/a	n/a

3. Functional problems detail

3.1 USB.2: In USB full-speed device mode, the ROOT2 endpoint test fails

Introduction:

The LPC540xx/LPC54S0xx includes a USB full speed interface (USB0) that can operate in device mode at full speed. It supports 10 physical (5 logical) endpoints including control endpoints. The device should not respond to those endpoints which are not supported.

Problem:

The device NAKed the OUT token addressed to an endpoint that is not present on the device causing the ROOT2 endpoint test to fail.

Work-around:

There is no work-around.

3.2 ADC.1: High current consumption in reduced low power modes when using ADC.

Introduction:

The 12-bit ADC controller is available on all LPC540xx/LPC54S0xx parts. The ADC can measure the voltage on any of the input signals on the analog input channel. For accurate voltage readings, the digital pin function on the ADC input channel must be disabled by writing a 0 to the DIGIMODE bit in the related IOCON register. This enables the analog mode functionality on the ADC input channel.

Problem:

For applications using the ADC, the current consumption could be higher than expected in reduced power modes (deep-sleep and deep power-down modes) or when the ADC is disabled using the PDRUNCFG register.

Work-around:

To prevent high current consumption, use the following steps in the software:

1. Following a chip reset, all 12 ADC input channels (ADC0_0 to ADC0_11) should be in Digital Mode (DIGIMODE = 1) in the related IOCON registers until the configuration of the ADC block is complete. See the Basic Configuration section in the LPC540xx/LPC54S0xx 12-bit ADC controller (ADC) chapter of the LPC540xx/LPC54S0xx User Manual.
2. After configuring the ADC, change only those pins that are used as ADC input channels to Analog Mode (DIGIMODE = 0) in the related IOCON registers before starting ADC conversions.
3. Before entering any reduced power mode (deep-sleep and deep power-down) or before powering down the ADC block (by writing to the PDEN_ADC0 bit in the PDRUNCFG register), the ADC input channel(s) must be changed back to Digital Mode.
4. After waking up from the reduced power mode or when re-enabling the ADC block (PDEN_ADC0 bit in the PDRUNCFG), the software must follow step 2 before starting ADC conversions.

3.3 SHA.1: Using MEMCTRL after DIGEST Ready to include more blocks via Mastering does not clear DIGEST bit.

Introduction:

The LPC540xx/LPC54S0xx includes a SHA hash block to compute SHA1 and SHA2-256 hash digests on flash images or messages in RAM. For maximum performance and ease of use, the hash block includes a master on the internal buses of the chip to read multiple blocks of memory while hashing, without involvement of the processor. This mastering model permits hashing up to 128 K bytes of memory (Flash, RAM, or SPI Flash).

Problem:

If the application uses the mastering on up to 128 K bytes and then uses it for additional blocks (without starting new), the DIGEST (digest ready) status does not clear when starting the next sequence via mastering. If the processor or DMA is used for the additional blocks, the DIGEST status is cleared.

Work-around:

If the purpose for the additional block(s) is to hash the last block (with padding and length), then the processor or DMA may be used to write the 16 words via INDATA, and the DIGEST status will clear when the 1st word is written.

If the purpose for additional blocks is to do a large number of blocks (for example, after doing 128 K, another 64 K is to be hashed), then the 1st block may be started by the processor (that is, the processor writes the 16 words to INDATA) followed by configuring MEMADDR and MEMCTRL for the remaining blocks. The MEMCTRL should be written within 64 cycles of writing the last word to INDATA to ensure DIGEST is 0.

4. AC/DC deviations detail

No known errata.

5. Errata notes

No known errata.

6. Legal information

6.1 Definitions

Draft — The document is a draft version only. The content is still under internal review and subject to formal approval, which may result in modifications or additions. NXP Semiconductors does not give any representations or warranties as to the accuracy or completeness of information included herein and shall have no liability for the consequences of use of such information.

6.2 Disclaimers

Limited warranty and liability — Information in this document is believed to be accurate and reliable. However, NXP Semiconductors does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information.

In no event shall NXP Semiconductors be liable for any indirect, incidental, punitive, special or consequential damages (including - without limitation - lost profits, lost savings, business interruption, costs related to the removal or replacement of any products or rework charges) whether or not such damages are based on tort (including negligence), warranty, breach of contract or any other legal theory.

Notwithstanding any damages that customer might incur for any reason whatsoever, NXP Semiconductors' aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the *Terms and conditions of commercial sale* of NXP Semiconductors.

Right to make changes — NXP Semiconductors reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.

Suitability for use — NXP Semiconductors products are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or malfunction of an NXP Semiconductors product can reasonably be expected to result in personal injury, death or severe property or environmental damage. NXP Semiconductors accepts no liability for inclusion and/or use of NXP Semiconductors products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

Applications — Applications that are described herein for any of these products are for illustrative purposes only. NXP Semiconductors makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Customers are responsible for the design and operation of their applications and products using NXP Semiconductors products, and NXP Semiconductors accepts no liability for any assistance with applications or customer product design. It is customer's sole responsibility to determine whether the NXP Semiconductors product is suitable and fit for the customer's applications and products planned, as well as for the planned application and use of customer's third party customer(s). Customers should provide appropriate design and operating safeguards to minimize the risks associated with their applications and products.

NXP Semiconductors does not accept any liability related to any default, damage, costs or problem which is based on any weakness or default in the customer's applications or products, or the application or use by customer's third party customer(s). Customer is responsible for doing all necessary testing for the customer's applications and products using NXP Semiconductors products in order to avoid a default of the applications and the products or of the application or use by customer's third party customer(s). NXP does not accept any liability in this respect.

Export control — This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from national authorities.

6.3 Trademarks

Notice: All referenced brands, product names, service names and trademarks are the property of their respective owners.

7. Contents

1	Product identification	3
2	Errata overview	4
3	Functional problems detail	5
3.1	USB.2: In USB full-speed device mode, the ROOT2 endpoint test fails	5
3.2	ADC.1: High current consumption in reduced low power modes when using ADC.	5
3.3	SHA.1: Using MEMCTRL after DIGEST Ready to include more blocks via Mastering does not clear DIGEST bit.....	6
4	AC/DC deviations detail	7
5	Errata notes	7
6	Legal information	8
6.1	Definitions	8
6.2	Disclaimers	8
6.3	Trademarks	8
7	Contents	9

Please be aware that important notices concerning this document and the product(s) described herein, have been included in section 'Legal information'.

© NXP B.V. 2019.

All rights reserved.

For more information, please visit: <http://www.nxp.com>

For sales office addresses, please send an email to: salesaddresses@nxp.com

Date of release: 27 January 2019

Document identifier: LPC54018JxM_LPC54S018JxM