MIC919

27MHz Low-Power SOT-23-5/SC-70 Op Amp

Final Information

The Infinite Bandwidth Company™

General Description

The MIC919 is a high-speed operational amplifier with a gain-bandwidth product of 27MHz. The part is unity gain stable. It has a very low 360µA supply current, and features the IttyBitty™ SOT-23-5 package and SC-70 package.

Supply voltage range is from ±2.5V to ±9V, allowing the MIC919 to be used in low-voltage circuits or applications requiring large dynamic range.

The MIC919 is stable driving any capacitative load and achieves excellent PSRR and CMRR, making it much easier to use than most conventional high-speed devices. Low supply voltage, low power consumption, and small packing make the MIC919 ideal for portable equipment. The ability to drive capacitative loads also makes it possible to drive long coaxial cables.

Features

- 27MHz gain bandwidth product
- 360µA supply current
- SOT-23-5 or SC-70 packages
- 1500V/µs slew rate
- drives any capacitive load
- Unity gain stable

Applications


- Video
- Imaging
- Ultrasound
- Portable equipment
- Line drivers

Ordering Information

Part Number	Junction Temp.	Range Package
MIC919BM5	–40C to +85C	SOT-23-5*
MIC919BC5	–40C to +85C	SC-70


*Contact factory about SOT-23-5 package.

Pin Configuration



SOT-23-5 or SC-70

Functional Pinout



SOT-23-5 or SC-70

Pin Description

Pin Number	Pin Name	Pin Function
1	IN+	Noninverting Input
2	V–	Negative Supply (Input)
3	IN–	Inverting Input
4	OUT	Output: Amplifier Output
5	V+	Positive Supply (Input)

Absolute Maximum Ratings (Note 1)

Supply Voltage ($V_{V+} - V_{V-}$) 20V
Differentail Input Voltage ($|V_{IN+} - V_{IN-}|$) ..... 4V, **Note 3**
Input Common-Mode Range (V_{IN+}, V_{IN-}) ..... V_{V+} to V_{V-}
Lead Temperature (soldering, 5 sec.) ..... 260°C
Storage Temperature (T_S) ..... 150°C
ESD Rating, **Note 4** 1.5kV

Operating Ratings (Note 2)

Supply Voltage (V_S) ..... ±2.5V to ±9V
Junction Temperature (T_J) ..... –40°C to +85°C
Package Thermal Resistance
SOT-23-5 ..... 260°C/W
SC-70-5 ..... 450°C/W

Electrical Characteristics (±5V)

V+ = +5V, V– = –5V, V_{CM} = 0V, R_L = 10MΩ; T_J = 25°C, **bold** values indicate –40°C ≤ T_J ≤ +85°C; unless noted.

Symbol	Parameter	Condition	Min	Typ	Max	Units
V_{OS}	Input Offset Voltage			0.43	**5**	mV
V_{OS}	V_{OS} Temperature Coefficient			1		µV/°C
I_B	Input Bias Current			0.13	**0.6**	µA
I_{OS}	Input Offset Current			0.06	**0.3**	µA
V_{CM}	Input Common-Mode Range	CMRR > 72dB	**–3.25**		**+3.25**	V
CMRR	Common-Mode Rejection Ratio	–2.5V < V_{CM} < +2.5V	**75**	87		dB
PSRR	Power Supply Rejection Ratio	±3.5V < V_S < ±9V	**95**	105		dB
A_{VOL}	Large-Signal Voltage Gain	R_L = 2k, V_{OUT} = ±2V	**70**	84		dB
		R_L = 100Ω, V_{OUT} = ±1V		85		dB
V_{OUT}	Maximum Output Voltage Swing	positive, R_L = 2kΩ	**+3.0**	3.7		V
		negative, R_L = 2kΩ		–3.7	**–3.0**	V
		positive, R_L = 200Ω	**+1.5**	3.0		V
		negative, R_L = 200Ω, **Note 5**		–2.5	**–1.0**	V
GBW	Unity Gain-Bandwidth Product			23		MHz
PM	Phase Margin			63		°
BW	–3dB Bandwidth			53		MHz
SR	Slew Rate	C=1.7pF, Gain=1, V_{OUT}=5V, peak to peak, positive SR = 450V/µs		850		V/µs
I_{SC}	Short-Circuit Output Current	source	**45**	57		mA
		sink	**20**	40		mA
I_S	Supply Current	No Load		0.30	**0.50**	mA
	Input Voltage Noise	f = 10kHz		10		nV/√Hz
	Input Current Noise	f = 10kHz		0.78		pA/√Hz

Electrical Characteristics

V+ = +9V, V– = –9V, V_{CM} = 0V, R_L = 10MΩ; T_J = 25°C, **bold** values indicate –40°C ≤ T_J ≤ +85°C; unless noted

Symbol	Parameter	Condition	Min	Typ	Max	Units
V_{OS}	Input Offset Voltage			0.4	**5**	mV
V_{OS}	Input Offset Voltage Temperature Coefficient			1		µV/°C
I_B	Input Bias Current			0.13	**0.60**	µA
I_{OS}	Input Offset Current			0.06	**0.3**	µA
V_{CM}	Input Common-Mode Range	CMRR > 75dB	**–7.25**		**+7.25**	V
CMRR	Common-Mode Rejection Ratio	–6.5V < V_{CM} < +6.5V	**75**	87		dB
PSRR	Power Supply Rejection Ratio	±3.5V < V_S < ±9V	**95**	105		dB

Symbol	Parameter	Condition	Min	Typ	Max	Units
A_{VOL}	Large-Signal Voltage Gain	R_L = 2k, V_{OUT} = ±2V	**75**	86		dB
		R_L = 100Ω, V_{OUT} = ±1V		92		dB
V_{OUT}	Maximum Output Voltage Swing	positive, R_L = 2kΩ	**6.5**	7.6		V
		negative, R_L = 2kΩ		–7.6	**–6.2**	V
GBW	Unity Gain-Bandwidth Product			27		MHz
PM	Phase Margin			61		°
BW	–3dB Bandwidth			60		MHz
SR	Slew Rate	C=1.7pF, Gain=1, V_{OUT}=5V, peak to peak, positive SR = 750V/µs		1500		V/µs
I_{SC}	Short-Circuit Output Current	source	**40**	59		mA
		sink	**25**	45		mA
I_S	Supply Current	No Load		0.36	**0.6**	mA
	Input Voltage Noise	f = 10kHz		10		nV/√Hz
	Input Current Noise	f = 10kHz		0.78		pA/√Hz

Note 1. Exceeding the absolute maximum rating may damage the device.

Note 2. The device is not guaranteed to function outside its operating rating.


Note 3. Exceeding the maximum differential input voltage will damage the input stage and degrade performance (in particular, input bias current is likely to change).

Note 4. Devices are ESD sensitive. Handling precautions recommended. Human body model, 1.5k in series with 100pF.


Note 5. Output swing limited by the maximum output sink capability.

Typical Characteristics


Offset Voltage vs. Temperature




Supply Current vs. Temperature




Supply Current vs. Supply Voltage




Offset Voltage vs. Common-Mode Voltage




Offset Voltage vs. Common-Mode Voltage




Offset Voltage vs. Common-Mode Voltage




Positive Slew Rate vs. Load Capacitance




Negative Slew Rate vs. Load Capacitance




Positive Slew Rate vs. Load Capacitance




Negative Slew Rate vs. Load Capacitance




Positive Slew Rate vs. Supply Voltage




Negative Slew Rate vs. Supply Voltage



Voltage Noise



Current Noise



Applications Information

The MIC919 is a high-speed, voltage-feedback operational amplifier featuring very low supply current and excellent stability. This device is unity gain stable, capable of driving high capacitance loads.

Driving High Capacitance

The MIC919 is stable when driving high capacitance, making it ideal for driving long coaxial cables or other high-capacitance loads.

Phase margin remains constant as load capacitance is increased. Most high-speed op amps are only able to drive limited capacitance.

> Note: increasing load capacitance does reduce the speed of the device. In applications where the load capacitance reduces the speed of the op amp to an unacceptable level, the effect of the load capacitance can be reduced by adding a small resistor (<100Ω) in series with the output.

Feedback Resistor Selection

Conventional op amp gain configurations and resistor selection apply, the MIC919 is NOT a current feedback device. Also, for minimum peaking, the feedback resistor should have low parasitic capacitance, usually 470Ω is ideal. To use the part as a follower, the output should be connected to input via a short wire.

Layout Considerations

All high speed devices require careful PCB layout. The following guidelines should be observed: Capacitance, particularly on the two inputs pins will degrade performance; avoid large copper traces to the inputs. Keep the output signal away from the inputs and use a ground plane.

It is important to ensure adequate supply bypassing capacitors are located close to the device.

Power Supply Bypassing

Regular supply bypassing techniques are recommended. A 10µF capacitor in parallel with a 0.1µF capacitor on both the positive and negative supplies are ideal. For best performance all bypassing capacitors should be located as close to the op amp as possible and all capacitors should be low ESL (equivalent series inductance), ESR (equivalent series resistance). Surface-mount ceramic capacitors are ideal.

Thermal Considerations

The SOT-23-5 package and SC-70 package, like all small packages, has a high thermal resistance. It is important to ensure the IC does not exceed the maximum operating junction (die) temperature of 85°C. The part can be operated up to the absolute maximum temperature rating of 125°C, but between 85°C and 125°C performance will degrade, in particular CMRR will reduce.

An MIC919 with no load, dissipates power equal to the quiescent supply current * supply voltage

$$P_{D(no\,load)} = \left(V_{V+} - V_{V-}\right) I_S$$

When a load is added, the additional power is dissipated in the output stage of the op amp. The power dissipated in the device is a function of supply voltage, output voltage and output current.


$$P_{D(output\,stage)} = \left(V_{V+} - V_{OUT}\right) I_{OUT}$$

$$Total\ Power\ Dissipation = P_{D(no\,load)} + P_{D(output\,stage)}$$


Ensure the total power dissipated in the device is no greater than the thermal capacity of the package. The SOT23-5 package has a thermal resistance of 260°C/W.

$$Max.\,Allowable\,Power\,Dissipation = \frac{T_{J(max)} - T_{A(max)}}{260\text{W}}$$

Package Information



SOT-23-5 (M5)



SC-70 (C5)

MICREL INC. 1849 FORTUNE DRIVE SAN JOSE, CA 95131 USA

TEL + 1 (408) 944-0800 FAX + 1 (408) 944-0970 WEB http://www.micrel.com

This information is believed to be accurate and reliable, however no responsibility is assumed by Micrel for its use nor for any infringement of patents or other rights of third parties resulting from its use. No license is granted by implication or otherwise under any patent or patent right of Micrel Inc.

© 2001 Micrel Incorporated