

SPECIFICATION SHEET**JFW MODEL 50T-142****TERMINATION**

JFW Industries, Inc.
Phone: 317-887-1340
sales@jfwindustries.com
www.jfwindustries.com

Description	Termination with Optional Bead Chain
Frequency Range	DC-8000 MHz
Impedance	50 Ohms nominal
VSWR	1.1:1 maximum DC-1000 MHz 1.2:1 maximum 1000-4000 MHz 1.35:1 maximum 4000-8000 MHz
RF Input Power	2 Watts average
RF Connector	N male
Available Model Numbers	50T-142 N M (with bead chain) 50T-142 N M NB (without bead chain)
Physical Size	See outline drawings: 092-1832 (with bead chain) 092-4208 (without bead chain)

ECR/ECN #	DATE	REV	APPR / DATE	ECR/ECN #	DATE	REV	APPR / DATE
1079	05/19/1998	A		23840	03/10/2014	D	TRS 03/10/2014
2894	02/18/2002	B		27936	07/11/2017	E	CLK 07/11/2017
9999	02/14/2003	C	SL 04/30/2003				