

6MBI550V-120-50

IGBT Modules

IGBT MODULE (V series) 1200V / 550A / 6 in one package

■ Features

- Compact Package
- P.C.Board Mount
- Low $V_{CE(sat)}$

■ Applications

- Inverter for Motor Drive
- AC and DC Servo Drive Amplifier
- Uninterruptible Power Supply
- Industrial machines, such as welding machines



■ Maximum Ratings and Characteristics

● Absolute Maximum Ratings (at $T_c=25^\circ\text{C}$ unless otherwise specified)

Items		Symbols	Conditions		Maximum ratings	Units
Inverter	Collector-Emitter voltage	V _{CES}			1200	V
	Gate-Emitter voltage	V _{GES}			±20	V
	Collector current	I _C	Continuous	T _c =25°C	750	A
		I _{C pulse}	1ms	T _c =100°C	550	
		-I _C			1100	
		-I _{C pulse}	1ms	550		
	Collector power dissipation	P _C	1 device		1100	W
Junction temperature		T _J			2500	°C
Operating junciton temperature (under switching conditions)		T _{Jop}			150	
Case temperature		T _C			125	
Storage temperature		T _{stg}			-40 ~ +125	
Isolation voltage	Between terminal and copper base (*1)	V _{iso}	AC : 1min.		2500	VAC
	Between thermistor and others (*2)					
Screw torque	Mounting (*3)	-			3.5	N m
	Terminals (*4)				4.5	

Note *1: All terminals should be connected together during the test.

Note *2: Two thermistor terminals should be connected together, other terminals should be connected together and shorted to base plate during the test.

Note *3: Recommendable Value : 2.5-3.5 Nm (M5)

Note *4: Recommendable Value : 3.5-4.5 Nm (M6)

● Electrical characteristics (at Tj= 25°C unless otherwise specified)


Items	Symbols	Conditions	Characteristics			Units
			min.	typ.	max.	
Zero gate voltage collector current	ICES	VGE = 0V, VCE = 1200V	-	-	3.0	mA
Gate-Emitter leakage current	IGES	VCE = 0V, VGE = ±20V	-	-	600	nA
Gate-Emitter threshold voltage	VGE (th)	VCE = 20V, IC = 600mA	6.0	6.5	7.0	V
Collector-Emitter saturation voltage	VCE (sat) (terminal)	VGE = 15V IC = 600A	Tj=25°C	2.50	2.95	V
			Tj=125°C	2.85	-	
			Tj=150°C	2.90	-	
	VCE (sat) (chip)	VGE = 15V IC = 600A	Tj=25°C	1.85	2.10	
			Tj=125°C	2.20	-	
			Tj=150°C	2.25	-	
Internal gate resistance	RG (int)	-	-	1.10	-	Ω
Input capacitance	Cies	VCE = 10V, VGE = 0V, f = 1MHz	-	48	-	nF
Turn-on time	t _{on}	VCC = 600V IC = 600A VGE = ±15V RG = 0.62Ω LS = 80nH	-	550	-	nsec
	t _t		-	180	-	
	t _{t(i)}		-	120	-	
Turn-off time	t _{off}		-	1050	-	
	t _t		-	110	-	
Forward on voltage	VF (terminal)	VGE = 0V, IF = 600A	Tj=25°C	2.40	2.85	V
			Tj=125°C	2.55	-	
			Tj=150°C	2.50	-	
	VF (chip)	VGE = 0V, IF = 600A	Tj=25°C	1.75	2.20	
			Tj=125°C	1.90	-	
			Tj=150°C	1.85	-	
Reverse recovery time	trr	IF = 600A	-	200	-	nsec
Thermistor	Resistance	T = 25°C	-	5000	-	Ω
		T = 100°C	465	495	520	
	B value	T = 25 / 50°C	3305	3375	3450	K

● Thermal resistance characteristics

Items	Symbols	Conditions	Characteristics			Units
			min.	typ.	max.	
Thermal resistance (1device)	Rth(j-c)	Inverter IGBT	-	-	0.060	°C/W
		Inverter FWD	-	-	0.100	
Contact thermal resistance (1device) (*5)	Rth(c-f)	with Thermal Compound	-	0.0167	-	

Note *5: This is the value which is defined mounting on the additional cooling fin with thermal compound.


■ Equivalent Circuit Schematic



■ Characteristics (Representative)


[Inverter]

Collector current vs. Collector-Emitter voltage (typ.)

 $T_J = 25^\circ\text{C}$ / chip


[Inverter]

Collector current vs. Collector-Emitter voltage (typ.)

 $T_J = 150^\circ\text{C}$ / chip


[Inverter]

Collector current vs. Collector-Emitter voltage (typ.)

 $V_{GE} = 15\text{V}$ / chip


[Inverter]

Collector-Emitter voltage vs. Gate-Emitter voltage (typ.)

 $T_J = 25^\circ\text{C}$ / chip


[Inverter]

Capacitance vs. Collector-Emitter voltage (typ.)

 $V_{GE} = 0\text{V}$, $f = 1\text{MHz}$, $T_J = 25^\circ\text{C}$ 


[Inverter]

Dynamic gate charge (typ.)

 $V_{CC} = 600\text{V}$, $I_C = 600\text{A}$, $T_J = 25^\circ\text{C}$ 


[Inverter]

Switching time vs. Collector current (typ.)
 $V_{CC}=600V$, $V_{GE}=\pm 15V$, $R_G=0.62\Omega$, $T_J=25^\circ C$




[Inverter]

Switching time vs. Collector current (typ.)
 $V_{CC}=600V$, $V_{GE}=\pm 15V$, $R_G=0.62\Omega$, $T_J=125^\circ C, 150^\circ C$




[Inverter]

Switching time vs. gate resistance (typ.)
 $V_{CC}=600V$, $I_C=550A$, $V_{GE}=\pm 15V$, $T_J=125^\circ C, 150^\circ C$




[Inverter]

Switching loss vs. Collector current (typ.)
 $V_{CC}=600V$, $V_{GE}=\pm 15V$, $R_G=0.62\Omega$, $T_J=125^\circ C, 150^\circ C$




[Inverter]

Switching loss vs. gate resistance (typ.)
 $V_{CC}=600V$, $I_C=600A$, $V_{GE}=\pm 15V$, $T_J=125^\circ C, 150^\circ C$




[Inverter]

Reverse bias safe operating area (max.)
 $+V_{GE}=15V, -V_{GE} \leq 15V$, $R_G \geq 0.62\Omega$, $T_J=150^\circ C$




[INVERTER]

Forward Current vs. Forward Voltage (typ.)
chip




[INVERTER]

Reverse Recovery Characteristics (typ.)
V_{CE}=600V, V_{GE}=±15V, R_G=0.62Ω, T_J=25°C




[INVERTER]

Reverse Recovery Characteristics (typ.)
V_{CE}=600V, V_{GE}=±15V, R_G=0.62Ω, T_J=125°C, 150°C




Transient Thermal Resistance (max.)




[THERMISTOR]


Temperature characteristic (typ.)



FWD safe operating area (max.)
T_J=150°C



■ Outline Drawings, mm



WARNING

1. This Catalog contains the product specifications, characteristics, data, materials, and structures as of May 2011.
The contents are subject to change without notice for specification changes or other reasons. When using a product listed in this Catalog, be sure to obtain the latest specifications.
2. All applications described in this Catalog exemplify the use of Fuji's products for your reference only. No right or license, either express or implied, under any patent, copyright, trade secret or other intellectual property right owned by Fuji Electric Co., Ltd. is (or shall be deemed) granted. Fuji Electric Co., Ltd. makes no representation or warranty, whether express or implied, relating to the infringement or alleged infringement of other's intellectual property rights which may arise from the use of the applications described herein.
3. Although Fuji Electric Co., Ltd. is enhancing product quality and reliability, a small percentage of semiconductor products may become faulty. When using Fuji Electric semiconductor products in your equipment, you are requested to take adequate safety measures to prevent the equipment from causing a physical injury, fire, or other problem if any of the products become faulty. It is recommended to make your design failsafe, flame retardant, and free of malfunction.
4. The products introduced in this Catalog are intended for use in the following electronic and electrical equipment which has normal reliability requirements.

• Computers	• OA equipment	• Communications equipment (terminal devices)	• Measurement equipment
• Machine tools	• Audiovisual equipment	• Electrical home appliances	• Personal equipment
			• Industrial robots etc.
5. If you need to use a product in this Catalog for equipment requiring higher reliability than normal, such as for the equipment listed below, it is imperative to contact Fuji Electric Co., Ltd. to obtain prior approval. When using these products for such equipment, take adequate measures such as a backup system to prevent the equipment from malfunctioning even if a Fuji's product incorporated in the equipment becomes faulty.

• Transportation equipment (mounted on cars and ships)	• Trunk communications equipment
• Traffic-signal control equipment	• Gas leakage detectors with an auto-shut-off feature
• Emergency equipment for responding to disasters and anti-burglary devices	• Safety devices
• Medical equipment	
6. Do not use products in this Catalog for the equipment requiring strict reliability such as the following and equivalents to strategic equipment (without limitation).

• Space equipment	• Aeronautic equipment	• Nuclear control equipment
• Submarine repeater equipment		
7. Copyright ©1996-2011 by Fuji Electric Co., Ltd. All rights reserved.
No part of this Catalog may be reproduced in any form or by any means without the express permission of Fuji Electric Co., Ltd.
8. If you have any question about any portion in this Catalog, ask Fuji Electric Co., Ltd. or its sales agents before using the product. Neither Fuji Electric Co., Ltd. nor its agents shall be liable for any injury caused by any use of the products not in accordance with instructions set forth herein.