New Jersey Semi-Conductor Products, Inc.

20 STERN AVE.
SPRINGFIELD, NEW JERSEY 07081
U.S.A.

TELEPHONE: (973) 376-2922
(212) 227-6005
FAX: (973) 376-8960

BLW83

NPN SILICON RF POWER TRANSISTOR

DESCRIPTION:

BLW83 is Designed for use in transmitting amplifiers operatimg in theh.f. and v.h.f. bands and for applications as linear amplifier in class-A and AB.

FEATURES:

- P_G = 20 dB min. at 10 W/30 MHz
- IMD_3 = -30 dBc max. at 10 W(PEP)
- *Omnigold*™ Metalization System

MAXIMUM RATINGS

I_C	3.0 A
V_{CES}	65 V
V_{CEO}	36 V
V_{EBO}	4.0 V
P_{DISS}	80 W @ T_C = 25 °C
T_J	-65 °C to +200 °C
T_{STG}	-65 °C to +150 °C
θ_{JC}	2.2 °C/W

PACKAGE STYLE .380 4L FLG



DIM	MINIMUM inches / mm	MAXIMUM inches / mm
A	.220 / 5.59	.230 / 5.84
B	.785 / 19.94	
C	.720 / 18.29	.730 / 18.54
D	.970 / 24.64	.980 / 24.89
E		.385 / 9.78
F	.004 / 0.10	.006 / 0.15
G	.085 / 2.16	.105 / 2.67
H	.160 / 4.06	.180 / 4.57
I		.280 / 7.11
J	.240 / 6.10	.255 / 6.48

CHARACTERISTICS T_C = 25 °C

SYMBOL	TEST CONDITIONS	MINIMUM	TYPICAL	MAXIMUM	UNITS
BV_{CES}	I_C = 10 mA	65			V
BV_{CEO}	I_C = 50 mA	36			V
BV_{EBO}	I_E = 10 mA	4.0			V
I_{CES}	V_{CE} = 36 V			5	mA
h_{FE}	V_{CE} = 5.0 V I_C = 1.25 A	10		100	---
C_{ob}	V_{CB} = 12.5 V f = 1.0 MHz		100		pF
G_{PE}	V_{CC} = 26 V I_{CQ} = 25 mA f = 30 MHz	20	21	---	dB
IMD_3	P_{OUT} = 10 W(PEP)		-30		dB

NJ Semi-Conductors reserves the right to change test conditions, parameter limits and package dimensions without notice. Information furnished by NJ Semi-Conductors is believed to be both accurate and reliable at the time of going to press. However, NJ Semi-Conductors assumes no responsibility for any errors or omissions discovered in its use. NJ Semi-Conductors encourages customers to verify that datasheets are current before placing orders.

Quality Semi-Conductors

Download from alldatasheet.com