


SUB-MINIATURE SILICON HIGH VOLTAGE RECTIFIER



PART NUMBER	PIV VOLTS	I_O mA @ 40° C	V_f @ I_O @ 25° C	I_r @ PIV @ 25° C	MAX SINGLE CYCLE SURGE CURRENT	T_{rr}
BT588-10	1000	500	7	1 uA	25 AMPS	100 nSec
BT588-20	2000	350	7	1 uA	25 AMPS	100 nSec
BT588-30	3000	250	7	1 uA	25 AMPS	100 nSec
BT588-40	4000	200	10	1 uA	25 AMPS	100 nSec
BT588-50	5000	150	10	1 uA	25 AMPS	100 nSec
BT588-60	6000	100	15	1 uA	25 AMPS	100 nSec
BT588-70	7000	75	15	1 uA	25 AMPS	100 nSec
BT588-80	8000	60	18	1 uA	25 AMPS	100 nSec
BT588-90	9000	60	18	1 uA	25 AMPS	100 nSec
BT588-100	10000	50	23	1 uA	25 AMPS	100 nSec
BT588-110	11000	50	23	1 uA	25 AMPS	100 nSec
BT588-120	12000	50	23	1 uA	25 AMPS	100 nSec
BT588-130	13000	50	23	1 uA	25 AMPS	100 nSec
BT588-140	14000	50	23	1 uA	25 AMPS	100 nSec
BT588-150	15000	50	38	1 uA	25 AMPS	100 nSec
BT588-160	16000	50	38	1 uA	25 AMPS	100 nSec
BT588-170	17000	50	38	1 uA	25 AMPS	100 nSec
BT588-180	18000	50	38	1 uA	25 AMPS	100 nSec
BT588-190	19000	50	38	1 uA	25 AMPS	100 nSec
BT588-200	20000	50	45	1 uA	25 AMPS	100 nSec

RECOVERY TIME: .5 Amp forward to 1 Amp Reverse, Recover to .25 Amp

SUFFIX "A" REPRESENTS AVALANCHE CHARACTERISTICS EX: BT588-150A

(203) 467-2591 TEL

(203) 469-5928 FAX

Email: Info@ edal.com

Internet: <http://www.edal.com>

EDAL industries, inc.

51 Commerce St. East Haven, CT 06512