LINEAR SYSTEMS

IT130
MONOLITHIC DUAL
PNP TRANSISTOR

micross

Linear Systems replaces discontinued Intersil IT130

The IT130 is a monolithic pair of PNP transistors mounted in a single TO-71 package. The monolithic dual chip design reduces parasitics and gives better performance while ensuring extremely tight matching. The IT130 is a direct replacement for discontinued Intersil IT130.

The hermetically sealed TO-71 is well suited for hi-rel and harsh environment applications.

(See Packaging Information).

IT130 Features:

- High h_{fe} at low current
- Tight matching
- Tight V_{BE} tracking
- Low Output Capacitance

FEATURES	
Direct Replacement for INTERSIL IT130	
HIGH h_{FE} @ LOW CURRENT	≥ 200 @ 10µA
OUTPUT CAPACITANCE	≤ 2.0pF
V_{BE} tracking	≤ 5.0µV°C

ABSOLUTE MAXIMUM RATINGS [1]
@ 25°C (unless otherwise noted)

Maximum Temperatures	
Storage Temperature	-65°C to +200°C
Operating Junction Temperature	-55°C to +150°C
Maximum Power Dissipation	
Continuous Power Dissipation (One side)	250mW
Continuous Power Dissipation (Both sides)	500mW
Linear Derating factor (One side)	2.3mW/°C
Linear Derating factor (Both sides)	4.3mW/°C
Maximum Currents	
Collector Current	10mA

MATCHING CHARACTERISTICS @ 25°C (unless otherwise stated)

SYMBOL	CHARACTERISTIC	MIN	TYP	MAX	UNITS	CONDITIONS
$\lvert V_{BE1} - V_{BE2} \rvert$	Base Emitter Voltage Differential	--	--	2	mV	I_C = 10µA, V_{CE} = 5V
$\Delta\lvert(V_{BE1} - V_{BE2})\rvert / \Delta T$	Base Emitter Voltage Differential Change with Temperature	--	--	5	µV/°C	I_C = 10µA, V_{CE} = 5V T_A = -55°C to +125°C
$\lvert I_{B1} - I_{B2} \rvert$	Base Current Differential	--	--	5	nA	I_C = 10µA, V_{CE} = 5V

Click To Buy

ELECTRICAL CHARACTERISTICS @ 25°C (unless otherwise noted)

SYMBOL	CHARACTERISTICS	MIN.	TYP.	MAX.	UNITS	CONDITIONS
BV_{CBO}	Collector to Base Voltage	45	--	--	V	I_C = 10µA, I_E = 0
BV_{CEO}	Collector to Emitter Voltage	45	--	--	V	I_C = 10µA, I_B = 0
BV_{EBO}	Emitter-Base Breakdown Voltage	6.2	--	--	V	I_E = 10µA, I_C = 0 [2]
BV_{CCO}	Collector to Collector Voltage	60	--	--	V	I_C = 10µA, I_E = 0
h_{FE}	DC Current Gain	200	--	--		I_C = 10µA, V_{CE} = 5V
		225	--	--		I_C = 1.0mA, V_{CE} = 5V
V_{CE}(SAT)	Collector Saturation Voltage	--	--	0.5	V	I_C = 0.5mA, I_B = 0.05mA
I_{EBO}	Emitter Cutoff Current	--	--	1	nA	I_C = 0, V_{EB} = 3V
I_{CBO}	Collector Cutoff Current	--	--	1	nA	I_E = 0, V_{CB} = 45V
C_{OBO}	Output Capacitance	--	--	2	pF	I_E = 0, V_{CB} = 5V
C_{C1C2}	Collector to Collector Capacitance	--	--	4	pF	V_{CC} = 0V
I_{C1C2}	Collector to Collector Leakage Current	--	--	10	nA	V_{CC} = ±60V
f_T	Current Gain Bandwidth Product	110	--	--	MHz	I_C = 1mA, V_{CE} = 5V
NF	Narrow Band Noise Figure	--	--	3	dB	I_C = 100µA, V_{CE} = 5V, BW=200Hz, R_G= 10KΩ, f = 1KHz

Notes:
1. Absolute Maximum ratings are limiting values above which serviceability may be impaired
2. The reverse base-to-emitter voltage must never exceed 6.2 volts; the reverse base-to-emitter current must never exceed 10µA.

Available Packages:


IT130 in TO-71
IT130 available as bare die

micross

Please contact Micross for full package and die dimensions:

Email: chipcomponents@micross.com
Web: www.micross.com/distribution.aspx

TO-71 (Bottom View)



Information furnished by Linear Integrated Systems and Micross Components is believed to be accurate and reliable. However, no responsibility is assumed for its use; nor for any infringement of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of Linear Integrated Systems.