LINEAR SYSTEMS

LS841
MONOLITHIC DUAL
N-CHANNEL JFET

micross

Linear Systems Ultra Low Leakage Low Drift Monolithic Dual JFET

The LS841 is a high-performance monolithic dual JFET featuring extremely low noise, tight offset voltage and low drift over temperature specifications, and is targeted for use in a wide range of precision instrumentation applications. The LS841 features a 10-mV offset and 10-µV/°C drift.

The 8 Pin P-DIP and 8 Pin SOIC provide ease of manufacturing, and the symmetrical pinout prevents improper orientation.

(See Packaging Information).

LS841 Applications:

- Wideband Differential Amps
- High-Speed,Temp-Compensated Single-Ended Input Amps
- High-Speed Comparators
- Impedance Converters and vibrations detectors.

FEATURES	
LOW DRIFT	$\lvert V_{GS1-2} / T \rvert \le 10\mu V/°C$
LOW LEAKAGE	I_G = 10pA TYP.
LOW NOISE	e_n = 8nV/√Hz TYP.
LOW OFFSET VOLTAGE	$\lvert V_{GS1-2} \rvert \le 10mV$

ABSOLUTE MAXIMUM RATINGS @ 25°C (unless otherwise noted)		
Maximum Temperatures		
Storage Temperature		-65°C to +150°C
Operating Junction Temperature		+150°C
Maximum Voltage and Current for Each Transistor – Note 1		
$-V_{GSS}$	Gate Voltage to Drain or Source	60V
$-V_{DSO}$	Drain to Source Voltage	60V
$-I_{G(f)}$	Gate Forward Current	50mA
Maximum Power Dissipation		
Device Dissipation @ Free Air – Total		400mW @ +125°C

MATCHING CHARACTERISTICS @ 25°C UNLESS OTHERWISE NOTED				
SYMBOL	CHARACTERISTICS	VALUE	UNITS	CONDITIONS
$\lvert V_{GS1-2} / T \rvert$ max.	DRIFT VS. TEMPERATURE	10	µV/°C	V_{DG}=20V, I_D=200µA T_A=-55°C to +125°C
$\lvert V_{GS1-2} \rvert$ max.	OFFSET VOLTAGE	10	mV	V_{DG}=20V, I_D=200µA

ELECTRICAL CHARACTERISTICS @ 25°C (unless otherwise noted)

SYMBOL	CHARACTERISTICS	MIN.	TYP.	MAX.	UNITS	CONDITIONS
BV_{GSS}	Breakdown Voltage	60	60	--	V	V_{DS} = 0 I_D=1nA
BV_{GGO}	Gate-To-Gate Breakdown	60	--	--	V	I_G= 1nA I_D= 0 I_S= 0
	TRANSCONDUCTANCE					
Y_{fss}	Full Conduction	1000	--	4000	µmho	V_{DG}= 20V V_{GS}= 0V f = 1kHz
Y_{fs}	Typical Operation	500	--	1000	µmho	V_{DG}= 20V I_D= 200µA
$\lvert Y_{FS1-2} / Y_{FS} \rvert$	Mismatch	--	0.6	3	%	
	DRAIN CURRENT					
I_{DSS}	Full Conduction	0.5	2	5	mA	V_{DG}= 20V V_{GS}= 0V
$\lvert I_{DSS1-2} / I_{DSS} \rvert$	Mismatch at Full Conduction	--	1	5	%	
	GATE VOLTAGE					
V_{GS}(off) or V_p	Pinchoff voltage	1	2	4.5	V	V_{DS}= 20V I_D= 1nA
V_{GS}(on)	Operating Range	0.5	--	4	V	V_{DS}=20V I_D=200µA
	GATE CURRENT					
$-I_G$max.	Operating	--	10	50	pA	V_{DG}= 20V I_D= 200µA
$-I_G$max.	High Temperature	--	--	50	nA	T_A= +125°C
$-I_G$max.	Reduced V_{DG}	--	5	--	pA	V_{DG} = 10V I_D= 200µA
$-I_{GSS}$max.	At Full Conduction	--	--	100	pA	V_{DG}= 20V , V_{DS} =0
	OUTPUT CONDUCTANCE					
Y_{OSS}	Full Conduction	--	--	10	µmho	V_{DG}= 20V V_{GS}= 0V
Y_{OS}	Operating	--	0.1	1	µmho	V_{DG}= 20V I_D= 200µA
$\lvert Y_{OS1-2} \rvert$	Differential	--	0.01	0.1	µmho	
	COMMON MODE REJECTION					
CMR	-20 log $\lvert V_{GS1-2} / V_{DS} \rvert$	--	100	--	dB	ΔV_{DS} = 10 to 20V I_D=200µA
	-20 log $\lvert V_{GS1-2} / V_{DS} \rvert$	--	75	--		ΔV_{DS} = 5 to 10V I_D=200µA
	NOISE					
NF	Figure	--	--	0.5	dB	V_{DS}= 20V V_{GS}= 0V R_G= 10MΩ f= 100Hz NBW= 6Hz
e_n	Voltage	--	--	10	nV/√Hz	V_{DS}=20V I_D=200µA f=1KHz NBW=1Hz
		--	--	15		V_{DS}=20V I_D=200µA f=10Hz NBW=1Hz
	CAPACITANCE			10		
C_{ISS}	Input	--	4			V_{DS}= 20V, I_D=200µA
C_{RSS}	Reverse Transfer	--	1.2	5	pF	
C_{DD}	Drain-to-Drain	--	0.1	--		


Click To Buy

Note 1 – These ratings are limiting values above which the serviceability of any semiconductor may be impaired

Available Packages:

LS841 / LS841 in PDIP & SOIC
LS841 / LS841 available as bare die
Please contact Micross for full package and die dimensions

PDIP & SOIC (Top View)



micross
Tel: +44 1603 788967
Email: chipcomponents@micross.com
Web: http://www.micross.com/distribution

Information furnished by Linear Integrated Systems and Micross Components is believed to be accurate and reliable. However, no responsibility is assumed for its use; nor for any infringement of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of Linear Integrated Systems.