
PIC12F510

Silicon Errata and Data Sheet Clarification

The PIC12F510 device that you have received conform functionally to the current Device Data Sheet (DS41268D), except for the anomalies described in this document.

The silicon/specification issues discussed in the following pages are for all silicon revisions. If, however, questions do arise concerning the silicon revision received in a particular factory shipment, please contact your local Microchip sales office for assistance.

Silicon Errata

None.

PIC12F510

Data Sheet Clarifications

The following typographic corrections and clarifications are to be noted for the latest version of the device data sheet (DS41268D). Changes described in Modules 1, 2, 3, and 4 below apply to the PIC12F510 only and not to the PIC16F506, which is described in the same data sheet (DS41268D):

Note: Corrections are shown in **bold**. Where possible, the original bold text formatting has been removed for clarity.

1. Module: Analog-to-Digital Converter (ADC)

The specifications listed in Table 1 supersede Table 13-3 in DS41268D. The PIC12F510 will meet the performance specifications stated in Table 1 below if the device is operated as described in this Errata.

TABLE 1: A/D CONVERTER CHARACTERISTICS

Param No.	Sym.	Characteristic	Min.	Typ†	Max.	Units	Conditions
A03	EIL	Integral Error	—	—	±1.5	LSB	V _{DD} = 5.0V
A04	EDL	Differential Error	—	—	-1 < EDL ≤ +1.5	LSB	V _{DD} = 5.0V
A06	EOFF	Offset Error	—	—	±1.5	LSB	V _{DD} = 5.0V
A07	EGN	Gain Error	—	—	±1.5	LSB	V _{DD} = 5.0V

† Data in "Typ" column is at 5.0V 25°C unless otherwise stated. The typical parameters are for design guidance only and are not tested.

Work around

None.

Table 9-2 below should replace the current Table 9-2 in the data sheet.

2. Module: Analog-to-Digital Converter (ADC)

Section 9.1 "Clock Divisors", paragraph 1 should read as shown in bold.

The ADC has 4 clock source settings, ADCS<1:0>. There are 3 divisor values, **16**, **8** and **4**. The fourth setting is INTOSC with a divisor of 4.

TABLE 9-2: T_{AD} FOR ADCs SETTINGS WITH VARIOUS OSCILLATORS⁽¹⁾

Source	ADCS<1:0>	Divisor	8 MHz	4 MHz	1 MHz	500 kHz	350 kHz	200 kHz	100 kHz	32 kHz
INTOSC	11	4	.5 μs	1 μs	—	—	—	—	—	—
FOSC	10	4	.5 μs	1 μs	4 μs	8 μs	11 μs	20 μs	40 μs	125 μs ⁽³⁾
FOSC	01	8	1 μs	2 μs	8 μs	16 μs	23 μs	40 μs	80 μs	250 μs
FOSC	00	16	2 μs ⁽²⁾	4 μs ⁽²⁾	16 μs	32 μs	46 μs	80 μs	160 μs	500 μs

- Note** 1: Operation of the ADC module clock in any of the shaded regions shown in this table (Table 9-2) may result in linearity errors exceeding the limits stated in Table 1 of this Errata.
- 2: If the internal oscillator is selected as the main clock source through the Configuration Word register, the divide-by-16 option for the ADC clock should be used.
- 3: Characterized but not tested.

Work around

None.

3. Module: Analog-to-Digital Converter (ADC)

Section 9.1.5 “Sleep”, bullets should read as follows (changes in bold).

- For accurate conversions, TAD must meet the following:
- **2 μ s $\leq$ TAD $<$ 125 μ s**
- TAD = 1/(Fosc/divisor)

Work around

None.

4. Module: Analog-to-Digital Converter (ADC)

Examples 9-1 and 9-2 changes shown in bold below.

EXAMPLE 9-1: PERFORMING AN ANALOG-TO-DIGITAL CONVERSION

```
;Sample code operates out of BANK0
    MOVLW 0xF1      ;configure A/D
    MOVWF ADCON0
    BSF ADCON0, 1   ;start conversion
loop0  NOP
       BTFSC ADCON0, 1;wait for 'DONE'
       GOTO loop0
       MOVF ADRES, W ;read result
       MOVWF result0 ;save result

       BSF ADCON0, 2 ;setup for read of
                       ;channel 1
       BSF ADCON0, 1 ;start conversion
loop1  NOP
       BTFSC ADCON0, 1;wait for 'DONE'
       GOTO loop1
       MOVF ADRES, W ;read result
       MOVWF result1 ;save result

       BSF ADCON0, 3 ;setup for read of
       BCF ADCON0, 2 ;channel 2
       BSF ADCON0, 1 ;start conversion
loop2  NOP
       BTFSC ADCON0, 1;wait for 'DONE'
       GOTO loop2
       MOVF ADRES, W ;read result
       MOVWF result2 ;save result
```

EXAMPLE 9-2: CHANNEL SELECTION CHANGE DURING CONVERSION

```
    MOVLW 0xF1      ;configure A/D
    MOVWF ADCON0
    BSF ADCON0, 1   ;start conversion
    BSF ADCON0, 2   ;setup for read of
                       ;channel 1
loop0  NOP
       BTFSC ADCON0, 1;wait for 'DONE'
       GOTO loop0
       MOVF ADRES, W ;read result
       MOVWF result0 ;save result

       BSF ADCON0, 1 ;start conversion
       BSF ADCON0, 3 ;setup for read of
       BCF ADCON0, 2 ;channel 2
loop1  NOP
       BTFSC ADCON0, 1;wait for 'DONE'
       GOTO loop1
       MOVF ADRES, W ;read result
       MOVWF result1 ;save result

       BSF ADCON0, 1 ;start conversion
loop2  NOP
       BTFSC ADCON0, 1;wait for 'DONE'
       GOTO loop2
       MOVF ADRES, W ;read result
       MOVWF result2 ;save result
       CLRF ADCON0 ;optional: returns
                       ;pins to Digital mode and turns off
                       ;the ADC module
```

Work around

None.

PIC12F510

5. Module: Analog-to-Digital Converter (ADC)

The Reset value for the ADCON0 register is updated for Resets other than Power-on Reset. Changes to the tables affected are listed below, in Table 10-3, and identified in bold and italic text.

TABLE 10-3: RESET CONDITIONS FOR REGISTERS – PIC12F510

Register	Address	Power-on Reset	MCLR Reset, WDT Time-out, Wake-up On Pin Change, Wake-up on Comparator Change
W	—	qqqq qqqu ⁽¹⁾	qqqq qqqu ⁽¹⁾
INDF	00h	xxxx xxxx	uuuu uuuu
TMR0	01h	xxxx xxxx	uuuu uuuu
PCL	02h	1111 1111	1111 1111
STATUS	03h	0001 1xxx	qq0q quuu ⁽²⁾
FSR	04h	110x xxxx	11uu uuuu
OSCCAL	05h	1111 111-	uuuu uu-
GPIO	06h	- -xx xxxx	- -uu uuuu
CM1CON0	07h	1111 1111	uuuu uuuu
ADCON0	08h	1111 1100	1111 1100
ADRES	09h	xxxx xxxx	uuuu uuuu
OPTION	—	1111 1111	1111 1111
TRISIO	—	- -11 1111	- -11 1111

Legend: u = unchanged, x = unknown, – = unimplemented bit, read as '0', q = value depends on condition.

Note 1: Bits <7:1> of W register contain oscillator calibration values due to MOVLW XX instruction at top of memory.

2: See Table 10-5 for Reset value for specific conditions.

Work around

None.

6. Module: Electrical Characteristics

The min. and max. values in Table 13-1 for Internal Voltage Reference (V_{REF}) have been revised. Changes to the table are listed below and identified in bold and italic text.

TABLE 13-1: COMPARATOR SPECIFICATIONS

Sym.	Characteristics	Min.	Typ.	Max.	Units	Comments
VOS	Input Offset Voltage	—	±3	±10	mV	(V _{DD} - 1.5V)/2
VCM	Input Common Mode Voltage	0	—	V _{DD} - 1.5	V	
CMRR	Common Mode Rejection Ratio	+55*	—	—	dB	
TRT	Response Time ⁽¹⁾	—	150	400*	ns	Internal
V _{REF}	Internal Voltage Reference	0.500	0.6	0.700	V	

* These parameters are characterized but not tested.

Note 1: Response time measured with one comparator input at (V_{DD} - 1.5)/2, while the other input transitions from V_{SS} to V_{DD} - 1.5V.

Work around

None.

7. Module: Electrical Characteristics

The max. values at 2V and 5V V_{DD} for LP Oscillator I_{DD} at 125°C have been revised as shown in Table 2 below.

TABLE 2: LP OSCILLATOR 125°C I_{DD}

DC Characteristics			Standard Operating Conditions (unless otherwise specified) Operating Temperature -40°C ≤ T _A ≤ +125°C (extended)				
Param No.	Sym.	Characteristics	Min.	Typ ⁽¹⁾	Max.	Units	Conditions
D010	I _{DD}	Supply Current ^(2,3)	—	11	24	μA	F _{OSC} = 32 kHz, V _{DD} = 2.0V
			—	38	110	μA	F _{OSC} = 32 kHz, V _{DD} = 5.0V

Note 1: Data in the Typical ("Typ") column is based on characterization results at 25°C. This data is for design guidance only and is not tested.

2: The supply current is mainly a function of the operating voltage and frequency. Other factors such as bus loading, oscillator type, bus rate, internal code execution pattern and temperature also have an impact on the current consumption.

3: The test conditions for all I_{DD} measurements in active operation mode are:
OSC1 = external square wave, from rail-to-rail; all I/O pins tri-stated, pulled to V_{SS}, T0CKI = V_{DD},
MCLR = V_{DD}; WDT disabled unless noted otherwise.

Work around

None.

8. Module: Electrical Characteristics

The typ. value at 5V V_{DD} and the max. values at 2V and 5V V_{DD} for ICMP have been revised as shown in Table 3 below.

TABLE 3: ICMP

DC Characteristics			Standard Operating Conditions (unless otherwise specified) Operating Temperature -40°C ≤ T _A ≤ +85°C or -40°C ≤ T _A ≤ +125°C				
Param No.	Sym.	Characteristic	Min.	Typ ⁽¹⁾	Max.	Units	Conditions
D023	ICMP	Comparator Current ⁽²⁾	—	15	26	μA	V _{DD} = 2.0V (per comparator)
			—	60	76	μA	V _{DD} = 5.0V (per comparator)

Note 1: Data in the Typical ("Typ") column is based on characterization results at 25°C. This data is for design guidance only and is not tested.

2: For standby current measurements, the conditions are the same as I_{DD}, except that the device is in Sleep mode. If a module current is listed, the current is for that specific module enabled and the device in Sleep.

Work around

None.

PIC12F510

APPENDIX A: DOCUMENT REVISION HISTORY

Rev A Document (03/2006)

First Revision – Module 1: Analog-to-Digital Converter.

Rev B Document (08/2006)

Clarifications/Corrections to the Data Sheet: Added Module 1: Analog-to-Digital Converter: Correction to Section 9.1 Clock Divisors, paragraph 1; Table 9-2, TAD for ADCS.

Rev C Document (03/2008)

Updated Module 1 by removing 25°C from Conditions and updated paragraph.

Clarifications/Corrections to the Data Sheet: Updated Module 1: Analog-to Digital Converter by rewording and adding Table 9-2 updates. Added Modules 2 and 3 (Analog-to Digital Converter).

Rev D Document (9/2008)

Removed Silicon from title; Renumbered Modules; Updated Module 2 by adding Notes 2 and 3 to Table 9-2 and removed shading from 125 $\mu\text{s}^{(3)}$ under the 32 kHz column; Added Table 2 to Module 1.

Rev E Document (1/2009)

Added Module 5: Analog-to-Digital Converter: Updates to Tables 10-3 and 10-4 (Reset Conditions); Added Module 6: Electrical Characteristic: Updates to Table 13-1 Comparator Specifications.

Rev F Document(6/2009)

Updated errata with the new format. Removed part number PIC16F506 from errata. See DS80475 for PIC16F506 errata items.

Data Sheet Clarifications: Revised Module 1. Added Modules 7 and 8. Other minor edits.

Note the following details of the code protection feature on Microchip devices:

- Microchip products meet the specification contained in their particular Microchip Data Sheet.
- Microchip believes that its family of products is one of the most secure families of its kind on the market today, when used in the intended manner and under normal conditions.
- There are dishonest and possibly illegal methods used to breach the code protection feature. All of these methods, to our knowledge, require using the Microchip products in a manner outside the operating specifications contained in Microchip's Data Sheets. Most likely, the person doing so is engaged in theft of intellectual property.
- Microchip is willing to work with the customer who is concerned about the integrity of their code.
- Neither Microchip nor any other semiconductor manufacturer can guarantee the security of their code. Code protection does not mean that we are guaranteeing the product as "unbreakable."

Code protection is constantly evolving. We at Microchip are committed to continuously improving the code protection features of our products. Attempts to break Microchip's code protection feature may be a violation of the Digital Millennium Copyright Act. If such acts allow unauthorized access to your software or other copyrighted work, you may have a right to sue for relief under that Act.

Information contained in this publication regarding device applications and the like is provided only for your convenience and may be superseded by updates. It is your responsibility to ensure that your application meets with your specifications. MICROCHIP MAKES NO REPRESENTATIONS OR WARRANTIES OF ANY KIND WHETHER EXPRESS OR IMPLIED, WRITTEN OR ORAL, STATUTORY OR OTHERWISE, RELATED TO THE INFORMATION, INCLUDING BUT NOT LIMITED TO ITS CONDITION, QUALITY, PERFORMANCE, MERCHANTABILITY OR FITNESS FOR PURPOSE. Microchip disclaims all liability arising from this information and its use. Use of Microchip devices in life support and/or safety applications is entirely at the buyer's risk, and the buyer agrees to defend, indemnify and hold harmless Microchip from any and all damages, claims, suits, or expenses resulting from such use. No licenses are conveyed, implicitly or otherwise, under any Microchip intellectual property rights.

Trademarks

The Microchip name and logo, the Microchip logo, dsPIC, KEELOQ, KEELOQ logo, MPLAB, PIC, PICmicro, PICSTART, rfPIC and UNI/O are registered trademarks of Microchip Technology Incorporated in the U.S.A. and other countries.

FilterLab, Hampshire, HI-TECH C, Linear Active Thermistor, MXDEV, MXLAB, SEEVAL and The Embedded Control Solutions Company are registered trademarks of Microchip Technology Incorporated in the U.S.A.

Analog-for-the-Digital Age, Application Maestro, CodeGuard, dsPICDEM, dsPICDEM.net, dsPICworks, dsSPEAK, ECAN, ECONOMONITOR, FanSense, HI-TIDE, In-Circuit Serial Programming, ICSP, ICEPIC, Mindi, MiWi, MPASM, MPLAB Certified logo, MPLIB, MPLINK, mTouch, nanoWatt XLP, Omniscent Code Generation, PICC, PICC-18, PICkit, PICDEM, PICDEM.net, PICTail, PIC³² logo, REAL ICE, rfLAB, Select Mode, Total Endurance, TSHARC, WiperLock and ZENA are trademarks of Microchip Technology Incorporated in the U.S.A. and other countries.

SQTP is a service mark of Microchip Technology Incorporated in the U.S.A.

All other trademarks mentioned herein are property of their respective companies.

© 2009, Microchip Technology Incorporated, Printed in the U.S.A., All Rights Reserved.



Printed on recycled paper.

QUALITY MANAGEMENT SYSTEM
CERTIFIED BY DNV
== ISO/TS 16949:2002 ==

Microchip received ISO/TS-16949:2002 certification for its worldwide headquarters, design and wafer fabrication facilities in Chandler and Tempe, Arizona; Gresham, Oregon and design centers in California and India. The Company's quality system processes and procedures are for its PIC® MCUs and dsPIC® DSCs, KEELOQ® code hopping devices, Serial EEPROMs, microperipherals, nonvolatile memory and analog products. In addition, Microchip's quality system for the design and manufacture of development systems is ISO 9001:2000 certified.



WORLDWIDE SALES AND SERVICE

AMERICAS

Corporate Office

2355 West Chandler Blvd.
Chandler, AZ 85224-6199
Tel: 480-792-7200
Fax: 480-792-7277
Technical Support:
<http://support.microchip.com>
Web Address:
www.microchip.com

Atlanta

Duluth, GA
Tel: 678-957-9614
Fax: 678-957-1455

Boston

Westborough, MA
Tel: 774-760-0087
Fax: 774-760-0088

Chicago

Itasca, IL
Tel: 630-285-0071
Fax: 630-285-0075

Cleveland

Independence, OH
Tel: 216-447-0464
Fax: 216-447-0643

Dallas

Addison, TX
Tel: 972-818-7423
Fax: 972-818-2924

Detroit

Farmington Hills, MI
Tel: 248-538-2250
Fax: 248-538-2260

Kokomo

Kokomo, IN
Tel: 765-864-8360
Fax: 765-864-8387

Los Angeles

Mission Viejo, CA
Tel: 949-462-9523
Fax: 949-462-9608

Santa Clara

Santa Clara, CA
Tel: 408-961-6444
Fax: 408-961-6445

Toronto

Mississauga, Ontario,
Canada
Tel: 905-673-0699
Fax: 905-673-6509

ASIA/PACIFIC

Asia Pacific Office

Suites 3707-14, 37th Floor
Tower 6, The Gateway
Harbour City, Kowloon
Hong Kong
Tel: 852-2401-1200
Fax: 852-2401-3431

Australia - Sydney

Tel: 61-2-9868-6733
Fax: 61-2-9868-6755

China - Beijing

Tel: 86-10-8528-2100
Fax: 86-10-8528-2104

China - Chengdu

Tel: 86-28-8665-5511
Fax: 86-28-8665-7889

China - Hong Kong SAR

Tel: 852-2401-1200
Fax: 852-2401-3431

China - Nanjing

Tel: 86-25-8473-2460
Fax: 86-25-8473-2470

China - Qingdao

Tel: 86-532-8502-7355
Fax: 86-532-8502-7205

China - Shanghai

Tel: 86-21-5407-5533
Fax: 86-21-5407-5066

China - Shenyang

Tel: 86-24-2334-2829
Fax: 86-24-2334-2393

China - Shenzhen

Tel: 86-755-8203-2660
Fax: 86-755-8203-1760

China - Wuhan

Tel: 86-27-5980-5300
Fax: 86-27-5980-5118

China - Xiamen

Tel: 86-592-2388138
Fax: 86-592-2388130

China - Xian

Tel: 86-29-8833-7252
Fax: 86-29-8833-7256

China - Zhuhai

Tel: 86-756-3210040
Fax: 86-756-3210049

ASIA/PACIFIC

India - Bangalore

Tel: 91-80-3090-4444
Fax: 91-80-3090-4080

India - New Delhi

Tel: 91-11-4160-8631
Fax: 91-11-4160-8632

India - Pune

Tel: 91-20-2566-1512
Fax: 91-20-2566-1513

Japan - Yokohama

Tel: 81-45-471- 6166
Fax: 81-45-471-6122

Korea - Daegu

Tel: 82-53-744-4301
Fax: 82-53-744-4302

Korea - Seoul

Tel: 82-2-554-7200
Fax: 82-2-558-5932 or
82-2-558-5934

Malaysia - Kuala Lumpur

Tel: 60-3-6201-9857
Fax: 60-3-6201-9859

Malaysia - Penang

Tel: 60-4-227-8870
Fax: 60-4-227-4068

Philippines - Manila

Tel: 63-2-634-9065
Fax: 63-2-634-9069

Singapore

Tel: 65-6334-8870
Fax: 65-6334-8850

Taiwan - Hsin Chu

Tel: 886-3-6578-300
Fax: 886-3-6578-370

Taiwan - Kaohsiung

Tel: 886-7-536-4818
Fax: 886-7-536-4803

Taiwan - Taipei

Tel: 886-2-2500-6610
Fax: 886-2-2508-0102

Thailand - Bangkok

Tel: 66-2-694-1351
Fax: 66-2-694-1350

EUROPE

Austria - Wels

Tel: 43-7242-2244-39
Fax: 43-7242-2244-393

Denmark - Copenhagen

Tel: 45-4450-2828
Fax: 45-4485-2829

France - Paris

Tel: 33-1-69-53-63-20
Fax: 33-1-69-30-90-79

Germany - Munich

Tel: 49-89-627-144-0
Fax: 49-89-627-144-44

Italy - Milan

Tel: 39-0331-742611
Fax: 39-0331-466781

Netherlands - Drunen

Tel: 31-416-690399
Fax: 31-416-690340

Spain - Madrid

Tel: 34-91-708-08-90
Fax: 34-91-708-08-91

UK - Wokingham

Tel: 44-118-921-5869
Fax: 44-118-921-5820