


Stealth Microwave's **SMTR2327-44** is a solid state bi-directional amplifier for use in 802.16e TDD products and systems. This compact, high linearity PA can easily be integrated into both BTS or CPE devices, and exhibits excellent uplink and downlink performance. Typical output power for 802.16e is 35-36 dBm meeting EVM and spectral mask requirements.




Features

- Auto (RF Tx Detect) or Manual (TTL) Tx/Rx Switching
- Integral receive filter
- Various RF connector and housing options available

Transmit Path				
Parameter	Specification			
	Min	Typ	Max	Unit
Frequency Range	2300	-	2700	MHz
802.16e Power Out	35	36.5		dBm
EVM at 35dBm		-33		dB
Gain		50 ± 1		dB
Gain Flatness		± 0.5		dB
Input Return Loss	-14	-18		dB
DC Input Voltage	10	12	13	V
Current Draw (RMS)		4.5		A
Receive Path				
Gain		20 ± 1		dB
P1dB	5			dBm
Noise Figure		3		dB
Input Return Loss		-14		dB
Current Draw		110		mA

Mechanical Dimensions	9.5 x 4.0 x 1.22 inches
RF Connectors	SMA Female
Weight	1 lb. 4 oz.
Operating Temperature (Baseplate)	-10°C to +70°C

DIMENSIONS IN INCHES



Pin	Description	Values
RADIO	Input Connector (SMA-F)	+ 10 dBm (typical, adjustable per customer requirement)
ANT	Antenna Connector (SMA-F)	+35-37 dBm burst power (802.16e)
+VDC	Supply Voltage	+12V
GND	Ground	--

WiMAX EVM MEASUREMENT - 35 dBm @ 2.3 GHz

IEEE 802.16-2004 OFDM							GENERAL SETTINGS
Frequency: 2.3 GHz	Signal Level Setting: 0.7 dBm		Ref. Level / Att: 10.7 dBm / 34 dB				
Sweep Mode: Continuous	Trigger Mode: Free Run		Trigger Offset: -10 μs				
Burst Type: OFDM DL Burst	Modulation: 64QAM3/4		No Of Data Symbols: 1/2425				
Result Summary							DEMOM SETTINGS
No. of Bursts	6						DISPLAY GRAPH
	Min	Mean	Limit	Max	Limit	Unit	
EVM All Carriers	- 31.56	- 31.11	- 31.00 *	- 30.63	- 31.00	dB	
EVM Data Carriers	- 31.59	- 31.13		- 30.65		dB	
EVM Pilot Carriers	- 31.07	- 30.62		- 30.24		dB	PUT ↕
IQ Offset	- 38.34	- 38.29	- 15.00	- 38.21	- 15.00	dB	
Gain Imbalance	0.00	0.00		0.00		dB	EVM ↕
Quadrature Error	0.000	0.000		0.000		°	
Center Frequency Error	- 41.63	- 75.93	± 18400	- 98.49	± 18400	Hz	SPECTRUM ↕
Clock Error	0.00	0.00	± 8	0.00	± 8	ppm	
Burst Power	36.49	36.49		36.49		dBm	CONSTELL ↕
Crest Factor	8.17	8.18		8.18		dB	
RSSI	54.21	54.21		54.29		dBm	STATISTICS↕
RSSI Standard Deviation		- 2.52				dB	
CINR	14.41	14.59		14.62		dB	
CINR Standard Deviation		13.34				dB	
Running ...							FILE MANAGER ↕
SPECTRUM	WIMAX	AUTO LVL	RUN SGL	RUN CONT	REFRESH	SCREEN B	

S_{21} PLOT

