
TRIAD MAGNETICS

Audio Transformer

Data/Voice Coupling

T Y - 3 1 0 P



Description:
The TY series transformers are used for a variety of applications including impedance matching, isolation, repeat coil, line balancing, bridging and hybrid circuits.

Electrical Specifications at 25º C:

Impedance (Ohms)		Max. DC Current	Typ. Insertion	Typ. Return	Typ. Freq. Response
Pri	Sec	(mA)	Loss (dB)	Loss (dB)	(dB)
600	600	0	1.0	26	±.5


Designed to meet FCC Part 68


Longitudinal Balance: (FCC 68.310) – 60 dB min. 200 – 1000 Hz
45 dB min. 1000 – 4000 Hz

Dielectric Strength: (FCC 68.304) – 1500VAC


Power Level: -45 dBm to +7 dBm

Frequency Range: Data/Voice = 300 to 3500 Hz
Data = 800 to 3500 Hz





Schematic:



RoHS Compliance: As of manufacturing date February 2005, all standard products meet the requirements of 2011/65/EU, known as the RoHS initiative.

*Upon printing, this document is considered “uncontrolled”.Please contact Triad Magnetics website for the most current version.

web:www.TriadMagnetics.com
Phone 951-277-0757
Fax 951-277-2757

460 Harley Knox Blvd.
Perris, California 92571

Publish Date: December 4, 2013