



## STEP-LESS CLOCK FOR SIS CHIPSET

### Table of Content-

|      |                                                                             |    |
|------|-----------------------------------------------------------------------------|----|
| 1.   | GENERAL DESCRIPTION .....                                                   | 2  |
| 2.   | PRODUCT FEATURES .....                                                      | 2  |
| 3.   | PIN CONFIGURATION .....                                                     | 3  |
| 4.   | PIN DESCRIPTION.....                                                        | 3  |
| 4.1  | Crystal I/O .....                                                           | 3  |
| 4.2  | CPU, SDRAM, PCI ,AGP Clock Outputs.....                                     | 4  |
| 4.3  | I2C Control Interface.....                                                  | 5  |
| 4.4  | Fixed Frequency Outputs .....                                               | 5  |
| 4.5  | Power Pins.....                                                             | 5  |
| 5.   | FREQUENCY SELECTION BY HARDWARE .....                                       | 6  |
| 6.   | SERIAL CONTROL REGISTERS.....                                               | 6  |
| 6.1  | Register 0: Frequency Select Register .....                                 | 9  |
| 6.2  | Register 1 : CPU Clock Register (1 = Active, 0 = Inactive) .....            | 9  |
| 6.3  | Register 2: PCI Clock Register (1 = Active, 0 = Inactive).....              | 9  |
| 6.4  | Register 3: SDRAM Clock Additional Register (1 = Active, 0 = Inactive)..... | 10 |
| 6.5  | Register 4: PCI Clock Additional Register (1 = Active, 0 = Inactive).....   | 10 |
| 6.6  | Register 5: Skew Register .....                                             | 10 |
| 6.7  | Register 6: Watchdog Timer Register .....                                   | 11 |
| 6.8  | Register 7: M/N Program Register and Divisor .....                          | 11 |
| 6.9  | Register 8: M/N Program Register .....                                      | 11 |
| 6.10 | Register 9: Divisor Register .....                                          | 12 |
| 6.11 | Register 10: Divisor Register.....                                          | 12 |
| 6.12 | Register 11: Winbond Chip ID Register (Read Only) .....                     | 12 |
| 6.13 | Register 12: Winbond Chip ID Register (Read Only) .....                     | 13 |
| 7.   | ORDERING INFORMATION .....                                                  | 14 |
| 8.   | HOW TO READ THE TOP MARKING.....                                            | 14 |
| 9.   | PACKAGE DRAWING AND DIMENSIONS.....                                         | 15 |
| 10.  | REVISION HISTORY .....                                                      | 16 |



## 1. GENERAL DESCRIPTION

The W83194BR-63S is a Clock Synthesizer which provides all clocks required for high-speed RISC or CISC microprocessor such as Intel Pentium II or Pentium III. W83194BR-63S provides 64 CPU/PCI frequencies which are selectable with smooth transitions by hardware or software. W83194BR-63S also provides 13 SDRAM clocks.


The W83194BR-63S provides step-less frequency programming by controlling the VCO freq. and the programmable PCI clock output divisor ratio. A watch dog timer is quipped and when time out, the RESET# pin will output 4ms pulse signal.

The W83194BR-63S accepts a 14.318 MHz reference crystal as its input. Spread spectrum built in at 0~-0.5% or  $\pm 0.25\%$  to reduce EMI. Programmable stopping individual clock outputs and frequency selection through I<sup>2</sup>C interface. The device meets the Pentium power-up stabilization, which requires CPU and PCI clocks be stable within 2 ms after power-up. Using dual function pin for the slots(ISA, PCI, CPU, DIMM) is not recommend.

## 2. PRODUCT FEATURES

- Supports Pentium™ II and Pentium™ III CPU with I<sup>2</sup>C.
- 3 CPU clocks (one free-running CPU clock)
- 13 SDRAM clocks for 3 DIMMs
- 6 PCI synchronous clocks
- 2 AGP clocks
- 2 REF clocks as 14.318MHz outputs
- < 250ps skew among CPU and SDRAM clocks
- < 250ps skew among PCI clocks
- Skew from CPU(earlier) to PCI clock 1 to 4ns, center 2.6ns.
- Smooth frequency switch with selections from 66 MHz to 200 MHz CPU
- Stepless frequency programming by controlling the VCO freq. and the clock output divisor ratio
- Programmable skew for CPU to SDRAM and CPU to AGP clock outputs
- I<sup>2</sup>C 2-Wire serial interface and I<sup>2</sup>C read back
- 0~-0.25% or  $\pm 0.5\%$  spread spectrum function to reduce EMI
- Programmable registers to enable/stop each output and select modes
- MODE pin for power Management and RESET# out when system hang
- One 48 MHz for USB & one 24\_48 MHz for super I/O
- 48-pin SSOP package

## 3. PIN CONFIGURATION



## 4. PIN DESCRIPTION

IN - Input

OUT - Output

I/O - Bi-directional Pin

# - Active Low

\* - Internal 120kΩ pull-up

### 4.1 Crystal I/O

| SYMBOL | PIN | I/O | FUNCTION                                                               |
|--------|-----|-----|------------------------------------------------------------------------|
| Xin    | 5   | IN  | Crystal input with internal loading capacitors and feedback resistors. |
| Xout   | 6   | OUT | Crystal output at 14.318MHz nominally.                                 |

## 4.2 CPU, SDRAM, PCI ,AGP Clock Outputs

| SYMBOL                 | PIN                     | I/O | FUNCTION                                                                                                                                                    |
|------------------------|-------------------------|-----|-------------------------------------------------------------------------------------------------------------------------------------------------------------|
| CPUCLK[0:1]            | 47,46                   | OUT | Low skew (< 250ps) clock outputs for host frequencies such as CPU, Chipset and Cache. Powered by VddLCPU. Stopped if CPU_STOP# is low.                      |
| CPUCS_C2               | 45                      | OUT | Low skew (< 250ps) clock outputs for host frequencies such as CPU, Chipset and Cache. Powered by VddLCPU. Stopped if CPU_STOP# is low and Register7 bit7=0. |
| SDRAM [ 0:7],12        | 42,41,40,38,37,36,34,33 | OUT | SDRAM clock outputs.                                                                                                                                        |
| SDRAM 8/PD#            | 31                      | OUT | Pin21 &Mode=0, SDRAM clock outputs.<br>Pin21 &Mode=1, PD# input                                                                                             |
| SDRAM9/<br>SDRAM_STOP# | 30                      | OUT | Pin21 &Mode=0, SDRAM clock outputs.<br>Pin21 &Mode=1, SDRAM_STOP# input                                                                                     |
| SDRAM 10/<br>PCI_STOP# | 28                      | OUT | Pin21 &Mode=0, SDRAM clock outputs.<br>Pin21 &Mode=1, PCI_STOP# input                                                                                       |
| SDRAM 11/<br>CPU_STOP# | 27                      | OUT | Pin21 &Mode=0, SDRAM clock outputs.<br>Pin21 &Mode=1, CPU_STOP# input                                                                                       |
| PCICLK0^/FS1           | 8                       | I/O | Low skew (< 250ps) PCI clock outputs.<br>Latched input for FS1 at initial power up for H/W selecting the output frequency of CPU, SDRAM and PCI clocks.     |
| PCICLK1^/FS2           | 9                       | I/O | Low skew (< 250ps) PCI clock outputs.<br>Latched input for FS2 at initial power up for H/W selecting the output frequency of CPU, SDRAM and PCI clocks.     |
| PCICLK [2:4]^          | 10,11,12                | I/O | Low skew (< 250ps) PCI clock outputs.<br>Latched Input. SEL24_48=0, Pin 21 is 24MHz;<br>SEL24_48=1, Pin21 is 48MHz                                          |
| PCICLK5/<br>RESET#     | 13                      | I/O | PCI clock during normal operation. (pin17 Mode1*=1)<br>If pin17 Mode1*=0, RESET# (open drain, 4ms low active pulse when Watch Dog time out)                 |
| AGPCLK0/<br>SEL24#_48* | 16                      | I/O | Low skew (< 250ps) AGP clock output.<br>Latched Input. SEL24#_48*=1, Pin 21 is 24MHz;<br>SEL24_48*=0, Pin21 is 48MHz                                        |
| AGPCLK1/<br>Mode1*     | 17                      | OUT | AGP clock outputs<br>Latched Input. Mode1*=1, Pin 13 is PCICLK;<br>Mode1*=0, Pin2 is RESET#                                                                 |

**4.3 I2C Control Interface**

| SYMBOL | PIN | I/O | FUNCTION                                                  |
|--------|-----|-----|-----------------------------------------------------------|
| SDATA* | 23  | I/O | Serial data of I <sup>2</sup> C 2-wire control interface  |
| SDCLK* | 24  | IN  | Serial clock of I <sup>2</sup> C 2-wire control interface |

**4.4 Fixed Frequency Outputs**

| SYMBOL                      | PIN | I/O | FUNCTION                                                                                                                                                               |
|-----------------------------|-----|-----|------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| REF0 <sup>^</sup> / &AGPSEL | 2   | I/O | 14.318MHz reference clock. This REF output is the atched input for &AGPSEL at initial power up for H/W selecting the output frequency of AGP clocks.                   |
| REF1 <sup>^</sup> / &FS3    | 3   | I/O | 14.318MHz reference clock.<br>Latched input for FS3 at initial power up for H/W selecting the output frequency of CPU, SDRAM and PCI clocks.                           |
| 24_48MHz / &Mode            | 21  | I/O | 24_48MHz output clock, selected by pin16.<br>Latched Input. &Mode=0, Pin 27,28,30,31 are SDRAM clocks; &Mode=1, Pin27,28,29,31 are CPU_STOP#,SDRAM_STOP#,PCI_STOP#,PD# |
| 48MHz / &FS0                | 20  | I/O | 48MHz output for USB during normal operation.<br>Latched input for FS0 at initial power up for H/W selecting the output frequency of CPU, SDRAM and PCI clocks.        |

**4.5 Power Pins**

| SYMBOL  | PIN                    | FUNCTION                                                      |
|---------|------------------------|---------------------------------------------------------------|
| Vdd     | 1                      | Power supply for Ref [0:1] crystal and core logic.            |
| VddAGP  | 15                     | Power supply for AGP output, 3.3V.                            |
| VddLCPU | 48                     | Power supply for CPUCLK[0:3], either 2.5V or 3.3V.            |
| VddP    | 7                      | Power supply for PCICLK_F, PCICLK[0:4], 3.3V.                 |
| VddSD   | 43,35,29,25            | Power supply for SDRAM[0:12], and CPU PLL core, nominal 3.3V. |
| Vdd48   | 19                     | Power for 24 & 48MHz output buffers and fixed PLL core.       |
| Vss     | 4,14,18,19,29,32,39,44 | Circuit Ground.                                               |

## 5. FREQUENCY SELECTION BY HARDWARE

|     |     |     |     | VCO   | CPU   | SDRAM | PCI   | AGPSEL=0 | AGPSEL=1 |
|-----|-----|-----|-----|-------|-------|-------|-------|----------|----------|
| FS3 | FS2 | FS1 | FS0 | (MHz) | (MHz) | (MHz) | (MHz) | (MHz)    | (MHz)    |
| 0   | 0   | 0   | 0   | 400   | 66.6  | 66.6  | 33.3  | 66.6     | 50       |
| 0   | 0   | 0   | 1   | 400   | 100   | 100   | 33.3  | 66.6     | 50       |
| 0   | 0   | 1   | 0   | 498   | 166   | 166   | 31.25 | 62.5     | 50       |
| 0   | 0   | 1   | 1   | 400   | 133.3 | 133.3 | 33.3  | 66.6     | 50       |
| 0   | 1   | 0   | 0   | 400   | 66.6  | 100   | 33.3  | 66.6     | 50       |
| 0   | 1   | 0   | 1   | 400   | 100   | 66.6  | 33.3  | 66.6     | 50       |
| 0   | 1   | 1   | 0   | 400   | 100   | 133   | 33.3  | 66.6     | 50       |
| 0   | 1   | 1   | 1   | 400   | 133.3 | 100   | 33.3  | 66.6     | 50       |
| 1   | 0   | 0   | 0   | 336   | 112   | 112   | 33.6  | 67.2     | 56       |
| 1   | 0   | 0   | 1   | 372   | 124   | 124   | 31    | 62       | 46.5     |
| 1   | 0   | 1   | 0   | 414   | 138   | 138   | 34.5  | 69       | 51.8     |
| 1   | 0   | 1   | 1   | 300   | 150   | 150   | 30    | 60       | 50       |
| 1   | 1   | 0   | 0   | 399.6 | 66.6  | 133   | 33.3  | 66.6     | 50       |
| 1   | 1   | 0   | 1   | 300   | 100   | 150   | 30    | 60       | 50       |
| 1   | 1   | 1   | 0   | 300   | 150   | 100   | 30    | 60       | 50       |
| 1   | 1   | 1   | 1   | 480   | 160   | 120   | 30    | 60       | 48       |

## 6. SERIAL CONTROL REGISTERS

The Pin column lists the affected pin number and the @PowerUp column gives the default state at true power up. "Command Code" byte and "Byte Count" byte must be sent following the acknowledge of the Address Byte. Although the data (bits) in these two bytes are considered "don't care", they must be sent and will be acknowledge. After that, the sequence described below (Register 0, Register 1, Register 2, ....) will be valid and acknowledged.

Bytes sequence order for I<sup>2</sup>C controller :

|                               |     |                              |     |                            |     |                            |
|-------------------------------|-----|------------------------------|-----|----------------------------|-----|----------------------------|
| Clock Address<br>A(6:0) & R/W | Ack | 8 bits dummy<br>Command code | Ack | 8 bits dummy<br>Byte count | Ack | Byte0,1,2...<br>until Stop |
|-------------------------------|-----|------------------------------|-----|----------------------------|-----|----------------------------|

Set R/W to 1 when Read back", the data sequence is as follows :

|                               |     |        |     |        |     |                              |
|-------------------------------|-----|--------|-----|--------|-----|------------------------------|
| Clock Address<br>A(6:0) & R/W | Ack | Byte 0 | Ack | Byte 1 | Ack | Byte2, 3, 4...<br>until Stop |
|-------------------------------|-----|--------|-----|--------|-----|------------------------------|

# W83194BR-63S



## Frequency by software

|       |       |       |       |       |       | VCO   | CPU   | SDRAM  | PCI    | AGPSEL=0 | AGPSEL=1 |
|-------|-------|-------|-------|-------|-------|-------|-------|--------|--------|----------|----------|
| SSEL5 | SSEL4 | SSEL3 | SSEL2 | SSEL1 | SSEL0 | (MHz) | (MHz) | (MHz)  | (MHz)  | (MHz)    | (MHz)    |
| 0     | 0     | 0     | 0     | 0     | 0     | 400   | 66.6  | 66.6   | 33.3   | 66.6     | 50       |
| 0     | 0     | 0     | 0     | 0     | 1     | 400   | 100   | 100    | 33.3   | 66.6     | 50       |
| 0     | 0     | 0     | 0     | 1     | 0     | 498   | 166   | 166    | 31.25  | 62.5     | 50       |
| 0     | 0     | 0     | 0     | 1     | 1     | 400   | 133.3 | 133.3  | 33.3   | 66.6     | 50       |
| 0     | 0     | 0     | 1     | 0     | 0     | 400   | 66.6  | 100    | 33.3   | 66.6     | 50       |
| 0     | 0     | 0     | 1     | 0     | 1     | 400   | 100   | 66.6   | 33.3   | 66.6     | 50       |
| 0     | 0     | 0     | 1     | 1     | 0     | 400   | 100   | 133    | 33.3   | 66.6     | 50       |
| 0     | 0     | 0     | 1     | 1     | 1     | 400   | 133.3 | 100    | 33.3   | 66.6     | 50       |
| 0     | 0     | 1     | 0     | 0     | 0     | 336   | 112   | 112    | 33.6   | 67.2     | 56       |
| 0     | 0     | 1     | 0     | 0     | 1     | 372   | 124   | 124    | 31     | 62       | 46.5     |
| 0     | 0     | 1     | 0     | 1     | 0     | 414   | 138   | 138    | 34.5   | 69       | 51.8     |
| 0     | 0     | 1     | 0     | 1     | 1     | 300   | 150   | 150    | 30     | 60       | 50       |
| 0     | 0     | 1     | 1     | 0     | 0     | 400   | 66.6  | 133.3  | 33.3   | 66.6     | 50       |
| 0     | 0     | 1     | 1     | 0     | 1     | 300   | 100   | 150    | 30     | 60       | 50       |
| 0     | 0     | 1     | 1     | 1     | 0     | 300   | 150   | 100    | 30     | 60       | 50       |
| 0     | 0     | 1     | 1     | 1     | 1     | 480   | 160   | 120    | 30     | 60       | 48       |
| 0     | 1     | 0     | 0     | 0     | 0     | 420   | 70    | 105    | 35     | 70       | 52.5     |
| 0     | 1     | 0     | 0     | 0     | 1     | 432   | 72    | 108    | 36     | 72       | 54       |
| 0     | 1     | 0     | 0     | 1     | 0     | 333.2 | 83.3  | 111.07 | 33.3   | 66.6     | 55.5     |
| 0     | 1     | 0     | 0     | 1     | 1     | 388   | 97    | 129.33 | 32.335 | 64.67    | 48.5     |
| 0     | 1     | 0     | 1     | 0     | 0     | 408   | 102   | 136    | 34     | 68       | 51       |
| 0     | 1     | 0     | 1     | 0     | 1     | 416   | 104   | 138.67 | 34.665 | 69.33    | 52       |
| 0     | 1     | 0     | 1     | 1     | 0     | 420   | 105   | 140    | 35     | 70       | 52.5     |
| 0     | 1     | 0     | 1     | 1     | 1     | 428   | 107   | 142.67 | 35.665 | 71.33    | 53.5     |
| 0     | 1     | 1     | 0     | 0     | 0     | 412   | 103   | 68.67  | 34.335 | 68.67    | 51.5     |
| 0     | 1     | 1     | 0     | 0     | 1     | 420   | 105   | 70     | 35     | 70       | 52.5     |
| 0     | 1     | 1     | 0     | 1     | 0     | 424   | 106   | 106    | 35.335 | 70.67    | 53       |
| 0     | 1     | 1     | 0     | 1     | 1     | 428   | 107   | 107    | 35.665 | 71.33    | 53.5     |
| 0     | 1     | 1     | 1     | 0     | 0     | 412   | 103   | 103    | 34.335 | 68.67    | 51.5     |
| 0     | 1     | 1     | 1     | 0     | 1     | 420   | 105   | 105    | 35     | 70       | 52.5     |
| 0     | 1     | 1     | 1     | 1     | 0     | 424   | 106   | 106    | 35.335 | 70.67    | 53       |
| 0     | 1     | 1     | 1     | 1     | 1     | 432   | 108   | 108    | 36     | 72       | 54       |

# W83194BR-63S



Frequency by software, continued

|       |       |       |       |       |       | VCO   | CPU   | SDRAM  | PCI    | AGPSEL=0 | AGPSEL=1 |
|-------|-------|-------|-------|-------|-------|-------|-------|--------|--------|----------|----------|
| SSEL5 | SSEL4 | SSEL3 | SSEL2 | SSEL1 | SSEL0 | (MHz) | (MHz) | (MHz)  | (MHz)  | (MHz)    | (MHz)    |
| 1     | 0     | 0     | 0     | 0     | 0     | 390   | 130   | 130    | 32.5   | 65       | 48.75    |
| 1     | 0     | 0     | 0     | 0     | 1     | 405   | 135   | 135    | 33.75  | 67.5     | 50.63    |
| 1     | 0     | 0     | 0     | 1     | 0     | 408   | 136   | 136    | 34     | 68       | 51       |
| 1     | 0     | 0     | 0     | 1     | 1     | 417   | 139   | 139    | 34.75  | 69.5     | 52.13    |
| 1     | 0     | 0     | 1     | 0     | 0     | 420   | 140   | 140    | 35     | 70       | 52.5     |
| 1     | 0     | 0     | 1     | 0     | 1     | 426   | 142   | 142    | 35.5   | 71       | 53.25    |
| 1     | 0     | 0     | 1     | 1     | 0     | 429   | 143   | 143    | 35.75  | 71.5     | 53.63    |
| 1     | 0     | 0     | 1     | 1     | 1     | 435   | 145   | 145    | 36.25  | 72.5     | 54.38    |
| 1     | 0     | 1     | 0     | 0     | 0     | 390   | 130   | 130    | 32.5   | 65       | 48.75    |
| 1     | 0     | 1     | 0     | 0     | 1     | 405   | 135   | 135    | 33.75  | 67.5     | 50.63    |
| 1     | 0     | 1     | 0     | 1     | 0     | 414   | 138   | 138    | 34.5   | 69       | 51.75    |
| 1     | 0     | 1     | 0     | 1     | 1     | 426   | 142   | 142    | 35.5   | 71       | 53.25    |
| 1     | 0     | 1     | 1     | 0     | 0     | 411   | 137   | 137    | 34.25  | 68.5     | 51.38    |
| 1     | 0     | 1     | 1     | 0     | 1     | 417   | 139   | 139    | 34.75  | 69.5     | 52.13    |
| 1     | 0     | 1     | 1     | 1     | 0     | 423   | 141   | 141    | 35.25  | 70.5     | 52.88    |
| 1     | 0     | 1     | 1     | 1     | 1     | 426   | 142   | 142    | 35.5   | 71       | 53.25    |
| 1     | 1     | 0     | 0     | 0     | 0     | 390   | 130   | 97.5   | 32.5   | 65       | 48.75    |
| 1     | 1     | 0     | 0     | 0     | 1     | 396   | 132   | 99     | 33     | 66       | 49.5     |
| 1     | 1     | 0     | 0     | 1     | 0     | 408   | 136   | 102    | 34     | 68       | 51       |
| 1     | 1     | 0     | 0     | 1     | 1     | 411   | 137   | 102.75 | 34.25  | 68.5     | 51.38    |
| 1     | 1     | 0     | 1     | 0     | 0     | 414   | 138   | 103.5  | 34.5   | 69       | 51.75    |
| 1     | 1     | 0     | 1     | 0     | 1     | 426   | 142   | 106.5  | 26.625 | 53.25    | 42.6     |
| 1     | 1     | 0     | 1     | 1     | 0     | 432   | 144   | 108    | 27     | 54       | 43.2     |
| 1     | 1     | 0     | 1     | 1     | 1     | 438   | 146   | 109.5  | 27.375 | 54.75    | 43.8     |
| 1     | 1     | 1     | 0     | 0     | 0     | 450   | 150   | 112.5  | 28.125 | 56.25    | 45       |
| 1     | 1     | 1     | 0     | 0     | 1     | 459   | 153   | 114.75 | 28.69  | 57.38    | 45.9     |
| 1     | 1     | 1     | 0     | 1     | 0     | 468   | 156   | 117    | 29.25  | 58.5     | 46.8     |
| 1     | 1     | 1     | 0     | 1     | 1     | 489   | 163   | 122.25 | 30.565 | 61.13    | 48.9     |
| 1     | 1     | 1     | 1     | 0     | 0     | 498   | 166   | 124.5  | 31.125 | 62.25    | 49.8     |
| 1     | 1     | 1     | 1     | 0     | 1     | 525   | 175   | 131.25 | 32.815 | 65.63    | 52.5     |
| 1     | 1     | 1     | 1     | 1     | 0     | 534   | 178   | 133.5  | 33.375 | 66.75    | 53.4     |
| 1     | 1     | 1     | 1     | 1     | 1     | 549   | 183   | 137.25 | 34.315 | 68.63    | 54.9     |



## 6.1 Register 0: Frequency Select Register

| Bit | @PowerUp | Pin | Description                                                                         |
|-----|----------|-----|-------------------------------------------------------------------------------------|
| 7   | 0        | -   | SSEL5 ( Frequency table selection by software via I <sup>2</sup> C)                 |
| 6   | 0        | -   | SSEL4 ( Frequency table selection by software via I <sup>2</sup> C)                 |
| 5   | 0        | -   | SSEL3 ( Frequency table selection by software via I <sup>2</sup> C)                 |
| 4   | 0        | -   | SSEL2 ( Frequency table selection by software via I <sup>2</sup> C)                 |
| 3   | 0        | -   | SSEL1 ( Frequency table selection by software via I <sup>2</sup> C)                 |
| 2   | 0        | -   | SSEL0 (Frequency table selection by software via I <sup>2</sup> C)                  |
| 1   | 0        | -   | 0 = Selection by hardware<br>1 = Selection by software I <sup>2</sup> C - Bit (7:2) |
| 0   | 0        | -   | 0 = Running<br>1 = Tristate all outputs                                             |

## 6.2 Register 1 : CPU Clock Register (1 = Active, 0 = Inactive)

| Bit | @PowerUp | Pin | Description                                                                                               |
|-----|----------|-----|-----------------------------------------------------------------------------------------------------------|
| 7   | 1        | -   | CPUCS_C2 free running control<br>1=can be stopped by CPU_STOP#<br>0= CPUCS_C2 is free running             |
| 6   | 1        | 27  | SDRAM11 (Active / Inactive)                                                                               |
| 5   | 0        | -   | 0 = Normal<br>1 = Spread spectrum enable                                                                  |
| 4   | 0        | -   | 0 = ±0.25% Center type Spread Spectrum Modulation<br>1 = 0 ~ (-0.5%) Down type Spread Spectrum Modulation |
| 3   | 1        | 26  | SDRAM12 (Active / Inactive)                                                                               |
| 2   | 1        | 45  | CPUCS_C2(Active / Inactive)                                                                               |
| 1   | 1        | 46  | CPUCLK1(Active / Inactive)                                                                                |
| 0   | 1        | 47  | CPUCLK0(Active / Inactive)                                                                                |

## 6.3 Register 2: PCI Clock Register (1 = Active, 0 = Inactive)

| Bit | @PowerUp | Pin | Description                 |
|-----|----------|-----|-----------------------------|
| 7   | 1        | 17  | AGPCLK1(Active / Inactive)  |
| 6   | 1        | 16  | AGPCLK0(Active / Inactive)  |
| 5   | 1        | 13  | PCICLK5 (Active / Inactive) |
| 4   | 1        | 12  | PCICLK4 (Active / Inactive) |
| 3   | 1        | 11  | PCICLK3 (Active / Inactive) |
| 2   | 1        | 10  | PCICLK2 (Active / Inactive) |
| 1   | 1        | 9   | PCICLK1 (Active / Inactive) |
| 0   | 1        | 8   | PCICLK0 (Active / Inactive) |

#### 6.4 Register 3: SDRAM Clock Additional Register (1 = Active, 0 = Inactive)

| Bit | @PowerUp | Pin | Description                |
|-----|----------|-----|----------------------------|
| 7   | 1        | 33  | SDRAM7 (Active / Inactive) |
| 6   | 1        | 34  | SDRAM6 (Active / Inactive) |
| 5   | 1        | 36  | SDRAM5 (Active / Inactive) |
| 4   | 1        | 37  | SDRAM4 (Active / Inactive) |
| 3   | 1        | 38  | SDRAM3 (Active / Inactive) |
| 2   | 1        | 40  | SDRAM2 (Active / Inactive) |
| 1   | 1        | 41  | SDRAM1 (Active / Inactive) |
| 0   | 1        | 42  | SDRAM0 (Active / Inactive) |

#### 6.5 Register 4: PCI Clock Additional Register (1 = Active, 0 = Inactive)

| Bit | @PowerUp | Pin | Description                 |
|-----|----------|-----|-----------------------------|
| 7   | X        | -   | AGPSEL#                     |
| 6   | X        | -   | FS3#                        |
| 5   | X        | -   | FS2#                        |
| 4   | X        | -   | FS1#                        |
| 3   | X        | -   | FS0#                        |
| 2   | 1        | 28  | SDRAM10 (Active / Inactive) |
| 1   | 1        | 30  | SDRAM9 (Active / Inactive)  |
| 0   | 1        | 31  | SDRAM8 (Active / Inactive)  |

#### 6.6 Register 5: Skew Register

| Bit | @PowerUp | Pin | Description                            |
|-----|----------|-----|----------------------------------------|
| 7   | 1        | -   | CSkew2 (SDRAM to CPU skew program bit) |
| 6   | 0        | -   | CSkew1 (SDRAM to CPU skew program bit) |
| 5   | 0        | -   | CSkew0 (SDRAM to CPU skew program bit) |
| 4   | 1        | -   | CAkew2 (AGP to CPU skew program bit)   |
| 3   | 0        | -   | CAkew1 (AGP to CPU skew program bit)   |
| 2   | 0        | -   | CAkew0 (AGP to CPU skew program bit)   |
| 1   | 1        | 21  | 24_48MHz(Active / Inactive)            |
| 0   | 1        | 20  | 48MHz(Active / Inactive)               |



### 6.7 Register 6: Watchdog Timer Register

| Bit | @PowerUp | Pin | Description                                       |
|-----|----------|-----|---------------------------------------------------|
| 7   | 0        | -   | Enable Count    1 = start timer    0 = stop timer |
| 6   | X        | -   | Second timeout status (READ ONLY)                 |
| 5   | 0        | -   | Second count 5                                    |
| 4   | 0        | -   | Second count 4                                    |
| 3   | 0        | -   | Second count 3                                    |
| 2   | 0        | -   | Second count 2                                    |
| 1   | 0        | -   | Second count 1                                    |
| 0   | 0        | -   | Second count 0                                    |

### 6.8 Register 7: M/N Program Register and Divisor

| Bit | @PowerUp | Pin | Description                |
|-----|----------|-----|----------------------------|
| 7   | 0        | -   | N value bit 8              |
| 6   | 1        | -   | Test 1 (Internal test use) |
| 5   | 0        | -   | Test 0 (Internal test use) |
| 4   | 0        | -   | M value bit 4              |
| 3   | 0        | -   | M value bit 3              |
| 2   | 0        | -   | M value bit 2              |
| 1   | 0        | -   | M value bit 1              |
| 0   | 0        | -   | M value bit 0              |

### 6.9 Register 8: M/N Program Register

| Bit | @PowerUp | Pin | Description   |
|-----|----------|-----|---------------|
| 7   | 0        | -   | N value bit 7 |
| 6   | 0        | -   | N value bit 6 |
| 5   | 0        | -   | N value bit 5 |
| 4   | 0        | -   | N value bit 4 |
| 3   | 0        | -   | N value bit 3 |
| 2   | 0        | -   | N value bit 2 |
| 1   | 0        | -   | N value bit 1 |
| 0   | 0        | -   | N value bit 0 |

### 6.10 Register 9: Divisor Register

| Bit | @PowerUp | Pin | Description                  |
|-----|----------|-----|------------------------------|
| 7   | 0        | -   | Spread spectrum up count 3   |
| 6   | 0        | -   | Spread spectrum up count 2   |
| 5   | 0        | -   | Spread spectrum up count 1   |
| 4   | 0        | -   | Spread spectrum up count 0   |
| 3   | 0        | -   | Spread spectrum down count 3 |
| 2   | 0        | -   | Spread spectrum down count 2 |
| 1   | 0        | -   | Spread spectrum down count 1 |
| 0   | 0        | -   | Spread spectrum down count 0 |

### 6.11 Register 10: Divisor Register

| Bit | @PowerUp | Pin | Description                                                                                                                                  |
|-----|----------|-----|----------------------------------------------------------------------------------------------------------------------------------------------|
| 7   | 0        | -   | 0: use frequency table<br>1: use M/N register to program frequency<br>The equation is <u><math>VCO\ freq. = 14.318MHz * (N+4) / M</math></u> |
| 6   | X        | -   | Ratio SEL3 (See ratio selection table)                                                                                                       |
| 5   | X        | -   | Ratio SEL2 (See ratio selection table)                                                                                                       |
| 4   | X        | -   | Ratio SEL1 (See ratio selection table)                                                                                                       |
| 3   | X        | -   | Ratio SEL0 (See ratio selection table)                                                                                                       |
| 2   | X        | -   | AGP Ratio SEL2 (See ratio selection table1)                                                                                                  |
| 1   | X        | -   | AGP Ratio SEL1 (See ratio selection table1)                                                                                                  |
| 0   | X        | -   | AGP Ratio SEL0 (See ratio selection table1)                                                                                                  |

### 6.12 Register 11: Winbond Chip ID Register (Read Only)

| Bit | @PowerUp | Pin | Description     |
|-----|----------|-----|-----------------|
| 7   | 0        | -   | Winbond Chip ID |
| 6   | 0        | -   | Winbond Chip ID |
| 5   | 0        | -   | Winbond Chip ID |
| 4   | 0        | -   | Winbond Chip ID |
| 3   | 0        | -   | Winbond Chip ID |
| 2   | 1        | -   | Winbond Chip ID |
| 1   | 0        | -   | Winbond Chip ID |
| 0   | 1        | -   | Winbond Chip ID |



## 6.13 Register 12: Winbond Chip ID Register (Read Only)

| Bit | @PowerUp | Pin | Description     |
|-----|----------|-----|-----------------|
| 7   | 0        | -   | Winbond Chip ID |
| 6   | 0        | -   | Winbond Chip ID |
| 5   | 1        | -   | Winbond Chip ID |
| 4   | 0        | -   | Winbond Chip ID |
| 3   | 0        | -   | Version ID      |
| 2   | 0        | -   | Version ID      |
| 1   | 0        | -   | Version ID      |
| 0   | 1        | -   | Version ID      |

## Ratio selection table

| Reg10<br>bit6 | Reg10<br>bit5 | Reg10<br>bit4 | Reg10<br>bit3 | VCO/<br>CPU | VCO/<br>SDRAM | VCO/<br>PCI |
|---------------|---------------|---------------|---------------|-------------|---------------|-------------|
| SSEL3         | SSEL2         | SSEL1         | SSEL0         | ratio       | ratio         | ratio       |
| 0             | 0             | 0             | 0             | 2           | 2             | 10          |
| 0             | 0             | 0             | 1             | 2           | 3             | 10          |
| 0             | 0             | 1             | 0             | 3           | 2             | 10          |
| 0             | 0             | 1             | 1             | 3           | 3             | 10          |
| 0             | 1             | 0             | 0             | 3           | 3             | 12          |
| 0             | 1             | 0             | 1             | 3           | 3             | 16          |
| 0             | 1             | 1             | 0             | 3           | 4             | 12          |
| 0             | 1             | 1             | 1             | 3           | 4             | 16          |
| 1             | 0             | 0             | 0             | 4           | 3             | 10          |
| 1             | 0             | 0             | 1             | 4           | 3             | 12          |
| 1             | 0             | 1             | 0             | 4           | 3             | 16          |
| 1             | 0             | 1             | 1             | 4           | 4             | 12          |
| 1             | 1             | 0             | 0             | 4           | 6             | 12          |
| 1             | 1             | 0             | 1             | 6           | 3             | 12          |
| 1             | 1             | 1             | 0             | 6           | 4             | 12          |
| 1             | 1             | 1             | 1             | 6           | 6             | 12          |

## Ratio Selection Table 1


| Reg10<br>bit2 | Reg10<br>bit1 | Reg10<br>bit0 | VCO/AGP |
|---------------|---------------|---------------|---------|
| AGP2          | AGP1          | AGP0          | ratio   |
| 0             | 0             | 0             | 3       |
| 0             | 0             | 1             | 5       |
| 0             | 1             | 0             | 6       |
| 0             | 1             | 1             | 8       |
| 1             | 0             | 0             | 4       |
| 1             | 0             | 1             | -       |
| 1             | 1             | 0             | -       |
| 1             | 1             | 1             | 10      |



## 7. ORDERING INFORMATION

| Part Number  | Package Type | Production Flow          |
|--------------|--------------|--------------------------|
| W83194BR-63S | 48 PIN SSOP  | Commercial, 0°C to +70°C |

## 8. HOW TO READ THE TOP MARKING



1st line: Winbond logo and the type number: W83194BR-63S

2nd line: Tracking code 2 8051234

2: wafers manufactured in Winbond FAB 2

8051234: wafer production series lot number

3rd line: Tracking code 814 G B B

002: packages made in '00, week 02


G: assembly house ID; O means OSE, G means GR

A: Internal use code

B: IC revision

All the trade marks of products and companies mentioned in this data sheet belong to their respective owners.

## 9. PACKAGE DRAWING AND DIMENSIONS



**10. REVISION HISTORY**

| VERSION | DATE         | PAGE | DESCRIPTION                                           |
|---------|--------------|------|-------------------------------------------------------|
|         |              | n.a. | All of the versions before 0.50 are for internal use. |
| 1.0     | 02/Apr       | n.a. | Change version and version on web site to 1.0         |
| 2.0     | May 19, 2005 | 16   | ADD Important Notice                                  |
|         |              |      |                                                       |

**Important Notice**

Winbond products are not designed, intended, authorized or warranted for use as components in systems or equipment intended for surgical implantation, atomic energy control instruments, airplane or spaceship instruments, transportation instruments, traffic signal instruments, combustion control instruments, or for other applications intended to support or sustain life. Further more, Winbond products are not intended for applications wherein failure of Winbond products could result or lead to a situation wherein personal injury, death or severe property or environmental damage could occur.

Winbond customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify Winbond for any damages resulting from such improper use or sales.

**Headquarters**

No. 4, Creation Rd. III,  
Science-Based Industrial Park,  
Hsinchu, Taiwan  
TEL: 886-3-5770066  
FAX: 886-3-5665577  
<http://www.winbond.com.tw/>

**Taipei Office**

9F, No.480, Rueiguang Rd.,  
Neihu District, Taipei, 114,  
Taiwan, R.O.C.  
TEL: 886-2-8177-7168  
FAX: 886-2-8751-3579

**Winbond Electronics Corporation America**

2727 North First Street, San Jose,  
CA 95134, U.S.A.  
TEL: 1-408-9436666  
FAX: 1-408-5441798

**Winbond Electronics Corporation Japan**

7F Daini-ueno BLDG, 3-7-18  
Shinyokohama Kohoku-ku,  
Yokohama, 222-0033  
TEL: 81-45-4781881  
FAX: 81-45-4781800

**Winbond Electronics (Shanghai) Ltd.**

27F, 2299 Yan An W. Rd. Shanghai,  
200336 China  
TEL: 86-21-62365999  
FAX: 86-21-62365998

**Winbond Electronics (H.K.) Ltd.**

Unit 9-15, 22F, Millennium City,  
No. 378 Kwun Tong Rd.,  
Kowloon, Hong Kong  
TEL: 852-27513100  
FAX: 852-27552064

*Please note that all data and specifications are subject to change without notice.  
All the trade marks of products and companies mentioned in this data sheet belong to their respective owners.*