

New Jersey Semi-Conductor Products, Inc.

20 STERN AVE.
SPRINGFIELD, NEW JERSEY 07081
U.S.A.

TELEPHONE: (973) 376-2922
(212) 227-6005
FAX: (973) 376-8960

Schottky Rectifier

High Reliability

Part Number	VRRM (V)	IF(AV) @ Tc		VFM @ IFM Tj = 100°C IFM = IF(AV) (V)	IFSM(1)		IRM @ Tj = 125°C & Rated VRWM (mA)	Max. Tj (°C)	Outline Number (5)	Notes	Case Style
		(A)	(°C)		50Hz (A)	60Hz (A)					
15CGQ100	100	15.0	100	0.77	TBD	TBD	7	150	H19	(2) (3)	TO-254AA M-PAK (4) 
20GQ100	100	20.0		0.92			45	175			
22CGQ045	45	22.0		0.89			20	175			
22DGQ045	45	22.0		0.89			20	175			
25GQ045	45	22.0		0.85			45	175			
15CLQ100	100	15.0	100	0.80	228	240	15	175	H21	(2)	SMD-1 
20CLQ045	45	20.0		0.75	285	300	15	175			
45CKQ100	100	45.0		TBD	TBD	TBD	TBD	175			
60CKQ045	45	60.0		TBD	TBD	TBD	TBD	175			


(1) PEAK HALF-CYCLE SINE WAVE, FOLLOWING ANY RATED LOAD CONDITION. VRWM REAPPLIED.

(2) DUAL-DIE COMMON CATHODE CONFIGURATION

(3) DUAL-DIE DOUBLER CONFIGURATION.

(4) PACKAGES CONTAINING BERYLLIA SHALL NOT BE GROUND, SANDBLASTED, MACHINED, OR HAVE OTHER OPERATIONS PERFORMED ON THEM WHICH WILL PRODUCE BERYLLIA OR BERYLLIUM DUST. FURTHERMORE, BERYLLIUM OXIDE PACKAGES SHALL NOT BE PLACED IN ACIDS THAT WILL PRODUCE FUMES CONTAINING BERYLLIUM.

(5) FOR CASE OUTLINE DRAWING SEE PAGE 136.



NJ Semi-Conductors reserves the right to change test conditions, parameter limits and package dimensions without notice. Information furnished by NJ Semi-Conductors is believed to be both accurate and reliable at the time of going to press. However, NJ Semi-Conductors assumes no responsibility for any errors or omissions discovered in its use. NJ Semi-Conductors encourages customers to verify that datasheets are current before placing orders.

Quality Semi-Conductors