

SV7-C-CE

CANopen Servo Drive

1pc. - 585.00
50pc. - 438.75



Product Features

- Programmable digital servo drive with built-in CANopen networking
- DSP-based current control, sinusoidal commutation and jerk filter
- Operates from 24-80 VDC
- Provides motor current up to 7.0 A rms continuous, 14.0 A rms peak
- CANopen DS301 and DSP402 supported
- Profile position, velocity and torque modes
- Several homing modes
- Objects for Q programming and data registers
- 8 digital inputs, 4 digital outputs, all optically isolated
- 2 analog inputs, +/-10 volt range
- RS-232 port for programming and communications



Description


The SV series servo drives are suitable for a wide range of motion applications. They are built around a powerful digital signal processor coupled to an efficient MOSFET PWM amplifier. The SV drives include 12 optically isolated I/O points plus analog inputs. A sophisticated, yet easy to tune position loop has independent digital settings for proportional, integral and derivative gains plus velocity feedback and velocity and acceleration feedforward.

All SV drives are capable of running brushless, brushed, and linear servo motors. A timing wizard automatically configures the encoder and commutation timing for virtually any brushless or brushed DC motor. Tuning is easy with our Quick Tuner™ software, featuring a built-in digital oscilloscope

Specifications

Model Number:	SV7-C-CE
Part Number:	5000-160
Supply Voltage:	24-80 VDC
Supply Voltage Type:	DC
Control Modes:	CANopen
Output Current, Continuous:	7.0
Output Current, Peak:	14.0
Communication Ports:	RS-232 CANopen
Feedback:	Halls + Incremental encoder
Setup Method:	Software setup
Digital Inputs:	8
Digital Outputs:	4
Analog Inputs:	1 differential or 2 single-ended
Dimensions:	5 x 3 x 1.78 inches
Weight:	10.0 oz
Ambient Temperature Range:	0 to 40 °C
Ambient Humidity:	90% max, non-condensing
Status LEDs:	1 red, 1 green
Circuit Protection:	Short circuit Over-voltage Under-voltage Over-temp

Software

Software:	DSP Firmware Downloader Q Programmer™ Quick Tuner™
Sample Code:	 CANopen_Example.zip

Downloads

Manuals:	SV7_HardwareManual_920-0012.pdf SV7-C_QuickSetup_920-0064.pdf CANopen_Manual_920-0025K.pdf
Datasheet:	http://s3.amazonaws.com/applied-motion-pdf/SV7-C-CE.pdf
Family Datasheet:	Servo-Products-Datasheet-925-0008.pdf CANopen_FAQ2.pdf SV7-CANopen-EDS.eds
2D Drawing:	SV7_simple_3D.pdf SV7_2D_Drawing.pdf
3D Drawing:	SV7-S-AE_solid.igs
Speed-Torque Curves:	SV7_speed-torque.pdf
Agency Approvals:	SV7-S_Q_Si_CE_DOC.pdf
Application Notes:	APPN0017_Wiring-integral-holding-brakes.pdf APPN0016_Simple-25-pin-mating-connections.pdf APPN0015_Make-a-serial-programming-cable.pdf

Pricing

SV7-C-CE Part No. 5000-160	
1pc.	\$585.00
25pc.	\$503.10
50pc.	\$438.75
100pc.	Request a Quote for 100+ piece pricing.

Mechanical Outline

