Coaxial Bandpass Cavity Filter

ZVBP-909+

50Ω 902 to 915 MHz

The Big Deal

- Low Insertion Loss, 2.0 dB typ.
- Excellent Close-in Rejection
 870 MHz, 950 MHz, 88 dB typical
 888 MHz, 929 MHz, 60 dB typical
- 15W Power handling

Product Overview

The Mini-Circuits ZVBP-909+ slabline filter offering outstanding close-in rejections for use in CDMA and GSM base stations.

Key Features

Feature	Advantages
Ultra-High Rejection Close to the Passband	Using slabline resonators, the ZVBP-909+ provides more that 70 dB rejection at only 32 MHz away from the passband of 902 to 915 MHz
Narrow Percent Bandwidth	The ZVBP-909+ design has been optimized to support 1dB passbandwidths down to 1.4% making this design ideal for high selectivity applications such as radio communications with stringent interfering blocking signals
Low Passband Insertion Loss for Ultra Narrow Filter	The ZVBP-909+ combines excellent insertion loss with narrow percent bandwidth operation. Employing a multi-section design to achieve the extremely close rejection, this filter maintains low passband insertion loss due to its unique resonator design.
Low Passband VSWR	ZVBP-909+ maintains typical VSWR of 1.2:1 making it easier to integrate into receiver and transmitter RF chains with less concerns for in-band ripple.
Wide Operating Temperature Range with Excellent Temperature Stability	Operating over an extended temperature range of -55 to +100°C, the ZVBP-909+ supports ± 0.4 dB passband insertion loss variation over the full range
Good Power Handling capability	Handling up to 15W CW within the passband, the ZVBP-909+ is ideally used in both TX and RX chains



For detailed performance specs & shopping online see web site

P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661 The Design Engineers Search Engine 2012 Provides ACTUAL Data Instantly at minicipality.com

IF/RF MICROWAVE COMPONENTS

Notes: 1. Performance and quality attributes and conditions not expressly stated in this specification sheet are intended to be excluded and do not form a part of this specification sheet.
2. Electrical specifications and performance data contained herein are based on Min-Circuit's applicable established test performance ordera and measurement instructions.
3. The parts covered by this specification sheet are subject to Mini-Circuit's applicable established test performance and measurement instructions.
3. The parts covered by this specification sheet are subject to Mini-Circuit's applicable established test performance order are entited to the rights and benefits contained therein. For a full statement of the Standard Terms'): Purchasers of this part are entited to the rights and benefits contained therein. For a full statement of the Standard Terms'): Purchasers of this parts.



CASE STYLE: KT1510

Coaxial **Bandpass Cavity Filter**

50Ω 902 to 915 MHz

Features

- Low Insertion loss, 2.0 dB typ.
- · Good VSWR, 1.2:1 typ. in passband
- · Narrow bandwidth with high selectivity

Applications

· CDMA band rejection for GSM base station

Receivers/Transmitters

Functional Schematic



Typical Frequency Response



+ RoHS compliant in accordance with EU Directive (2002/95/EC)

The +Suffix has been added in order to identify RoHS Compliance. See our web site for RoHS Compliance methodologies and qualifications.

ZVBP-909+

Mini-Circuits

CASE STYLE: KT1510 SMA Connectors Model Price Qty. IN FEM OUT FEM ZVBP-909-S+ \$299.00 ea. (1-9)

Electrical Specifications at 25°C

Parameter		F#	Frequency (MHz)	Min.	Тур.	Max.	Unit
Pass Band	Center Frequency	—	—	—	908.5	—	MHz
	Insertion Loss	F1-F2	902 - 915	_	2.0	2.7	dB
	VSWR	F1-F2	902 - 915	-	1.2	1.4	:1
Stop Band, Lower	Insertion Loss	DC-F3	10 - 895	20	33	_	dB
	VSWR	DC-F3	10 - 895	-	30	_	:1
Stop Band, Upper	Insertion Loss	F4-F5	925 - 2300	20	34	_	dB
	VSWR	F4-F5	925 - 2300	_	25	_	:1

Maximum Ratings					
Operating Temperature	-55°C to 100°C				
Storage Temperature	-55°C to 100°C				
RF Power Input*	15W max. at 25°C				

*Derate linearly to 5 W at 100°C Permanent damage may occur if any of these limits are exceeded

Typical Performance Data at 25°C

Frequency (MHz)	Insertion Loss (dB)	VSWR-In (:1)	VSWR-Out (:1)	
10.00	104.69	1737.18	1737.18	
870.00	98.08	289.53	289.53	
888.00	61.26	108.58	108.58	
895.00	33.04	34.07	37.77	
897.50	17.32	14.50	17.05	
899.00	6.81	5.25	6.21	
900.00	3.15	2.09	2.37	
902.00	1.85	1.14	1.09	
908.50	1.44	1.10	1.15	
915.00	1.77	1.17	1.18	
918.00	3.98	1.65	1.24	
919.00	9.87	3.58	2.55	
920.00	18.20	10.56	7.94	
925.00	47.86	43.44	41.37	
929.00	63.41	64.35	64.35	
950.00	102.83	157.93	157.93	
1300.00	103.35	434.30	434.30	
2300.00	98.96	193.02	248.17	





Mini-Circuits

For detailed performance specs & shopping online see web site

P.O. Box 350166, Brooklyn, New York 11235-0003 (718) 934-4500 Fax (718) 332-4661 The Design Engineers Search Engine Control Provides ACTUAL Data Instantly at minicipality.com IF/RF MICROWAVE COMPONENTS

Notes: 1. Performance and quality attributes and conditions not expressly stated in this specification sheet are intended to be excluded and do not form a part of this specification sheet. 2. Electrical specifications and performance data contained herein are based on Mini-Circuit's applicable established test performance criteria and measurement instructions. 3. The parts covered by this specification sheet are subject to Mini-Circuit's standard Terms"); Purchasers of this part are entitled to the rights and benefits contained herein. For a full statement of the Standard Terms and the exclusive rights and remedies thereunder, please visit Mini-Circuit's website at www.minicircuits.com/MCLStore/terms.jsp.

REV. OR M126295 ZVBP-909+ EDU-1316/1 URJ/NY 111011 Page 2 of 3

ZVBP-909+

Coaxial Connections

INPUT	SMA FEMALE
OUTPUT	SMA FEMALE

Outline Drawing



Outline Dimensions (inch)

А	В	С	D	E	F	G	н	J
10.193	3.110	1.150	0.300	0.150	0.236	9.893	2.637	9.593
258.90	78.99	29.21	7.62	3.81	5.99	251.28	66.98	243.66
ĸ		м	N	D	0	D	S	wet
0 127	0.577	0 761	2 340	0 150	9 250	0 638	0.638	arame
0.121	14.00	10.00	2.040 E0.00	0.100	004.05	10.000	10.000	9/5 00



For detailed performance specs & shopping online see web site

Infright and the second of the beside of the