


Description

The DC1900A30 is a low profile, high performance 30dB directional coupler. It is designed for AMPS applications. This component is suitable for feed-forward amplifier and signal sampling circuits where low insertion loss, high directivity is required. It can be used in power applications up to 120 Watts.

Parts have been subjected to rigorous qualification testing and they are using materials with coefficients of thermal expansion (CTE) compatible with common substrates such as FR4, G-10, RF-35, RO4350B and polyimide.



Features:

- 1700-2000 MHz
- AMPS
- Low Insertion Loss
- High Directivity
- Low VSWR
- Good Repeatability
- CTE compatible with FR4, G-10, RF-35, RO4350B and polyimide
- Immersion gold, prevent surface oxidation & scratch
- RoHS Compliant
- Tape & Reel Package available


Electrical Specifications

Frequency	Coupling	Directivity	VSWR
MHz	dB	dB Min	Max : 1
1700 - 2000	30±1.5	18	1.20
Insertion Loss	Power	Operating Temp.	
dB Max	Avg. CW Watts	°C	
0.21	120	-55 to +95	

Note:

1. All above test data resulting from specify demo board.
2. Insertion loss has removed the thru board loss.

Mechanical Outline




Yantel Corporation

Add: 3F, Building 3, Southern District 2 of Zhongguan Honghualing Industrial Park, Xili, Nanshan, Shenzhen, China
Tel: 86-755-8355-1886 Fax: 86-755-8355-2533

For detailed performance specs & shopping online see Yantel web site : www.yantel-corp.com

Directional Coupler Pin Configuration

The DC1900A30 has an orientation marker to denote Pin 1. Once port one has been identified the other ports are known automatically. Please see the chart below for clarification:



Pin 1	Pin 2	Pin 3	Pin 4
Input	Transmission	Isolate	Coupling
Transmission	Input	Coupling	Isolate

Typical Performance Data (@25°C)


Frequency (MHz)	Coupling (dB)	Transmission (dB)	Insertion Loss (dB)	Directivity (dB)	Return Loss(dB)			
					S11	S22	S33	S44
1700	-29.15	-0.10	-0.09	-28.64	-23.81	-23.73	-21.80	-24.22
1715	-28.96	-0.09	-0.09	-20.61	-23.86	-23.81	-21.51	-24.50
1730	-29.03	-0.11	-0.10	-21.81	-23.78	-23.99	-21.64	-24.89
1745	-29.13	-0.13	-0.13	-24.27	-23.72	-24.20	-21.93	-25.34
1760	-29.06	-0.15	-0.15	-27.55	-23.88	-24.40	-22.18	-25.87
1775	-28.98	-0.14	-0.14	-27.65	-24.19	-24.71	-22.34	-26.26
1790	-28.92	-0.12	-0.11	-28.64	-24.58	-24.98	-22.42	-26.53
1805	-28.85	-0.09	-0.09	-29.85	-24.87	-25.23	-22.44	-26.80
1820	-28.80	-0.08	-0.08	-32.03	-24.91	-25.54	-22.40	-27.23
1835	-28.82	-0.11	-0.11	-31.35	-24.89	-25.92	-22.38	-27.91
1850	-28.82	-0.13	-0.12	-27.73	-25.00	-26.37	-22.47	-28.77
1865	-28.81	-0.12	-0.11	-31.82	-25.14	-26.85	-23.75	-29.54
1880	-28.91	-0.09	-0.08	-34.71	-25.41	-27.32	-22.92	-30.11
1895	-29.15	-0.10	-0.09	-28.94	-25.71	-27.72	-23.08	-30.34
1910	-29.41	-0.09	-0.09	-26.19	-26.16	-28.19	-23.03	-30.36
1925	-29.48	-0.11	-0.10	-23.51	-26.63	-28.71	-23.41	-30.78
1940	-29.45	-0.12	-0.11	-24.14	-26.63	-29.58	-23.67	-31.58
1955	-29.35	-0.12	-0.12	-28.56	-26.81	-30.57	-24.20	-32.74
1970	-29.28	-0.10	-0.10	-31.07	-27.14	-31.65	-24.66	-34.16
1985	-29.19	-0.07	-0.06	-24.52	-27.61	-32.77	-24.93	-35.30
2000	-29.32	-0.06	-0.05	-19.89	-27.91	-33.72	-24.89	-35.05

Yantel Corporation

Add: 3F, Building 3, Southern District 2 of Zhongguan Honghualing Industrial Park, Xili, Nanshan, Shenzhen, China
Tel: 86-755-8355-1886 Fax: 86-755-8355-2533

For detailed performance specs & shopping online see Yantel web site : www.yantel-corp.com

Typical Performance (-55°C, 25°C, 95°C, 125°C: 1700-2000 MHz)




Yantel Corporation

Add: 3F, Building 3, Southern District 2 of Zhongguan Honghualing Industrial Park, Xili, Nanshan, Shenzhen, China
Tel: 86-755-8355-1886 Fax: 86-755-8355-2533

For detailed performance specs & shopping online see Yantel web site : www.yantel-corp.com

Typical Performance (-55°C, 25°C, 95°C, 125°C: 1700-2000 MHz)



Yantel Corporation

Add: 3F, Building 3, Southern District 2 of Zhongguan Honghualing Industrial Park, Xili, Nanshan, Shenzhen, China

Tel: 86-755-8355-1886 Fax: 86-755-8355-2533

For detailed performance specs & shopping online see Yantel web site : www.yantel-corp.com

Description of Measured Specifications

Parameter	Description
VSWR	Voltage standing wave ratio, the impedance match to 50 Ω , the ideal value is 1:1.
Return Loss	Loss of signal power resulting from the reflection caused by discontinuity of transmission line.
Insertion Loss	The input power divided by sum of power at the coupling port & transmission port.
Coupling	The input power divided by the power at coupling port.
Transmission	The input power divided by the power at transmission port.
Directivity	The power at the coupling port divided by the power at the isolated.

Test Method

1. Calibrating your vector network analyzer.
2. Connect the VNA 4 Port to DUT respectively.
3. Measure the data of coupling through port 1 to port 4(S41).
4. Measure the data of transmission through port 1 to port 2(S21).
5. Measure the data of isolation through port 1 to port 3(S31).
6. Measure the data of return loss port 1, port 2, port 3 & port 4.
7. According to the above data to calculate insertion loss, directivity.

Note:

1. When calculating insertion loss at room temperature, coupling & transmission data both need remove demo board loss. Please see demo board loss data below the table :

Frequency Range(MHz)	Demo Board Loss (dB) @25℃
470-860	0.06~0.10
800-1000	0.10~0.15
1200-1700	0.15~0.20
1700-2000	0.20~0.25
2000-2300	0.20~0.25
2300-2700	0.25~0.30





Figure 1: Dimensions of the proposed antenna. The diagram shows a square patch antenna with a grid of 10x10 vias. Key dimensions include: total width 10,92; total height 5,59; patch width 1,9; patch height 1,65; via diameter ø0,8; and distance from the left edge to the first via 1,02. The antenna is connected to a 4x50Ω line.

1. 50Ω line width is shown above designing from RO4350B dielectric thickness 0.762mm; copper 1 OZ
2. Bottom side of the PCB is continuous ground plane.
3. All dimensions shown in mm.

The graph illustrates the temperature profile of a reflow soldering process. The vertical axis represents Temperature in degrees Celsius (C), and the horizontal axis represents Time in seconds (s). The curve shows the temperature rising from the start, passing through a preheat/soak phase (60-80sec), entering a spaking zone (60-90sec), reaching a peak temperature (235-255 C) within the reflow zone (50-90sec), and finally cooling down. A horizontal line indicates the melting point of the alloy at 217-219 C.

Phase	Duration (sec)	Temperature Range (C)
Preheat/soak	60-80	-
Spaking Zone	60-90	-
Reflow Zone	50-90	235-255
Peak temperature	-	235-255
Melting point alloy	-	217-219
Cooldown	-	-


Reliability Test Flow



Yantel Corporation

Add: 3F, Building 3, Southern District 2 of Zhongguan Honghualing Industrial Park, Xili, Nanshan, Shenzhen, China
 Tel: 86-755-8355-1886 Fax: 86-755-8355-2533
 For detailed performance specs & shopping online see Yantel web site : www.yantel-corp.com


Reliability Test Flow



Yantel Corporation

Tape and Reel Drawing




Feeding Direction




ITEM	W	A0	B0	K0	P	F	E	D	D1	P0	P2	T	7"
DIM(mm)	24.00	9.30	14.70	2.40	12.00	11.50	1.75	1.50	1.50	4.00	2.00	0.30	P/R
TOLE	+0.30 -0.30	+0.10 -0.10	+0.10 -0.10	+0.10 -0.10	+0.10 -0.10	+0.10 -0.10	+0.10 -0.10	+0.10 -0.00	+0.10 -0.00	+0.10 -0.10	+0.10 -0.10	+0.05 -0.05	500 pcs

Notice:

- A.10 Sprocket hole pitch cumulative tolerance is 0.2mm.
- B. Carrier camber shall be not more than 1mm per 100mm through a length of 250mm.
- C. All dimensions meet EIA-418-B requirements.
- D. A0 & B0 measured as indicated.
- E. K0 measured from a place on the inside bottom of the pocket to top surface of carrier.
- F. Material: PE 100
- G. Thickness: 0.30±0.05mm
- H. 500 units (maximum) / T&R



Symbol	Dimensions (mm)
W	24.5±0.4
A	177±0.5
N	63±0.3
T	1.8±0.2
E	2.1±0.3
F	10.75±0.3
D	13.5+0.5/-0.2



Yantel Corporation

Add: 3F, Building 3, Southern District 2 of Zhongguan Honghualing Industrial Park, Xili, Nanshan, Shenzhen, China

Tel: 86-755-8355-1886 Fax: 86-755-8355-2533

For detailed performance specs & shopping online see Yantel web site : www.yantel-corp.com