

PHASE LOCKED OSCILLATOR

MODEL MDR6100-06000 (6000 MHz)



Features

- Low Phase Noise: -120 dBc/Hz @ 100 kHz
- Low Spurious: -80 dBc Typical
- External Reference
- Environmental Screening Available

Specifications¹

CHARACTERISTIC	TYPICAL Ta = 25 °C	MIN/MAX Ta = -20 °C to +65 °C
Frequency (MHz) ²	6000	6000
Mechanical Tuning		
Bandwidth (MHz) ³	+/- 10	+/- 10 Min.
Output Power (dBm) ⁴	+13	+12
Variation Over Temperature (dBm)	+/- 0.75	+/- 1
Spurious (dBc)	-80	-70
Phase Noise (dB) ⁵	-104 dBc/Hz @ 1 KHz -114 dBc/Hz @ 10 KHz -120 dBc/Hz @ 100 KHz -136 dBc/Hz @ 1 MHz	
VSWR	1.5	2.0
Harmonics (dBc)	-20	-15
External Reference	100 MHz	1 / 200 MHz
Lock Indicator	TTL (High=Locked)	TTL (Low=Unlocked)
Supply Power DC ⁶	+12	+12
	mA	265
Phase Voltage		
Set to (nom.)	+5.0 VDC	
Lock Range (min.)	+2 to +9 VDC	
Phase-Lock Alarm		
Locked	Transistor Collector (NPN)	
Unlocked ⁷	Open Vc = 30 VDC max. Saturated to Ground Vce = +0.5 VDC max. Ic = 50 mA max.	

Description

Spectrum Microwave's Series MDR6100 Phase Locked Oscillators use a Dielectric Resonator in the resonant circuit. The circuit is lightly loaded to obtain the lowest phase noise possible.


The resonator is epoxied to a printed circuit board and well grounded to minimize modulation sidebands during shock and vibration.

Buffer amplifiers are used to provide isolation from load VSWRs; Regulators filter noise on the DC input voltage.

Internal reference models are also available. A lock indicator circuit is provided to signal an out-of-lock condition.

Notes:

1. Specifications labeled "min." or "max." are guaranteed in a 50 Ohm system over the specified temperature range.
2. Output frequency must be specified, and it is an integer multiple of the internal crystal reference frequency.
3. Mechanical tuning of PLO in unlocked mode.
4. Higher output power is available.
5. Phase Noise at offsets <100 kHz is dependent on external reference and can be approximated as follows: $Phase\ Noise\ (dB) = 20\log(N) + 3\ dB\ above\ the\ external\ reference\ phase\ noise$, where $N = multiple\ of\ reference$.
6. Other input voltages are available.
7. Actual or impending loss of lock.
8. Package must be verified by Spectrum Microwave.



PHASE LOCKED OSCILLATOR

MODEL MDR6100-06000 (6000 MHz)



Outline Drawing

