



# LABC7-6V Charger

## 6V Lead-Acid Battery Smart Charger

### INPUT SPECIFICATIONS

All specifications are typical at nominal input, full load.

### INPUT SPECIFICATIONS

Input Voltage	AC 100 – 264VAC
Input Frequency	50 – 60Hz
Protection	Reverse Polarity, short circuit
Battery Sizes	6V volt SLA, VRLA, Gel, AGM or flooded



### OUTPUT SPECIFICATIONS 6V /12V

Charge Voltage Limited	7.4V
Float Charge Voltage	6.8V
Charging Current	1.2 amp
Battery Types	All types 6V lead acid batteries

#### Charging Algorithm Auto 3 Stages

Constant Current	Stage 1 Constant current 1.2 amp
Constant Voltage	Stage 2 Constant voltage 7.4V
Floating	Stage 3 Float charge 6.8V

LED Indications	Pwr on, no battery connected –Green Charging – Red Charged - Flashing Green Charge/Float charging – Green Dim Reverse polarity – Red and Green flashing
-----------------	---

### GENERAL SPECIFICATIONS

MTBF(Calculated)	30,000 Calculated hours at 25°C by MIL-HDBK-217F
Hi pot, ESD	3,000V, 1 minute ESD 8000V

### FEATURES

- UNIVERSAL INPUT (AC100-240V)
- CONSTANT CURRENT/VOLTAGE,
- REVERSE POLARITY INDICATOR
- SHORT CIRCUIT PROTECTION
- 3 STAGE AUTO CHARGING

### ENVIRONMENTAL SPECIFICATIONS

Operating Temperature	-10°C~+40°C
Storage Temperature	-40°C ~ +70°C
Cooling.	Convection
Operating Humidity	20 – 80% Rh
Storage Humidity	10 – 90% Rh

### MECHANICAL SPECIFICATIONS

Case Dimension	L81 x W51 x H28(mm)
Input Configuration	Fixed cord 2 pin USA
Output Connector	5.5 x 2.1 x 11.0 mm C+
Weight	150 grams



# LABC7-6V Charger

## Mechanical Drawing:

