



PF1 thru PF7


Surface Mount Glass Passivated Fast Recovery Rectifier
Reverse Voltage 50~1000V Forward Current 1A

Features

- Glass passivated fast recovery rectifiers
- Heatsink structure
- Low profile, typical thickness 0.8mm
- Low forward voltage drop
- Low leakage current
- Moisture sensitivity: level 1, per J-STD-020
- Solder dip 260 °C, 10 s



RoHS
COMPLIANT



iSGA
(SOD-123HS)

Typical Applications

For use of general purpose rectification in lighting, cellular phone, portable device, power supplies, and other consumer applications.

Maximum Ratings (TA = 25 °C unless otherwise noted)									
Parameter	Symbol	PF1	PF2	PF3	PF4	PF5	PF6	PF7	Unit
Maximum repetitive peak reverse voltage	VRRM	50	100	200	400	600	800	1000	V
Maximum RMS voltage	VRMS	35	70	140	280	420	560	700	V
Maximum DC blocking voltage	VDC	50	100	200	400	600	800	1000	V
Maximum average forward rectified current	IF(AV)	1.0							A
Peak forward surge current 8.3 ms single half sine-wave superimposed on rated load	IFSM	30							A
Rating for fusing(t<8.3ms)	I ² t	3.8							A ² sec
Operating junction and storage temperature range	TJ, TSTG	- 55 to + 150							°C

Electrical Characteristics (TA = 25 °C unless otherwise noted)										
Parameter	Test Conditions	Symbol	PF1	PF2	PF3	PF4	PF5	PF6	PF7	Unit
Minimum Breakdown voltage	Ta=25°C, IR=100uA	V _{BR}	400			600	1000			V
Maximum instantaneous forward voltage	IF=1 A, Ta=25°C	V _F	1.3							
	IF=1 A, Ta=125°C		0.98							
Maximum DC reverse current at rated DC blocking voltage	TA=25°C	I _R	5.0							µA
	TA=125°C		50							
Maximum reverse recovery time	IF=0.5A, IR=1.0A, I _{rr} =0.25A	t _{rr}	150			250			nS	
Typical junction capacitance	4.0 V, 1 MHz	C _J	7.5							pF
Typical thermal resistance	junction to ambient	R _{θJA} ¹⁾	63							°C/W
	junction to lead	R _{θJL} ¹⁾	9							
	junction to case	R _{θJC} ²⁾	39							

Note: 1), The thermal resistance from junction to ambient or lead, mounted on P.C.B with 5x5mm copper pads, 2 OZ, FR4 PCB

2), The thermal resistance from junction to case, mounted on P.C.B with recommended copper pads, 2 OZ, FR4 PCB



Ratings and Characteristics Curves

(TA = 25°C unless otherwise noted)




Figure 1. Forward Current Derating Curve




Figure 2. Maximum Non-Repetitive Peak Forward Surge Current




Figure 3. Typical Reverse Characteristics




Figure 4. Typical Instantaneous Forward Characteristics






Figure 5. Typical Junction Capacitance

Package Outline Dimensions



Package	iSGA	
Unit:mm	MIN	MAX
A	0.75	0.90
B	0.85	1.05
B1	0.85	1.05
C	0.1	0.25
D	1.9	2.1
E	2.9	3.1
L1	2.0	2.45
L2	0.4	0.85
L3	1.3	1.7
HE	3.5	3.9

Soldering footprint




Packing Information

Packing quantities:

Reel size	Quantity/reel	Quantity/inner Box	Quantity/Carton
7"	3K	30K	120K

Packing Tape Specification





PF1 thru PF7

Surface Mount Glass Passivated Fast Recovery Rectifier
Reverse Voltage 50~1000V Forward Current 1A

Disclaimers

These materials are intended as a reference to assist our customers in the selection of the Suzhou Good-Ark product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Suzhou Good-Ark Electronics Co., Ltd. or a third party.

Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.

All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Suzhou Good-Ark Electronics Co., Ltd. without notice due to product improvements or other reasons. It is therefore recommended that customers contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized Suzhou Good-Ark Electronics Co., Ltd. for the latest product information before purchasing a product listed herein. The information described here may contain technical inaccuracies or typographical errors. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors. Please also pay attention to information published by Suzhou Good-Ark Electronics Co., Ltd. by various means, including our website home page.
(<http://www.goodark.com>)

When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, Please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.

The prior written approval of Suzhou Good-Ark Electronics Co., Ltd. is necessary to reprint or reproduce in whole or in part these materials.

Please contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized distributor for further details on these materials or the products contained herein.