4-Channel High-Performance Differential Switch

Check for Samples: HD3SS3412

FEATURES

- **Compatible with Multiple Interface Standards Operating up to 12Gbps Including PCI Express Gen III and USB 3.0**
- **Wide –3dB Differential BW of over 8GHz**
- **Excellent Dynamic Characteristics (at 4GHz)**
  - **Crosstalk = –35dB**
  - **Off Isolation = –19dB**
  - **Insertion Loss = –1.5dB**
  - **Return Loss = –11dB**
- **VDD Operating Range 3.3 V ±10%**
- **Small 3.5 mm x 9.0 mm, 42-Pin TQFN Package**
- **Common Industry Standard Pinout**

APPLICATIONS

- **Desktop and Notebook PCs**
- **Server/Storage Area Networks**
- **PCI Express Backplanes**
- **Shared I/O Ports**




Figure 1. HD3SS3412 Pinout & Switch Flow Through Routing

DESCRIPTION

The HD3SS3412 is a high-speed passive switch capable of switching four differential channels, including applications such as two full PCI Express x1 lanes from one source to one of two target locations in a PC/server application. With its bidirectional capability the HD3SS3412 will also support applications that allow connections between one target and two source devices, such as a shared peripheral between two platforms. The HD3SS3412 has a single control line (SEL Pin) which can be used to control the signal path between Port A and either Port B or Port C.

The HD3SS3412 is offered in an industry standard 42-pin QFN package available in a common footprint shared by several other vendors. The device is specified to operate from a single supply voltage of 3.3V over the full industrial temperature range of –40°C to 85ºC

The HD3SS3412 is a generic 4-CH high speed mux/demux type of switch that can be used for routing high-speed signals between two different locations on a circuit board. Although it was designed specifically to address PCI Express Gen III applications, the HD3SS3412 will also support several other high-speed data protocols with a differential amplitude of <1800mVpp and a common mode voltage of <2.0V, as with USB 3.0 and DisplayPort 1.2. The device's one select input (SEL) pin can easily be controlled by an available GPIO pin within a system or from a micro-controller.

Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

PRODUCTION DATA information is current as of publication date. Products conform to specifications per the terms of the Texas Instruments standard warranty. Production processing does not necessarily include testing of all parameters.

Copyright © 2012–2012 , Texas Instruments Incorporated

ORDERING INFORMATION(1)


PART NUMBER	PART MARKING	PACKAGE
HD3SS3412RUAR	HD3SS3412	42-pin RUA Reel (Large)
HD3SS3412RUAT	HD3SS3412	42-pin RUA Reel (Small)

(1) For the most current package and ordering information, see the Package Option Addendum at the end of this document, or see the TI web site at www.ti.com

Table 1. HD3SS3412 Control Logic

CONTROL PIN (SEL)	PORT A TO PORT B CONNECTION STATUS	PORT A TO PORT C CONNECTION STATUS
L (Default State)	Connected	Disconnected
H	Disconnected	Connected

FUNCTIONAL DIAGRAM



PIN FUNCTIONS

PIN	PIN NAME	I/O	DESCRIPTION
SWITCH PORT A			
2 3	A0+ A0–	I/O	Port A, Channel 0, High Speed Positive Signal Port A, Channel 0, High Speed Negative Signal
6 7	A1+ A1–	I/O	Port A, Channel 1, High Speed Positive Signal Port A, Channel 1, High Speed Negative Signal

Copyright © 2012–2012 , Texas Instruments Incorporated

PIN FUNCTIONS (continued)

PIN	PIN NAME	I/O	DESCRIPTION
11 12	A2+ A2–	I/O	Port A, Channel 2, High Speed Positive Signal Port A, Channel 2, High Speed Negative Signal
15 16	A3+ A3–	I/O	Port A, Channel 3, High Speed Positive Signal Port A, Channel 3, High Speed Negative Signal
SWITCH PORT B			
38 37	B0+ B0–	I/O	Port B, Channel 0, High Speed Positive Signal lPort B, Channel 0, High Speed Negative Signal
36 35	B1+ B1–	I/O	Port B, Channel 1, High Speed Positive Signal Port B, Channel 1, High Speed Negative Signal
29 28	B2+ B2–	I/O	Port B, Channel 2, High Speed Positive Signal Port B, Channel 2, High Speed Negative Signal
27 26	B3+ B3–	I/O	Port B, Channel 3, High Speed Positive Signal Port B, Channel 3, High Speed Negative Signal
SWITCH PORT C			
34 33	C0+ C0–	I/O	Port C, Channel 0, High Speed Positive Signal Port C, Channel 0, High Speed Negative Signal
32 31	C1+ C1–	I/O	Port C, Channel 1, High Speed Positive Signal Port C, Channel 1, High Speed Negative Signal
25 24	C2+ C2–	I/O	Port C, Channel 2, High Speed Positive Signal Port C, Channel 2, High Speed Negative Signal
23 22	C3+ C3–	I/O	Port C, Channel 3, High Speed Positive Signal Port C, Channel 3, High Speed Negative Signal
CONTROL, SUPPLY, AND NO CONNECT			
9	SEL	I	Select between port B or port C. Internally tied to GND via 100kΩ resistor
5, 13, 20, 30, 40	VDD	Supply	Positive power supply voltage
1, 4, 10, 14, 17, 19, 21, 39, 41, Center Pad	GND	Supply	Negative power supply voltage
8, 18, 42	NC		Electrically not connected


Table 2. MUX Pin Connections(1)

PORT A CHANNEL	PORT B OR PORT C CHANNEL CONNECTED TO PORT A CHANNEL	
	SEL = L	SEL = H
A0+	B0+	C0+
A0–	B0–	C0–
A1+	B1+	C1+
A1–	B1–	C1–
A2+	B2+	C2+
A2–	B2–	C2–
A3+	B3+	C3+
A3–	B3–	C3–

(1) The HD3SS3412 can tolerate polarity inversions for all differential signals on Ports A, B and C. Care should be taken to ensure the same polarity is maintained on Port A vs. Port B/C.

Copyright © 2012–2012 , Texas Instruments Incorporated

TYPICAL APPLICATION



ABSOLUTE MAXIMUM RATINGS(1)(2)

Over operating free-air temperature range (unless otherwise noted)

		VALUE		UNIT
		MIN	MAX	
Supply voltage range (V_{DD})	Absolute minimum/maximum supply voltage range	–0.5	4	V
Voltage range	Differential I/O	–0.5	4	V
	Control pin (SEL)	–0.5	VDD+0.5	
Electrostatic discharge	Human body model(3)		±4,000	V
	Charged-device model(4)		±1,500	

(1) Stresses beyond those listed under *absolute maximum ratings* may cause permanent damage to the device. These are stress ratings only and functional operation of the device at these or any conditions beyond those indicated under *recommended operating conditions* is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.
(2) All voltage values, except differential voltages, are with respect to network ground terminal.
(3) Tested in accordance with JEDEC/ESDA JS-001-2011
(4) Tested in accordance with JEDEC JESD22 C101-E

THERMAL INFORMATION

THERMAL METRIC(1)		HD3SS3412	UNITS
		42-PIN TQFN (RUA)	
θ_{JA}	Junction-to-ambient thermal resistance	53.8	°C/W
θ_{JCtop}	Junction-to-case (top) thermal resistance	38.2	
θ_{JCbot}	Junction-to-case (bottom) thermal resistance	21.9	
θ_{JB}	Junction-to-board thermal resistance	27.4	
ψ_{JT}	Junction-to-top characterization parameter	5.6	
ψ_{JB}	Junction-to-board characterization parameter	27.3	
Device Power Dissipation (P_D)		15.5 (Typ) 21.6 (Max)	mW

(1) For more information about traditional and new thermal metrics, see the *IC Package Thermal Metrics* application report, SPRA953.

Copyright © 2012–2012 , Texas Instruments Incorporated

RECOMMENDED OPERATING CONDITIONS

Typical values for all parameters are at V_{DD} = 3.3V and T_A = 25°C. (Temperature limits are specified by design)

			MIN	TYP	MAX	UNIT
V_{DD}	Supply voltage		3.0	3.3	3.6	V
V_{IH}	Input high voltage (SEL Pin)		2.0		VDD	V
V_{IL}	Input low voltage (SEL Pin)		–0.1		0.8	V
V_{I/O_Diff}	Differential voltage (differential pins)	Switch I/O diff voltage	0		1.8	VPP
V_{I/O_CM}	Common voltage (differential pins)	Switch I/O common mode voltage	0		2.0	V
T_A	Operating free-air temperature	Ambient temperature	–40		85	°C

ELECTRICAL CHARACTERISTICS

over operating free-air temperature range (unless otherwise noted)

PARAMETER		CONDITIONS	MIN	TYP	MAX	UNITS
DEVICE PARAMETERS						
I_{IH}	Input High Voltage (SEL)	V_{DD} = 3.6 V; V_{IN} = VDD			95	µA
I_{IL}	Input Low Voltage (SEL)	V_{DD} = 3.6 V; V_{IN} = GND			1	µA
I_{LK}	Leakage Current (Differential I/O pins)	V_{DD} = 3.6 V; V_{IN} = 0 V; V_{OUT} = 2 V (I_{LK} On OPEN outputs) [Ports B and C]			130	µA
		V_{DD} = 3.6 V, V_{IN} = 2 V; V_{OUT} = 0 V (I_{LK} On OPEN outputs) [Port A]			4	
I_{DD}	Supply Current	V_{DD} = 3.6 V; SEL = V_{DD}/GND; Outputs Floating		4.7	6	mA
C_{ON}	Outputs ON Capacitance	V_{IN} = 0 V; Outputs Open; Switch ON		1.5		pF
C_{OFF}	Outputs OFF Capacitance	V_{IN} = 0 V; Outputs Open, Switch OFF		1		pF
R_{ON}	Output ON resistance	V_{DD} = 3.3 V; V_{CM} = 0.5 V to 1.5 V ; I_O = –8 mA		5	8	Ω
ΔR_{ON}	On resistance match between channels	V_{DD} = 3.3 V ; –0.35 V ≤ V_{IN} ≤ 1.2 V; I_O = –8 mA			2	Ω
	On resistance match between pairs of the same channel	V_{DD} = 3.3 V; –0.35 V ≤ V_{IN} ≤ 1.2 V; I_O = –8 mA			0.7	Ω
R_{FLAT_ON}	On resistance flatness ($R_{ON(MAX)}$ – $R_{ON(MAIN)}$)	V_{DD} = 3.3 V; –0.35 V ≤ V_{IN} ≤ 1.2 V			1.15	Ω
DEVICE PARAMETERS (Continued) R_{SC} and R_{LOAD} = 50Ω and C_L = 50 pF unless otherwise noted						
t_{PD}	Switch propagation delay	Rsc and R_{LOAD} = 50Ω			85	ps
	SEL-to-switch Ton	Rsc and R_{LOAD} = 50Ω		70	250	ns
	SEL-to-switch Toff			70	250	
T_{SKEW_Inter}	Inter-pair output skew (CH-CH)	Rsc and R_{LOAD} = 50Ω			20	ps
T_{SKEW_Intra}	Intra-pair output skew (bit-bit)				8	ps
R_L	Differential return loss (VCM = 0V) Also see typical plots section	f = 0.3 MHz		–28		dB
		f = 2500 MHz		–12		
		f = 4000 MHz		–11		
X_{TALK}	Differential Crosstalk(VCM = 0V) Also see typical plots section	f = 0.3 MHz		–90		dB
		f = 2500 MHz		–39		
		f = 4000 MHz		–35		
O_{IRR}	Differential Off-Isolation(VCM = 0V) Also see typical plots section	f = 0.3 MHz		–75		dB
		f = 2500 MHz		–22		
		f = 4000 MHz		–19		
I_L	Differential Insertion Loss (VCM = 0V) Also see typical plots section	f = 0.3 MHz		–0.5		dB
		f = 2500 MHz		–1.1		
		f = 4000 MHz		–1.5		
BW	Band Width	At –3 dB		8		GHz

Copyright © 2012–2012 , Texas Instruments Incorporated

TEST TIMING DIAGRAMS

Select to Switch Output On (T_{ON}) and Off (T_{OFF})






Figure 2. Switch On/Off Timing Diagram

Propagation Delay and Skew





$T_{SKEWInter}$ = Difference between t_{PD} for any two pairs of outputs

$T_{SKEWIntra}$ = Difference between t_{P1} and t_{P2} of same pair

Figure 3. Propagation Delay Timing Diagram and Test Setup

Copyright © 2012–2012 , Texas Instruments Incorporated

TYPICAL PERFORMANCE PLOTS




Figure 4. Differential Insertion Loss




Figure 5. Differential Return Loss




Figure 6. Differential Crosstalk




Figure 7. Differential Off Isolation

SOURCE EYE DIAGRAM




Figure 8. Source Eye Diagram Test Setup

TYPICAL PERFORMANCE PLOTS (continued)




Figure 9. 10Gbps Source Eye Diagram at A: V_{ID} = 800mVpp; 2^7-1 PRBS; V_{CM}=0V




Figure 10. Output Eye Diagram Test Setup

Copyright © 2012–2012 , Texas Instruments Incorporated

TYPICAL PERFORMANCE PLOTS (continued)






Figure 11. 10Gbps Output Eye Diagram at A: V_{ID} = 800mVpp; 2^7-1 PRBS; V_{CM}= 0V; V_{DD}= 3.3v; SEL= 0V

CROSS TALK MEASUREMENT SETUP



TYPICAL PERFORMANCE PLOTS (continued)

OFF ISOLATION MEASUREMENT SETUP



Copyright © 2012–2012 , Texas Instruments Incorporated

REVISION HISTORY

NOTE: Page numbers of current version may differ from previous versions.

Changes from Original (February 2012) to Revision A **Page**

- Changed Differential BW Feature bullet from "7.5GHZ" to "8GHz" 1
- Changed Dynamic Characteristics Feature sub-bullet from "Isolation" to "Off Isolation" 1
- Changed Dynamic Characteristics sub-bullet Return Loss from "-9dB" to "-11dB" 1
- Deleted Dynamic Characteristics sub-bullet "Max Intra-Pair (Bit-Bit) Skew" 1
- Changed ESD, Human body model, MAX voltage from "±2000" to "±4,000" in Absolute Maximum Ratings table 4
- Deleted ESD, Machine model spec from Absolute Maximum Ratings table 4
- Changed I_{LK} spec (Diff I/O pins) MAX value from "4 µA" to "130 µA" and added [Ports B and C] and [Port A] to Conditions statements. 5
- Changed t_{PD} spec MAX delay from "50" ps to "85" ps in Device Parameters table 5
- Changed SEL-to-switch T_{on} and T_{off} spec TYP values from "175" ns to "70" ns; in the Device Parameters table 5
- Changed T_{SKEW_Inter} and T_{SKEW_Intra} spec MAX values from "5 ps" and "4 ps" respectively, to "20 ps" and "8 ps" respectively, in Electrical Characteristics table. 5
- Changed R_L spec TYP value from "–25" and "–9" dB to "–28" and "–11" dB for f=0.3 MHz and f=4000 MHz, respectively, in Electrical Characteristics table. 5
- Changed O_{IRR} spec TYP value from "–70" to "–75" dB for f=0.3 MHz, in Electrical Characteristics table. 5
- Changed BW spec TYP value from "7.5" GHz to "8" GHz in Electrical Characteristics table. 5
- Changed graphic image for Figure 4. 7
- Changed graphic image for Figure 5 7

Copyright © 2012–2012 , Texas Instruments Incorporated

PACKAGING INFORMATION

Orderable Device	Status (1)	Package Type	Package Drawing	Pins	Package Qty	Eco Plan (2)	Lead/ Ball Finish	MSL Peak Temp (3)	Samples (Requires Login)
HD3SS3412RUAR	ACTIVE	WQFN	RUA	42	3000	Green (RoHS & no Sb/Br)	CU NIPDAUAG	Level-2-260C-1 YEAR	
HD3SS3412RUAT	ACTIVE	WQFN	RUA	42	250	Green (RoHS & no Sb/Br)	CU NIPDAUAG	Level-2-260C-1 YEAR	

(1) The marketing status values are defined as follows:
ACTIVE: Product device recommended for new designs.
LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.
NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.
PREVIEW: Device has been announced but is not in production. Samples may or may not be available.
OBSOLETE: TI has discontinued the production of the device.

(2) Eco Plan - The planned eco-friendly classification: Pb-Free (RoHS), Pb-Free (RoHS Exempt), or Green (RoHS & no Sb/Br) - please check http://www.ti.com/productcontent for the latest availability information and additional product content details.
TBD: The Pb-Free/Green conversion plan has not been defined.
Pb-Free (RoHS): TI's terms "Lead-Free" or "Pb-Free" mean semiconductor products that are compatible with the current RoHS requirements for all 6 substances, including the requirement that lead not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, TI Pb-Free products are suitable for use in specified lead-free processes.
Pb-Free (RoHS Exempt): This component has a RoHS exemption for either 1) lead-based flip-chip solder bumps used between the die and package, or 2) lead-based die adhesive used between the die and leadframe. The component is otherwise considered Pb-Free (RoHS compatible) as defined above.
Green (RoHS & no Sb/Br): TI defines "Green" to mean Pb-Free (RoHS compatible), and free of Bromine (Br) and Antimony (Sb) based flame retardants (Br or Sb do not exceed 0.1% by weight in homogeneous material)


(3) MSL, Peak Temp. -- The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.


In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

TAPE AND REEL INFORMATION

REEL DIMENSIONS



TAPE DIMENSIONS




A0	Dimension designed to accommodate the component width
B0	Dimension designed to accommodate the component length
K0	Dimension designed to accommodate the component thickness
W	Overall width of the carrier tape
P1	Pitch between successive cavity centers

TAPE AND REEL INFORMATION

*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
HD3SS3412RUAR	WQFN	RUA	42	3000	330.0	16.4	3.8	9.3	1.0	8.0	16.0	Q1
HD3SS3412RUAT	WQFN	RUA	42	250	180.0	16.4	3.8	9.3	1.0	8.0	16.0	Q1


TAPE AND REEL BOX DIMENSIONS



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
HD3SS3412RUAR	WQFN	RUA	42	3000	346.0	346.0	33.0
HD3SS3412RUAT	WQFN	RUA	42	250	210.0	185.0	35.0

RUA (R–PWQFN–N42) PLASTIC QUAD FLATPACK NO–LEAD



NOTES:
A. All linear dimensions are in millimeters. Dimensioning and tolerancing per ASME Y14.5M–1994.
B. This drawing is subject to change without notice.
C. QFN (Quad Flatpack No–Lead) package configuration.
D. The package thermal pad must be soldered to the board for thermal and mechanical performance.
E. See the additional figure in the Product Data Sheet for details regarding the exposed thermal pad features and dimensions.


RUA (R–PWQFN–N42) PLASTIC QUAD FLATPACK NO–LEAD

THERMAL INFORMATION

This package incorporates an exposed thermal pad that is designed to be attached directly to an external heatsink. The thermal pad must be soldered directly to the printed circuit board (PCB). After soldering, the PCB can be used as a heatsink. In addition, through the use of thermal vias, the thermal pad can be attached directly to the appropriate copper plane shown in the electrical schematic for the device, or alternatively, can be attached to a special heatsink structure designed into the PCB. This design optimizes the heat transfer from the integrated circuit (IC).

For information on the Quad Flatpack No–Lead (QFN) package and its advantages, refer to Application Report, QFN/SON PCB Attachment, Texas Instruments Literature No. SLUA271. This document is available at www.ti.com.

The exposed thermal pad dimensions for this package are shown in the following illustration.




Bottom View

Exposed Thermal Pad Dimensions

4208352/D 06/11

NOTE: All linear dimensions are in millimeters

RUA (R–PWQFN–N42) PLASTIC QUAD FLATPACK NO–LEAD



NOTES:
A. All linear dimensions are in millimeters.
B. This drawing is subject to change without notice.
C. Publication IPC–7351 is recommended for alternate designs.
D. This package is designed to be soldered to a thermal pad on the board. Refer to Application Note, Quad Flat–Pack Packages, Texas Instruments Literature No. SLUA271, and also the Product Data Sheets for specific thermal information, via requirements, and recommended board layout. These documents are available at www.ti.com <http://www.ti.com>.
E. Laser cutting apertures with trapezoidal walls and also rounding corners will offer better paste release. Customers should contact their board assembly site for stencil design recommendations. Refer to IPC 7525 for stencil design considerations.
F. Customers should contact their board fabrication site for recommended solder mask tolerances and via tenting recommendations for vias placed in the thermal pad.

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products		**Applications**	
Audio	www.ti.com/audio	Automotive and Transportation	www.ti.com/automotive
Amplifiers	amplifier.ti.com	Communications and Telecom	www.ti.com/communications
Data Converters	dataconverter.ti.com	Computers and Peripherals	www.ti.com/computers
DLP® Products	www.dlp.com	Consumer Electronics	www.ti.com/consumer-apps
DSP	dsp.ti.com	Energy and Lighting	www.ti.com/energy
Clocks and Timers	www.ti.com/clocks	Industrial	www.ti.com/industrial
Interface	interface.ti.com	Medical	www.ti.com/medical
Logic	logic.ti.com	Security	www.ti.com/security
Power Mgmt	power.ti.com	Space, Avionics and Defense	www.ti.com/space-avionics-defense
Microcontrollers	microcontroller.ti.com	Video and Imaging	www.ti.com/video
RFID	www.ti-rfid.com		
OMAP Mobile Processors	www.ti.com/omap		
Wireless Connectivity	www.ti.com/wirelessconnectivity		
	TI E2E Community Home Page		e2e.ti.com

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2012, Texas Instruments Incorporated