

SANYO

No.3129

2SB1323/2SD1997

PNP/NPN Epitaxial Planar Silicon Transistors

Compact Motor Driver Applications

Features

- Contains input resistance(R_1), base-to-emitter resistance(R_{BE}).
- Contains diode between collector and emitter.
- Low saturation voltage
- Large current capacity
- Small-sized package making it easy to provide high-density, small-sized hybrid ICs

(): 2SB1323


Absolute Maximum Ratings at $T_a = 25^\circ\text{C}$

			unit
Collector to Base Voltage	V_{CBO}	(-)40	V
Collector to Emitter Voltage	V_{CEO}	(-)30	V
Emitter to Base Voltage	V_{EBO}	(-)6	V
Collector Current	I_C	(-)3	A
Collector Current(Pulse)	I_{CP}	(-)5	A
Collector Dissipation	P_C (Mounted on ceramic board $250\text{mm}^2 \times 0.8\text{mm}$)	1.5	W
Junction Temperature	T_j	150	$^\circ\text{C}$
Storage Temperature	T_{stg}	-55 to +150	$^\circ\text{C}$


Electrical Characteristics at $T_a = 25^\circ\text{C}$

			min	typ	max	unit
Collector Cutoff Current	I_{CBO}	$V_{CB} = (-)30\text{V}, I_E = 0$			(-)1.0	μA
DC Current Gain	$h_{FE}(1)$	$V_{CE} = (-)2\text{V}, I_C = (-)0.5\text{A}$	70			
	$h_{FE}(2)$	$V_{CE} = (-)2\text{V}, I_C = (-)2\text{A}$	50			
Gain-Bandwidth Product	f_T	$V_{CE} = (-)2\text{V}, I_C = (-)0.5\text{A}$		100		MHz
Output Capacitance	c_{ob}	$V_{CB} = (-)10\text{V}, f = 1\text{MHz}$		(55)40		pF
C-E Saturation Voltage	$V_{CE(sat)}$	$I_C = (-)1\text{A}, I_B = (-)50\text{mA}$		0.12	0.3	V
				(-0.18)	(-0.4)	
B-E ON-State Voltage	$V_{BE(ON)}$	$V_{CE} = (-)2\text{V}, I_C = (-)1\text{A}$	(-)1	(-)2	(-)5	V
C-B Breakdown Voltage	$V_{(BR)CBO}$	$I_C = (-)10\mu\text{A}, I_E = 0$	(-)40			V
C-E Breakdown Voltage	$V_{(BR)CEO(1)}$	$I_C = (-)10\mu\text{A}, R_{BE} = \infty$	(-)40			V
	$V_{(BR)CEO(2)}$	$I_C = (-)10\text{mA}, R_{BE} = \infty$	(-)30			V
Diode Forward Voltage	V_F	$I_F = 0.5\text{A}$			1.5	V
Base to Emitter Resistance	R_{BE}			0.8		$\text{k}\Omega$
Base Resistance	R_1		120	160	200	Ω

Marking 2SB1323: BK
2SD1997: DO

Electrical Connection**Package Dimensions 2038**

(unit: mm)












E: Emitter
C: Collector
B: Base

SANYO: PCP

(Bottom View)

SANYO Electric Co., Ltd. Semiconductor Business Headquarters
TOKYO OFFICE Tokyo Bldg., 1-10, 1 Chome, Ueno, Taito-ku, TOKYO, 110 JAPAN





- No products described or contained herein are intended for use in surgical implants, life-support systems, aerospace equipment, nuclear power control systems, vehicles, disaster/crime-prevention equipment and the like, the failure of which may directly or indirectly cause injury, death or property loss.
- Anyone purchasing any products described or contained herein for an above-mentioned use shall:
 - ① Accept full responsibility and indemnify and defend SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors and all their officers and employees, jointly and severally, against any and all claims and litigation and all damages, cost and expenses associated with such use;
 - ② Not impose any responsibility for any fault or negligence which may be cited in any such claim or litigation on SANYO ELECTRIC CO., LTD., its affiliates, subsidiaries and distributors or any of their officers and employees jointly or severally.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.