

17 dBm Controlled EDFA for Metro and Long Haul Applications

OA 3500 Amplifier Series



Key Features



- Variable gain, 5 to 23 dB
- Fast transient suppression
- Variable optical attenuator (VOA)
- Constant gain, power, and current modes
- Alarms
- Platform flexibility

Applications

- C band
- Dense wavelength division multiplexing (DWDM) networks
- Metro, long haul, or ultra long haul networks
- Pre-amplifier, inline, or booster amplification

JDSU's Agile Optical Amplifiers respond dynamically to accommodate changes in number of wavelengths or signal powers using advanced transient suppression techniques. As a result, they preserve gain, flatness and output power over a wide range of input conditions to meet the needs of reconfigurable optical networks.

The JDSU OA 3500 Series is a controlled optical amplifier that features variable gain and transient suppression. The maximum optical output of 17 dBm and variable gain range of 5 to 23 dB make the module suitable for pre-amplifier, inline, and booster applications.

The transient suppression feature of the module minimizes transmission penalties as channels are added and dropped in the network, or as input power varies. The control interface is a Transistor-Transistor Logic (TTL) level RS232 driven by a 5 V power supply.

JDSU has extensive experience with the development of fully functioning erbium doped fiber amplifiers (EDFAs), and can design standard, high-performance optical amplifier products that meet your technical performance, cost target, and time-to-market requirements.

2

Specifications**Parameter** **OAC-17F3500Cx**

Signal wavelength	1530 to 1563 nm
Total input signal power (full channel load)	-28 to 12 dBm
Total output signal power	17 dBm
Signal gain (design point)	5 to 23 dB
Flatness	1.0 dB
Noise figure	6.0 dB
Gain transient suppression time	See table below
Gain transient overshoot/undershoot	See table below
Power supply requirements	5 V
Dimensions (W x H x D)	130 x 212 x 14.75 mm
Operating temperature	-5 to 70 °C



Gain Transient

Transient Event	Maximum Excursion (Overshoot/Undershoot)	Settling Time (Typical)	Settling Time (Maximum)
3 dB add/drop	0.8 dB	150	300
9 dB add/drop	1.5 dB	200	400
15 dB add/drop	2.0 dB	300	500

Ordering Information

For more information on this or other products and their availability, please contact your local JDSU account manager or JDSU directly at 1-800-498-JDSU (5378) in North America and +800-5378-JDSU worldwide or via e-mail at customer.service@jdsu.com.

Sample: OAC-17F3500CA

OAC- 	F 03500C 																					
<table style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: left; border-right: 1px solid black;">Code</th> <th>Power Out¹</th> </tr> </thead> <tbody> <tr> <td style="border-right: 1px solid black;">17</td> <td>17 dBm</td> </tr> </tbody> </table>	Code	Power Out ¹	17	17 dBm	<table style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: left; border-right: 1px solid black;">Code</th> <th>Gain Flatness</th> </tr> </thead> <tbody> <tr> <td style="border-right: 1px solid black;">F</td> <td>Flattened</td> </tr> </tbody> </table>	Code	Gain Flatness	F	Flattened	<table style="width: 100%; border-collapse: collapse;"> <thead> <tr> <th style="text-align: left; border-right: 1px solid black;">Code</th> <th>Connector Type²</th> </tr> </thead> <tbody> <tr> <td style="border-right: 1px solid black;">3</td> <td>FC/APC</td> </tr> <tr> <td style="border-right: 1px solid black;">5</td> <td>SC/APC</td> </tr> <tr> <td style="border-right: 1px solid black;">9</td> <td>FC/UPC</td> </tr> <tr> <td style="border-right: 1px solid black;">A</td> <td>SC/UPC (default)</td> </tr> <tr> <td style="border-right: 1px solid black;">C</td> <td>MU</td> </tr> </tbody> </table>	Code	Connector Type ²	3	FC/APC	5	SC/APC	9	FC/UPC	A	SC/UPC (default)	C	MU
Code	Power Out ¹																					
17	17 dBm																					
Code	Gain Flatness																					
F	Flattened																					
Code	Connector Type ²																					
3	FC/APC																					
5	SC/APC																					
9	FC/UPC																					
A	SC/UPC (default)																					
C	MU																					

1. Other output power options available upon request.
2. More connector options available upon request.

User Safety

The invisible laser light emitted from this module is harmful to the human eye. Proper laser safety eyewear must be worn during operation.

ESD Protection

The laser diodes and photodiodes contained in this module are very reliable under normal operating conditions. However, they are easily destroyed by inadvertent electrostatic discharge (ESD). Take extreme precaution to prevent ESD. Use wrist straps, grounded work surfaces, and antistatic techniques when operating this module. When not in use, the fiber amplifier must be kept in a static-free environment with the shorting plug covering the connector.

All statements, technical information and recommendations related to the products herein are based upon information believed to be reliable or accurate. However, the accuracy or completeness thereof is not guaranteed, and no responsibility is assumed for any inaccuracies. The user assumes all risks and liability whatsoever in connection with the use of a product or its application. JDSU reserves the right to change at any time without notice the design, specifications, function, fit or form of its products described herein, including withdrawal at any time of a product offered for sale herein. JDSU makes no representations that the products herein are free from any intellectual property claims of others. Please contact JDSU for more information. JDSU and the JDSU logo are trademarks of JDS Uniphase Corporation. Other trademarks are the property of their respective holders. ©2006 JDS Uniphase Corporation. All rights reserved. 10143101 Rev.003 10/06 OA3500.DS.CMS.AE