
features

- Low Dropout Voltage Regulator, 1.2-V
- 150-mA Load Current Capability
- Power Okay (POK) Function
- Load Independent, Low Ground Current,150-μA
- Current Limiting
- Thermal Shutdown
- Low Sleep State Current (Off Mode)
- Fast Transient Response
- Low Variation Due to Load and Line Regulation
- Output Stable With Low ESR Capacitors
- TTL Logic Controlled Enable Input

DBV PACKAGE
(TOP VIEW)



applications

- Processor Powerup Sequencing
- Palmtop Computers, Laptops, and Notebooks

description

The TPPM0125 is a low dropout voltage regulator with an output tolerance of ±2% over the operating range. The device is optimized for low noise applications and has a low quiescent current (enable <0.8 V). The device has a low dropout voltage at full load (150 mA). The power okay function monitors the output voltage and indicates when an error occurs in the system (active low). In the event of an output fault such as overcurrent, thermal shutdown, or dropout, the power okay output is pulled low (open drain).

The TPPM0125 has a fast transient response recovery capability in the event of load transition from heavy load to light load. The device also minimizes overshoot during this condition. During power down, the output capacitor and load are de-energized through the internal active shutdown clamp, which is turned on when the device is disabled.


The TPPM0125 requires a small output capacitor for stability with low ESR. An input capacitor is not required unless the bulk ac capacitor is placed away from the device or the power supply is a battery. In this situation, a 1-μF capacitor is recommended for the application. Low ESR ceramic capacitors may be used with the device to reduce board space in power applications, a key concern in hand-held wireless devices.

Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

PRODUCTION DATA information is current as of publication date. Products conform to specifications per the terms of Texas Instruments standard warranty. Production processing does not necessarily include testing of all parameters.

Copyright © 2001, Texas Instruments Incorporated

functional block diagram



Terminal Functions

TERMINAL NAME	TERMINAL NO.	I/O	DESCRIPTION
EN	3	I	Enable/shutdown input (active high)
GND	2	I	Ground
POK	4	I	Power okay indicator
V_I	1	I	Input supply voltage
V_O	5	O	Output voltage

absolute maximum ratings over operating free-air temperature (unless otherwise noted)†

Main input voltage range, V_I (see Notes 1 and 2) . . . . . 0 V to 7 V
Enable input voltage range, $V_{(EN)}$ (see Notes 1 and 2) . . . . . 0 V − V_I
Power okay output voltage range $V_{(POK)}$, (see Notes 1 and 2) . . . . . 0 V − V_I
Regulated output current limit, I_O . . . . . 400 mA
Continuous power dissipation, P_D, T_A = 25°C . . . . . 0.5 W
Electrostatic discharge susceptibility, $V_{(HBMESD)}$, (see Note 3) . . . . . 2 kV
Junction temperature, T_J, ... 150°C
Storage temperature range, T_{stg} . . . . . −55°C to 150°C
Lead temperature (soldering, 10 sec) . . . . . 260°C

† Stresses beyond those listed under “absolute maximum ratings” may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under “recommended operating conditions” is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

NOTES: 1. All voltage values are with respect to GND.
2. Absolute negative voltage on these terminals should not go below –0.5 V.
3. The human body model is a 100-pF capacitor discharged through a 1.5-kΩ resistor into each terminal. Devices are ESD sensitive. Handling precautions are recommended.

recommended operating conditions

	MIN	TYP	MAX	UNIT
Main input voltage, V_I (see Notes 1 and 2)	3		5.25	V
Enable input voltage, $V_{(EN)}$ (see Notes 1 and 2)	0		V_I	V
Power okay voltage, $V_{(POK)}$ (see Notes 1 and 2)	0		V_I	V
Operating ambient temperature, T_A	0		70	°C

NOTES: 1. All voltage values are with respect to GND.
2. Absolute negative voltage on these terminals should not go below –0.5 V.

electrical characteristics, T_A = 25°C, V_I = 5 V, $V_{(EN)} = V_I$, I_O = 100 μA, C_L = 1 μF (unless otherwise noted)

regulator V_O

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNITS
V_O	Output voltage	I_O = 25 mA		1.2		V
	Output voltage accuracy	I_O = 0	−1%		1%	
		I_O = 50 mA, T_A = 0°C to 70°C (see Note 4)	−2%		2%	
I_Q	Quiescent supply current	$V_{(EN)} \le 0.8$ V		1		μA
$I_{(GND)}$	Ground terminal current (see Note 5)	I_O = 0		150		μA
		I_O = 150 mA		150		
I_L	Output load current		150			mA
$I_{(Limit)}$	Output current limit	V_O = 0	160	300		mA
$\Delta V_{(LNR)}$	Line regulation	V_I = 3 V to 5.25 V		10		mV
$\Delta V_{(LDR)}$	Load regulation	I_O = 0.1 mA to150 mA, See Note 6		2%	3%	
$V_I - V_O$	Dropout voltage	I_O = 100 μA		1		V
		I_O = 150 mA		1		
C_L	Load capacitance	ESR and capacitance tradeoffs		1		μF
$I_{(REV)}$	Reverse output current on V_I	V_I = GND, V_O = regulated voltage			50	μA

NOTES: 4. Assured by design, not tested in production.
5. Ground terminal current is the regulator quiescent current drawn from the supply to support the load current.
6. Regulation is measured at constant junction temperature using low duty cycle pulse testing. Devices are tested for load regulation in the load range from 0.1 mA to 150 mA.

enable input

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNITS
V_{IL}	Regulated shutdown	V_I = 3 V to 5.25 V regulated shutdown			0.8	V
V_{IH}	Regulated enabled	V_I = 3 V to 5.25 V regulated enabled	2			V
$I_{(EN)}$	Enable input current	Shutdown, $V_{IL} \le 0.8$ V		0.01		μA
		Enabled, $V_{IH} \ge 2$ V		0.01		
	Resistance discharge	$V_{(EN)} \le 0.8$ V		500		Ω

thermal protection (see Note 4)

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNITS
$T_{(SD)}$	Thermal shutdown			165		°C
$T_{(SDHYS)}$	Hysteresis			15		°C

NOTE 4: Assured by design, not tested in production.

power okay (see Note 7)

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNITS
$V_{(POKLO)}$	Low threshold	Output falls % of V_O (power NOT okay)	85%			
$V_{(POKTH)}$	High threshold	Output reaches % of V_O, starts delay timer (power okay)			90%	
V_{OL}	V_O out of regulation	Fault condition, I_{OL} = 100 μA			0.4	V
I_{lkg}	Leakage current	V_I = 5 V			1	μA

NOTE 7: Power okay is a function of the output voltage being 5% lower than the specified range. The function is a detection of one of the following: over current, over temperature, or dropout.

switching characteristics (see Note 4),T_A = 25°C, V_I = 5 V, $V_{(EN)}$ = V_I, I_O = 100 μA, C_L = 1 μF(unless otherwise noted)

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
	Power up overshoot	Maximum voltage overshoot allowed on output during powerup		1%		
$t_{(STEP)}$	Output transient time limit	Time for output to return within specified regulation range		5		μs
	Output transient voltage limit	Voltage that load step can affect the nominal output voltage		1%		
$I_{(SR)}$	Load step current slew rate	I_L = 0.1 mA to 150 mA		10		mA/μs
t_r	Power up rise time			50		μs
t_f	Power down fall time	Discharge resistance = 500 Ω, V_O < 1.08 V		60		μs
$t_{d(POK)}$	Power okay delay time	V_I > $V_{(POKTH)}$ until POK↑		2.5		ms

NOTE 4: Assured by design, not tested in production.

thermal resistance

PARAMETER		TEST CONDITIONS	MIN	TYP	MAX	UNIT
$R_{\theta JC}$	Thermal impedance, junction-to-case			145		°C/W
$R_{\theta JA}$	Thermal impedance, junction-to-ambient			235		°C/W

PARAMETER MEASUREMENT INFORMATION




Figure 1. Power Okay Timing During Power Up




Figure 2. Power Okay Delay Timing and Output Voltage Supervisory

TYPICAL CHARACTERISTICS




Figure 3. Load Regulation, 50-mA Dynamic Load Step (V_I = 3 V)




Figure 4. Load Regulation, 150-mA Dynamic Load Step (V_I = 3 V)

TYPICAL CHARACTERISTICS




Figure 5. Load Regulation, 50-mA Dynamic Load Step (V_I = 5 V)




Figure 6. Load Regulation, 150-mA Dynamic Load Step (V_I = 5 V)

TYPICAL CHARACTERISTICS




Figure 7. Power Okay Delay During Power Up Condition




Figure 8. Power Okay Delay During Power Down Condition

THERMAL INFORMATION

The TPPM0125 is designed to provide a continuous load current of 150 mA when the maximum power dissipation of the package is not exceeded in the application. To determine the maximum power dissipation of the package, use the junction-to-ambient thermal resistance of the device. The basic equation is as follows:

Maximum power dissipation (W)

$$P_{D(MAX)} = (T_{J(MAX)} - T_A) / R_{\theta JA} \text{ (maximum power dissipation limit)}$$

Where:

$T_{J(MAX)}$ is the maximum junction temperature of the die (less than 150°C, minimum thermal shutdown)
T_A is the operating ambient temperature
$R_{\theta JA}$ is the thermal resistance and is layout dependent

The recommended minimum footprint offers a $R_{\theta JA}$ of 235°C/W.
To determine the actual power dissipation of the regulator, use the following equation:

$$P_D = (V_I - V_O) I_O + V_I I_{(GND)} \text{ (Watts)}$$

Power dissipation resulting from quiescent current is negligible. When the power dissipation is excessive, the thermal protection circuit is triggered.

APPLICATION INFORMATION




Figure 9. Typical Application Schematic





Figure 10. Typical Application For Processor VID Code Power Sequencing Schematic

MECHANICAL DATA

DBV (R-PDSO-G5) **PLASTIC SMALL-OUTLINE**



NOTES: A. All linear dimensions are in millimeters.
B. This drawing is subject to change without notice.
C. Body dimensions do not include mold flash or protrusion.
D. Falls within JEDEC MO-178

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

Products		**Applications**	
Amplifiers	amplifier.ti.com	Audio	www.ti.com/audio
Data Converters	dataconverter.ti.com	Automotive	www.ti.com/automotive
DSP	dsp.ti.com	Broadband	www.ti.com/broadband
Clocks and Timers	www.ti.com/clocks	Digital Control	www.ti.com/digitalcontrol
Interface	interface.ti.com	Medical	www.ti.com/medical
Logic	logic.ti.com	Military	www.ti.com/military
Power Mgmt	power.ti.com	Optical Networking	www.ti.com/opticalnetwork
Microcontrollers	microcontroller.ti.com	Security	www.ti.com/security
RFID	www.ti-rfid.com	Telephony	www.ti.com/telephony
RF/IF and ZigBee® Solutions	www.ti.com/lprf	Video & Imaging	www.ti.com/video
		Wireless	www.ti.com/wireless

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2008, Texas Instruments Incorporated