

Audio Transformer

## **Data/Voice** Coupling

# TY-307P

#### **Description:**

The TY series transformers are used for a variety of applications including impedance matching, isolation, repeat coil, line balancing, bridging and hybrid circuits.

### Electrical Specifications at 25° C:

Impedance		Max. DC	Тур.	Тур.	Typ. Freq.
(Ohms)		Current	Insertion	Return	Response
Pri	Sec	(mA)	Loss (dB)	Loss (dB)	(dB)
600	600	0	1.0	26	±.5

#### Designed to meet FCC Part 68


Longitudinal Balance: (FCC 68.310) – 60 dB min. 200 – 1000 Hz 45 dB min. 1000 – 4000 Hz

Dielectric Strength: (FCC 68.304) - 1500VAC

Power Level: -45 dBm to +7 dBm

Frequency Range: Data/Voice = 300 to 3500 Hz Data = 800 to 3500 Hz


Schematic:





**RoHS Compliance:** As of manufacturing date February 2005, all standard products meet the requirements of 2011/65/EU, known as the RoHS initiative.

\*Upon printing, this document is considered "uncontrolled".Please contact TriadMagnetics website for the most current version.

web:www.TriadMagnetics.com	460 Harley Knox Blvd.	
Phone 951-277-0757	Perris, California 92571	Publish Date: December 4, 2013
Fax 951-277-2757		







.443 +/- .010