


T1/CEPT/ISDN-PRI TRANSFORMER S553-3855-02

TM0009


Bel introduces a new "pick and place" compatible, small footprint, surface mount impedance matching transformer for ISDN-PRI/T1/CEPT applications.

- * Pick and Place Compatible.
- * Small form factor to maximize board space.

MECHANICALS



SCHEMATIC



Dimensions in inches (mm)
Dimension tolerance +/- 0.01(0.25)
unless otherwise stated

ELECTRICALS @ 25° C

Part Number	Turns Ratio		Primary Inductance OCL (mH) Min	Leakage Inductance L _L (mH) Max		Interwinding Capacitance C _{ww} (pF) Max	DC Resistance DCR Pri (ohm) Max	DC Resistance DCR Sec (ohm) Max		Hipot (Vrms) Min
	Pins (16-14):(1-3)	Pins (6-8):(11-9)		Pins (16-14)*	Pins (6-8)**			Pins (1-3)	Pins (11-9)	
S553-3855-02	1:1.15CT	1CT:2CT	1.20	0.6	0.8	30	0.70	0.70	1.00	1500

* Leakage Inductance is measured with Pins (1-3) shorted.
** Leakage Inductance is measured with Pins (11-9) shorted.

Corporate Office
Bel Fuse Inc.
198 Van Vorst Street, Jersey City, NJ 07302-4496
Tel: 201-432-0463
Fax: 201-432-9542
E-Mail: BelFuse@belfuse.com
Internet: http://www.belfuse.com

Far East Office
Bel Fuse Ltd.
8F/8 Luk Hop Street
San Po Kong
Kowloon, Hong Kong
Tel: 852-2328-5515
Fax: 852-2352-3706

European Office
Bel Fuse Europe Ltd.
Preston Technology Management Centre
Marsh Lane, Preston PR1 8UD
Lancashire, U.K.
Tel: 44-1772-556601
Fax: 44-1772-888366