

# Double Balanced Mixer

# Model MO4xxG-9

Octave Band

RF 3.7 to 8.6 GHz

## Electrical Specifications:<sup>(1)</sup>

Parameter	Conditions			Specifications		
	RF (GHz)	LO (GHz)	IF (MHz)	Min	Typical	Max
SSB Conversion loss: <sup>(2) (3)</sup>	3.7-8.6	3.7-8.6	DC-500		5.5 dB	7.0 dB
	3.7-8.6	3.7-8.6	DC-1500		7.0 dB	8.5 dB
	3.7-8.6	3.7-8.6	DC-2000		8.5 dB	10.5 dB
Isolation LO to RF: LO to IF: RF to IF:		3.7-8.6		25 dB	38 dB	
	3.7-8.6	3.7-8.6		20 dB	30 dB	30 dB
Input 1 dB Compression Point:	3.7-8.6	3.7-8.6	DC-2000		+1 dBm +4 dBm +8 dBm +12 dBm	MO43 MO44 MO46 MO47
Input Third Order Intercept Point:	3.7-8.6	3.7-8.6	DC-2000		+11 dBm +14 dBm +18 dBm +21 dBm	MO43 MO44 MO46 MO47
LO Power: <sup>(4)</sup>	3.7-8.6	3.7-8.6	DC-2000		+7 dBm +10 dBm +14 dBm +19 dBm	MO43 MO44 MO46 MO47

## Model MO4xxG-9

### LO Power

3 = +7 dBm  
4 = +10 dBm  
6 = +14 dBm  
7 = +19 dBm

Drop-In Module or With SMA(F) Connectors  
M = Module  
P = With Connectors

### Notes:

- Specifications are guaranteed when tested as a downconverter in a 50 Ohm system from -55°C to +100°C with the nominal LO power. Specifications indicated as typical are not guaranteed.
- Noise figure is typically within ±0.5 dB of conversion loss for IF frequencies greater than 10 MHz.
- Conversion loss typically degrades less than 0.5 dB at +100°C and improves less than 0.5 dB at -55°C.
- Usable LO drives are up to 2 dB below and 3 dB above nominal.

