

TC9316F-001

DTS MICRO CONTROLLER (DTS-11)

The TC9316F-001 is a digital tuning system optimum for portable sets such as pocket radios, headphone stereo sets, etc... By combining TC9316F-001 with prescaler TD7101F or TD6134AF, 4-band of FM/MW/LW (TV)/SW are provided compatibly with worldwide destinations.

FEATURES

○ Receiving band

AREA	CODE		MW STEP	FM STEP	BAND	RECEIVING FREQUENCY [Hz]	STEP [Hz]	FREF [Hz]	IF [Hz]							
	E0	E1														
U.S.A.	0	0	—	—	TV	2~13ch	1ch	3.125k	10.7M							
				0 / 1	FM	(*1) 87.5~108.0M	100 / 200k	12.5k								
			0	—	MW	—	520~ 1710k	10k	5k	450k						
			1	—		—	522~ 1620k	9k	3k							
East Eur.	0	1	—	0 / 1	FM	65.0~ 74.0M 87.5~108.0M	50 / 100k	12.5k	10.7M							
				0	—	MW	—	522~ 1620k		9k	3k					
			1	—	—		520~ 1620k	10k	5k	450k						
			—	—	LW	—	144~ 281k	1 / 9k (*3)	1k							
General	1	0	—	0 / 1	FM	87.5~108.0M	50 / 100k	12.5k	10.7M							
				0	—	MW	—	522~ 1620k		9k	3k					
			1	—	—		520~ 1620k	10k	5k	450k						
			—	—	LW	—	144~ 281k	1 / 9k (*3)	1k							
China	1	1	—	0 / 1	FM	87.0~108.0M	50 / 100k	12.5k	10.7M							
				0	—	MW	—	522~ 1611k		9k	3k					
			1	—	—		531~ 1602k									
—	SW ₀	SW ₁	—	—	—	—	—	—	—							
SW	0	0	—	—	—	—	—	—	—							
										0	1	SW	3.8~ 12.5M	5k	5k	450k
										1	0		5.95~ 15.6M			
										1	1		2.3~ 6.2M			
1	1	7.1~21.85M														

- (*1) If step in 200kHz, receiving frequency range is 87.5~108.1MHz.
- (*2) It's able to combination with any area in SW band.
- (*3) There's only Auto tuning function with 9kHz step.

980910EBA2

● TOSHIBA is continually working to improve the quality and the reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to observe standards of safety, and to avoid situations in which a malfunction or failure of a TOSHIBA product could cause loss of human life, bodily injury or damage to property. In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent products specifications. Also, please keep in mind the precautions and conditions set forth in the TOSHIBA Semiconductor Reliability Handbook.

● The products described in this document are subject to the foreign exchange and foreign trade laws.

● The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA CORPORATION for any infringements of intellectual property or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any intellectual property or other rights of TOSHIBA CORPORATION or others.

● The information contained herein is subject to change without notice.

- Tuning function
 - Manual tuning
 - Auto-tuning
- Memory function

	Fixed	Random
FM / AM	10 / 10	15 stations
FM / AM / LW (TV)	10 / 10 / 5	15 stations
FM / AM / SW-A or B	10 / 5 / 5	15 stations
FM / AM / SW ₁ / SW ₂	5 / 5 / 5 / 5	10 stations
FM / AM / LW / SW-A or B	5 / 5 / 5 / 5	10 stations
- 12 / 24 Hour Clock indication.
- Sleep / Alarm / Snooze function.

