

# High-Speed PCI Interfaces for CompactRIO

## NI cRIO-9052, NI cRIO-9052CardBus, NI cRIO-9052PXI, NI cRIO-9052PCI **NEW!**

- Laptop, PXI, or PC control of any CompactRIO reconfigurable chassis
- High bandwidth for high-channel-count CompactRIO applications
- Up to 50 MB/s sustained throughput from any NI cRIO-910x chassis
- Up to 14 m cable length
- Dual 9 to 35 VDC supply inputs that deliver isolated power to CompactRIO chassis/modules
- -40 to 70 °C temperature range



## Overview and Applications

The National Instruments cRIO-9052 is a high-performance solution for remote control of any NI cRIO-910x reconfigurable chassis using a laptop, PXI system, or PC. With the NI cRIO-9052, you can interface with the FPGA inside of a CompactRIO reconfigurable chassis at rates up to 50 MB/s. The result is a reconfigurable solution ideal for applications requiring the flexibility of the FPGA within CompactRIO and high bandwidth for high-channel-count applications. The cRIO-9052 is designed for extreme ruggedness, reliability, and low power consumption with dual 9 to 35 VDC supply inputs that deliver isolated power to the CompactRIO chassis/modules and a -40 to 70 °C temperature range.



## System Configuration

The cRIO-9052, attached to a cRIO-910x reconfigurable chassis, communicates with an NI 8310 device (CardBus, PXI, or PCI) over two CAT-5 cables at distances up to 14 m. The cRIO-9052 and NI 8310 devices use a StarFabric interface to implement a PCI-to-PCI bridge, providing a transparent link where the CompactRIO reconfigurable chassis appears to users as if it were a PCI board within the host computer itself.

You can use built-in functions within NI LabVIEW and LabVIEW Real-Time software for interfacing directly with the FPGA in the CompactRIO chassis. This feature provides PXI and PC users the ability to build a deterministic, real-time application to communicate with the LabVIEW code running on the FPGA of a CompactRIO reconfigurable chassis. Once you have started an application using the CompactRIO chassis, you can disconnect your

laptop, PC, or PXI system from CompactRIO while the application continues to run. This functionality eliminates the need to dedicate the laptop, PC, or PXI system to the CompactRIO application only.



## Ordering Information

### CompactRIO Interface Module

NI cRIO-9052 .....779506-01

### Laptop Interface Kit

NI cRIO-9052CardBus .....779528-01  
*Includes one cRIO-9052, one CardBus card (CardBus-8310), and two 3 m cables.*

### PXI Interface Kit

NI cRIO-9052PXI .....779529-01  
*Includes one cRIO-9052, one PXI module (PXI-8310), and two 3 m cables.*

### PC Interface Kit

NI cRIO-9052PCI .....779530-01  
*Includes one cRIO-9052, one PCI board (PCI-8310), and two 3 m cables.*

### Cables

Ethernet Cable Kits (includes two cables)

3 m .....779544-03  
10 m .....779544-10  
14 m .....779544-14

## BUY NOW!

For complete product specifications, pricing, and accessory information, call (800) 813 3693 (U.S.) or go to [ni.com/dataacquisition](http://ni.com/dataacquisition).

# High-Speed PCI Interface for CompactRIO

## Specifications

### StarFabric Communication

Interface .....	4 LVDS transmit pairs, 4 LVDS receive pairs
Communication rates	
Theoretical maximum .....	133 MB/s
Typical <sup>1</sup> .....	50 MB/s

<sup>1</sup> This rate varies depending on your host system specifications, such as processor, RAM, and so on.

### Cabling requirements

Cables .....	2 shielded CAT5 Ethernet cables
Maximum difference between the lengths of the two cables....	2.54 cm (1 in.)
Maximum cabling length.....	14 m (45.93 ft)

### Power Requirements

You must use a National Electric Code (NEC) Class 2 power source with the cRIO-9052.

Recommended power supply.....	48 W secondary, 18 VDC to 24 VDC
-------------------------------	-------------------------------------

Power consumption	
cRIO-9052 only.....	1.5 W, max
cRIO-9052 supplying power to 8 CompactRIO modules .....	17 W, max <sup>1</sup>

### Power supply

On power up .....	9 to 35 V
After power up .....	6 to 35 V

<sup>1</sup> This is the maximum amount of power that the entire system should consume at the power connector.

**Note:** The cRIO-9052 powers up only at 9 V or higher, but after it is powered up, it can run on as little as 6 V.

### Physical Characteristics

If you need to clean the device, wipe it with a dry towel.

Screw-terminal wiring. ....	12 to 24 AWG copper conductor wire with 10 mm (0.39 in.) of insulation stripped from the end
-----------------------------	--

Torque for screw terminals.....	0.5 to 0.6 N • m (4.4 to 5.3 lb • in.)
---------------------------------	---

Weight.....	Approx. 546 g (19.2 oz)
-------------	-------------------------

## Safety

### Safety Voltages

Connect only voltages that are within these limits.

V-to-C.....	35 V max, Measurement Category I
-------------	----------------------------------

Measurement Category I is for measurements performed on circuits not directly connected to the electrical distribution system referred to as MAINS voltage. MAINS is a hazardous live electrical supply system that powers equipment. This category is for measurements of voltages from specially protected secondary circuits. Such voltage measurements include signal levels, special equipment, limited-energy parts of equipment, circuits powered by regulated low-voltage sources, and electronics.

### Safety Standards

The cRIO-9052 is designed to meet the requirements of the following safety standards for electrical equipment for measurement, control, and laboratory use:

EN 61010-1, IEC 61010-1
UL 61010-1
CAN/CSA-C22.2 No. 61010-1

**Note:** For UL and other safety certifications, refer to the product label, or visit [ni.com/certification](http://ni.com/certification).

### Environmental

The cRIO-9052 is intended for indoor use only. For outdoor use, mount the CompactRIO system in a suitably rated enclosure.

### Operating temperature

(IEC 60068-2-1, IEC 60068-2-2) .....	-40 to 70 °C
--------------------------------------	--------------

**Note:** To meet this operating temperature range, follow the guidelines in the installation instructions for the CompactRIO system.

### Storage temperature

(IEC 60068-2-1, IEC 60068-2-2) .....	-40 to 85 °C
--------------------------------------	--------------

### Ingress protection .....

IP 40
-------

### Operating humidity (IEC 60068-2-56).....

10 to 90% RH, noncondensing
-----------------------------

### Storage humidity (IEC 60068-2-56).....

5 to 95% RH, noncondensing
----------------------------

### Maximum altitude.....

2,000 m
---------

### Pollution degree (IEC 60664) .....

2
---

### Shock and Vibration

To meet these specifications, you must panel mount the CompactRIO system and affix ferrules to the end of the terminal wires.

### Operating vibration

Random (IEC 60068-2-64) .....	5 g <sub>rms</sub> , 10 to 500 Hz
-------------------------------	-----------------------------------

Sinusoidal (IEC 60068-2-6) .....	5 g, 10 to 500 Hz
----------------------------------	-------------------

### Operating shock (IEC 60068-2-27) .....

30 g, 11 ms half sine, 50 g, 3 ms half sine,
---

18 shocks at 6 orientations
-----------------------------

### Electromagnetic Compatibility

Emissions .....	EN 55011 Class A at 10 m FCC Part 15A above 1 GHz
-----------------	--

Immunity.....	Industrial levels per EN 61326:1997 + A2:2001, Table A.1
---------------	---

EMC/EMI.....	CE, C-Tick, and FCC Part 15 (Class A) Compliant
--------------	--

**Note:** For EMC compliance, operate this device with shielded cabling.

### CE Compliance

This product meets the essential requirements of applicable European directives, as amended for CE marking, as follows:

Low-Voltage Directive (safety) .....	73/23/EEC
--------------------------------------	-----------

### Electromagnetic Compatibility

Directive (EMC).....	89/336/EEC
----------------------	------------

**Note:** Refer to the Declaration of Conformity (DoC) for this product for any additional regulatory compliance information. To obtain the DoC for this product, visit [ni.com/certification](http://ni.com/certification).

# NI Services and Support



NI has the services and support to meet your needs around the globe and through the application life cycle – from planning and development through deployment and ongoing maintenance. We offer services and service levels to meet customer requirements in research, design, validation, and manufacturing. Visit [ni.com/services](http://ni.com/services).

## Training and Certification

NI training is the fastest, most certain route to productivity with our products. NI training can shorten your learning curve, save development time, and reduce maintenance costs over the application life cycle. We schedule instructor-led courses in cities worldwide, or we can hold a course at your facility. We also offer a professional certification program that identifies individuals who have high levels of skill and knowledge on using NI products. Visit [ni.com/training](http://ni.com/training).

## Professional Services

Our Professional Services Team is comprised of NI applications engineers, NI Consulting Services, and a worldwide National Instruments Alliance Partner program of more than 600 independent consultants and

integrators. Services range from start-up assistance to turnkey system integration.

Visit [ni.com/alliance](http://ni.com/alliance).



## OEM Support

We offer design-in consulting and product integration assistance if you want to use our products for OEM applications. For information about special pricing and services for OEM customers, visit [ni.com/oem](http://ni.com/oem).

## Local Sales and Technical Support

In offices worldwide, our staff is local to the country, giving you access to engineers who speak your language. NI delivers industry-leading technical support through online knowledge bases, our applications engineers, and access to 14,000 measurement and automation professionals within NI Developer Exchange forums. Find immediate answers to your questions at [ni.com/support](http://ni.com/support).

We also offer service programs that provide automatic upgrades to your application development environment and higher levels of technical support. Visit [ni.com/ssp](http://ni.com/ssp).

## Hardware Services

### NI Factory Installation Services

NI Factory Installation Services (FIS) is the fastest and easiest way to use your PXI or PXI/SCXI combination systems right out of the box. Trained NI technicians install the software and hardware and configure the system to your specifications. NI extends the standard warranty by one year on hardware components (controllers, chassis, modules) purchased with FIS. To use FIS, simply configure your system online with [ni.com/pxiadvisor](http://ni.com/pxiadvisor).

### Calibration Services

NI recognizes the need to maintain properly calibrated devices for high-accuracy measurements. We provide manual calibration procedures, services to recalibrate your products, and automated calibration software specifically designed for use by metrology laboratories. Visit [ni.com/calibration](http://ni.com/calibration).

### Repair and Extended Warranty

NI provides complete repair services for our products. Express repair and advance replacement services are also available. We offer extended warranties to help you meet project life-cycle requirements. Visit [ni.com/services](http://ni.com/services).



[ni.com](http://ni.com) • (800) 813 3693

National Instruments • [info@ni.com](mailto:info@ni.com)

© 2005 National Instruments Corporation. All rights reserved. CompactRIO, LabVIEW, National Instruments, National Instruments Alliance Partner, NI, ni.com, and SCXI are trademarks of National Instruments. Other product and company names listed are trademarks or trade names of their respective companies.

A National Instruments Alliance Partner is a business entity independent from NI and has no agency, partnership, or joint-venture relationship with NI.

2005-6296-161-101